# Popular Electronics®

WORLD'S LARGEST-SELLING ELECTRONICS MAGAZINE

MARCH 1981

## PE Tests Pioneer's VP-1000 Video Disc Player

## Beep!

## A Look at Pocket Telephone Pagers

## Low-noise, Low-distortion Phono Preamplifier

# Reactance Measuring Set




## Audio Product of the Month:
## Luxman Model K-8 Cassette Deck

0 03
14024 14278

# Edison had over 1,800 patents in his name, but you can be just as inventive with an Apple.

Apple is the company with the brightest ideas in hardware and software *and* the best support — so you can be as creative with a personal computer system as Edison was with the incandescent bulb.

## How Apple grows with you.

With Apple's reliable product family, the possibilities of creating your own system are endless. Have expansion capabilities of 4 or 8 accessory slots with your choice of system.

Expand memory to 64K bytes or 128K bytes. Add an A to D conversion board. Plug into time sharing, news and electronic mail services. Use an IEEE 488 bus to monitor lab instruments. Add 4 or 6 disk drives — the 5¼", 143K bytes, high-speed, low-cost drive that's the most popular on the market.

## Apple speaks many languages.

Since more than 100 companies create software for Apple, you'll have the most extensive library in the personal computer world. Want to write your own programs? Apple is fluent in BASIC, Pascal, FORTRAN, PILOT and 6502 assembly language.

There's even a series of utility programs called the DOS Tool Kit that not only lets you design high-resolution graphic displays, but lets you work wonders with creative animation.

## More illuminating experiences in store.

You won't want to miss all the Apple products being introduced at your computer store all the time. Don't let history pass you by. Visit your nearest Apple dealer or call **800-538-9696**. In California, **800-662-9238**. Or write: Apple Computer, 10260 Bandley Drive, Cupertino, CA 95014.

**apple computer inc.**

CIRCLE NO. 6 ON FREE INFORMATION CARD

# Beckman brings a new dimension to hand held Digital Multimeters




## True RMS capability at an affordable price

Now you can measure the exact power content of *any signal* — regardless of waveform. Beckman delivers the new TECH™ 330 multimeter with true RMS capability and many more fine performance features for just $210.

Unlike most multimeters calibrated to read only the true power content of sine waves, the TECH 330 extends its true RMS capability to give you accurate readings of both sine and non-sine waveforms.

True RMS makes a significant difference in accuracy when measuring switching power supplies, flyback power circuits, SCR or TRIAC controlled power supplies or any other circuit generating a non-sine signal.

The TECH 330 also accurately measures the entire audio band up to 20 kHz. But that's not all you can expect from Beckman's top-of-the-line multimeter.

**Measurement Comparison Chart**

| Waveforms (Peak = 1 Volt) | Average Responding Meter | Beckman TECH 330 | Correct Reading |
|---|---|---|---|
| Sine Wave | 0.707V | 0.707V | 0.707V |
| Full Wave Rectified Sine Wave | 0.298V | 0.707V | 0.707V |
| Half Wave Rectified Sine Wave | 0.382V | 0.500V | 0.500V |
| Square Wave | 1.110V | 1.000V | 1.000V |
| Triangular Sawtooth Wave | 0.545V | 0.577V | 0.577V |

You also get 0.1% basic dc accuracy, instant continuity checks, 10 amp current ranges, a separate diode test function, 22 megohm dc input impedance, and an easy-to-use rotary switch.

With so much capability in hand, you'll be able to depend on the TECH 330 for a long time. That's why Beckman designed it tough enough to go the distance.

Enclosed in a rugged water-resistant case, the TECH 330 can take a 6-foot fall onto concrete and still perform up to spec. And to further ensure reliable, trouble-free operation, the TECH 330 gives you 1500 Vdc overload protection, RF shielding, 2000-hour battery life, gold switch contacts, and fewer electronic components to worry about.

Add another dimension to your world of electronics. Visit your Beckman distributor today for more information on the TECH 330 and Beckman's complete line of digital multimeters, starting at $120.

For your nearest distributor, or a free brochure:

**CALL TOLL FREE**
**24 HOURS A DAY, 7 DAYS A WEEK**
**1-(800)-821-7700 (ext. 517)**
in Missouri 1-(800)-892-7655 (ext. 517)

**BECKMAN**

CIRCLE NO. 63 ON FREE INFORMATION CARD

# NOW CLEANING YOUR OWN DISKETTE HEADS COULD SAVE YOU A $40 SERVICE CALL. AND A LOT MORE.

The recording heads on your diskette drives may be dirty—and that can cause you a lot of grief. There's the serviceman you have to call when the machine doesn't perform. (You know how much service calls cost these days!) There's machine down-time. Idle data entry clerks. All the other delays a cranky machine can cause.

And that service call might not even be necessary.

**3M solves the problem in seconds—and leaves your heads "Computer Room Clean".**

The Scotch® head-cleaning diskette kit lets you clean the read-write heads on your 8" or 5¼" diskette drives. In just 30 seconds, without any disassembly, mess or bother, the heads can be completely cleansed of dirt, dust, magnetic oxides—all the things that can get into your machines every day. And foul them up.

Just saturate the special white cleaning pad in its jacket with the cleaning solution. Then insert the jacket into the diskette drive and turn it on. Your machine does the rest. The



heads are microscopically cleaned without wear, without abrasion.

This 3M head-cleaning diskette kit has been evaluated and approved by major diskette drive manufacturers. It's the best possible way to clean your heads without service calls or machine teardowns.

**At only $1 per cleaning—it's the best insurance you can get.**

This fast-cleaning new Scotch kit comes with everything you need (including special fluid, applicator tip, cleaning diskettes) to handle up to 30 cleanings. That's only about a dollar a cleaning.

With the Scotch head-cleaning diskette kit, you could save yourself a lot more than just a service call. So try this remarkable kit today. For the name of



*A Scotch cleaning diskette shown before use, and after 15 cleanings of recording heads.*

the dealer nearest you, call toll free: 800-328-1300. (In Minnesota, call collect: 612-736-9625.) Ask for the Data Recording Products Division.

CIRCLE NO. 35 ON FREE INFORMATION CARD

3M

MARCH 1981 VOLUME 19, NUMBER 3

# Popular Electronics®

WORLD'S LARGEST-SELLING ELECTRONICS MAGAZINE

## Feature Articles

**BEEP! A LOOK AT POCKET PAGERS**/*George Leon* — 59
*How the new lightweight, pocket-sized radio devices operate.*

**BINARY, OCTAL AND HEXADECIMAL NUMBERS**/*Fred Blechman* — 63
*Understanding and applying the three basic systems in computer programming.*

## Construction Articles

**A REACTANCE MEASURING SET**/*James Barbarello and Edwin Iriye* — 67
*Measures inductances as well as capacitances.*

**A HIGH-PERFORMANCE PHONO PREAMPLIFIER**/*John Roberts* — 79
*Features low noise and distortion and allows choice of cartridge types.*

**AN AUTOMATIC LINE VOLTAGE REGULATOR**/*Herbert Elkin* — 85
*Gives the line a .6-volt boost when it drops too low.*

## Equipment Reviews

**LUXMAN MODEL K-8 STEREO CASSETTE DECK** — 23

**PIONEER MODEL VP-1000 VIDEODISC PLAYER** — 31

**BECKMAN TECH MODEL 310 DIGITAL MULTIMETER** — 44

## Columns

**ENTERTAINMENT ELECTRONICS**
**Life With Video Discs**/*Ivan Berger* — 14
**New Sonic Hologram**/*Harold A. Rodgers* — 20

**COMPUTER BITS**/*Carl Warren* — 48
*Good Grief! More Conversion.*

**COMPUTER SOURCES**/*Les Solomon* — 51

**SOLID-STATE DEVELOPMENTS**/*Forrest M. Mims* — 88
*Magnets, Bubbles and Garnets.*

**HOBBY SCENE**/*John McVeigh* — 92

**EXPERIMENTER'S CORNER**/*Forrest M. Mims* — 93
*Programmable-Gain Amplifiers.*

**DX LISTENING**/*Glenn Hauser* — 97
*Shortwave Broadcasting and the FCC.*

**PROJECT OF THE MONTH**/*Forrest M. Mims* — 100
*Transistorized Light Flasher.*

## Departments

**EDITORIAL**/*Art Salsberg* — 4
*Hunting of the Quark.*

**LETTERS** — 7

**NEW PRODUCTS** — 8

**AUDIOPHILE RECORDINGS**/*Harold A. Rodgers* — 20

**OPERATION ASSIST** — 101

**ADVERTISERS INDEX** — 115

**PERSONAL ELECTRONICS NEWS** — 116

COPYRIGHT © 1981 BY ZIFF-DAVIS PUBLISHING COMPANY. All rights reserved. Popular Electronics (ISSN 0032-4485) March 1981, Volume 19, Number 3. Published monthly by Ziff-Davis Publishing Co., at One Park Ave., New York, NY 10016. Philip B. Korsant, President; Selwyn Taubman, Treasurer; Bertram A. Abrams, Secretary. One year subscription rate for U.S. and Possessions, $14.00; Canada, $17.00; all other countries, $19.00 (cash orders only, payable in U.S. currency). Controlled circulation Postage Paid at Salem, IL 62881. Authorized as second class mail by the Post Office Dept., Ottawa, Canada, and for payment of postage in cash. POPULAR ELECTRONICS including ELECTRONICS WORLD, Trade Mark Registered. Indexed in the Reader's Guide to Periodical Literature. Ziff-Davis also publishes Boating, Car and Driver, Cycle, Flying, Popular Photography, Skiing, Stereo Review, Electronic Experimenter's Handbook, and Tape Recording & Buying Guide. **Forma 3579 and all Subscription Correspondence:** POPULAR ELECTRONICS. Circulation Dept. P.O. Box 2774, Boulder, CO 80302. **Please allow at least eight weeks for change of address, enclosing, if possible, an address label from a recent issue. Permissions.** Material in this publication may not be reproduced in any form without permission. Requests for permission should be directed to John Babcock, Rights and Permissions, Ziff-Davis Publishing Co., One Park Ave., New York, NY 10016.




**The Right Touch Is a Discwasher SC-2 Stylus Care System.**

The SC-2 is a three-function system which safely removes microscopic stylus contaminations that cause record abrasion.

SC-2 Fluid enhances and speeds cleaning and yet protects diamond adhesives, cartridge mounting polymers and fine-metal cantilevers against the corrosive effects of many other "cleaners".

The Discwasher SC-2 System. Stylus care with which your cartridge and records can live.

**discwasher®**
PRODUCTS TO CARE FOR YOUR MUSIC

Discwasher, Inc.
1407 N. Providence Rd.
Columbia, MO 65201

CIRCLE NO. 16 ON FREE INFORMATION CARD

# EDITORIAL

## Hunting of the Quark

How often does one read about or discuss quarks? Strangely, the subject of quarks came up on three separate occasions during the New Year's vacation period. The first time was listening to my 13-year-old son telling me that an atom was the smallest particle of matter. I corrected him, reciting a list of what's inside an atom that could be subdivided into smaller elements. This led to a discussion of electrical force, Thomson's bottled lightning experiments that identified electrons, his discovery of the proton, etc.

My son didn't really believe me because his science teacher had told him. . . . So I laughingly offered to bet him that the smallest element was called a quark, and that there are up quarks, down quarks, strange quarks, charmed quarks, as well as anti quarks. The gauntlet was quickly picked up. "I'll bet you an Atari game cartridge against a hockey game," he responded. I agreed, but more about this later.

Later that evening, I read an article in *Scientific American* (December 1980) on "Cosmic Asymmetry," attracted to it by my growing interest in astronomy and because we'll be picturing a sophisticated telescope on next month's cover. And there was a discussion and many illustrations relating to quarks that are thought to make up each proton and neutron, bound together by gluons. What a coincidence, I thought.

The next day, I continued reading a book, *Fantastic Journeys* by Mark Hunter. Surprise! I reached the beginning of a dozen pages that discussed quarks, written in layman terms. I learned that two American scientists, Murray Gell-Mann and George Zweig, concluded in 1963 that hadrons were not fundamental particles because there were too many of them. They postulated that there were more basic particles, which Gell-Mann named "quarks," a word he recalled from *Finnegans Wake*. (James Joyce created the name for something that is real but cannot be seen.)

Moreover, I discovered that there was a fifth quark, named a bottom quark, that halted decay. And since basic elements come in pairs, there should be a sixth quark that has not yet been identified. Furthermore, with that many quarks, it's likely that there are many more. If so, scientists say that quarks are not the smallest particles. Interestingly, one American physicist, Leon Lederman, who predicted the existence of the fifth quark, speculated that maybe there are no elementary particles at all and that every particle has smaller parts. Perhaps the hunting of the sixth quark will be concluded when a new particle accelerator that will produce collision energies exceeding 270 GeV (G=1 billion) is built. A few are now under construction.

Triumphantly showing my son the book that described quarks, I learned that I had not actually won the bet, owing to my naivete in dealing with smaller matter, whether quarks or my son. He calmly informed me that there was no bet at all since we didn't shake hands on it.

Art Salsberg


**JOE MESICS**
*Publisher*

**ARTHUR P. SALSBERG**
*Editorial Director*

**HAROLD A. RODGERS**
*Executive Editor*

**LESLIE SOLOMON**
*Senior Technical Editor*

**JOHN R. RIGGS**
*Managing Editor*

**EDWARD I. BUXBAUM**
*Art Director*

**ALEXANDER W. BURAWA**
*Features Editor*

**JOHN J. McVEIGH**
*Technical Editor*

**ANDRE DUZANT**
*Technical Illustrator*

**CARMEN ROBLES**
*Production Editor*

**JEFF NEWMAN**
*Editorial Assistant*

*Contributing Editors*
**Carl Warren, Stan Prentiss**
**Glenn Hauser, Julian Hirsch, Forrest Mims**

**MARIE MAESTRI**
*Executive Assistant*

**OLIVIA WILSON**
*Promotion Coordinator*

**PEARL HARRINGTON**
*Assistant to the Publishing Director*

**SIDNEY HOLTZ**
*Publishing Director*

**Popular Electronics®**

Editorial and Executive Offices
One Park Avenue
New York, New York 10016
212 725-3500

**Publisher**
Joe Mesics
212 725-3568

**New York Office**
Advertising Manager:
Richard Gowatski (725-7460)

Eastern Advertising Manager
Bonnie B. Kaiser (725-3580)
Richard B. Eicher (725-3578)

**Midwestern Office**
Suite 1400, 180 N. Michigan Ave.,
Chicago, IL 60601 (312 346-2600)
Sales: Ted Welch

**Western Representative**
Norman S. Schindler & Associates, Inc.
7050 Owensmouth Ave., #209
Canoga Park, CA 91303 (213 999-1414)
Sales: Norm Schindler, Jon Marshall

**Representation In Japan**
James Yagi
Oji Palace Aoyama
6-25, Minami Aoyama, 6 Chome, Minato-Ku
Tokyo, Japan (407-1930/6821, 582-2851)

**Ziff-Davis Publishing Company**

| | |
|---|---|
| Philip B. Korsant | President |
| Richard Friese | Senior Vice President |
| Phillip T. Heffernan | Senior Vice President |
| Sidney Holtz | Senior Vice President |
| Edward D. Muhlfeld | Senior Vice President |
| Philip Sine | Senior Vice President |
| Albert S. Traina | Senior Vice President |
| Robert Bavier | Vice President |
| Paul Chook (Research) | Vice President |
| Baird Davis (Production) | Vice President |
| Edgar G. Hopper (Marketing) | Vice President |
| George Morrissey | Vice President |
| Selwyn Taubman | Treasurer |
| Bertram A. Abrams | Secretary |
| W. Bradford Briggs | Vice Chairman |

**Ziff Corporation**

| | |
|---|---|
| William Ziff | Chairman |
| I. Martin Pompadur | President |
| Hershel B. Sarbin | Executive Vice President |
| Furman Hebb | Vice President |
| Bruce Maggin | Vice President |
| Lawrence Sporn | Vice President |

**Editorial correspondence:** POPULAR ELECTRONICS, 1 Park Ave., New York, NY 10016. Editorial contributions must be accompanied by return postage and will be handled with reasonable care; however, publisher assumes no responsibility for return or safety of manuscripts, art work, or models submitted.



The publisher has no knowledge of any proprietary rights which will be violated by the making or using of any items disclosed in this issue.

Member Audit Bureau of Circulations

# "No one else gives you as many functions in a handheld DMM.

# Now you can move up to Fluke."

We've got great news for people who've been holding out for a high quality, high performance DMM at a moderate price: Fluke's new nine-function model D 804 is now available at select electronics supply stores.

With a suggested list price of only $229 and features you won't find in any other handheld DMM, the D 804 is an exceptional value. Here's why.

**Logic level and continuity testing:** A real time-saver for troubleshooting passive circuits in pcb's, cables, relay panels and the like. The D 804 has a switch-selectable audible tone and visual symbols to indicate continuity or logic levels.

**Direct temperature readings in °C:** Used with any K-type thermocouple, the D 804 delivers fully-compensated readings in °C from -20°C to +1265°C, for checking heating and refrigeration systems.

**Peak hold feature captures transients:** A short-term memory in the D 804 captures and holds peak readings.

**And more:** 0.1% basic dc accuracy, conductance, 26 measurement ranges, battery, safety-designed test leads and a one year parts and labor warranty. A full line of accessories is also available to extend the measurement capabilities of your DMM.

Ask your dealer about the powerful, versatile D 804 and the rest of Fluke's new Series D line of low-cost digital multimeters.

**From the world leader in DMM's. Now we've designed one for you.**




*Suggested U.S. list price

For technical data circle no.

If your dealer doesn't carry Series D Multimeters yet, call this number. We'll be happy to tell you who does. **1-800-426-9182**

FLUKE®

# How to get 50% more sound without turning up the volume.



**A dbx Dynamic Range Expander restores the music dynamics that were lost in the recording process – giving you up to 50% more sound. The technology is based on a technique originally developed by dbx for professional recording studios.**

There's a whole range of sound in a live performance that you never hear from your stereo system. And it's not a question of turning up the volume.

The problem is in the records you play.

When recording engineers master a record, they electronically eliminate up to half the music. They literally compress the sound to make it "fit" on the vinyl record.

Fortunately, there's one solution to the problem: dbx Dynamic Range Expanders.

A dbx Dynamic Range Expander in your system restores most of the lost music. And it reduces annoying record surface noise by as much as 20 dB. So instead of a compressed 50 or 60 dB of dynamic range, you get a full 75 to 90 dB. The loud passages begin to thunder. The softs are truly subtle. All your music comes to life.

And you can use a dbx Dynamic Range Expander not only with your records, but also with tapes and FM broadcasts.

Visit your authorized dbx retailer for a demonstration of the 1BX, 2BX and 3BX Dynamic Range Expanders. Then select the model that's best for your system.

Because there's a lot more to music than has been reaching your ears.

dbx, Inc., 71 Chapel St., Newton, MA 02195 U.S.A. Tel. (617) 964-3210. Telex 92-2522. Distributed throughout Canada by BSR (CANADA) Ltd., Rexdale, Ontario.

**dbx®**

**Making good sound better**






CIRCLE NO. 14 ON FREE INFORMATION CARD

# LETTERS

### New Battery-Charger Use

I recently had what appeared to be a "dead" car battery and, in trying to locate the trouble, discovered an unexpected use for my "Battery Charger" (January 1981, p 66.). When the LED lights up on TRICKLE charge but not on FULL charge position of *S1*, it is indicating an open battery element or a corroded battery post. If the LED is much brighter on FULL than on TRICKLE, either the battery is fully discharged or there is a short. In my case, the problem turned out to be an open battery element.—*Cass Lewart, Holmdel, NJ.*

### BSEE vs BET

In "They're Wooing You in Electronic Land!" (January 1981), I was appalled at the statement, "There are proposals out at the IEEE to eliminate calling BET graduates 'Engineers,' but they do indeed perform as engineers at work." I worked very hard for 5 years to receive my BSEE, while every BET I knew was only learning how to be a 4-year technician. I have noted that the BETs I've worked with perform their duties like technicians not engineers. I believe many companies are using BETs because they can be paid less that BSEEs and there is a shortage of the latter. It is also advisable for companies to call as many employees engineers as possible for proposal writing purposes. This is reducing the integrity of the true engineering profession. The IEEE proposal will uphold that integrity.—*Gregory D. Gogates, Pittsburgh, PA.*

### Cordless Phone Confusion

In "PE Examines Cordless Telephones" (December 1980), the last two paragraphs about the Pathcom phones on page 23 are confusing. To quote, the next-to-last paragraph says, "All Ez Phones offer full duplex and answer/originate operation." Then, the first sentence of the next paragraph says, "Pathcom's two economy systems are the Model 8501/8511 full duplex answer-only and Model 8400 simplex push-to-talk systems. . . ." Which are they—answer/originate or answer only?—*Gary A. Ditges, Lansing, KS.*

*The Ez Phones are Models 8502/8510 and they have answer/originate operation. The Models 8501/8511 and 8400 are not in the Ez Phone line and are answer only.—Ed.*

### No Professional Amplifiers?

In "PE Tests Eight Audio Power Amplifiers" (January 1981), why were no standard professional models included? As a professional musician and technician, I own and work with pro recording and sound reinforcement equipment. Anyone serious enough about his stereo system to be willing to spend $600 to $1600 on a power amplifier should be made aware of amps such as BGW, Crown, and Crest—to name a few. These amps come in standardized packages, can be mistreated electrically with no damage, and some were undoubtedly used to mix the records played on your home system.—*Eric Wenocur, Columbia, MD.*

*The consumer orientation was intentional. In fact, when we tested a Crown Amplifier (March 1980), we chose the consumer version. We have nothing against professional amplifiers, but we feel that the extreme ruggedness designed into them is overkill for domestic applications.—Ed.*

### Solar Controller Kit Info

We have received numerous requests for information concerning the Wolfway Solar Controller Thermostats as described in your New Products of January 1981. Our product information pamphlet can be obtained by sending $1.00 (refundable with order) to Wolfway Product Consultants, Inc. R.D. #1, Box 1135, Tamaqua, PA 18252. All models and kits may be ordered via that pamphlet directly.—*R. M. Hollenbach, Tamaqua, PA.*


GENUINE SHURE® V15 TYPE IV PHONO CARTRIDGE

For all the facts circle 50 on free information card



not simply a "cartridge"... but an innovative playback system

**Dynamic Stabilizer** Suspended from two viscous-damped bearings, acts like a shock absorber to maintain a constant cartridge-to-record distance and uniform tracking force; eliminates record groove skipping caused by warp, cushions the stylus from accidental damage.

**Electrostatic Neutralizer** 10,000 conductive graphite fibers discharge static electricity from the record during play. Eliminates attraction of dust and tracking force variations caused by static charges.

**Hyperelliptical Tip** Elongated, uniform groove contact reduces harmonic and intermodulation distortion by as much as 25% over conventional Elliptical or long contact tips.

**Telescoped Shank** Greatly improves trackability at the critical middle and high frequencies. Lowest effective mass, with no sacrifice of necessary stiffness or strength.

**Two-Function Bearing** Unique bearing system is optimized for both low frequencies and high frequencies independently. Enhances trackability across entire audio spectrum.

**Laminated Core** Low-loss, laminated electromagnetic structure provides consistently flat frequency response, exceptional channel separation, higher signal level output.

GENUINE SHURE®

Shure Brothers Inc., 222 Hartrey Ave., Evanston, IL 60204
Manufacturers of high fidelity components, microphones, sound systems and related circuitry.

# NEW PRODUCTS

*Additional information on new products covered in this section is available from the manufacturers. Either circle the item's code number on the Free Information Card or write to the manufacturer at the address given.*

## Shure Cartridge/ Headshell Combo

Shure has expanded its M97 Era IV phono cartridge line with the M97ED-AH integrated cartridge/headshell assembly. The AH indicates that the M97HE cartridge comes already mounted in a universal four-pin headshell that is compatible with many leading tonearms. The integrated design is said to offer 4 to 6 grams of total weight reduction compared to separate cartridge and headshell combinations. The cartridge features a nude-mounted hyperelliptical diamond stylus, viscous-damped dynamic stabilizer, telescoped stylus shank, and Shure's "Side Guard" stylus protection. Recommended tracking force range is ¾ to 1½ grams. $120.

**CIRCLE NO. 88 ON FREE INFORMATION CARD**

## Deluxe Scope Curve Tracer

Daltec Systems' Expand-A-Scope connects to the horizontal and vertical inputs of a scope and provides nine reference standards against which the traces of resistors, capacitors, diodes, zeners, and other components can be compared. Current through a component under test is 5 mA maximum. The dual mode allows comparison of unknown components against known ones. An impedance/voltage/current display permits the comparisons, while an audible tone is used for continuity testing of circuits under 10 ohms. $250. Optional test probes, $15. Address: Daltec Systems, Inc., P.O. Box 157, Onondaga Branch, Syracuse, NY 13215.

## Radio Shack Line Printer

Radio Shack's Line Printer IV is a proportionally spaced high-density dot-matrix impact printer designed for use with the TRS-80 microcomputer. The printer can also be set up to produce 80 or 132 fixed-space characters per 8″ line. Both upper- and lower-case letters are available in all three printing modes. Special characters available include the grave accent, braces, back slash, and caret. True underlining, subscripting, superscripting, enlarged characters, bold facing, and forward and reverse line feed are also available. Print density is 10 or 16.7 monospaced or 8.2 to 24.6 proportionally spaced characters per inch, and print speed is 50 characters per second or 22 lines per minute. The printer accepts roll, pin-feed, 9½″ fan-fold, or single-sheet plus two carbons paper. Size is 15″ x 11″ x 5″ and weight is 12 lb. $999.

**CIRCLE NO. 91 ON FREE INFORMATION CARD**

## Heat-Sink Clamps

Six new heat-sink clamps designed to facilitate the soldering of delicate electronic components have been produced by Desco Industries. The clamps reportedly are made of beryllium copper and have parallel-jaw construction. Two sizes, with overall lengths of 1.5″ and 2.5″, respectively, are available. Finger grips are plastic coated. The clamps are available with either chrome plating for resistance to wetting or chrome plating and a Plastisol coating for resistance to wetting and increased heat-dissipation characteristics. Prices range from $1.98 each to $2.70 each. Address: Desco Industries, Inc., 351 F Oak Place, Brea, CA 92621.

## Teac Cassette Deck

Teac's new Model V-9 stereo cassette deck features a new two-head, three-motor transport mechanism and a unique spectrograph metering system. Assigned to each channel is a series of six color-coded peak-indicating lamps that display recording or playback levels. The transport's drive mechanism is controlled by IC logic, without the need for solenoids. Other features include one-touch selection of bias and equalization (the V-9 accepts all modern tape formulations, including metal), Dolby noise-reduction circuitry, a timer control for use with an optional timer unit, and REC MUTE. $399.

**CIRCLE NO. 89 ON FREE INFORMATION CARD**

## Noise Filter For Videotape

The Model DNF-1201A Burwen noise filter from KLH is claimed to dramatically reduce tape hiss encountered when playing videotapes through hi-fi systems. The filter operates on the principle of selective suppression of noise, having its greatest effect on quiet passages by automatically reducing high-frequency response. The device is rated to provide between 5 and 14 dB of tape hiss reduction. It is also rated to deliver a frequency response from 10 to 20,000 Hz ±0.5 dB maximum, with a dynamic range of 96 dB. Installation in a VCR/hi-fi system is via the tape-monitor jacks on the latter and the audio output jack on the VCR. Pushbutton controls on the DNF-1201A allow selection of maximum, minimum, or medium noise reduction. A sensitivity control and LED readout are also provided for calibration. $379.

**CIRCLE NO. 92 ON FREE INFORMATION CARD**

## Simplified Port Switching

Inmac's T-Switch permits a computer user to switch two 24-signal lines without switching all cables. According to the company, an all-purpose asynchronous null modem ensures compatibility between the communicating devices. The T-

# Magnavision® is Gourmet Video.

## Video for people who know and love video.

Simulated TV picture.

If you seek the ultimate in your electronic gear, Magnavox has a bright idea for you called Magnavision. It is Gourmet Video for the video gourmet.

**A picture that's clearer than tape and less costly, too.**

Magnavision is an advanced LaserVision™ videodisc player. Its optical laser scanner, a videodisc and your TV set team up to give you a picture that's amazingly sharp and clear.

Even better, the Magnavision picture remains this good even after thousands of viewings. That's because there is no direct contact between our laser and the disc. Unlike your phonograph, Magnavision doesn't use a needle.

**The hearing's as good as the seeing.**

Magnavision is designed to be played through your home stereo system so you hear what you see in full high-fidelity stereophonic sound. And since there is no disc wear, the Magnavision sound stays crystal clear, playing after playing.

**Studio-like controllability puts you in command of the action.**

Now the real fun begins. You not only watch and hear Magnavision. You play with it, too. Reverse, Slow Motion, Still, Fast Forward, Search, Numerical Index, Stereo Sound. Only LaserVision systems like Magnavision let you watch and play so many different ways.

**Watch what you want whenever you want.**

With Magnavision, you have a complete library of MCA DiscoVision® programming to choose from. Blockbuster movies like *The Electric Horseman.* Classic films like *The Bride of Frankenstein.* Cooking lessons by Julia Child. Documentaries from Jacques Cousteau. How-to-do-it tennis, golf, swimming and crafts. Music, concerts, cartoons, the arts and NFL football.

Discover Gourmet Video today. Call toll-free 800-447-4700 for the Magnavision dealer nearest you. In Illinois, call 800-322-4400.

©1963 ALFRED J. HITCHCOCK PRODUCTIONS, INC.

©1981 MAGNAVOX CONSUMER ELECTRONICS CO.

**CIRCLE NO. 38 ON FREE INFORMATION CARD**

MAGNAVOX

**The brightest ideas in the world are here to play.**

## Ditton Two-Way Speaker System



The Ditton 130 is a two-way acoustic-suspension speaker system from Celestion Industries. Its 8" woofer and dome tweeter are said to offer increased efficiency and wider dispersion over previous Ditton models, plus better octave-to-octave balance. The HF 1001 tweeter is designed to have greater power-handling ability than its predecessors, while a new low-mass PVC surround on the woofer is said to provide lower distortion and greater efficiency than would be possible with a neoprene surround. Technical specifications: 75 to 20,000 Hz ± 3 dB anechoic frequency response; 8 ohms impedance; 10 watts minimum driving power required; 87.5 dB SPL for 1 watt input at 1 meter. Size is 19"H x 9¾"W x 9"D, and weight is 17 lb. $200.

CIRCLE NO. 93 ON FREE INFORMATION CARD

Switch features three A-800 Series 25-pin female connectors, and the common ground is not switched. All contacts are




reported to be gold-plated. $175. Address: Inmac, Dept. 1025, 2465 Augustine Drive, Santa Clara, CA 95051.

## Kantronics Communications Filter

The Varifilter from Kantronics is claimed to provide optimum reception results from communications equipment without ringing, oscillating, or instability. Frequency and bandwidth can be varied to peak one signal or notch an interfering signal and it works with CW, SSB, and AM signals. Bandwidth is variable from less than 30 Hz to greater than 1 kHz, while frequency range is from less than 150 Hz to beyond 3 kHz. Once set, bandwidth remains constant regardless of changes in frequency-range setting. A tuning "eye" lets you see when a desired signal has been filtered out. The filter's built-in power supply is




switchable for 117- to 230-volt ac operation. For maximum convenience, the Varifilter can also be powered from a 12-to-18-volt dc source. $139.95. Address: Kantronics, Inc., 1202 E. 23 St., Lawrence, KS 66044.

## Triplett True RMS DMM



The Model 4200 digital multimeter from Triplett Corp. features true rms conversion for improved measurement of complex ac signals. It features a 3½-digit LED display, ±0.2% typical accuracy, and 32 ranges for measuring ac and dc voltages and currents and resistance. Other features include: pushbutton function selection, single range-selection switch, auto-zero and auto-polarity in the voltage and current modes, and r-f shielding. The instrument is fuse overload protected to 1000 volts on all ranges. Priced at $270, the DMM comes with safety test leads, and combination carrying handle and bench stand. Available options include: high-voltage probes, miniature clips, 30-amp dc current shunt, clamp-on ac ammeter, and simulated-leather carrying case.

CIRCLE NO. 94 ON FREE INFORMATION CARD

## O.K. Wire Stripper



O.K. Machine and Tool's new Model ST-300 manual wire stripper has an adjustable stop built into it to allow consistent wire-strip lengths. Designed to accommodate 14- to 22-gauge solid or stranded wire, it is reported to be able to strip almost any type of insulation—including Kynar, vinyl, polyethylene, rubber, etc.—in current use. The tool is designed to remove up to ¾" of insulation in a single motion, without damaging or nicking the wire. $9.95.

CIRCLE NO. 95 ON FREE INFORMATION CARD

## Interactive Video Interface

The CAVI (Computer Assisted Video Interface) Model 400 from BCD Associates is a single-board video tape controller for

## "Smart" Bearcat Scanner

Electra's Bearcat 350 scanner radio can display with words or abbreviations the source of messages being received on each of its 50 channels, using up to eight characters per channel. The same fluorescent display will also indicate exact received frequency when a button is pushed to put the radio into the numeric mode. In this case, frequencies are displayed to four decimal places to accommodate the new uhf-T band assignments. A second fluorescent display indicates the channel number being received and any special features actuated. Seven-band coverage includes low and high bands, uhf, uhf-T, 2-meter and 70-cm amateur FM bands, and the entire AM aircraft band. Other features include selectable scan speed, priority, direct channel access, automatic up/down search, and manual step search, plus automatic squelch and a function that permits automatic activation of an alarm or recorder when calls are received on channels of special interest. $600.

CIRCLE NO. 96 ON FREE INFORMATION CARD

# *Video Review*® knows a bright idea when it sees one.

Simulated TV picture. Simulated wood cabinet.

*Video Review* magazine tests a lot of sophisticated video products.

They get to see virtually every make and type of color TV receiver.

Which makes their selection of Magnavox as their standard TV receiver pretty impressive.

**"We thought the Magnavox picture quality and resolution were superb."**

"Ever since *Video Review* began testing products," says the magazine, "we've been looking for a top quality, 19-inch TV set that might serve as a standard of reference for all of the other products we test...video cameras, video cassette recorders, video cassettes.

"We thought the Magnavox picture quality and resolution were superb, and that off-the-air sensitivity was also extremely good.

"Major VHF channels were received with uniformly accurate color fidelity. This receiver produced superior color pictures even when using its own indoor VHF and UHF antennas."

**"The special tuning features and remote control capabilities of the Magnavox receiver are awesome."**

"The tuning system is purely electronic and totally digital," they continue. "There is a fine tune switch and a memory lock button. If any channel is received mistuned, the user simply fine tunes up or down in frequency by holding the button, and when perfect tuning has been achieved, the button is released and the memory lock button is depressed once.

"Nearby is Magnavox's Videomatic feature. Depressing this button activates the electronic eye for automatic brightness adjustment, color adjustment circuits and automatic fine tune."

**"...unusually good for any receiver."**

Overall, *Video Review* rated the Magnavox 9.5 or better (out of a possible 10.0) on Video Quality, Reception Sensitivity, Color Fidelity, and Video Resolution and Fidelity. As they put it, "...unusually good for any receiver."

We can only add that once you see a Magnavox color TV at your Magnavox dealer, we think you'll agree.

For Magnavox color TV specifications, write Magnavox Consumer Electronics Company, Dept. 700, P.O. Box 6950, Knoxville, Tennessee 37914.

© 1980 MAGNAVOX CONSUMER ELECTRONICS CO.

MAGNAVOX

**The brightest ideas in the world are here to play.**

CIRCLE NO. 39 ON FREE INFORMATION CARD

Apple II computers. It can be used to control industrial type VHS, Beta, and ¾-inch video recorder/players without modifications to the computer or VTR. By counting pulses from the tape control track, the system hardware/software permits precise video tape positioning. The unit contains a video audio switcher to allow alternate display of computer-generated or taped video on a single monitor. BASIC software allows searching for the beginning of a video scene, and play until the end of that scene. The Computer Assisted Instruction (CAI) software is available on a separate diskette. This program allows persons with no computer expertise to create and modify CAI lessons and video tape logs. CAVI is $495, CAI $295.

CIRCLE NO. 97 ON FREE INFORMATION CARD

## Zenith "Smart" Terminal

Zenith Data Systems' Model Z19 is a Z80-controlled "smart" data terminal whose special deflection system is designed to create smaller on-screen spot size for sharper resolution. The terminal's 12" CRT displays 24 lines by 80 upper-

and lower-case (with true descenders) characters and has a 25th user-status line. The keyboard is laid out in standard typewriter format and is supplemented by a separate numeric keypad. Video features permit complete control, and direct cursor control permits users to move anywhere on the screen for corrections and editing. Interfacing with a computer is via a standard RS-232 port, at baud rates from 110 to 9600. Compatibility with the DECOVT52 Digital Electronics terminal can be accomplished from the keyboard, an outside computer, or an interior switch. $995.

CIRCLE NO. 98 ON FREE INFORMATION CARD

## Ace Audio Infrasonic Filter



Ace Audio's Model 4000-X24 infrasonic filter is designed to reduce or eliminate infrasonic noise from warped records, off-center spindle holes, turntable rumble, and tonearm mass/stylus compliance resonance effects. The device's circuitry employs a combination of active Bessel and passive filter sections to maintain the lowest possible phase shift. Ace Audio states that each 4000-X24 is individually hand calibrated to improve accuracy. Distortion is rated at 0.002% at 2 volts output, and response is down 3 dB at 20 Hz (ultimate slope 24 dB/octave). $148.50.

CIRCLE NO. 99 ON FREE INFORMATION CARD

## 30-Channel Cable TV Converter

The ETCO AE047 converter makes all cable-TV channels from 2 to the super band suitable for viewing on the uhf portion of a TV receiver. The converter can be used with remote control systems or manual uhf selection. The converter can also be used with a VCR to regain programmability when video recording from the cable system. It comes with matching transformer and power supply. $39.95.

CIRCLE NO. 100 ON FREE INFORMATION CARD





CIRCLE NO. 5 ON FREE INFORMATION CARD

# The first personal computer for under $200.

## The Sinclair ZX80. A complete computer—only $199.95 *plus $5.00 shipping.*

Now, for just $199.95, you can get a complete, powerful, full-function computer, matching or surpassing other personal computers costing several times more.

It's the Sinclair ZX80. The computer that "Personal Computer World" gave 5 stars for 'excellent value.'

The ZX80 cuts away computer jargon and mystique. It takes you straight into BASIC, the most common, easy-to-use computer language.

You simply take it out of the box, connect it to your TV, and turn it on. And if you want, you can use an ordinary cassette recorder to store programs. With the manual in your hand, you'll be running programs in an hour. Within a week, you'll be writing complex programs with confidence.

All for under $200.

### Sophisticated design makes the ZX80 easy to learn, easy to use.

We've packed the conventional computer onto fewer, more powerful LSI chips—including the Z80A microprocessor, the faster version of the famous Z80. This makes the ZX80 the world's first truly portable computer (6½" x 8¼" x 1½" and a mere 12 oz.). The ZX80 also features a touch sensitive, wipe-clean keyboard and a 32-character by 24-line display.

Yet, with all this power, the ZX80 is easy to use, even for beginners.




### Your course in computing.

The ZX80 comes complete with its own 128-page guide to computing. The manual is perfect for both novice and expert. For every chapter of theory, there's a chapter of practice. So you learn by doing—not just by reading. It makes learning easy, exciting and enjoyable.

You'll also receive a catalog packed with items that can make your ZX80 even more useful. Including 27 program cassettes, from games and home budgeting for just $6.95, to Sinclair's unique Computer Learning Lab (a workbook, six cassettes with 100 lessons, and two cassettes for storing programs).

### ZX80's advanced design features.

Sinclair's 4K integer BASIC has performance features you'd expect only on much larger and more expensive computers.

- Unique 'one touch' entry. Key words (RUN, PRINT, LIST, etc.) have their own single-key entry to reduce typing and save memory space.
- Automatic error detection. A cursor identifies errors immediately to prevent entering programs with faults.
- Powerful text editing facilities.
- Also programmable in machine code.
- Excellent string handling capability—up to 26 string variables of any length.
- Graphics, with 22 standard symbols.
- Built-in random number generator for games and simulations.

Sinclair's BASIC places no arbitrary restrictions on you—with many other flexible features, such as variable names of any length.

And the computer that can do so much for you now will do even more in the future. Options will include expansion of 1K user memory to 16K, a plug-in 8K floating-point BASIC chip, applications software, and other peripherals.

### Order your ZX80 now!

The ZX80 is available only by mail from Sinclair, a leading manufacturer of consumer electronics worldwide.

To order by mail, use the coupon below. But for fastest delivery, order by phone and charge to your Master Charge or VISA. The ZX80 is backed by a 10-day money-back guarantee, and a 90-day limited warranty which can be extended by 12 months under Sinclair's extended service program for $25.00.

**Price includes TV and cassette connectors, AC adaptor, and 128-page manual.**

All you need to use your ZX80 is a standard TV (color or black and white). The ZX80 comes complete with connectors that easily hook up to the antenna terminals of your TV. Also included is a connector for a portable cassette recorder, if you choose to store programs. (You use an ordinary blank cassette.)



The ZX80 is a family learning aid. Children 10 and above will quickly understand the principles of computing—and have fun learning.

**To order call toll free:** 800-543-3000.
**In Ohio call:** 800-582-1364.
Ask for operator #508.
Phones open 24 hours a day, 7 days a week.

sinclair

**Sinclair Research Ltd., 475 Main St., P.O. Box 3027, Wallingford, CT 06492.**

To: **Sinclair Research Ltd., 475 Main St., P.O. Box 3027, Wallingford, CT 06492.**
Please send me _____ ZX80 personal computer(s) at $199.95 each (US dollars), plus $5 shipping. (Your ZX80 may be tax deductible.) For Conn. deliveries, add sales tax.
Send me _____ Computer Learning Lab(s) at $49.95 each.
Register me for _____ extended service program(s) at $25.00 each.
I enclose a check/money order payable to Sinclair Research Ltd. for $_____.
Name _____
Address _____
City _____ State _____ Zip _____
Occupation _____ Age _____
Intended use of ZX80 _____
Have you ever used a computer? ☐ Yes ☐ No Do you own another personal computer? ☐ Yes ☐ No
PE-3-1

# ENTERTAINMENT ELECTRONICS

## Life with Video Discs

THERE is probably still time to be the first on your block with a videodisc player—if you want to be. Magnavox and Pioneer have just put their laser-scanned disc players into more or less national distribution, and they'll still be a novelty in many areas. Even if someone beats you to the punch, you can still be first with an RCA "CED" disc player or a Japanese-developed "VHD" player, both of which are due by about the time you see this. I had a Magnavox for test about a year ago and have the Pioneer player here right now. They're fun to have. But whether you'll find them worth buying will depend on as many personal factors as technical ones.

Why have a videodisc that just plays programs when you can get a tape deck that records them, too? It's really the same question as "Why have a phonograph when a cassette recorder is available?" and the answers are just about the same. Like the phonograph, the videodisc can give you the best reproduction available. For example, I've gotten resolution better than 300 lines (horizontal) from a much-played laser-scanned video test "record," while the best I've seen on recent VCRs was about 250 lines. The disc picture was also far freer of snow and other noise, and there was no color smear, a common fault with tape. Of course, there is *some* noise and loss of detail. In fact, a really good broadcast or cable signal would give a better picture. I confirmed that by comparing a broadcast test pattern with that from my video test disc.

When it comes to sound quality, the laser-scanned video disc (the only type we've worked with to date) runs rings around the VCR and may even beat what comes off the air. The audio signal is stereo, with enough separation for bilingual use, as well. Stereo-sound VCR's are just now appearing (Akai's is the only one I know) and stereo TV broadcasting must await an FCC decision.

What's more, all the special effects work better on the disc than on a VCR. Still-frame, for example, is free of jitter, blur, and noise bars. Speeds range from normal down to a slow-motion 12 frames per minute (1/150 normal), and there are two fast modes—one at three times normal speed for reviewing or previewing a portion of the program) and one that zips through the entire disc in less than 30 seconds. All functions operate as smoothly and cleanly as normal play, and in both forward and reverse.

The videodisc frame counter puts the ones on VCR's to shame. Instead of an arbitrary four-digit number half-hidden behind a little window, there's a five-digit number on the screen (when you want it there) that identifies every one of the more than 50,000 frames on each side. On the Pioneer (but not the Magnavision), you can even punch in the frame number and have the player find it for you. Some discs have chapter numbers to help you find sections rather than frames. They can even carry signals that stop the player at each chapter's end. (Frame-by-frame access is coming to home VCR's, though.)

Otherwise, videodisc has much the same advantages and disadvantages compared to tape as the phonograph does. Disc software is cheaper to manufacture than prerecorded tapes, and access to stored information is the much faster random rather than sequential.

But if the videodisc shares the phonodisc's advantages, it has its major disadvantage as well: reliance on program material from outside sources, rather than on user-made recordings. That's important for two reasons: First, since the phonograph preceded tape, there was already a vast library of recordings available when the latter hit the scene. Videodisc is a Johnny-come-lately, and most of what's available is on tape, not disc. Second, with three incompatible disc systems contending for market share, the odds are against picking the one that will survive.

If you could make your own discs, that would be a small problem. If a video tape system becomes obsolete, there will still be enough demand to keep blank tapes available for years—suppliers can sell the same blanks to everyone, regardless of their tastes in programming. But once a disc system dies, don't expect suppliers to produce new program discs indefinitely.

How will the two new systems—RCA's CED and the Japanese VHD—compare? RCA's disc will initially have only monophonic sound. This is not as much of a drawback as some critics claim, I suspect, since so little video material with stereo is yet available. It also won't allow still-framing and some of the other fancy features of the laser disc. On the other hand, there are reports that the VHD disc will require some extra "frame-store" circuitry to do still-framing. And the long-play (CLV) laser discs, which have 60 minutes per side instead of the standard (CAV) discs' 30, don't allow still-framing, frame-number display, triple-speed play or frame-number search. (There is a counter readout, but it shows minutes and seconds rather than frames.)

Projected costs for both CED and VHD are lower than the laser disc's. RCA says its CED disc players will sell for $500; presumably, the rest (from Zenith, Hitachi, Radio Shack and others) will cost about the same. On the VHD side, Sansui (which just announced a player for later in '81) says the cost will be "at least $200 less than laser disc players," in other words about $550-$600. But discounts are available already, here and there, even with just two laser players on the market; with more competition, more price cuts are likely.

There's no telling how VHD and CED discs will compare with the laser disc for reliability. The laser-system disc seems the most long-lived, on paper (no physical disc contact, for one thing), but it has had problems. Early discs, on early players, would occasionally loop back to repeat a segment of the program, or stop altogether. There have been rumors of a high rejection rate at MCA's disc plant, and dealers have reported as many as one-third of their discs being returned. But disc production techniques have now improved (the return rate is now "almost as low as audio discs," says Magnavox), and Magnavox has modified its new players and those already in the field to eliminate the problem. A new laser-disc plant is rising in Japan, for Universal-Pioneer (the Pioneer player's actual manufacturer); if it lives up to the Japanese reputation for quality audio disc pressing, there should be no further problems.

How do the Magnavox and Pioneer players compare? Quite closely. I used them several months apart, so I can't say for sure that there was any difference in performance between the two. My Magnavox (an early, unmodified one) did sometimes skip into a loop on one specific disc side, and my Pioneer doesn't seem to have that problem. The Pioneer does have some extra features, though, such as the random-access system, a clever remote control (wireless, but with a wired option, in case it uses the same signal frequencies as your TV set), and a rear-panel jack for a potential digital-audio disc decoder.

That digital-audio output raises another idea that should intrigue computer enthusiasts. Estimating from the bit content of digital audio, a half-hour disc should hold about 150 megabytes, roughly the same as a 14-inch hard disc (allowing for redundant bits and the like). Track-to-track access would be a bit slower than disc systems designed for computer use, but a worst-case access time of about 30 seconds, on a data store that big, would still be acceptable, especially for hobbyist applications. Coming up, though not soon, are laser-disc systems that can record as well as play. That would turn the videodisc into a cross between hard disc and super ROM, with more capacity than most

(Continued on page 20)

Even if you own the best stereo system, it's still only two-dimensional sound totally lacking the brilliance of the missing third dimension — Omnisonic Imagery.™

No matter whether your system is stereo, quadraphonic or mono the 801 Omnisonic Imager™ will improve its performance. All this is now possible after years of research in the field of psychoacoustics.

Simply connect the 801 to the tape or preamp input/output jacks and listen to clear, distinct sound images that seem to surround you — even while moving around. In fact, the impact is so great that the sound seems to come from outside the speaker plane — at times even overhead and behind you. And amazingly enough, any tape recorded through the 801 will retain the Omnisonic dimensional effect when it is played back on a conventional stereo system.

To really hear the dramatic increase in presence that's been missing from your records, digitally recorded discs and 8-track, open reel or cassette tapes, take a few of your favorites to an Omnisonix dealer and ask for a demonstration. You're in for a surprising musical experience. The 801 Omnisonic Imager can also produce astonishing results with ordinary AM and TV sound.

You can even take Omnisonic Imagery on the road with you. The Imager™ 801-A does for your car stereo what the 801 does for your home music system.

Since both models are designed and built for lasting performance, under the strictest quality control conditions, Omnisonix offers them with a lifetime warranty on the active proprietary circuitry.

Join the growing thousands of music buffs who have found it completely affordable to enjoy the omnidimensional sound they've been missing with conventional stereo. Call today, toll-free 800-243-0688 for information and the name of your nearby Omnisonix dealer.

Omnisonix, Ltd., P.O. Box 430, Middletown Ave., Northford, CT 06472

**OMNISONIX, LTD.**

**Setting Sound Free**

CIRCLE NO. 51 ON FREE INFORMATION CARD

# You gotta shop around.



**When you do, you'll probably pick CIE. You can't afford to settle for less when it comes to something like electronics training that could affect your whole life.**

When you shop around for tires, you look for a bargain. After all, if it's the same brand, better price—why not save money?

Education's different. There's no such thing as "same brand!" No two schools are alike. And, once you've made your choice, the training you get stays with you for the rest of your life.

So, shop around for your training. Not for the bargain. For the best. Thorough, professional training to help give you pride and confidence.

* * *

If you talked to some of our graduates, chances are you'd find a lot of them shopped around for their training. They pretty much knew what was available. And they picked CIE as number one.

## Why you should shop around yourself.

We hope you'll shop around. Because, frankly, CIE isn't for everyone.

There are other options for the hobbyist. If you're the ambitious type—with serious career goals in electronics—take a close look at what we've planned for you at CIE.

## What you should look for first.

Part of what makes electronics so interesting is it's based on scientific discoveries—on ideas! So the first thing to look for is a program that starts with ideas and builds on them!

That's what happens with CIE's Auto-Programmed® Lessons. Each lesson takes one or two principles and helps you master them—before you start using them!

## How practical is the training?

This is the next big important question. After all, your career will be built on what you can do—and on how well you do it.

Here are ways some of CIE's trouble-shooting programs help you get your "hands-on" training...

**With CIE's Personal Training Laboratory...** you learn and review the basics—perform dozens of experiments. Plus, you use a 3-in-1 precision Multimeter to learn testing, checking, analyzing!

**When you build your own 5 MHz Triggered-Sweep, Solid-State Oscilloscope** you take your first real professional step. You use it as a doctor uses an X-ray machine— to "read" waveform patterns... lock them in...study, understand and interpret them!

**When you get your Digital Learning Laboratory** you'll be into digital theory—essential training today for anyone



who wants to keep pace with the state of the art of electronics in the eighties. With CIE's Digital Lab, you'll be applying in dozens of fascinating ways the theory you've learned. For example, you'll compare analog and digital devices. You'll learn to make binary to decimal conversions and to work with semiconductor devices and circuits. You'll see how digital equipment is vital in today's exciting, growing fields such as security where digital theory provides the brains for space-age alarm and protective devices.

Of course, CIE offers even more advanced training programs, too. But the main point is simply this:

All this training takes effort. But you'll enjoy it. And it's a real plus for a troubleshooting career!

## Do you prepare for your FCC License?

Avoid regrets later. Check this out before you enroll in any program.

More than half of CIE's courses prepare you for the government-administered FCC License exam. In continuing surveys, nearly 4 out of 5 CIE graduates who take the exam get their Licenses!

## Associate Degree

Now, CIE offers an Associate in Applied Science Degree in Electronics Engineering Technology. In fact, all or most of every CIE Career Course is directly creditable towards the Associate Degree.

## Shop around...but send for CIE's free school catalog first!

Mail the card. If it's gone, cut out and mail the coupon. If you prefer to write, mention the name and date of this magazine. We'll send you a copy of CIE's FREE school catalog—plus a complete package of independent home study information! For your convenience, we'll try to have a representative contact you to answer your questions. Mail the card or coupon—or write:

CIE, 1776 East 17th St., Cleveland, OH 44114.

**CIE** Cleveland Institute of Electronics, Inc.

1776 East 17th Street, Cleveland, Ohio 44114
Accredited Member National Home Study Council

☐ **YES...** I'm shopping around for the **right** kind of career training in electronics troubleshooting — and CIE sounds well worth looking into. Please send me my FREE CIE school catalog — including details about the Associate Degree program — plus my FREE package of home study information!

Print Name _____

Address _____ Apt. _____

City _____

State _____ Zip _____

Age _____ Phone _____ (area code)

Check box for G.I. Bill information:
☐ Veteran ☐ Active Duty

**Mail today!**

PE-34

# DISCOUNT PRICES!

**Top Quality**
**Money-Back Guarantee**
**All Factory Prime**

**MICROPROCESSOR IC'S**

| | | | |
|---|---|---|---|
| Z-80 | 8.95 | 6800 | 6.75 |
| Z-80A | 10.95 | 6802 | 11.50 |
| **8085A** | **9.50** | 6502 | 9.50 |
| 8085A | 11.95 | 6504 | 9.50 |
| Z8001 | 189.00 | 6505 | 9.50 |
| Z8002 | 139.00 | **Z601** | **8.95** |

**MICROPROCESSOR SUPPORT IC'S**

| | | | |
|---|---|---|---|
| 8212 | 2.49 | Z80-PIO | 6.95 |
| 8214 | 3.90 | Z80A-PIO | 8.25 |
| 8216 | 2.49 | Z80-CTC | 6.95 |
| 8224 | 2.95 | Z80A-CTC | 8.25 |
| 8226 | 2.25 | Z80-DMA | 24.95 |
| 8228 | 4.75 | Z80A-DMA | 32.95 |
| 8238 | 4.90 | Z80-SIO/0 | 33.95 |
| 8251 | 5.95 | Z80A-SIO/1 | 37.95 |
| 8253 | 19.50 | **8T26** | **1.49** |
| 8255 | 5.70 | **8T28** | **1.49** |
| 8257 | 19.50 | **8T97** | **1.19** |
| 8259 | 19.50 | **8T98** | **1.19** |
| 6810 | 4.75 | 6860 | 8.95 |
| 6820 | 3.90 | 6520 | 6.75 |
| 6821 | 3.90 | 6522 | 9.75 |
| 6850 | 4.10 | 6532 | 19.95 |
| 6852 | 3.90 | 6551 | 13.75 |

**MEMORY • RAMS • PROMS • EPROMS**

| | | | |
|---|---|---|---|
| **2114L-450 ns** | **4.50** | 2101-450 ns | 1.95 |
| 2114L-200 ns | 5.95 | 21L02-250 ns | 1.10 |
| 4044-450 ns | 4.25 | 21L02-450 ns | .99 |
| 4116-200 ns | 7.95 | 2111-450 ns | 2.95 |
| 4116-150 ns | 12.95 | 2112-450 ns | 1.95 |
| **4096-5** | **4.50** | 2147-85 ns | 19.95 |
| **MCM 6604 AC** | **4.50** | **2708-450 ns** | **8.95** |
| **AM 9060 CPC** | **2.95** | **2716-450 ns** | **9.95** |
| **4402** | **5.50** | **2732-450 ns** | **49.95** |

**SOUND GENERATORS**

| | | |
|---|---|---|
| SN76477 | Complex Sound Generator | 2.49 |
| AY-3-8910 | Gi Sound Gen. (Add $3.00 for manuall 64 Pgs. | 11.95 |

**UARTS**

| | | | |
|---|---|---|---|
| AY-5-1013A | 3.95 | AY-3-1015A | 5.10 |
| AY-3-1014A | 6.50 | TR1602A | 3.50 |

**LINEAR**

| | | | |
|---|---|---|---|
| | | LM 3401 Series | 1.15 |
| LM 301N-8 | .32 | LM 387N-8 | .99 |
| LM 301AH | .32 | LM 393N-8 | .99 |
| LM 307N-8 | .25 | LM 3909N-14 | .58 |
| LM 307H | .25 | LM 3909N-8 | .99 |
| LM 308H | .75 | LM 7360C-14 | .99 |
| LM 311N-8 | .59 | **LM 741K-14** | **.19** |
| LM 319H | .90 | LM 747CN-14 | .59 |
| LM 320K Series | 1.35 | RC 1556NB-8 | 1.25 |
| LM 320T Series | 1.15 | LM 4250CH | .95 |
| LM 323K | 4.95 | CA 3130T | 2.25 |
| LM 339N-14 | .98 | LM 4136N-14 | .95 |
| LM 340K Series | 1.35 | LM 383T | 1.25 |

**VERBATIM DISKETTES**

5¼" Soft, 10, 16 Pkg. $2.35
Ea. in boxes of 10
8" Soft, Hard $2.75
Ea. in boxes of 10

Verbatim

**DIP SWITCH**

8 Pos. $1.25 ea.
8 Pos. Single Pole Double Throw $1.49 ea.

**SPECIALS OF THE MONTH**
*While Supply Lasts*

| | |
|---|---|
| ECL 10146L RAM 1024X1-29 ns | 6.95 |
| AM 3705 PROMS 8-Ch. Multiplexer | 6.95 |
| 95H90 Hi-Speed Div. 10/11 Prescaler | 10.95 |
| MC16 Dual Opto. Isolator 1500V | .99 |
| AY-5-2376 Keyboard Encoder, 88 Keys | 10.50 |
| AY-3-3600 Keyboard Encoder, 90 Keys | 9.95 |
| 1488 or 1489 Liner Driver/Receiver | .99 |
| 16-Pin Low Profile Sockets End Stackable | .10 |
| DAC 100 8 & 10 Bit A to D Converter | 13.95 |
| **LM337K Adjustable Neg. Volt. Reg. (-1.2 – -37)** | **5.95** |
| 18 Pin Low Profile Socket | .08 |
| 22 Pin Low Profile Socket | .08 |

**HOW TO ORDER** – Pay by check, credit card, or C.O.D. Foreign pay in U.S. Funds. Order by phone or mail $25.00 minimum. Prices valid thru last day of cover date. Shipping – $2.00 for the first 2 lbs. For each add. 2lbs. add 1 lb. Fee and .50 for each add'l lb. Foreign – Add 10% - for shipping and handling. C.O.D. add $1.85. Guaranteed satisfaction or your money back. We reserve the right to limit quantities. Some items subject to prior sale. We are not responsible for typos.
SEND FOR OUR FREE FLYER Contains complete list of 74LS00 IC's.

**Components Express, Inc.**
1380 E. Edinger, Unit PE
Santa Ana, CA 92705
(714) 558-3972
*"Have you kissed your computer lately?"*

CIRCLE NO. 10 ON FREE INFORMATION CARD




*(Continued from page 14)*

microcomputer users ever dream of.

Digital audio discs will probably be using that output long before computers are. But don't be too sure. The one laser-based audio disc system I've seen concrete proposals on is Philips' Compact Audio Disc. It uses the same technology but is incompatible with the current video disc players. Should the industry choose that (and Sony is already backing it), the digital audio outputs on the Pioneer video player won't be much use—which Pioneer admits: "We don't know where the industry is going—nor does anybody else—but we wanted to leave as many options as possible open . . ," says Pioneer's John Talbot.

If all this leaves you a bit confused, you're not alone. So are the manufacturers. Sansui, for example, while announcing its VHD disc player (with provision for VHD-compatible AHD audio discs which have three digital sound channels plus still pictures), also announced that it's conversant with both RCA's CED videodisc system and the Philips Compact Disc audio system, and could produce either (or both) if the market seemed to warrant it. —*Ivan Berger*

## New Sonic Hologram

THAT the Carver Sonic Hologram is now available separately as Model C-9 for a suggested retail price of $279 is news, but not news that would normally make this column. What's chiefly of interest is that the new model incorporates newly revised circuitry meant to overcome some of the limitations of the early version.




First, solipsism has been banished; you can listen to the new hologram along with friends. The cross-fed, delayed signal has been recalibrated so that, in addition to a central position that receives an intense holographic image, there are two flanking positions where the image is almost as good. Flipping a switch optimizes the unit once again for a solitary, centrally located listener.

Second, frequency response has been improved. The comb filtering that is the inevitable consequence of mixing delayed and undelayed versions of the same signal has been reduced, according to Carver, to where the ripple is on the order of 1 dB. Also, the unintended bass boost introduced by the earlier circuit has been removed.

Listening tests essentially confirm Carver's claims for the C-9. Bass is better, and when the device is set to produce a wide listening area, seating position seems almost noncritical. The effect is at times startling. It is easy to sit in one of the flanking positions without paying particular attention and be shocked at the piano that (acoustically, at least) seems to have materialized in your living room. The only oddity I observed is some image shifting when you move your head between, say, a flanking position and the center position. An added bonus is that the new hologram banishes the "in-the-head effect" in headphone listening.

Recently, the new hologram circuit has been included in the C-4000 preamp/control center. Owners of older C-4000s will be pleased to know that a retrofit of the new hologram is available for $65.—*Harold A. Rodgers*

# AUDIOPHILE RECORDINGS

**By Harold A. Rodgers**
**Executive Editor**

JOHN WILLIAMS: ***The Empire Strikes Back*** (symphonic Suite from the Original motion picture score). National Symphonic Orchestra conducted by Charles Gerhardt. Chalfont SDG 13 (dbx PS-1018). Judging by public acceptance rather than by effects from musical academia, the suite distilled from a motion-picture score is at least arguably the 20th century's principal invention in musical form. While there are those who would dismiss it as "mass-market" art, film music has been composed by figures as august as Copland and Prokofiev.

This should not be interpreted as an apologia for the music of John Williams for none is necessary. *The Empire Strikes Back* is dynamic, listenable, and even more impressive on its own, freed from visual distractions and sound effects. Williams has obviously absorbed many of the 20th-century musical practices that were once hailed or condemned as "avant-garde" and uses them in a way that is above all accessible and communicative. Yet there is no need for the musical sophisticate to despair, for the work is original and musicianly.

The sound of the disc is worthy of its digital mastering, and the prodigious dynamic range provided via dbx encoding lets the energetic and powerful reading given by the performing forces come through in the listening room.

# THE FIRST HIGH GRADE VIDEOTAPE.

Video cassette recorders have changed a lot in the last few years. New features like six-hour recording, slow motion and freeze frame have added a great deal to home recording.

But there's one drawback. To utilize these new features, you must operate your cassette recorder at a slower speed. And this places increased pressure on the videotape, which can cause the magnetic oxide particles on the tape's surface to loosen and eventually fall off. Once this starts to happen, a loss of picture quality isn't far behind.

At Maxell, we've always been aware that a video cassette recorder can only be as good as the tape that goes in it. So while all the video cassette recorder manufacturers were busy improving their recorders, we were busy improving our videotape.

The result is Maxell Epitaxial HG, the first high grade VHS videocassette. In technical terms, there are several significant differences between our high grade and regular videotape.

For one thing, our oxide particles are smaller and more densely packed on the tape surface. Which is why we have a better frequency response and signal-to-noise ratio, especially at the slower recording speeds.

And, because of our unique binding process and calendering system, the oxide particles on Maxell HG stay put. This drastically reduces friction and video recorder head wear. So not only will you get better picture quality, but you'll be able to enjoy it a lot longer.

All in all, no other home videotape can deliver better color resolution, sharper images or cleaner sound than Maxell HG.

So if you own a VHS recorder, please remember one thing. If you want high grade picture quality, you need a high grade tape.

**maxell**

IT'S WORTH IT.

Maxell Corporation of America, 60 Oxford Drive, Moonachie, N.J. 07074

CIRCLE NO. 40 ON FREE INFORMATION CARD

# AMERICA'S, MOST SOPHISTICATED SCANNER IS ALSO THE EASIEST TO PROGRAM SCANNER.

*Presenting the Bearcat® 300 Scanner with Service Search.*

*It's like having a frequency directory already pre-programmed in your set—to let you tune in all the action at the touch of a button.*

The incredible. 50 channel Bearcat 300 Scanner with Service Search is another first in scanner innovation. Another triumph in synthesized spaceage technology. Another first from the leader in real excitement.

Over 2100 active frequencies are pre-programmed into the Bearcat 300 Scanner memory bank. These frequencies are arranged in eleven service categories, as allocated by the F.C.C.

Simply push the police service button, for example. You'll search and find only the frequencies allocated to police—and be able to monitor every local, active frequency. Then they are programmed into the normal scan operation via keyboard entry.

It's that easy. That automatic for every service category—fire, marine, HAM, emergency, air, etc. It's truly like having a frequency directory already pre-programmed in your set.

The 50-channel Bearcat 300 Scanner brings you every feature you've ever wanted, and then some. 7-band coverage, AM/aircraft and FM. Patented Track Tuning. Automatic squelch. Priority. Automatic lockout. Activity count. Selective scan delay. Direct channel access. Digital display, and a lot, lot more—even a digital clock, and mountings for mobile operation.

The Bearcat 300 Scanner. Possibly the ultimate Scanner. Certainly the most automatic, easiest to use Scanner ever.

Now that's real excitement.

# BEARCAT® 300 SCANNER.

***Step into tomorrow with Number One.***

Electra

Copyright 1980 Electra Company, Division of Masco Corp. of Indiana.
300 E. County Line Road South, Cumberland, Indiana 46229

CIRCLE NO. 19 ON FREE INFORMATION CARD

# Audio Product of the Month

**CHOSEN BY THE EDITORS OF POPULAR ELECTRONICS**

# *Luxman K-8 Stereo Cassette Deck*

## Flexible operation and tasteful styling

SOLENOID-OPERATED tape transport controls and full compatibility with metal tapes as well as conventional formulations are included in the two-head, single-motor K-8 cassette deck from Luxman. Among its operating conveniences are fast-responding fluorescent peak level indicators, light-touch transport control buttons, timer-controlled operation in both recording and playback modes, and several automatic play/rewind functions. The tape index counter is a highly legible, three-digit fluorescent display. Microphone inputs can be substituted for the line inputs (but not mixed with them), and unwanted noises can be deleted by muting the recording temporarily without stopping the tape.

The Luxman K-8, with a suggested retail price of $499, is housed in a wood-grain veneered cabinet with pale gold-colored panel and knobs and measures 17¼″ W × 11¼″ D × 4¼″H. Its weight is 13.2 lb. A plug-in remote-control accessory is available for $100.

**General Description.** Access to the cassette well is gained by pushing a button at the upper left of the front panel. Most of the cassette, which is backlighted, can be seen through the transparent door while in operation. If Luxman cassettes are used, it is possible to minimize azimuth error from a tape made on another machine by adjusting tape skew with a small screwdriver through a hole in the cassette door.

Tape-transport controls are flat "feathertouch" buttons that operate solenoids through logic circuits. These enable switching from any mode to any other without use of the STOP button. The tape normally does halt before changing speed or direction, but that happens automatically. It is possible to make a "flying start" recording while playing a tape, by holding in the PLAY button and pressing the RECORD button.

Each time the recorder is turned on, the counter resets to 000, unlike mechanical index counters. Manual reset can be accomplished by pressing a small button. Another button activates the memory circuit, which causes the tape to stop at a 000 index reading when in rewind mode. Arrows near the index numerically indicate tape motion.

The level indicators are a pair of blue, fluorescent 12-segment horizontal lines. Each channel is calibrated from −20 dB to +5 dB (the segments are solid below 0 dB and outlines above 0 dB). When the deck is set for metal tape, the range of the display is extended to +8 dB.

Two three-position lever switches select bias and equalization. Each has positions marked NORM, $CrO_2$, and METAL. Basic bias settings can be altered by ±10% via a center-detented vernier control. The switch for the Dolby noise reduction system has an OFF and two ON positions, one of which engages a MPX filter to remove any 19-kHz pilot carrier that might remain in the audio from an FM tuner. Recording levels are adjusted by two concentric controls coupled by a slip clutch, and a single knob sets the playback output level. Another three-position switch selects MIC or LINE inputs or a spring-loaded REC MUTE position that kills the signal to the record head. This does not remove the incoming signal from the line outputs or affect the readings of the level indicator. Front-panel microphone jacks (for medium impedance dynamic microphones) are provided, with a headphone jack.

Automatic operation under timer control is possible using a small rotary knob switch. It chooses between normal operation, timer-controlled playback, timer-controlled recording, and three automatic modes: PLAY, REWIND, and REPEAT. Touching the REWIND button when PLAY has been selected causes the tape to rewind to its beginning (or to 000




*Frequency-response curves for three different types of tape.*

if the MEMORY button is engaged) and go into play automatically. The REWIND position causes the tape to rewind automatically when it reaches its end, stopping either at 000 or its beginning. The REPEAT mode is similar except that play begins again when the beginning reference point has been reached.

Sendust record/play and erase heads are used in the K-8 along with a direct-coupled recording amplifier—an unusual touch in a cassette deck. "Analogue switches," presumably solid-state devices such as FETs, are used for various control functions. With these, the leads routed to front-panel controls handle only dc signals and cannot degrade the audio.



*Spectrum-analyzer photos of two-tone IM distortion tests. Input signal consisted of equal amplitude tones at 14 and 15 kHz, each at a −16-dB level. Top to bottom are results on TDK AD, TDK SA-X, and TDK MA tapes.*

Specifications of the K-8 include record/playback frequency response (±3 dB) from 30 Hz to either 15,000, 18,000, or 20,000 Hz (normal, $CrO_2$ and metal tapes respectively). The corresponding S/N ratios (with Dolby) are 60 to 65 dB. The rated flutter (wrms) is 0.055%.

**Laboratory Measurements.** Lacking specific recommendations—other than an implication that Luxman tapes (not widely available) were suitable—we measured record/playback frequency response with a number of tape formulations. For NORMAL (normal bias, 120 μs EQ) tape, we used TDK AD and OD, Maxell UD-XL I, and Fuji FX-I. The $CrO_2$ (high bias, 70 μs EQ) tapes were TDK SA-X, Maxell UD-XL II, and Fuji FX-II, and metal tapes were TDK MA, Maxell MX, and Fuji Metal.

Although good results were obtained with all the tapes, our curves suggested that the recorder had been set up for TDK tapes, and we used them for our subsequent testing. All the others gave a slightly drooping high-end response, suggestive of a slight overbias. The BIAS FINE control was found to vary response above 10 kHz by about ±1 or ±2 dB, enough to flatten out the response curves from the Maxell and Fuji tapes. Measurements were made with this control centered.

Response with TDK AD was within ±2 dB from 20 to 16,500 Hz at −20 dB, with the 0-dB curve dropping off above 7,000 Hz to intersect the −20 dB curve at 12,500 Hz. OD tape was close but not quite as good at high frequencies. TDK SA-X delivered a response, within ±0.5 dB from 37 to 17,000 Hz and −3 dB at 20 and 18,500 Hz. Intersection of the 0-dB and −20-dB curves occurred at 13.8 kHz. Metal tape (TDK MA) was almost identical in response to SA-X (±0.5 dB from 40 to 17,500 Hz), but its dramatically better high-frequency characteristics were demonstrated by the fact that the 0-dB curve was still 12 dB above the −20-dB curve at 20 kHz.

Playback equalization was measured with TEAC 116SP (70 μs) and TDK AC-336 (120 μs) test tapes. Data from both lay within ±1 dB over the full range (40 Hz to 10,000 or 12,500 Hz respectively). Dolby tracking was superb. From −20 dB to −40 dB, the Dolby system affected the response curves by less than 1 dB at any frequency in a record/playback measurement. The MPX filter gave a flat response to about 12,000 Hz, rising to a +1.5 dB peak at 14,500 Hz and cutting off sharply. By 17,000 Hz, output was down more than 25 dB, and was negligible at higher frequencies.

For a 0-dB recording input, a LINE signal of 76 millivolts or a MIC signal of 0.17 millivolts was required. Overload of the MIC inputs occurred at a rather low 16-millivolt input. Playback output from a 0-dB signal was between 1.14 and 1.3 volts, depending on the tape being used.

# DISCWASHER® AUDIOSCIENCE™ SERIES

## Record Care, Part 2: A Record Life Study

How long will your phonograph records last?

How many times can you safely play records without degrading sound quality?

Using quality playback equipment, the factors of Record Longevity are twofold and closely interrelated: the record must be kept free of contamination, and the stylus must be kept clean during playback.

Scanning electron microscopy clearly shows the need and contribution of both record cleaning and stylus care.

Exhaustive research shows that with proper record/stylus care, an entire "life span" of 200 play events will not damage record surface quality or fidelity. (Most albums are played a total of 50 times or less.)

200 Plays Without Record Cleaning



Pit from dust abrasion.

Ground-in microdust.

Prominent dust abrasion.

200 Plays Without Stylus Care



Prominent stylus path from abrasive-coated diamond face.

Vinyl particles welded by contaminated upper area of stylus.

200 Plays With Record and Stylus Care



Results of D4 Record Care:

Clean central radius due to capillary attraction of D4 Fluid into D4 pad fabric.

Microdust-free stylus path due to exclusive D4 "spiral fiber" particle holding.

No wall-slurry of "lubricant" products.

Results of SC-2 Stylus Care:

Reduced wall abrasion due to uncontaminated diamond face.

Cleaned stylus leaves no welded-in particles.

There is no substitute for the valid research you get with Discwasher products. Ask for them where better dealers take interest in a longer "life span" for you.

**discwasher®**
PRODUCTS TO CARE FOR YOUR MUSIC

Discwasher, Inc., 1407 N. Providence Rd., Columbia, MO 65201

CIRCLE NO. 17 ON FREE INFORMATION CARD

Playback distortion (third harmonic of a 1,000-Hz signal) at 0 dB input was about 0.8% with AD and MA and 1% with SA-X. Reference distortion of 3% required an input of +5 dB with AD and MA, and +4 dB with SA-X. The S/N relative to those levels, with CCIR/ARM weighting and Dolby on, was about 68 dB for AD and SA-X, and about 65.5 dB with MA.

The effect of tape type on distortion is shown in the spectrum-analyzer photos from two-tone IM distortion tests. Using an input signal consisting of equal amplitude tones at 14 and 15 kHz, each of them at a −16-dB level (so that their combined peak was equivalent to a −10-dB sine-wave input), playback output was displayed on the 0-to-20,000-Hz scan of the analyzer. TDK AD gave the lowest output from the two high-frequency tones, with the third-order IM products at 13,000 and 16,000 Hz suppressed by only 10 to 11 dB. The second-order difference component, at 1,000 Hz, was down 53 dB relative to the recorder's 0-dB level. TDK SA-X gave reproduced tone levels 3 to 4 dB higher than AD tape, and its IM products were about 16 to 17 dB below the tones. The 1,000-Hz distortion product was at −64 dB. Although TDK MA produced playback test tones only 1 or 2 dB higher than SA-X, third-order distortion products were down a full 33 dB. The 1,000-Hz product was about the same as with SA-X, and may well represent the distortion of the playback amplifier rather than tape nonlinearity, which normally creates only odd-order distortion products.

The level indicators responded instantaneously to program peaks or short tone bursts, and a standard Dolby level tape gave a +1-dB indication on playback (the Dolby calibration mark was at 0 dB). Crosstalk from right to left channel at 1,000 Hz was −55 dB, and headphone volume was excellent, even with high-impedance phones. Tape speed was 1.8% fast, and in the fast-wind modes, a C-60 cassette was moved from end to end in 75 to 81 seconds. JIS flutter (wrms) was 0.05% and the weighted peak flutter was ±0.08%. Except for a single component at 30 Hz, most of the flutter was below 15 Hz.

**User Comment.** To judge the quality of a cassette deck audibly, we record interstation hiss from an FM tuner at various levels and compare the playback to the sound of the original. Even slight high-frequency tape saturation will cause a pronounced dulling of the sound in a playback, so that few recorders give accurate playback when noise is recorded at 0 dB (and many cannot do it at −20 dB). In our tests, tapes used behaved just about as their measured performance would suggest. TDK AD was nearly perfect at −10 dB, but had noticeable dulling of the extreme highs at 0 dB. At 0 dB, TDK SA-X matched the performance of AD at −10 dB, and MA was essentially perfect at 0 dB.

It must be realized that these levels were true peak readings, which gives the K-8 a tactical advantage over other machines that use slower, average-reading meters. If one were to record at a 0-dB indicated level with such meters, the peaks would be considerably higher and would cause more high-frequency tape saturation.

On the basis of our listening tests, the Luxman K-8 is capable of true high-fidelity performance. Dubbed program material coming out of it sounds just like what went in, although some types of live material can exceed the recorder's capabilities or overload the mic inputs.

In use, the deck is an unalloyed pleasure. Minor or rarely used controls are located on the front panel, but with very small knobs that avoid a cluttered appearance while preserving operational flexibility. The styling, thus, is at once tasteful and functional. Such niceties as the flying-start recording capability, the REC MUTE, and the automatic and timer operated modes help to distinguish this unit even more.—*Julian D. Hirsch*

CIRCLE NO. 101 ON FREE INFORMATION CARD


ΩMEGA SALES CO.

"WHOLESALE COMPUTER PRICES" DIRECT TO THE PUBLIC
12 Meeting St., Cumberland, RI 02864

PRODUCT SPECIAL of the MONTH!!

Diablo 630
$1995
$2195 (with tractor feed)



Products are NOW IN STOCK AT ΩMEGA SALES CO.

ΩMEGA OFFERS THE BEST DELIVERY AND PRICE ON:
APPLE • ATARI • TRS-80 Model II • INTERTEC •
DIABLO • EPSON • HEWLETT-PACKARD • SOROC •
COMMODORE • NEC • QUME • CENTRONICS



Intertec Superbrain
32K Ram - $2649
64K Ram - $2649

NEC spinwriter
5510-5530 - $2449

Epson MX-80 - $599

Atari 800 - $769

APPLE II 16K $ 949
48K $1099

Televideo
912 B or C — $699
920 C — $769

| | | | |
|---|---|---|---|
| 730-3 | $ 599 | Centronics (limited quantities- call for availability) | 779-II $ 749 |
| 737-1 | $ 699 | | 704-9 $1500 |

CALL TOLL FREE FOR ΩMEGA'S PRICE!
1-800-556-7586

ΩMEGA sells only quality merchandise to our customers.
ΩMEGA will try to match any current advertised price with similar purchase conditions. Before you buy anywhere else — be sure to call ΩMEGA Sales Co.
1-401-722-1027

VISA

ΩMEGA ships via UPS, truck, or air. COD's,
Visa, Mastercharge accepted, with no service charge.

# The Guard is America at its best.

You can't train somebody to be a hero. And the Army Guard people on this page would be the last to label themselves that.

But it was Army Guard people like these who flew into the teeth of a devastating blizzard last winter to save a farm family that had become trapped by the big snow. And it's Army Guard people like these, working in their own communities, who have helped their neighbors and friends to survive everything from floods to blizzards to tornadoes.

Put Army Guard people in situations like those and they perform at their flat-out best.

In the Army Guard, you're ready to meet any kind of challenge head-on. The training is geared to develop important human skills that work hand-in-glove with military readiness.

You'll join your friends and neighbors who train at home.

But it won't just happen. You've got to do something first. Rip out the attached postcard, fill it out and mail it in. Better yet, call us right now. It's toll-free and won't cost a penny. The number is 800-638-7600.* Or see your Army Guard recruiter. He has the whole story. Ask about the benefits that can last a lifetime and the money you'll earn.

Then get on the Guard team. And be your best.

*In Hawaii: 737-5255; Puerto Rico: 723-4550; Virgin Islands (St. Croix): 773-6438; Maryland: 728-3388; in Alaska: consult local phone directory.

**CIRCLE NO. 45 ON FREE INFORMATION CARD**

ARMY NATIONAL GUARD

The Guard belongs.

# Here's the easy way to write your own programs.

**Heathkit Self-Study Courses give you a complete command of computer language, so you can write the programs that do your specific tasks. Choose from four programming languages.**

### Easy, step-by-step learning

You learn at your own pace, performing exercises on your computer and following a clearly written and illustrated text. Tests at the end of each unit assure your understanding before proceeding to the next unit. In most courses your reading is reinforced by cassette tapes, so you *see and hear*, for more thorough learning.

### Hands-on programming exercises

You learn by doing, not just reading. Special exercises guide you through the steps of designing and writing your own programs for your computer. Upon completion of the courses you'll be able to tailor existing programs to your specific needs, or write your own original programs from scratch.

### Recommended for college credit

Many Heathkit Courses are now recommended for college credit by the American Council on Education. If you can't go back to college, now you can bring college home to you.

### Free Heathkit Catalog

Details and prices on the complete line of Heathkit Self-Study Courses on computer and electronics subjects are in the new, free Heathkit Catalog. Send for yours today or pick one up at your nearby Heathkit Electronic Center.

**FOUR HEATHKIT PROGRAMMING COURSES**

BASIC™: easiest-to-learn, hobbyist's language
PASCAL™: sophisticated, easy-to-use language
COBOL™: the businessman's language
ASSEMBLY: very efficient, very precise language
Coming soon: FORTRAN™ and Microsoft™ BASIC™

**Send for free catalog**
Write to Heath Co., Dept. 010-754, Benton Harbor, MI 49022.
In Canada, write Heath Co., 1480 Dundas Highway East, Mississauga, Ontario, L4X 2R7.

**Visit your Heathkit Store**
Heathkit products are displayed, sold and serviced at 62 Heathkit Electronic Centers in the U.S. and Canada. See your telephone white pages for locations.
In the U.S., Heathkit Electronic Centers are units of Veritechnology Electronics Corporation.

**Heathkit®**

CIRCLE NO. 28 ON FREE INFORMATION CARD

ED-159

# Popular Electronics Tests *the Pioneer Model VP-1000 Videodisc Player*

**LaserDisc system connects directly to TV receiver and offers remote control with pause and freeze-frame**

GATHER up 65 integrated circuits, 188 transistors, a 2-kilovolt helium/neon laser, precision lenses, and a two-speed turntable motor, put them all together in an attractive tan and walnut plastic package weighing 38.6 lb, and you have Pioneer's marvelous videodisc player. It uses a laser optical system licensed by N. V. Philips and is designed to play videodiscs of the MCA DiscoVision and now 3M labels.

Pioneer's system offers all the features available with the Philips/Magnavox player plus a full-feature remote-control system, pause and freeze-frame capabilities, and on-screen display of both chapter and frame numbers.

The player connects directly to the vhf antenna terminals of any TV receiver and optionally to the inputs of a stereo amplifier. Any disc can be played without interruption from beginning to end in a one-button operation, or any desired portion of a disc can be played simply by keying in its chapter (and/or frame) number. You can also fast scan or play back in slow motion in either direction. Sound reproduction can be in full stereo or in mono left or mono right. Finally, the two-speed player offers up to 30 minutes viewing time per disc side in standard play or up 60 minutes per side in continuous nonstop extended play.




*Fig. 1. Diagram showing the path of the laser beam as it is reflected on to the disc and back again to photo diode.*

Housed in an attractive tan and walnut-grain plastic enclosure, the player measures 21⅝"W x 16"D x 5⅝"H and weighs 38.6 lb. Suggested retail price for the player is $749. The optional Model RU-1000 remote-control unit lists for $50.

**General Description.** Audio and video information are encoded on the disc as a series of microscopic indentations laid down in a spiral. The segment of the spiral scanned in one disc revolution is called a track and represents one video frame. Tracks are separated from one another by only 65 millionths of an inch (1.6 micrometers), but they contain all required intelligence for 8.1 MHz composite video, in addition to dual-channel (practically no crosstalk) sound. Each track is 0.4 micrometer wide. The discs have a surface of reflective material and a transparent outer casing. Minor scratches on the transparent layer do not degrade reproduction. Current prices for single recordings are $5.95, and those for multi-record albums range from $15.95 for older releases to $24.95 for more recent feature films.

When the player operates, red light emerges from the laser as a linear cone to the first and second fixed mirrors (Fig. 1). These change its directions and adjust the optical axis to the desired position on the grating. There, the beam's center is split into several parts, of which two are used to read tracking signals while the center, or zero-order, beam reads the FM and focus signals. The other residuals around the circumference are at lower energy levels and have no effect.

The three remaining beams now enter the diverging lens where they converge again on a focal point and continue as a pencil of rays into a prism that passes P-polarized, or parallel, light, but rejects S-polarized, or perpendicularly polarized, light. The ¼-wave plate following adds a 90° phase lag and changes the polarization to circular. Tracking and tangential mirrors then take the beams to the objective lens, where the pencil of rays is focused as an extremely fine spot on the signal (reflective) surface of the disc. A focus servomechanism keeps this spot constantly aligned with the disc's signal track.

Light impinging on millions of disc pits is reflected back through the objective lens, the path-altering tangential and tracking mirrors, and the ¼-wavelength plate. Once more there is a 90° phase lag, producing a total 180° phase alteration from the starting phase, and linearly P-polarized parallel light again emerges through the prism, with S-perpendicular light excluded. Light beams, thereafter, reach the cylindrical lens and the photo diode; and it is the photo diode that transforms the optical information into electrical signals.

The same signals also contain information from the FM focus and tracking beams (Fig. 2). When radial beams A and C are identical in value, they are on proper track and the zero-order beam is precisely on center. But when these two first-order beams are not equivalent, a difference output develops and is used by the tracking servo to correct the tracking mirror. The tangential mirror, whose changing angles derive from the video circuits, will correct any errors in disc revolutions, distortions, and concentricity. The laser and all optics are mounted on a motor-driven slide assembly that passes beneath the video disc as playback proceeds.

*(Text continues on page 40)*




*Fig. 2. Optical information is converted into electrical signals for the audio, video, and tracking systems. (Figure 3 is on page 34)*

# We've got it all together.

Weller

Weller

Xcelite

Wiss

## Boker
## Crescent
## Lufkin
## Nicholson
## Plumb
## Weller, Wiss
## Xcelite

Lufkin

Nicholson

Crescent

Boker

Take a good look round this ad and you'll agree that "All together" is no exaggeration. Whether you're making or mending, cutting or joining, striking, measuring or stripping, there's a Cooper tool that's just right for the job. Don't take chances on tools. Specify Cooper and get 'em right the first time!

Plumb

# from Cooper The Toolmaker.T.M.

COOPER INDUSTRIES

**The Cooper Group**

BOKER "CRESCENT" LUFKIN "NICHOLSON" PLUMB "WELLER" WISS "XCELITE"

P.O. Box 728, Apex, North Carolina 27502. Tel: (919) 362-7510 Telex: 579497

CIRCLE NO. 13 ON FREE INFORMATION CARD




*Fig. 3. Block diagram of the control system for the video disc player. Electronic circuits are contained on 15 separate boards. (See text on page 40)*

# $7·95* WSU-30M

NEW WIRE-WRAPPING TOOL DOES ALL

The new WSU-30M "Hobby Wrap" tool performs the complete wire-wrapping function. First, the tool wraps 30 AWG (0.25mm) wire onto standard .025 inch (0.6mm) square DIP Socket Posts. In addition, the tool also unwraps and, finally, it strips 30 AWG wire nick-free.

WSU-30M makes a "modified" style of wrap, in which approximately 1½ turns of insulated wire are wrapped in addition to the bare wire for purposes of added mechanical stability. Designed for the serious amateur, the WSU-30M features compact, all metal construction for years of dependable service. This unique tool is remarkable value performing the work of three separate tools at a fraction of the cost.

WIRE WRAPPING-STRIPPING-UNWRAPPING TOOL

The compact, inexpensive WSU-30 "Hobby Wrap" Tool does the job of three tools at a fraction of their comparable prices. The tool wraps, unwraps, and even strips wire thanks to a unique built-in stripping blade. Designed for use with 30 AWG (0.25mm) wire on standard .025 inch (0.6mm) DIP Socket Posts. Takes minutes to learn to use; makes perfect connections in seconds without solder.

**WSU-30**
**$6·95***

**OK Machine & Tool Corporation**
3455 Conner St., Bronx, N.Y. 10475 U.S.A.
Tel. (212) 994-6600 Telex 125091

*Minimum billings $25.00, add shipping charge $2.00
New York State residents add applicable tax


CIRCLE NO. 48 ON FREE INFORMATION CARD

# Now NRI takes you inside the new TRS-80 Model III microcomputer to train you at home as the new breed of computer specialist!

**NRI teams up with Radio Shack advanced technology to teach you how to use, program, and service state-of-the-art microcomputers.**



It's no longer enough to be just a programmer or a technician. With microcomputers moving into the fabric of our lives (over 200,000 of the TRS-80™ alone have been sold), interdisciplinary skills are demanded. And NRI can prepare you with the first course of its kind, covering the complete world of the microcomputer.

## Learn At Home in Your Spare Time

With NRI training, the programmer gains practical knowledge of hardware, enabling him to design simpler, more effective programs. And, with advanced programming skills, the technician can test and debug systems quickly and easily.

Only NRI gives you both kinds of training with the convenience of home study. No classroom pressures, no night school, no gasoline wasted. You learn at your convenience, at your own pace. Yet you're always backed by the NRI staff and your instructor, answering questions, giving you guidance, and available for special help if you need it.



## You Explore the New TRS-80 Model III Inside and Out

NRI training is hands-on training, with practical experiments and demonstrations as the very foundation of your knowledge. You don't just program your computer, you go inside it…introduce and correct faults…watch how circuits interact…interface with other systems…gain a real insight into its nature.

**Training includes new TRS-80 Model III microcomputer, solid state volt-ohm meter, digital frequency counter, and the NRI Discovery Lab with hundreds of tests and experiments.**

You also build essential test instruments like a solid state volt-ohm meter and CMOS digital frequency counter. You work with the exclusive NRI Discovery Lab, performing over 60 separate experiments in all. You learn how your troubleshooting tools work, and gain greater understanding of the information they give you.

## Advanced Technology Microcomputer Is Yours to Keep

As part of your training, NRI sends you the new, state-of-the-art TRS-80 Model III microcomputer. This functional unit is complete with 65-key keyboard and 12" display in one desk-top unit. It features built-in interface and commands for optional printers, housing for optional disc drives, and high-speed cassette loading. It's 4K RAM is internally expandable to 16K or 32K and its BASIC language is compatible with most Model I software.

Along with volt-ohm meter, frequency counter, and NRI Discovery Lab, this latest concept in microcomputers is yours to learn with, yours to keep and use for your own personal programs, business use, and other applications.

## Send for Free Catalog…No Salesman Will Call

Get all the details on this exciting course in NRI's free, 100-page catalog. It shows all equipment, lesson outlines, and facts on other electronics courses such as Complete Communications with CB, TV and Audio Servicing, Digital Electronics, eleven different interest areas in all.



Send today, no salesman will ever bother you. Keep up with the latest technology as you learn on the world's most popular computer. If postcard has been used, write to NRI Schools, 3939 Wisconsin Ave., Washington, D.C. 20016.

**NRI Schools**
McGraw-Hill Continuing Education Center
3939 Wisconsin Ave.
Washington, D.C. 20016

(TRS-80 is a trademark of the Radio Shack division of Tandy Corp.)

*(Continued from page 32)*

The two-speed turntable motor operates at a constant 1800 rpm on standard play or 600 to 1800 rpm on extended play. Separate CAV (constant angular velocity) and CLV (constant linear velocity) LEDs indicate which type of disc is being played. Freeze-frame capability is possible only with CAV discs. In the fast-forward mode, one track is jumped at the end of each field, and a still picture results when the same track is repeated. In the search mode, hundreds of tracks are skipped.

Electronics for the VP-1000 are contained on what appear to be 15 separate divisions or boards having such identifications as VDEM, AUDB, SPDL, FTSB, LOGB, KEYA, etc., meaning video, audio, spindle and drives, focus tracking, logic for tracking, and key control, respectively. Schematics and wiring diagrams, along with adjustment instructions, are liberally contained in a 139-page service manual, which is both well-written and nicely illustrated. All mechanical sections are shown as exploded illustrations in reasonable 3D. There are also flowcharts for troubleshooting as well as a few logic diagrams.

The Control System (Fig. 3, p. 34) comprises KEYA, KEYB, IRAB, LAMP, and CONT boards, including a microcomputer arrangement that controls the playback modes and helps monitor operation of the entire video disc system. The RU-1000 remote control, with its wired remote control jack, can be used either through the IRAB sensor and amplifier as a completely wireless infrared remote control or plugged into the remote control jack and on to the photo coupler as a *wired* remote unit when noise is a problem. An IR inhibit grounds and defeats the IR remote function when the control is not used. Observe, however, that the photo coupler and key scanner/encoder will function with the N.C. COM plug at the rear of the receiver either in or out.

Upon command, the key scanner and encoder convert the signal into 10-bit serial pulse-code modulation (pcm), which is impressed on a 38-kHz carrier and transmitted back to IRAB and the input comparator. IRAB picks up these wired or wireless remote signals, detects and modifies their waveforms, then passes them to the key decoder. The 10-bit pcm code from IRAB is decoded into a 5-bit parallel binary code for the large data processor. A 455-kHz oscillator serves as clock.

On the other side of the data processor is a phase-locked loop with a 3.02-MHz clock that generates timing frequencies for character dots of the frame number display and uses an external horizontal drive (HD) signal to synchronize frame and chapter numbers on its slave TV screen with horizontal sync. Inputs to the data processor are from the input buffer, microprocessor and data VGP (external).

Through the input buffer, data enters the microprocessor from the lid sensor switch, inside/outside limit switch, and focus and spindle lock, along with r-f information. It also has a control bus from the slow mode VR timer and its shunt potentiometer. The microprocessor is an 8-bit unit with a two-kiloword master program stored in memory. The data processor also governs the decoder driver lamp and LED readouts as well and off/on signals for audio Ch. 1 and audio Ch. 2.




*Fig. 4. Block diagram of the remote control unit. It can be wired direct or use infrared transmission.*

Signal transfer for player to TV receiver occurs after the 2.3-MHz channel 1 (left) and 2.8-MHz channel 2 (right) have been limited and detected, mixed and applied to the output radio frequency (r-f) modulator or pcm jack on the rear. Manual switching selects either stereo or Ch. 1 or Ch. 2 outputs. The video signal is separated from audio on the VDEM board by bandpass filtering and demodulation, then transferred to a rear VIDEO OUT jack on the player as well as the AM video modulator. Included are sync, color burst, and drop-out protection. (The latter provides a means of covering up dropouts caused by dust and scratches on the disc, and appearing as gaps in the FM waveform. A seriously defective line of video is replaced by a previous line so that any signal interruption becomes virtually unnoticed.) The r-f modulator now processes audio and video by combining them on a regulation carrier (channels 3 or 4, in this instance), applying the result to the television receiver.

Remote control is (so far) the VP-1000's big exclusive feature. Its 26 keys deliver 30 different commands to the overall system using a 455-kHz ceramic vibrator matched to a similar oscillator on the key decoder. They duplicate virtually every command on the player itself except REJECT/OPEN and POWER on/off. There are search keys, chapter and frame displays, left/right audio buttons, chapter and frame, pause and play, in addition to still/step, slow, scan, and 3 X fast—the last four in either forward or reverse.

Serial pcm from the code pulse generator passes through a transistor driver (Fig. 4) on to the four LEDs. These consume approximately 1 ampere of peak current and, along with the 455 kHz oscillator, are not operational until some command key is pushed. Transmissions consist of 10-bit words. Each pulse string is generated by 10 clock pulses at the 38-kHz carrier frequency.

Advantages over the competition in this system include the remote control, two control buttons for frame and chapter digital locations rather than one, separate CAV (standard play) and CLV (extended play) lighted indicators, digital keys used in the search mode for frame and chapter location, the PCM jack on the back, and direct antenna and TV connections rather than a separate connector box. Unit operation seems also to be somewhat less mechanically and electronically noisy, although this can vary from sample to sample.

*(Continued on page 42)*

**MODEL VP-1000 VIDEODISC PLAYER LABORATORY DATA**

| Parameter | Measurement |
|---|---|
| Video carrier: | −52.7 dBm |
| Audio carrier: | −61.7 dBm |
| S/N ratio for both carriers: | 50 dB |
| Usable video bandpass: | ≃4 MHz |
| Usable audio bandpass (−20 dB): | ≃80 kHz |
| Power supply varied from 95 to 130 V ac with equipment operating satisfactorily. | |
| Operating power consumption: | 71 W |

*Note: dBm 50 to 75 ohms conversion, decrease reading by 5.72 dB. Also, dBm = dBV − 10 log Z + 30; where Z, in this instance, = 75 ohms. Test equipment used: Tektronix 492 and 7L5 spectrum analyzers and Sencore PR57 Power-rite.*

*"It's about time America gave REACT its full support"*

Robert G. Paul, *President*
*The Antenna Specialists Co.*

# the antenna specialists co. announces a major new REACT support program to help keep our highways safe.

"For more than 19 years, hundreds of thousands of REACT volunteers have been contributing their time, their energy and their own money to provide vital emergency communications services to the public.

"Over 80 million Americans have benefited directly from REACT's CB radio handling of emergencies and calls for assistance. Last year, for example, REACT responded to over *one million automobile accidents—one every 29 seconds, 24 hours a day.*

"There is no finer expression of the American way of helping each other than REACT—and it deserves more than token support.

**A REACT team for every community...**

"As successful and effective as REACT is, its capacity to grow and expand its services has until now been limited. REACT should be expanded drastically. It should implement important new public service programs it cannot now afford. Increase its service to cover *every community in the nation.*

"Even though REACT services are entirely free to the public, it costs a lot of money to organize, train and operate thousands of REACT teams. While some individuals and companies, including ours, have regularly made contributions each year to help support REACT, the simple truth is that REACTers themselves still pay over 70% of this cost.

**It's time America and the CB industry paid their dues!**

"As a citizen and motorist, I am constantly reassured on the highway, knowing that REACT is listening. And as the nation's largest manufacturer of CB antennas, we are grateful for the support we have received through the years from the CB community. Now we are determined to return that support ...to pay *our* dues.

"Some months ago I directed our people to find a way for our company to help REACT in a major way. They came up with a super program, which I have approved and which has the 100% support of all A/S employees:

## 1. the antenna specialists co. will provide massive direct financial assistance to REACT.

Very soon we will be introducing a brand new, professional quality mobile CB antenna. We believe it will be the best performing CB antenna available.

**For every single one of these new antennas purchased during the entire year 1981, A/S will donate a dollar to REACT. This activity alone should generate tens of thousands of dollars in new income to expand REACT. But that's only the beginning...**

## 2. the antenna specialists co. will help increase REACT membership by funding and producing special programs:

**We will sponsor and advertise nationally a first quarter REACT membership drive to bring in new members and form new teams. Cash awards will be made directly to REACT teams achieving the greatest increases in membership...and to REACT Councils helping to establish the most new teams in a state. This is only the first of several special support programs of this type planned for 1981.**

In addition, every CB product package shipped from our factory will carry a brochure describing REACT and its importance to highway safety.

## 3. the antenna specialists co. will exert all possible influence to encourage additional, important industry support for REACT.

**"Our company has budgeted a major effort for 1981 in direct contributions, advertising support, national publicity and special action programs.**

"We hope and believe our leadership and commitment will encourage other manufacturers, distributors, dealers and foundations to join this movement...to make REACT even stronger, to bring its outstanding services to every corner of the nation."

Robert G. Paul

**the antenna specialists co.**

®-"Stripes of Quality"

a member of **The Allen Group Inc.**
12435 Euclid Avenue, Cleveland, Ohio 44106

CIRCLE NO. 4 ON FREE INFORMATION CARD

# AMERICA'S BEST SELLING SCANNER JUST GOT EVEN BETTER.

Look what you get with the Bearcat 210 XL. Exciting, new spaceage styling. No-crystal, pushbutton tuning. New, 18 channel, 6-band coverage of over 6000 frequencies. And features like 2 scan speeds. Automatic Squelch, Search, and Lockout. Direct Channel Access. Selective Scan Delay. And much more. There's never been a Scanner like the Bearcat 210XL.

"TAKE IT FROM A SMART OPERATOR."

BEARCAT 210XL SCANNER $209.

# THE LOWEST PRICED, FULL-FEATURE, BEARCAT NO-CRYSTAL SCANNER EVER.

Bring home all the real excitement of scanning, and save! Bearcat 160 features a smooth, keyless keyboard for all controls including volume and squelch. Has 5-band, 16 channel coverage. Priority, Selective Scan Delay, Automatic Lockout and Search. And much more. Bearcat is number one in scanning.

"TAKE IT FROM A SMART OPERATOR."

BEARCAT 160 SCANNER $189.00

Add $6.00 per scanner for U.P.S. ground shipping in the continental U.S. or $12.00 for U.P.S. air shipping. Send your cashier's check or money order to our address below or order by phone if you have a Visa or Master Charge card. Order today!

COMMUNICATIONS ELECTRONICS™

854 Phoenix □ Box 1002 □ Ann Arbor, Michigan 48106 U.S.A.
Call TOLL-FREE (800) 521-4414 or outside U.S.A. (313) 994-4444

CIRCLE NO. 1 ON FREE INFORMATION CARD







*Fig. 5. Spectrum analysis shows output signal on channel 3 with video carrier on left and audio on right. The S/N of 50 dB is excellent.*




*Fig. 6. Baseband video fills 5-MHz spectrum analyzer "window."*




*Fig. 7. Audio bandpass extends over 80 kHz with drop of 20 dB.*

*(Continued from page 40)*

**Evaluation.** Lab tests usually involve oscilloscope and voltmeter readings. But here you have r-f carriers in addition to baseband video and audio outputs, and that requires spectrum analyzers. Furthermore, the usual 50-ohm impedance analyzer input must be matched to the 75-ohm output of the discplayer, and that results in an addition of 5.72 dB. Nonetheless, absolute levels are not nearly as important in this analysis as relative levels, so a rounded 6 dB difference in scale reading for Fig. 5 really won't matter much. For instance, the video carrier reading of −45 dBm becomes −51 dBm after correction for the 75-ohm termination.

But the important points are the position of this carrier with respect to the audio carrier and the S/N ratio. Here, the channel 3 video carrier rests at 61.25 MHz and the audio at 65.75 MHz, right where it should be. The audio carrier is slightly less than 10 dB below the video carrier, which is close to what we found on a broadcast signal.

Neglecting a few spikes about the video and audio carriers, the S/N ratio is about 50 dB, considerably in excess of the claimed 42 dB. The tallest voltage excursion next to the audio carrier is the 3.58-MHz color burst at −40 dB relative to video.

In the second spectrum analyzer photo (Fig. 6) baseband composite video from the player's output jack was evaluated. Beginning at zero reference on the left, the trace shows, once more, a slight rise around the 3.58 MHz color information, and then a gradual tail-off at 5 MHz. As you can see, the remainder of the waveform, taken during disc operation, is remarkably clean.

Good reports are also forthcoming about the audio output. Here, we're looking at a 100-kHz window, of which some 20 kHz is reference, but the remaining 80 kHz is surprisingly uniform with only a 20 dB drop. The spikes you see at 15-kHz intervals in Fig. 7 (and don't hear) are TV horizontal flyback pulses picked up by the lightly-shielded coaxial connector between player and analyzer. Audio connected to a stereo receiver sounded reasonable, as long as there was good quality stereo sound available for reproduction.

One thing you'll have to be careful about is software quality control. Good discs give positively superb results, but not all of them are good. You'll have to pick and choose carefully. In short, try before you buy!

If there's a negative remark to be made about the VP-1000 player, it's minor: the lid to the turntable section is a little stiff to open. Otherwise, this tastefully styled and nicely engineered product performed exceedingly well. From where we sit, the videodisc is for real and here to stay.—*Stan Prentiss*

CIRCLE NO. 102 ON FREE INFORMATION CARD

# THE AFFORDABLE HOME COMPUTER

# IS NOW ON SALE.

When PMC-80 was first introduced to the United States, the response was overwhelming! The Computer World was ASTONISHED at the QUALITY, as well as the PRICE. In fact, the PMC-80 has almost all the features of America's best selling computer, the TRS-80, but with a price tag of $200.00 less! (SIMUTEK'S price is $275.00 less!)

**Microsoft's Level II Basic and 16K Memory.**

Another reason for all the commotion is that the PMC-80 uses the same, easy to learn, LEVEL II BASIC language that the TRS-80 uses! What does this mean? It means that the PMC-80 can run all the 1000's of programs that have been written for the TRS-80 Level II, 16K computer! Some of the programs available include: Flight simulation, World Champion Chess program, Scores of educational and business programs. Word processing programs and hundreds of other games and simulations.

**The PMC-80 is expandable!**

Your PMC-80 is ready to grow with your needs. Using a special cable, available from Simutek for $35.00, it may be connected to Radio Shack's Expansion interface, to give you up to 48,000 characters of memory, up to 4 disk drives, addition of a telephone communication system, Voice Synthesizer, various printers, a real time clock, as well as plotters and other neat interfaces! As your skills with the PMC-80 improve, you're sure to want some of the ADD-ON's described above. (And these are just a few!)

**Save Money! Use your own television!**

The PMC-80 has a built in RF MODULATOR so you can use your black and white or color TV for a VIDEO MONITOR! A simple hook-up to your television's antenna connector, makes channel 3 your computer's video channel.

**Special Introductory Offer: 25 Free Programs**

SIMUTEK, a leading innovator in Home Computer Software, is making a SPECTACULAR INTRODUCTORY OFFER to people that ORDER the PMC-80 NOW. With each purchase, we will give 25 FREE HOME COMPUTER PROGRAMS! Some of these include: Home Amortization tables program, Loan payment programs, Depreciation rate program, Interest table program, Annuity and Investment calculation programs as well as these great animated games: GRAPHIC-TREK 2000: Command the Enterprise!, INVASION WORG. Stop the invading marauders from space before they take over earth! You command Earth's forces of androids, space fighters, laser guns etc., against the enemy's robots, saucers, proton destroyers, etc!, STAR WARS: Fly your space fighter into the Death Star to destroy it! But watch out, Darth Vader doesn't like you!, SPACE TARGET: A fantastic animated arcade game of skill and daring!, SAUCERS: Can you win win the coveted Medal of Honor?

**Comparison Chart**

| Features | PMC-80 | TRS-80 |
|---|---|---|
| Microsoft's Fantastic Level II Basic | Yes | Yes |
| Full 128 x 48 Graphics | Yes | Yes |
| 16,000 characters memory | Yes | Yes |
| Tape recorder for storing or retrieving programs | Yes | Yes |
| Use your own TV (Save $$) | Yes | No |
| Expandable to 48,000 characters of in computer memory | Yes | Yes |
| Use TRS-80 expansion interface | Yes | Yes |
| Expandable to 4 floppy disk drives (over 100,000 characters of storage on each one!) | Yes | Yes |
| Telephone Communications available: connect to large computers/electronic mail etc. | Yes | Yes |
| 1000's of ready made programs availble for "educational" and "scientific" applications? | Yes | Yes |
| Printers available | Yes | Yes |
| High Speed Z80 CPU | Yes | Yes |
| Interface available for controlling lights and appliances in home | Yes | Yes |
| **Retail Price** | **$645.00** | **$849.00** |

**Here's what you get:**

The PMC-80 microcomputer with 16,000 characters of "In Computer Memory", Microsoft's Level II Basic (in 12K ROM), a cassette player for storing or retrieving programs or data (cassette player is built into the computer!), an RF Modulator for connecting the PMC-80 to your television set, 25 FREE programs so you start using your computer immediately, complete instruction manual, learning manual and owners manual so you can begin writing your own programs right away!

Also available is a special Leedex Video Monitor. Regular price $170.00. Special price to PMC-80 customers $139.95. The resolution of the Leedex Monitor is 10 times better than a regular television.

There is a 10 day money-back guarantee on all SIMUTEK PRODUCTS.

This price is good for a limited time only.

## Order Now Save $50.00

Credit card holders may use our TOLL FREE NUMBER. Or send check for $595.00 plus $10.00 delivery. (Arizona residents add $35.70 sales tax). Please mention this magazine. (No tax on out of state orders).

**Call Toll Free**
**800-528-1149**

In Arizona call 602-323-9391 Collect

**SIMUTEK COMPUTER PRODUCTS**™

4877 E. Speedway Blvd.
Tucson, AZ 85712

TRS-80 is a registered trademark of Radio Shack, a Tandy Corp.

CIRCLE NO. 60 ON FREE INFORMATION CARD

# Popular Electronics Tests




## Beckman Tech 310 Digital Multimeter

THE Beckman Tech 310 Digital Multimeter is designed for both bench and field use. Its features include: large (½" high) LCD display capable of indicating to 1999; autopolarity with either a (+) or (−) displayed; automatic decimal point placement; overrange indication; 29 ranges with seven functions accessed by a single rotary switch; Insta-Ohms, a quick-continuity indicator; 10-amperes ac/dc measuring capability; up to 6-kV transient-voltage protection; semiconductor protecting test voltage; an approximate 2000-hour (about two working years) battery life when using an alkaline battery; and the capability of withstanding a 6-foot drop in accordance with MIL-T-28800. Accuracy is guaranteed for one year.

The Tech 310 measures 6.85" long x 3.65" wide x 1.8" thick and weighs one pound. Suggested retail price is $140.

**General Description.** One interesting feature of the Tech 310 is that the LCD display, function/range switch, and the safety test lead connectors are submerged below the case rim to save them from damage if the instrument is dropped and happens to land face down. Four recessed safety test lead connectors provide the common, volts/ohms, 2-ampere, and 10-ampere inputs. The only control on the instrument is a large-handled rotary switch that not only turns the Tech 310 power off, but selects function and range. (Power is automatically applied when the switch is placed in any function position.) Each alternate function is displayed in a darker shade than the ones on either side, making the switch easy to read. The six functions can be selected by placing the pointer on the switch center bar to ACV (ac volts), ACA (ac amperes), ohms or diode test, DCA, and DCV.

The DCV function provides five ranges from 200 mV to 1500 V. Accuracy is ±0.25% reading +1 digit; input resistance is 22 megohms; normal-mode rejection is greater than 60 dB above 49 Hz; common-mode rejection is greater than 160 dB up to 1500 V; and overload protection is 1500 volts dc or peak ac on any range.

The ACV function provides five ranges from 200 mV to 1000 V with an accuracy of ±0.75% reading +3 digits from 45 Hz to 2 kHz; ±1.5% reading +5 digits from 2 to 5 kHz; and ±2.5% reading +9 digits from 5 to 10 kHz. The conversion technique uses average sensing, calibrated to display rms value of sine wave. Input impedance is 2.2 megohms, shunted by less than 75 pF on all ranges, and overvoltage protection extends to 1000 volts ac (1500 V peak) or 250 V dc above 450 mV on the 200-mV range.

The DCA and ACA provide six ranges from 200 μA to 10A full scale with an average accuracy of ±1% reading +1 digit. The voltage burden is 250 mV on the 200-μA to 200-mA ranges, and 700 mV on the 2- and 10-ampere ranges. Overcurrent protection is provided by a 2-ampere fuse on the 2-A range and the circuit is protected to 20 amperes on the 10-A range.

There are six resistance ranges from 200 ohms to 20 megohms full scale with the Insta-Ohms continuity indicator (a Greek omega) coming on within 100 ms of a test lead short. Test current ranges

# Albia Electronics

# NEW...

## LOW COST CAPACITANCE METER MODULE!!

NOT A KIT




**$49.95** Includes Warranty

INSTANT ORDER INFORMATION BELOW!

Completely assembled and tested . . . for only

Connect this high-quality Albia Capacitance Meter Module Model DM-8 to your digital multimeter and turn it into a Digital Capacitance Meter — the low cost way!
- — Push to read range (button) from 1 pf to 20,000 µF.
- — Zero calibration control
- — In one easy to use, self-contained package
- — Battery powered (with "push to read" battery saver)

**IN STOCK! IMMEDIATE DELIVERY!**

## LOW COST HIGH FREQUENCY COUNTER

NOT A KIT

The Albia Model DM-7, 8 Digit High Frequency Counter is easy to use, switch selectable time base input by a single BNC, nothing to build — nothing more to buy!
- — 5 Hz to 550 MHz
- — 8 big easy-to-read .43" high intensity LED display
- — Crystal (±3 ppm @ 25°C) controlled 0.1 or 1.0 sec. gate times
- — Convenient benchtop size (7"x10"x3") durable attractive case

**NEVER BEFORE AT THIS LOW PRICE . . . . . $119.95** Includes Warranty

**COMPLETELY ASSEMBLED • PRE-CALIBRATED • PRE-TESTED**

NOT A KIT

INSTANT ORDER INFORMATION BELOW!

### NEW ALBIA DESIGN-MATE CIRCUIT DESIGNER

Albia Quality Hardware — your ideas — not a kit — pre-wired pre-tested — don't let this price fool you, this is a high quality, high IC capacity, portable self-contained circuit designer — includes:
- — Control switches and buffered LED logic indicators.
- — Plug in your IC's into solderless breadboards, tie in power and ground, connect your logic switches and LED indicators — FAST, EASY TO USE!
  - — All interconnections between LED's, switches, and circuits via 22-26 solid wire.
  - — Self-powered, in one compact, good looking and durable carrying case.
  - — Ideal for home experiments, the laboratory and students.
  - — Battery (4 1½ Volt C cells*) or AC powered provides economical bench use or convenient portable use. Available in two models.

Albia Model DM-5A containing 4 LEDs and 4 logic switches **$49.95** Includes Warranty

Albia Model DM-5 contains 8 LEDs and 8 logic switches **$64.95** Includes Warranty

*Batteries not included.

### ALBIA'S ECONOMY DIGITAL DM-9 MULTI-LOGIC COMPATIBLE 5-15VDC PROBE

The features are many on this quality Albia test instrument; will detect low repeat rate pulses (up to 1.5 MHz); detects low, high or pulsed logic levels with a minimum detectable pulse width of 300 nsec. Easy-to-interpret 3 LED readout. Built-in over-voltage and reverse polarity protection.

**$26.95** Includes Warranty

**IMMEDIATE DELIVERY . . . NOT A KIT**

### ALBIA EXTERNAL REGULATED, SHORT PROOF ADAPTER

Model DM-5B, supplies up to 300 MilliAmps at 5V, saves batteries . . . ONLY **$19.95** Includes Warranty

## REGULATED TRIPLE POWER SUPPLY BARGAIN PRICED ALBIA MODEL DM-6

A fully assembled and tested power supply that provides a solid, fully wired triple power supply including fixed 5V @ 1 Amp, 5V to 15V @ 0.5 Amp, and −5V to −15V @ 0.5 Amp — all supplies regulated, short proof. Each supply has short indicator LED. Complete and ready for use in a durable (8"x6"x3½") metal case.

**$79.95** Includes Warranty

**ALBIA SATISFACTION WARRANTY:** If for any reason, whatsoever, you are not completely satisfied with your purchase, return it within 30 days of purchase date for a full refund — it's as simple as that!

| POSTAGE & HANDLING | |
|---|---|
| ORDERS | ADD |
| UP TO $10.00 | $1.75 |
| $10.01 - $25.00 | 2.25 |
| $25.01 - $50.00 | 2.75 |
| $50.01 - $100.00 | 3.25 |
| ORDERS OVER $100.00 WITHIN UNITED STATES | N/C |

**FREE!! BIG 1981 SALE CATALOG**

**42 pages of exciting bargains! Send today!!**

**FOR FAST AND DEPENDABLE DELIVERY SERVICE**

**CALL TOLL FREE: 1-800-243-6953** 9 A.M. to 5 P.M. E.S.T.

WE ACCEPT MASTER CHARGE, VISA AND AMEX CREDIT CARDS

Connecticut Residents add 7½% Sales Tax • Prices shown in U.S. currency only. Foreign orders add 15%.

# ALBIA ELECTRONICS INC

24 Albia St. • New Haven, CT 06512

**FREE ALBIA "TEMPLATE" WITH EVERY ORDER RECEIVED by March 25, 1981**

## HOW THEY'RE TESTED



CERTIFICATE OF CALIBRATION

LOCKHEED ELECTRONICS COMPANY, INC.

Plainfield, New Jersey

INSTRUMENT: DMM RECORDER MODEL 310 — SERIAL NO. 90521102

PROPERTY OF: ZIFF-DAVIS PUBLISHING COMPANY — WORK ORDER NO. 74-6200-5208

The above instrument has been checked and calibrated against our working standards which are traceable to the National Bureau of Standards. All specifications were found to meet those set forth by the manufacturer. The metrology procedures utilized conform to and satisfy the requirements set forth in MIL-C-45662A.

NBS REPORT NUMBER: GUF 9155, s/n 39,362 E81035 NB6# 219833 Dated 11/27/78

LOCKHEED ELECTRONICS COMPANY, INC. by: M. J. Corrigan, Jr.

TEST PERFORMED BY: Supple — DATE OF TEST: 9-27-80

TEMPERATURE: 72° — HUMIDITY: 47%

LEC 11-4

*Certificate of qualification issued by the laboratory.*

A basic rule in electrical measurement states that test equipment must be *at least* one order of magnitude (10X) better than the system under test. Otherwise, the test data may be a series of artifacts.

Most of the new bench instruments using the latest in semiconductor technology are capable of accuracy exceeding that of laboratory instruments of several years back. To check the new instruments, "super" test gear is required. Besides being quite expensive, such "super" instrumentation must be calibrated against parameters directly traceable to the National Bureau of Standards (NBS) at regular intervals.

POPULAR ELECTRONICS, as a service to its readers, has started a new program of instrument testing using an independent testing service.

Lockheed Electronics Company, a wholly-owned subsidiary of the Lockheed Corporation, is one of this nation's leaders in the design, development, production, and testing of electronic products and systems for the military, government, and industry. The Instrumentation Measurements Laboratory (IML), a division of this company, will perform all electronic tests of test equipment chosen by POPULAR ELECTRONICS. Since all tests are directly traceable to the National Bureau of Standards, our readers can now be assured that what they read in the device specifications is "what it is." The tests we ask for are simple. All the particular piece of equipment must do is be the equal of its advertised (or manual) specifications. If it is, then IML will issue a certificate of compliance which we will publish along with a "hands on" report written by our staff after using the piece of test equipment for a period of time.

The electronic capabilities of Lockheed's IML include:

- dc voltage from 1 $\mu$V to 30 kV, $\pm 0.0001\%$ to $\pm 0.01\%$ accuracy.
- dc current from 1 pA to 100 A, $\pm 0.005\%$ to $\pm 0.1\%$ accuracy.
- ac voltage from 1 $\mu$V to 1.5 kV, 20 Hz to 12.4 GHz, $\pm 0.01\%$ to $\pm 0.1\%$ accuracy.
- alternating current from 1 mA to 30 A, $\pm 0.01\%$ to $\pm 0.1\%$ accuracy.
- resistance from 100 $\mu$ohm to 10 Gohms, $\pm 0.0005\%$ to $\pm 0.1\%$ accuracy.
- capacitance from 0.001 pF to 10 $\mu$F, $\pm 0.0001\%$ to $\pm 0.01\%$ accuracy.
- inductance from 0.1 nH to 1000 H, $\pm 0.001\%$ to $\pm 0.1\%$ accuracy.
- frequency from 0.001 Hz to 26 GHz, $\pm$ 2 parts in $10^{11}$ accuracy.
- attenuation to 18 GHz to 100 dB, $\pm 0.02$ dB to $\pm 1.0$ dB accuracy.
- audiometrics ISO, ASA, ANSI specifications, 20 Hz to 40 kHz, 0 to 140 dB, $\pm 0.2$ dB.
- Q to 75 MHz, $\pm 2\%$.
- standing wave ratio to 12.4 GHz, $\pm 1\%$ (swept technique).
- ratio: ac to 10 kHz, 1:1 $\times$ $10^{-7}$, $\pm 0.00005\%$; dc $\pm 0.0001\%$.

**Comments.** The Tech 310 was checked by Lockheed Electronics Co. Inc., Plainview, NJ, against standards traceable to the National Bureau of Standards. After tests, the lab issued a certificate testifying that the unit met specifications in all respects.

After several weeks of bench and field service, including at least two unscheduled "drop tests," the instrument showed no signs of mechanical or electrical damage. The case is easily cleaned using mild detergent and warm water.

Few meters in the Tech 310 price range can be used to measure CMOS currents less than 100 $\mu$A. The Tech 310 did this easily and was found useful down to 100 nA. The Insta-Ohms feature was very handy for checking wiring and pc board foil patterns for continuity, especially since it is not necessary to wait for the meter to "settle down."

Another convenient feature is that with overrange conditions, the display shows an unambiguous OL instead of a blank or flashing display used in other DMMs.

One valuable use of the 310 is in testing unknown diodes or transistors. When the test leads are connected across a junction (in or out of circuit), the display indicates the forward voltage drop, quickly identifying a germanium or silicon device. The range extends high enough to measure the forward voltage drop of a LED, which may be a volt or more. If the OL display comes on with both orientations of the test leads, the junction is open. If the display is zero in both orientations, the junction is shorted. The addition of a couple of resistors (shown in the manual) enables measurement of transistor beta. This is of great value when matching transistors are required by a circuit.

Even capacitors having a value greater than 0.01-$\mu$F can be checked. The 310 does not indicate value, but will show whether or not the capacitor is shorted or accepting a charge.

The ac voltage ranges can be used to measure decibels. In the 200-mV range, measurements from $-10$ to $-40$ dB (0 dB = 1 mW into 600 ohms) can be made. The manual indicates the conversions when using the 2-to-1000-volt ac ranges.

A number of options are available for the 310. These include both a vinyl and deluxe carrying case, a 30-kV high-voltage probe, and r-f probe good to 200 MHz, an ac current clamp rated to 200 amperes, and a kit of test leads and assortment of tips for a variety of testing applications.

We found the 310 slightly bulkier and heavier than some portable DMMs, but it will still fit into a jacket pocket. The LCD display is very readable from several feet away, the large jet-black digits being in sharp contrast to the silvery background. In its price range, the Tech 310 offers a well-chosen balance of features and performance that would be very hard to improve on.—*Leslie Solomon, Senior Technical Editor.*

CIRCLE NO. 103 ON FREE INFORMATION CARD

from 2.5 mA on the 200-ohm range to 25 nA on the 20-megohm range. Accuracy is better than 1% +1 digit. Maximum open-circuit voltage is 0.5 volt on all ranges except low-power ohms, where it is 250 mV. Overload protection extends to 300 volts dc or rms ac on any of the ranges.

The diode test function has a range from 0 to 2 volts (to indicate forward bias diode voltage), with a resolution of 1 mV, accuracy of $\pm 0.25\%$ reading +2 digits, test current of 5 mA, and an overload protection of 300 V dc or rms ac.

The instrument rests on two "feet" and a strip on its rear side. Both the feet and the strip, like the bottom of the tilt stand, are skid-proofed.

Licenced by Sinclair Research Ltd.

# A Microcomputer for everyone at a Micro Price




## The MicroAce - a new generation of miniature computers



**A COMPLETE COMPUTER for $149.00 for 1K Kit**

Post and Packing FREE

(Add 6% Tax for Shipments inside California)

## The unique and valuable components of the MicroAce

The MicroAce is not just another personal computer. Quite apart from its exceptionally low price, the MicroAce has two uniquely advanced components: the powerful BASIC interpreter, and the simple teach yourself BASIC manual.

The unique versatile BASIC interpreter offers remarkable programming advantages:

- **Unique 'one-touch' key word entry: the MicroAce eliminates a great deal of tiresome typing. Key words (RUN, PRINT, LIST, etc.) have their own single-key entry.**
- Unique syntax check. Only lines with correct syntax are accepted into programs. A cursor identifies errors immediately. This prevents entry of long and complicated programs with faults only discovered when you try to run them.
- Excellent string-handling capability — takes up to 26 string variables of any length. All strings can undergo all relational tests (e.g. comparison). The MicroAce also has string input — to request a line of text when necessary. Strings do not need to be dimensioned.
- Up to 26 single dimension arrays.
- FOR/NEXT loops nested up 26.
- Variable names of any length.
- BASIC language also handles full Boolean arithmetic, conditional expressions, etc.
- Exceptionally powerful edit facilities, allows modification of existing program lines.
- Randomise function, useful for games and secret codes, as well as more serious applications
- Timer under program control.
- PEEK and POKE enable entry of machine code instructions, USR causes jump to a user's machine language sub-routine.
- High-resolution graphics with 22 standard graphic symbols.
- All characters printable in reverse under program control.
- Lines of unlimited length.

## 'Excellent value' indeed!

For just $149.00 (excluding handling charge) you get everything you need to build a personal computer at home... PCB, with IC sockets for all ICs; case; leads for direct connection to a cassette recorder and television (black and white or color); everything!

Yet the MicroAce really is a complete, powerful, full-facility computer, matching or surpassing other personal computers at several times the price.

The MicroAce is programmed in BASIC, and you can use it to do quite literally anything, from playing chess to managing a business.

The MicroAce is pleasantly straightforward to assemble, using a fine-tipped soldering iron. It immediately proves what a good job you've done: connect it to your TV ... link it to the mains adaptor ... and you're ready to go.

## Fewer chips, compact design, volume production-more power per Dollar!

The MicroAce owes its remarkable low price to its remarkable design: the whole system is packed on to fewer, newer, more powerful and advanced LSI chips. A single SUPER ROM, for instance, contains the BASIC interpreter, the character set, operating system, and monitor. And the MicroAce 1K byte RAM (expandable to 2K on board) is roughly equivalent to 4K bytes in a conventional computer — typically storing 100 lines of BASIC. (Key words occupy only a single byte.)

The display shows 32 characters by 24 lines.

And Benchmark tests show that the MicroAce is faster than all other personal computers.

No other personal computer offers this unique combination of high capability and low price.

## The MicroAce teach-yourself BASIC manual.

If the features of the BASIC interpreter mean little to you-don't worry. They're all explained in the specially-written book *free* with every kit! The book makes learning easy, exciting and enjoyable, and represents a complete course in BASIC programming-from first principles to complex programs. (Available separately-purchase price refunded if you buy a MicroAce later.)

A hardware manual is also included with every kit.

## The MicroAce Kit: $149.00 with IK COMPLETE $169.00 with 2K

Demand for the MicroAce is very high: use the coupon to order today for the earliest possible delivery. All orders will be despatched in strict rotation. If you are unsuccessful in constructing your kit, we will repair it for a fee of $20.00, post and packing FREE. Of course, you may return your MicroAce as received within 14 days for a full refund. We want you to be satisfied beyond all doubt — and we have no doubt that you will be.




**Your MicroAce kit contains...**

- Printed circuit board, with IC sockets for all ICs.
- Complete components set, including all ICs-all manufactured by selected world-leading suppliers.
- New rugged keyboard, touch-sensitive, wipe-clean.
- Ready-moulded case.
- Leads and plugs for connection to domestic TV and cassette recorder. (Programs can be SAVEd and LOADed on to a portable cassette recorder.)
- Mains adaptor of 600 mA at 9VDC nominal unregulated.
- FREE course in BASIC programming and user manual.

## JOIN THE REVOLUTION - DON'T GET LEFT BEHIND - ORDER YOUR MICRO ACE NOW!!

Send Check, Money Order or quote your Credit Card No. to:
**MicroAce** 1348 East Edinger, Santa Ana, California, Zip Code 92705.
**or phone** (714) 547 2526 quoting your Credit Card Number.

| Quantity | Description | Unit Price | TOTAL |
|---|---|---|---|
| | MicroAce Kit 1K | $149.00 | |
| | MicroAce Kit 2K | $169.00 | |
| | Manual | $10.00 | |
| | 1K Upgrade Kit | $29.00 | |
| Shipments inside California add 6% TAX | | **TOTAL** | |

☐ Amex.
☐ Diners
☐ Check
☐ Money Order
☐ Master Charge
☐ Visa

Card No. _____

Exp. Date _____

Name _____

Address _____

City _____ State _____ Zip _____

CIRCLE NO. 42 ON FREE INFORMATION CARD

# COMPUTER BITS

By Carl Warren

## Good Grief! More Conversion

IN THE last few issues, I have discussed conversion techniques for the BASIC language. As a result, I've received a number of letters in the mail and notes on MicroNet. Many of these asked about *The BASIC Handbook*, by Dr. David Lein, which I had mentioned in passing in a previous column. The book is 360 pages long and is very concise in its presentation of the various syntaxes used in numerous BASICs. You can obtain it from just about any B. Dalton Pickwick Bookstore or by contacting the publisher directly: Compusoft Publishing, 1050 Pioneer Way, Suite E, Dept. C-1, El Cajon, CA 92020 (Tel: 714-588-0996). The price is $14.95 plus $1.35 for mailing. When you write or call, be sure to give the department number.

Those of you who are really serious about doing BASIC translation will want to get a copy of: "Interdialect Translatability of the BASIC Programming Language," by Gerald L. Isaacs. This is ACT Technical Bulletin No. 11. Order it from the Research and Development Div., American College Testing Program, Box 168, Iowa City, IA 52440. Written in 1972, the Bulletin covers various concerns in translation. Two years ago, it cost $4.50; but it may be more now, so write to them for the cost.

A letter of particular interest to me came from Harvey Cowell, of Angola, IN, who pointed out that he recognized the importance of conversion principles for the Apple and TRS-80 but felt cheated since nothing was said about the North Star system.

Harvey, your point is well taken. Systems like North Star did exist long before the others, and you deserve your due. So, here goes.

**To Translate to North Star.** The version of North Star BASIC to be discussed is Release 5, introduced at the end of 1978. Although numerous BASICs preceded North Star, this version became one of the more serious attempts that was made at designing a business-oriented language.

In its original form, North Star BASIC was an upgraded version of a Tiny BASIC published in *Dr. Dobbs Journal*. Gradually, this BASIC was upgraded to take advantage of the sophistication that was built into the North Star operating system.

Some software experts consider North Star BASIC difficult and poorly structured. However, this may be the beauty of it. Although I'm a proponent of structured design of an application and, to a degree, of structured programming, I feel their constraints make them difficult for the novice to use. There are no such constraints with North Star.

An example of the power of the BASIC and good planning was demonstrated in a program called WHATSIT (Wow, How Did All That Stuff Get In There), developed by a company called Computer Headwear in early 1978. This particular program made extensive use of the ability of North Star BASIC to locate specific points in a record within a file and set pointers. Interestingly, WHATSIT proved that a very high-level data-base management system could be implemented on a microcomputer in BASIC.

Getting Down to Cases. The PRINT statement in North Star BASIC is an output function and works basically the same as in any BASIC. A program line such as:

PRINT "NORTH STAR BASIC"

will produce an output to the screen of: NORTH STAR BASIC. The double quotes are used to inform BASIC that this is a string expression.

Now if you want to drive the same message out to the printer, you must let North Star BASIC know that. To do this, you employ the use of the pound sign (#). For example, to output to the printer:

PRINT #1, "MESSAGE"

would cause the printer to print the message. If you leave out the device number, which can be from 0 to 7 (0 is usually the default), the output goes to the CRT.

The TRS-80 Level II BASIC uses LPRINT; for example, LPRINT "MESSAGE." If you typed PRINT #1, in the same BASIC, it would assume that you want to perform some input to disk buffer #1.

The eight possible devices you can communicate with on the North Star system include the disks and you can address them by device number. The number that you enter (0-7) represents the port address. (They call it the pseudo port since it only points to the actual port location in the memory map.) The way you emulate this in the TRS-80/Microsoft BASIC is to use the OUT function and an argument representing the value of the port in decimal. Thus OUT (26) would send data (one byte at a time) to the port designated by $26_{10}$ (1A in hexadecimal).

North Star BASIC lets you perform this I/O without worrying about actual address or port designators.

**A Way to POKE.** The POKE function allows you to put information into memory. North Star has the same function but calls it FILL. Both POKE and FILL work the same way. You enter the function, a memory location, and the byte you want to put there. For example:

POKE 65535, A

and

FILL 65535, A

Both do the same thing—putting byte A into location 65535.

The inverse of POKE and FILL, is PEEK and EXAM. These functions allow you to examine at a given memory location. North Star uses the word EXAM to mean "let's look at a memory location." To convert this:

EXAM 65535, A

is equal to

PEEK 65535, A

Not all the functions are as easily understood or translated. For example, the North Star function TYP(e) allows you to determine what type of data item is going to be found in an open disk file. A numeric item would produce a 2, a string 1, and, if the end of the file is reached, a zero. This is a *disk* function and not a *real* function of BASIC—it is an *extension*. To use this function you have to decide what you are looking for. If you want to detect the end of file mark, you write:

IF TYPE (*n*) = 0 THEN xxx where n is the number of the open file and xxx is the line to branch to. If you are doing a *read* and you want to ensure that you are *reading* the right data into the correct variable (either string or numeric), then you can set up a test. For example:

```
10 IF TYP(1) = 1 THEN 20
20 READ #1, S$
```

This says: if the next data item on file #1 is a string, read it into the string variable S$. A numeric test is handled the

*Start learning and computing for only* ***$<u>129.95</u>*** *with a Netronics 8085-based computer kit. Then expand it in low-cost steps to a business/development system with 64k or more RAM, 8″ floppy disk drives, hard disks and multi-terminal I/O.*

# THE NEW EXPLORER/85 SYSTEM

**Special!** *Full 8″ floppy, 64k system for less than the price of a mini! Only* **$1499.95!**

(Also available wired & tested, $1799.95)

Imagine — for only $129.95 you can own the starting level of Explorer/85, a computer that's expandable into full business/development capabilities — a computer that can be your beginner system, an OEM controller, or an IBM-formatted 8″ disk small business system. From the first day you own Explorer/85, you begin computing on a significant level, and applying principles discussed in leading computer magazines. Explorer/85 features the advanced Intel 8085 cpu, which is 100% compatible with the older 8080A. It offers onboard S-100 bus expansion, Microsoft BASIC in ROM, plus instant conversion to mass storage disk memory with standard IBM-formatted 8″ disks. All for only $129.95, plus the cost of power supply, keyboard/terminal and RF modulator if you don't have them (see our remarkable prices below for these and other accessories). With a Hex Keypad/display front panel, Level "A" can be programmed with no need for a terminal, ideal for a controller, OEM, or a real low-cost start.



*Full 8″ disk system for less than the price of a mini (shown with Netronics Explorer/85 computer and new terminal). System features floppy drive from Control Data Corp., world's largest maker of memory storage systems (<u>not</u> a hobby brand!)*



*Level "A" is a complete operating system, perfect for beginners, hobbyists, industrial controller use. $129.95*



*Level "A" With Hex Keypad/Display.*

### LEVEL "A" SPECIFICATIONS

Explorer/85's Level "A" system features the advanced Intel 8085 cpu, an 8355 ROM with 2k deluxe monitor/operating system, and an advanced 8155 RAM I/O . . . all on a single motherboard with room for RAM/ROM/PROM/EPROM and S-100 expansion, plus generous prototyping space.

**PC Board:** Glass epoxy, plated through holes with solder mask. • **I/O:** Provisions for 25-pin (DB25) connector for terminal serial I/O, which can also support a paper tape reader . . . cassette tape recorder input and output . . . cassette tape control output . . . LED output indicator on SOD (serial output) line . . . printer interface (less drivers) . . . total of four 8-bit plus one 6-bit I/O ports. • **Crystal Frequency:** 6.144 MHz. • **Control Switches:** Reset and user (RST 7.5) interrupt . . . additional provisions for RST 5.5, 6.5 and TRAP interrupts onboard. • **Counter/Timer:** Programmable, 14-bit binary. • **System RAM:** 256 bytes located at F800, ideal for smaller systems and for use as an isolated stack area in expanded systems . . . RAM expandable to 64K via S-100 bus or 4k on motherboard.

**System Monitor (Terminal Version):** 2k bytes of deluxe system monitor ROM located at FØØØ, leaving ØØØØ free for user RAM/ROM. Features include tape load with labeling . . . examine/change contents of memory . . . insert data . . . warm start . . . examine and change all registers . . . single step with register display at each break point, a debugging/training feature . . . go to execution address . . . move blocks of memory from one location to another . . . fill blocks of memory with a constant . . . display blocks of memory . . . automatic baud rate selection to 9600 baud . . . variable display line length control (1-255 characters/line) . . . channelized I/O monitor routine with 8-bit parallel output for high-speed printer . . . serial console in and console out channel so that monitor can communicate with I/O ports.

**System Monitor (Hex Keypad/Display Version):** Tape load with labeling . . . tape dump with labeling . . . examine/change contents of memory . . . insert data . . . warm start . . . examine and change all registers . . . single step with register display at each break point . . . go to execution address. Level "A" in this version makes a perfect controller for industrial applications, and is programmed using the Netronics Hex Keypad/Display. It is low cost, perfect for beginners.

### HEX KEYPAD/DISPLAY SPECIFICATIONS

Calculator type keypad with 24 system-defined and 16 user-defined keys. Six digit calculator-type display, that displays full address plus data as well as register and status information.

### LEVEL "B" SPECIFICATIONS

Level "B" provides the S-100 signals plus buffers/drivers to support up to six S-100 bus boards, and includes: address decoding for onboard 4k RAM expansion selectable in 4k blocks . . . address decoding for onboard 8k EPROM expansion selectable in 8k blocks . . . address and data bus drivers for onboard expansion . . . wait state generator (jumper selectable), to allow the use of slower memories . . . two separate 5 volt regulators.

### LEVEL "C" SPECIFICATIONS

Level "C" expands Explorer/85's motherboard with a card cage, allowing you to plug up to six S-100 cards directly into the motherboard. Both cage and card are neatly contained inside Explorer's deluxe steel cabinet. Level "C" includes a sheet metal superstructure, a 5-card, gold plated S-100 extension PC board that plugs into the motherboard. Just add required number of S-100 connectors.

*Explorer/85 With Level "C" Card Cage.*

### LEVEL "D" SPECIFICATIONS

Level "D" provides 4k of RAM, power supply regulation, filtering decoupling components and sockets to expand your Explorer/85 memory to 4k (plus the original 256 bytes located in the 8155A). The static RAM can be located anywhere from ØØØØ to EFFF in 4k blocks.

### LEVEL "E" SPECIFICATIONS

Level "E" adds sockets for 8k of EPROM to use the popular Intel 2716 or the TI 2516. It includes all sockets, power supply regulator, heat sink, filtering and decoupling components. Sockets may also be used for 2k x 8 RAM IC's (allowing for up to 12k of onboard RAM).

### DISK DRIVE SPECIFICATIONS

- 8″ CONTROL DATA CORP. professional drive.
- LSI controller.
- Write protect.
- Single or double density.
- Data capacity: 401,016 bytes (SD), 802,032 bytes (DD), unformatted.
- Access time: 25ms (one track).

### DISK CONTROLLER/ I/O BOARD SPECIFICATIONS

- Controls up to four 8″ drives.
- 1771A LSI (SD) floppy disk controller.
- Onboard data separator (IBM compatible).
- 2 Serial I/O ports
- Autoboot to disk system when system reset.
- 2716 PROM socket included for use in custom applications.
- Onboard crystal controlled.
- Onboard I/O baud rate generators to 9600 baud.
- Double-sided PC board (glass epoxy.)

### DISK DRIVE CABINET/POWER SUPPLY

- Deluxe steel cabinet with individual power supply for maximum reliability and stability.

## ORDER A COORDINATED EXPLORER/85 APPLICATIONS PAK!

**Beginner's Pak (Save $26.00!)** — Buy Level "A" (Terminal Version) with Monitor Source Listing and AP-1 5-amp Power Supply: (regular price $199.95), now at SPECIAL PRICE: **$169.95** plus post. & insur.

**Experimenter's Pak II (Save $53.40!)** — Buy Level "A" (Hex Keypad/Display Version) with Hex Keypad/Display, Intel 8085 User Manual, Level "A" Hex Monitor Source Listing, and AP-1 5-amp Power Supply: (regular price $279.35), all at SPECIAL PRICE: **$219.95** plus post. & insur.

**Special Microsoft BASIC Pak (Save $103.00!)** — Includes Level "A" (Terminal Version), Level "B", Level "D" (4k RAM), Level "E", 8k Microsoft in ROM, Intel 8085 User Manual, Level "A" Monitor Source Listing, and AP-1 5-amp Power Supply: (regular price $439.70), now yours at SPECIAL PRICE: **$329.95** plus post. & insur.

**ADD A TERMINAL WITH CABINET, GET A FREE RF MODULATOR:** Save over $114 at this SPECIAL PRICE: **$499.95** plus post. & insur.

**Special 8″ Disk Edition Explorer/85 (Save over $104!)** — Includes disk-version Level "A", Level "B", two S-100 connectors and brackets, disk controller, 64k RAM, AP-1 5-amp power supply, Explorer/85 deluxe steel cabinet, cabinet fan, 8″ SD/DD disk drive from famous CONTROL DATA CORP. (not a hobby brand!), drive cabinet with power supply, and drive cable set-up for two drives. This package includes everything but terminal and printers (see coupon for them). Regular price $1630.30, all yours in kit at SPECIAL PRICE: **$1499.95** plus post. & insur. Wired and tested, only **$1799.95.**

**Special! Complete Business Software Pak (Save $625.00!)** — Includes CP/M 2.0, Microsoft BASIC, General Ledger, Accounts Receivable, Accounts Payable, Payroll Package: (regular price $1325), yours now at SPECIAL PRICE: **$699.95.**

***Please send the items checked below:***

- ☐ **Explorer/85 Level "A" kit** (Terminal Version) . . . **$129.95** plus $3 post. & insur.
- ☐ **Explorer/85 Level "A" kit** (Hex Keypad/Display Version) . . . **$129.95** plus $3 post. & insur.
- ☐ **8k Microsoft BASIC** on cassette tape, **$64.95** postpaid.
- ☐ **8k Microsoft BASIC in ROM kit** (requires Levels "B", "D" and "E") . . . **$99.95** plus $2 post. & insur.
- ☐ **Level "B" (S-100) kit** . . . **$49.95** plus $2 post. & insur.
- ☐ **Level "C" (S-100 6-card expander) kit** . . . **$39.95** plus $2 post. & insur.
- ☐ **Level "D" (4k RAM) kit** . . . **$69.95** plus $2 post. & insur.
- ☐ **Level "E" (EPROM/ROM) kit** . . . **$5.95** plus 50¢ p&h.
- ☐ **Deluxe Steel Cabinet** for Explorer/85 . . . **$49.95** plus $3 post. & insur.
  - ☐ Fan For Cabinet . . . **$15.00** plus $1.50 post. & insur.
- ☐ **ASCII Keyboard/Computer Terminal kit:** features a full 128 character set, u&l case; full cursor control; 75 ohm video output; convertible to baudot output; selectable baud rate, RS232-C or 20 ma. I/O, 32 or 64 character by 16 line formats, and can be used with either a CRT monitor or a TV set (if you have an RF modulator) . . . **$149.95** plus $3.00 post. & insur.
  - ☐ **DeLuxe Steel Cabinet** for ASCII keyboard/terminal . . . **$19.95** plus $2.50 post. & insur.
- ☐ **New! Terminal/Monitor:** (See photo) Same features as above, except 12″ monitor with keyboard and terminal is in deluxe single cabinet; kit . . . **$399.95** plus $7 post. & insur.
- ☐ **Hazeltine terminals:** Our prices too low to quote — **CALL US**
- ☐ **Lear-Sigler terminals/printers:** Our prices too low to quote: **CALL US**
- ☐ **Hex Keypad/Display kit** . . . **$69.95** plus $2 post. & insur.
- ☐ **AP-1 Power Supply Kit** ±8V @ 5 amps) in deluxe steel cabinet . . . **$39.95** plus $2 post. & insur.
- ☐ **Gold Plated S-100 Bus Connectors** . . . **$4.85** each, postpaid.
- ☐ **RF Modulator kit** (allows you to use your TV set as a monitor) . . . $8.95 **postpaid.**
- ☐ **16k RAM kit** (S-100 board expands to 64k) . . . **$199.95** plus $2 post. & insur.
- ☐ **32k RAM kit** . . . **$299.95** plus $2 post. & insur.
- ☐ **48k RAM kit** . . . **$399.95** plus $2 post. & insur.
- ☐ **64k RAM kit** . . . **$499.95** plus $2 post. & insur.
- ☐ **16k RAM Expansion kit** (to expand any of the above in 16k blocks up to 64k) . . . **$99.95** plus $2 post. & insur. each.
- ☐ **Intel 8085 cpu Users' Manual** . . . **$7.50** postpaid.
- ☐ **12″ Video Monitor** (10MHz bandwidth) . . . **$139.95** plus $5 post. & insur.
- ☐ **Beginner's Pak** (see above) **$169.95** plus $4 post. & insur.
- ☐ **Experimenter's Pak** (see above) . . . **$219.95** plus $6 post. & insur.
- ☐ **Special Microsoft BASIC Pak Without Terminal** (see above) . . . **$329.95** plus $7 post. & insur.
- ☐ Same as above, plus **ASCII Keyboard Terminal With Cabinet, Get Free RF Modulator** (see above) . . . **$499.95** plus $10 post. & insur.
- ☐ **Special 8″ Disk Edition Explorer/85** (see above) . . . **$1499.95** plus $26 post. & insur.
  - ☐ **Wired & Tested** . . . **$1799.95** plus $26 post. & insur.
- ☐ **Extra 8″ CDC Floppy Drives** . . . **$499.95** plus $12 post. & insur.
  - ☐ **Cabinet & Power Supply For Drive** . . . **$69.95** plus $3 post. & insur.
- ☐ **Drive Cable Set-up For Two Drives** . . . **$25** plus $1.50 post. & insur.
- ☐ **Disk Controller Board With I/O Ports** . . . **$199.95** plus $2 post. & insur.
- ☐ **Special: Complete Business Software Pak** (see above) . . . **$699.96** postpaid.
  - SOLD SEPARATELY:
  - ☐ **CP/M 1.4** . . . **$100** postpaid.
  - ☐ **CP/M 2.0** . . . **$150** postpaid.
  - ☐ **Microsoft BASIC** . . . **$325** postpaid.
- ☐ **Intel 8085 cpu User Manual** . . . $7.50 **postpaid.**
- ☐ **Level "A" Monitor Source Listing** . . . **$25** postpaid.

**Continental U.S.A. Credit Card Buyers Outside Connecticut**

**CALL TOLL FREE: 800-243-7428**

To Order From Connecticut Or For Technical Assistance, call (203) 354-9375

Total Enclosed (Conn res. add sales tax) $ ________
Paid By:
☐ Personal Check ☐ Cashier's Check/Money Order
☐ **VISA** ☐ **Master Charge** (Bank No. ____)
Acct. No. ____________ Exp. Date ______
Signature ____________
Print Name ____________
Address ____________
City ____________
State ________ Zip ________

**NETRONICS Research & Development Ltd.**
**333 Litchfield Road, New Milford, CT 06776**

# ARKON KITS

**LED POWER METER**

Uses the popular LM3915 display driver. Features switch selectable peak or average peak power level indication. The front end utilizes precision half wave rectification. LED displays included 30 db (−24 db to +3db) dynamic range ..... $24.95

**LED VU/POWER METER**

Same as LED power meter but uses NSM series display. Two types: NSM 3915 ..... 30 db (−24 db to +3 db power) NSM 3916 — 23 db (−20 db to +3 db VU) ..... $29.95

**THE BRUTE 300 WATT AMP**

This kit is not recommended for beginners or inexperienced constructors. Power output: 200 watts RMS, 8 ohms, 310 watts RMS, 4 ohm. Input sensitivity: IV for total output. This kit uses all standard parts and comes complete with instructions and printed circuit board (mono) (transformer required 100 VCT 5 amps. is available for $51.00 #167P100

P.C. Board $11.25

**COLOUR MODULATOR**

This video modulator has been designed to complement the small home computer. It allows the standard colour television to be used as a high quality colour video monitor. Uses state of the art integrated circuit technology. Direct coupling is employed to provide white level compensation in the vestigal sideband output. The gain device of the LM1889's croma oscillator is used to buffer, level shift, and invert the incoming composite colour input. The signal then passes to the RF modulator where a channel 7 carrier is provided. Requires 12 volt DC for operation ..... $24.95

**VIDEO TO RF MODULATOR**

Converts a video signal to a RF signal. The RF output terminals connect to the antenna of your TV. Connecting in the video and supplying 5 to 10 volts DC is all that is needed. You turn your channel selector to 4, 5 or 6 (whichever is not used in your area) and tune the adjusting coil for a suitable display ..... $8.95

**ASCII KEYBOARD KIT**

60 Key complete ASCII character set. Highest commercial quality key switches. Uses a KR2376 ST encoder IC. Output compatible with TTL. Caps lock for upper case alpha characters. Repeat key parity/data invertable. Positive and negative key pressed and strobe signals. Requires +5 volts to +30 volts at 100ma ..... $99.95

**ARKON LOGIC PROBE LOGIC 1**

Easy to build Logic Probe kit. A full performance logic probe. With it, the logic levels in a digital circuit translates into light from the Hi or Lo LED. Pulses as narrow as 300 nano seconds are stretched into blinks of the pulse LED's. Specs — 300K ohm imp. Power — 30ma at 5 volts, 40ma at 15 volts, 15 volts max. Max. Speed — 300 nano seconds 1.5 MHZ. Input Protection — +50 volts DC continuous, 117 volts AC for 15 seconds. (case included) ..... $24.95

Send certified cheque, money order, Chargex, Master Charge...include expiry date, card number and signature. We process only prepaid orders. Minimum order $10.00 Add 5% (minimum $2.00) for shipping and handling. Ontario residents add 7% sales tax. All prices subject to change.
*Dealer inquiries welcome.*

arkon electronics ltd

409 Queen Street West, Toronto, Ontario Canada M5V 2A5. Tel. (416) 868-1315

CIRCLE NO. 7 ON FREE INFORMATION CARD



computique computique computique

**TEXAS INSTRUMENTS** INCORPORATED electronic calculators

| | | | |
|---|---|---|---|
| TI-30SP | 17.95 | | |
| TI-35SP | 24.95 | | |
| Bus. Anal. I | 21.95 | | |
| BA II Exec. NEW | 44.95 | | |
| Bus. Card | 39.95 | | |
| Invest. Anal. NEW | 49.95 | | |
| TI-55 | 34.95 | | |
| TI-57 | 54.95 | | |
| TI-5100 | 39.95 | | |
| TI-5015 | 64.95 | | |
| TI-5040 | 89.95 | | |
| TI-5135 NEW | 79.95 | | |
| TI-5142 NEW | 124.95 | Speak & Spell | 59.95 |
| TI-808-41 NEW | 62.95 | Speak & Read NEW | CALL |
| TI-58C | 104.95 | Speak & Math NEW | CALL |
| TI-59 | 209.95 | Lang. Tutor NEW | 169.95 |
| PC-100C | 169.95 | Home Comp. 99/4 | |
| TI-58/59 Libraries | 35.00 | Console Only | 499.95 |

**THE HP-85!**

*Complete Enhancements, Peripherals and Accessories*

Your HEWLETT PACKARD Headquarters

| | | | |
|---|---|---|---|
| HP-33C NEW | 89.95 | HP-41C NEW | CALL |
| HP-34C NEW | 124.95 | HP-85 NEW | CALL |
| HP-38C NEW | 124.95 | HP-41CV NEW | CALL |
| HP-32E | 124.95 | HP-83 NEW | CALL |
| HP-37E | 59.95 | | |

(714) 549-7373 INFORMATION LINE — (800) 432-7066 TOLL FREE (Within CA) — (800) 854-0523 TOLL FREE (Outside CA)

| | | | |
|---|---|---|---|
| APF IMAGINATION MACHINE | 495.00 | CHESS CHALLENGER "7" | 99.95 |
| Apple computer II PLUS (16K) | 999.95 | SENSORY CHESS CHALLENGER "8" NEW | 129.95 |
| Apple III NEW | CALL | 800 (16K) STARTER SYSTEM | 899.95 |
| SHARP 6200 NEW EXECUTIVE | 99.95 | ATARI 1000 | 109.99 |
| 5813 NEW SCI PROGRAMMABLE | 34.95 | 1750 NEW | 269.95 |
| 5100 NEW LCD ALPHANUMERIC | 89.95 | CODE-A-PHONE TIMER NEW | 59.95 |
| 5102 NEW FIN. PROG. | 79.95 | CONTROLLER COMMAND | 33.95 |
| 7000 NEW MEMO WRITER | 124.95 | | |
| CASIO MG-90 | 49.95 | | |
| FX-68 | 27.95 | | |

ALSO: CANON, TOSHIBA, NSC, SEIKO, MATTEL, PEARLCORDER, ITT, GTE, AND MANY OTHERS. ALL AT GREAT PRICES!!

WE WILL MEET OR BEAT ANY COMPETITOR'S ADVERTISED PRICE ON MOST ITEMS IF HE HAS THE MDSE. ON HAND. VISA, MASTERCARD, MONEY ORDER, PERS. CK. (14 WRKG. DAYS TO CLR.), COD ACCEPTED: MIN. $4.95 SHIPPING U.S.A.; AIR ON REQST.; CAL. RES. ADD 6% SALES TX.; ALL MDSE. SUBJ. TO AVAIL.; PRICES SUBJ. TO CHANGE; POPEL-Mar.

MAIL & PHONE ORDERS ONLY — computique — WRITE OR CALL FOR FREE CATALOG

Send orders to:
3211 SO. HARBOR BLVD. SANTA ANA, CA 92704
NEWPORT (714) 549-7373
WEST LOS ANGELES (213) 8200423
TARZANA (213) 705-7507
MID-WILSHIRE (213) 385-7777
LAWNDALE (213) 370-5795
PASADENA (213) 795-3007
BREA (714) 990-6600

PROFESSIONAL DISCOUNTS

CIRCLE NO. 12 ON FREE INFORMATION CARD




same way. The problem associated with this is not so much converting it to another form, but trying to figure out when to replace a specific function in another BASIC with TYP. If you have a situation where you want to find the end of a file, you would have something like this in TRS-80/Microsoft BASIC:

```
10 OPEN "I", #1, "STUFF.DAT"
20 IF EOF(1) THEN 50
30 INPUT #1, A
40 . . . .
50 . . . .
```

What we are saying here is, if you detect an End of File Marker (EOF) which is a 1A, then go do something else on line 50. Otherwise, READ in the data. What the EOF does is return a (−1) if the end is reached and is true, or a (0) if data is available (false).

The EOF function is used with sequential files, and can't be used to detect the end in a random file. You do that by knowing how much you can put out on a disk then use LOF (Last Output File mark).

Testing for the data value, numeric or string, in TRS-80 BASIC isn't as simple as doing a TYP test in North Star. Here you have to be a little inventive. To demonstrate:

```
10 OPEN "O", 1, "STUFF.DAT"
20 PRINT #1, 1 : REM identify data as numeric
30 PRINT #1, N : REM output actual data
40 . . . .
```

To input it again:

```
10 OPEN "I", 1, "STUFF.DAT"
20 INPUT #1, N : REM check for identifier
30 IF N = 1 THEN 50 : REM if numeric get rest
40 INPUT #1, N$ : REM otherwise read alpha data
50 INPUT #1, D
```

What occurs is a simple test for a condition to determine whether or not the data was a string or numeric in nature. And, depending on the results, read it into the correct variable type. Unfortunately, this takes memory and is simplified using the TYP function.

By now it should be obvious that translation, while not trivial, can be achieved if you sit down and analyze the problem. ◇




*"In shutting down the machines, Mr Simms, you don't just pull the plug!"*

# COMPUTER SOURCES

By Leslie Solomon
Senior Technical Editor

## Hardware

**S-100/C Bus.** The Model IOP I/O processor, used with the S-100 bus incorporates a Z-80A, 16K of RAM and up to 32K of PROM. It can be used stand-alone or as a satellite processor on the S-100 bus. It can also be used to interface the S-100 to peripherals via a new bus, called "C-bus," which operates independently of the S-100. To the host processor, the IOP appears as two output and two input ports, whose base addresses are switch selectable. The IOP can interrupt the host with a preprogrammed interrupt vector. A daisy-chain connector is used for prioritizing the interrupt. $695. Address: Cromemco Inc., 280 Bernardo Ave., Mountain View, CA 94043 (Tel: 415-964-7400).

**Multi-User I/O.** The INO-288 Multi-User Serial I/O Board was designed for S-100 systems where up to 8 additional serial I/O ports are required. The device is also available with four channels expandable to 8. All ports are fully programmable, using the 8251A programmable communication interface. Each port supports RS-232C with full handshaking, and can operate asynchronously or synchronously with 16 selectable baud rates, and can be interrupt driven. $435 for 4-channel version, $715 for 8-channel version (less the personality boards). Address: Measurement Systems and Controls, 867 North Main St., Orange, CA 92668 (Tel: 714-633-4460).

**Hardware Catalog.** Called "The Engineers Guide to Microcomputing Packaging," this brochure covers plug-in prototype boards, racks, and accessories for S-100/IEEE 696, Apple II, Pet, Expandamem, Super-kim, STD bus, Motorola Exorciser, Rockwell AIM, T1980, DEC LSI-11, PDP-8, Heath H-11, Intel SBC 80, and National BLC Series 80. Address: Vector Electronic Co., 12460 Gladstone Ave., Sylmar, CA 91342 (Tel: 213-365-9661).

**Low-Cost EPROM Programmer.** One of the most useful items for any serious computer user is a means of permanently saving important programs. The low-cost EPROM Programmer kit consists of a finished pc board and full documentation. The completed programmer connects to a parallel port and the programming verifies that the EPROM is erased and programmed with new data, checks that the data is correct, and allows transfer of data to system RAM. Documentation is available for 6800, 6809, 8080/8085/Z80, and 6502 in the near future. Specify processor when ordering. $15. Address: Micro Technical Products, 814 W. Keating Ave., Mesa, AZ 85202 (Tel: 602-839-8902).

**Apple Printer Interface.** The Model 7728 Printer Interface enables an Apple II to operate the Integral Data Paper Tiger, Okidata Microline 80, Microtek MT-80P, MPI 88T, as well as Centronix printers. An on-board ROM provides all driver firmware. Users who choose to develop their own drivers may replace the ROM with RAM. The 7728 resides in any Apple slot, and supports the interface daisy chain, and daisy chain pass through. The interface includes an 8-bit data output bus, four status inputs, data strobe and acknowledge handshakes, and printer reset signal. $119.95. Address: California Computer Systems, 250 Caribbean Dr., Sunnyvale, CA 94086 (Tel: 408-734-5811).

**OS Light Pen.** A deluxe version of the Lewis Computer System light pen kit features a coiled cord and Kwik-disconnect plug. It is designed for use with



Ohio Scientific computer systems. $29.95. Address: Faragher Associates, Inc., 7635 West Bluemound Rd., Milwaukee, WI 53213 (Tel: 800-558-0870).

**Music Sweetener.** This device is a low-pass filter designed to improve the quality of commercial and home-brew music synthesizers. It attenuates unwanted high-frequency sampling noise four times better than an audio system treble control. The device is connected between the music peripheral and the audio system. $39.95 plus $2 shipping/handling. Address: Newtech Computer Systems Inc., 230 Clinton St., Brooklyn, NY 11201 (Tel: 212-625-6220).

**Atari Memory.** The Mosaic 32K RAM Board can be used to add 32K of memory to both the Atari 400 and 800 systems. It enables the 400 owners to use disk drive. With the additional 32K of RAM, Atari owners can use disk


WANT AUTO-RANGING?

AWS EZ 6100

AND...

- An unprecedented five-year warranty
- Pricing as low as $105
- 3 1/2 digit display
- Autoranging on Volts and Ohms
- Continuity buzzer (Model EZ 6100)
- Range hold (Model EZ 6100)
- Autopolarity
- Automatic indication, unit and signs
- Feather touch button to select AC/DC - Lo Ω/Ω function
- Low battery warning sign
- Safety fused

| | |
|---|---|
| **EZ 6100** | |
| DCV 0-1000 | 5-Autoranges |
| ACV 0-600 | 4-Autoranges |
| DCMA 0-200 | 2-Ranges |
| ACMA 0-200 | 2-Ranges |
| Ω 0-2000KΩ | 5-Autoranges |
| Low Power Ω | 0-2000KΩ |
| 4-Autoranges | Plus Continuity Buzzer |
| **EZ 6200** | |
| DCV 0-1000 | 5-Autoranges |
| ACV 0-600 | 4-Autoranges |
| DCMA 0-200 | 1-Range |
| ACMA 0-200 | 1-Range |
| Ω 0-2000KΩ | 5-Autoranges |
| Low Power Ω | 0-2000KΩ |
| 4-Autoranges | |

- Order AWS EZ 6200 . . . $105
- Order AWS EZ 6100 with continuity buzzer and range hold . . . . . $142
- Order AWS C-30 Ever-Ready carrying case . . . . $20

☐ For ordering information call toll-free: 800-645-5398 (N.Y., Hawaii, Alaska call collect 516-231-7050).

A.W. SPERRY INSTRUMENTS INC.
The Measurable Advantage.
245 Marcus Blvd., Hauppauge, N.Y. 11787

CIRCLE NO. 61 ON FREE INFORMATION CARD

J&R "RATED NO. 1 FOR SERVICE & RELIABILITY"

THIS MONTH'S SUPER SPECIALS!

Audio & Video

| VIDEO | |
|---|---|
| SONY SL-5400 Betamax | $799 |
| JVC HR-6700 Video Rec | $799 |
| ZENITH VR-9000 Beta Vid. Rec | $699 |
| RCA VET-250 Video Rec | $775 |
| RCA VEP-150 Port. Vid. Rec. | $729 |
| SONY KV-1914 19" Color TV | $439 |
| PANASONIC CT 9010 19" Col. TV | $359 |
| PANASONIC CT 288 12" Col TV | $279 |

| AUDIO | |
|---|---|
| TECHNICS RS-M45 Cass. Deck | $225 |
| B.I.C. T-2 Cassette Deck | $159 |
| DUAL 606/55 T.T. W/Cart | $219 |
| TECHNICS SA-202 Receiver | $165 |
| PIONEER SX-3700 Receiver | $259 |
| TECHNICS SL-D2 Turntable | $109 |
| AKAI UCU-2 Micro Int. Amp | $159 |
| TECHNICS STZ1 Tuner | $115 |

CAR STEREO

PIONEER

| CASSETTE IN-DASH W/RADIO | |
|---|---|
| KP-1500 | 84.90 |
| KP-2500 | 99.00 |
| KP-4500 | 114.90 |
| KP-5500 | 124.90 |
| KP-8500 | 141.90 |
| KE-2100 | 174.90 |
| KE-3000 | 209.90 |
| KEX-20 | 214.90 |
| KP-3500-(foreign cars) | 129.90 |
| KP-4502-(foreign cars) | 144.90 |
| KP-8000 | 154.90 |
| KPX9000-(req. amp) | 154.90 |
| KPX9500-(req. amp) | 176.90 |

| CASSETTE UNDER DASH | |
|---|---|
| KP-373 | 84.90 |
| KP-575 | 94.90 |
| KP-500 | 129.90 |
| KP-66G-(req. amp) | 78.50 |
| KP-77G-(req. amp) | 104.90 |
| KP-88G-(req. amp) | 99.90 |
| KPX600 | 118.90 |
| KP707G | 144.90 |

| POWER AMPS/EQUALIZERS | |
|---|---|
| BP-320 | 49.90 |
| AD-30 | 89.90 |
| AD-50 | 141.90 |
| GM-40 | 49.90 |
| GM-120 | 106.90 |
| CD-5 | 89.90 |

| CAR SPEAKERS | |
|---|---|
| TS-M2 | 32.90/PAIR |
| TS-T3 | 32.90/PAIR |
| TS107 | 37.90/PAIR |
| TS167 | 44.90 PAIR |
| TS168 | 82.90/PAIR |
| TS695 | 82.90 PAIR |
| TS-X6 | 69.90/PAIR |
| TX-X9 | 129.90/PAIR |

WE ALSO CARRY THE FULL LINE OF CAR STEREOS BY PANASONIC, GRUNDIG, MITSUBISHI, CONCORD, SONY, AUDIOVOX AND CRAIG.

JENSEN

| CASSETTE IN-DASH W/RADIO | |
|---|---|
| R-402 receiver | 174.90 |
| R-406 receiver | 199.90 |
| R-410 receiver | 219.90 |
| R-420 receiver | 259.90 |

| SPEAKERS | |
|---|---|
| J-1001 6x9 separates | 94.90 |
| J-1065 6x9 triax | 62.50 |
| J-1033 6x9 triax II | 79.50 |
| J-1201 6x9 coax II thin | 59.90 |
| J-1101 4x10 triax | 62.50 |
| J-1130 4x10 triax II | 79.90 |
| J-1174 5¼ triax | 62.50 |
| J-1124 5¼ triax II | 79.95 |
| J-1188 6½ coax thin | 42.95 |
| J-1069 6x9 coax | 40.50 |
| J-1037 6x9 coax II | 59.50 |
| J-1041 5¼ coax II | 49.50 |

SANYO

| IN-DASH CASSETTE | |
|---|---|
| FT-1496 | 179.95 |
| FT-1498 | 219.90 |
| FT-1495 | 119.95 |
| FT-2400 | 224.90 |
| FT-C2 | 54.90 |
| FT-C4 | 64.90 |
| FT-C6 | 71.90 |
| FT-C8 | 99.90 |
| FT-C10 | 109.90 |
| FT-C16 | 147.90 |

BLAUPUNKT

| | |
|---|---|
| CR-2001 | 238.90 |
| CR-3001 | 432.90 |
| CR-4000 | 259.90 |
| CR-5001 | 331.90 |
| BEA-100 | 107.90 |
| BEA-200 | 174.90 |
| BEA-50 | 74.95 |

CLARION

| | |
|---|---|
| PE-959 programmable | 569.90 |
| PE-9568 | 319.90 |
| PE-7588 | 172.90 |
| PE-554A | 94.90 |
| 100EQB3 | 77.90 |
| 300EQB2 | 137.90 |

BLANK CASSETTES

| AUDIO | |
|---|---|
| AMPEX GRAND MASTER I OR II C90 | 2.99 |
| BASF PRO. I II OR III C90 | 2.99 |
| FUJI FX I OR II, C90 | 2.99 |
| SCOTCH HIGHLANDER C-90-3-PK. | 4.99 |
| MEMOREX HI BIAS C90 | 2.99 |
| SCOTCH MASTER II OR III C90 | 3.25 |
| SONY FECR C90 | 3.25 |
| SONY LNX C90 | 1.64 |
| TDK HD-01 DEMAGNETIZER | 16.95 |
| TDK DC60 | 1.19 |
| TDK DC90 | 1.68 |
| TDK ADC60 | 1.68 |
| TDK ADC90 | 2.45 |
| TDK SAC60 | 2.15 |
| TDK SAC90 | 2.99 |
| TDK MA C90 (METAL) | 6.29 |
| TDK MA C90 (METAL) | 7.99 |
| MAXELL UD, UDXLI, UDXLII CALL OR WRITE FOR PRICES. | TOO LOW TO ADVERTISE. |
| SANSUI AUD 5B Int. Amp | 274.00 |
| TECHNICS SA-303 Receiver | 199.00 |

VIDEO

WE CARRY VIDEO TAPES BY AMPEX, BASF, FUJI, JVC, MAXELL, PANASONIC, MEMOREX, TDK, SCOTCH, SONY, RCA, AND QUASAR.

| | |
|---|---|
| ALL BETA L 500 | 10.95 |
| ALL BETA L 750 | 13.95 |
| ALL VSH T120 (EXCEPT HG) | 14.95 |
| MATTEL INTELLIVISION | 219.90 |
| ATARI VIDEO GAME CX 2600 | 148.95 |
| SPACE INVADERS CARTRIDGE | 23.00 |
| PANA. PV-1400 Video Rec | 889.00 |
| ZENITH VR-9750 | 1020.00 |

WE STOCK B&W AND COLOR TV'S, VHS AND BETA VIDEO RECORDERS, AND HOME MOVIES FROM ALL MAJOR HOLLYWOOD STUDIOS. SEND FOR CATALOGUE.

MINIMUM ORDER 12 TAPES
100% GUARANTEED

ACCESSORIES

| CAR ACCESSORIES | |
|---|---|
| FUZZBUSTER ELITE | 134.95 |
| FOX XK RADAR DETECTOR | 99.50 |
| FOX XKRW (remote) | 109.50 |
| SUPERFOX | 224.90 |
| PAGE ALERT 4000 | 114.95 |
| BELL 810 (superhet) | 154.95 |
| HAR FA-80 (Ant.) | 33.95 |

| MISCELLANEOUS | |
|---|---|
| BIC FM-6 BEAM BOX | 24.90 |
| BIC FM-8 BEAM BOX | 34.90 |
| BIC FM-10 BEAM BOX | 64.90 |
| CASIO C-80 Cal Watch | 44.90 |
| CASIO ML-81 CALCULATOR | 31.95 |
| CHESS CHALLENGER X7 | 87.90 |
| BACKGAMMON CHALLENGER 7 | 85.90 |
| BSR X10 (Kit) | 68.95 |
| BSR X10211 (Timer) | 59.95 |
| BIC B-1 | 19.95 |
| BONE FONE RADIO | 63.95 |
| SONY TPSL2 PORT. STEREO | 179.95 |

| HEADPHONES | |
|---|---|
| KOSS PRO 4/AAA | 46.50 |
| KOSS TECH VFR | 46.50 |
| KOSS HVX/LC | 46.99 |
| SENNHEISER HD-420 | 52.50 |
| SENNHEISER HD-430 | 72.50 |
| AUDIO TECHNICA ATH-7 | 94.90 |
| PIONEER SE-205 | 22.95 |
| SONY MDR-3 | 34.50 |
| SONY MDR-7 | 54.95 |

| CARTRIDGES | |
|---|---|
| SHURE M91ED | 19.95 |
| SHURE M95ED | 29.95 |
| SHURE V15IV | 96.99 |
| PICKERING XSV 3000 | 53.95 |

WE ALSO STOCK AUDIO TECHINICA, EMPIRE, STANTON, ADC. AT LOWEST PRICES.

RECORDS

ALL ROCK, JAZZ & CLASSICAL

All 7.98 List 4.99 · All 8.98 List 5.99 · All 9.98 List 6.99

Cass & 8-Track Same Price as LP: Minimum Order: 5 Records or Tapes

PRICES MAY VARY ON IMPORTED RECORDS We Stock all Major Labels

HOW TO ORDER BY MAIL. For prompt shipment send money order, certified check, cashier's check. Master Charge or Visa (include card number, expiration date and signature). Shipping insurance charge is 5% of total or $3.95 minimum ($5 additional for orders outside of Continental U.S.) N.Y.S. residents add tax. No C.O.D. All merchandise 100% guaranteed brand new and factory fresh. 3 weeks delay on personal checks.

ORDER TOLL FREE (800) 221-8180 Customer Service Hot Line (212) 233-0857
For more information call: 732-8600

J&R MUSIC WORLD

23 PARK ROW, NEW YORK, N.Y. 10038 DEPT. PE

SEND FOR OUR 200 PAGE FREE CATALOG

CIRCLE NO. 34 ON FREE INFORMATION CARD

drives and large data arrays while operating in the high-resolution graphics mode. Address: Mosaic Electronics, Box 748, Oregon City, OR 97045.

**S-100 EPROM Board.** The MB8A 1K-16K EPROM board provides sockets for up to sixteen 2708 EPROMS. The board can operate in 1K increments and the Magic Mapping features allows overlaying RAM and ROM at the same address in any desired increment. Address: SSM Microcomputer Products, 2190 Paragon Dr., San Jose, CA 95131 (Tel: 408-946-7400).

**Winchester Systems.** The C2-D from Ohio Scientific is the same as their C2-OEM system with an 8″ Winchester hard disk, and comes with 52K RAM, serial I/O, bootstrap and diagnostic firmware, and single 8″ floppy drive. Software includes OS-65U small-business operating system and 9-digit Microsoft BASIC. Optional software includes WP-2 word processor, OS-DMS data base manager and information management system, OS-AMCAP small business acounting package, PASCAL, FORTRAN, and assembler/editor. $6,795. The C3-D system uses the triple processor Challenger III with an 8″ Winchester. It incorporates 52K RAM, serial I/O, bootstrap/diagnostic firmware, 8″ floppy disk drive, OS-65A DOS, and 9-digit Microsoft BASIC. Optional software is similar to that for the C2-D system. The machine also runs OS-CP/M complete with assembler/editor, BASIC, FORTRAN, COBOL, and compatible software. $7,600. Address: Ohio Scientific, 1333 South Chillicothe Rd., Aurora, OH 44202 (Tel: 216-831-5600).

## Software

**Dictionary for CP/M.** WordSearch, a program that can be used with WordStar and other CP/M compatible word-processing systems, will help the user produce material free from misspelled words. The "unknown" words are identified by the program as both a list of words or in context of the original text. Words not found in the library are added on command. Word libraries can be tailored to handle special vocabulary requirements. $195. Address: Key Bits Inc., Box 592293, Miami, FL 33159.

**AMI Pascal.** Designed for the Intel MDS, Motorola Exorciser, TI 990/4, Tektronix 8002A, and AMI Phoenix systems, the AMI-Pascal compiler runs under the AMIX operating system and supports such practices as top down, structured, and modular programming. It includes extensions for business programming as well. Separate modules written in assembly language or FORTRAN-77 can be linked. It produces threaded code for use with the resident runtime library of AMIX and can be used for algorithm design and debugging. It requires 48K, dual disks, and CRT terminal. $275. Address: American Microsystems, Inc., 3800 Homestead Rd., Santa Clara, CA 95051 (Tel: 408-246-0330).

**Decathalon Game.** Written for the TRS-80 and Apple machines, Olympic Decathalon is a skill game that encompasses 10 events: 100-meter dash, long jump, pole vault, discus throw, shot put, 400-meter dash, 110-meter hurdles, 1500-meter run, high jump, and javelin throw. Each event is accompanied by animated graphics. Players use a combination of keyboard controls. One to eight players may compete. Cassette version for the TRS-80 requires 16K, disk version requires 32K; Apple disk version is upcoming. $24.95. Address: Microsoft Consumer Products, 400 108th Ave., NE, Suite 200, Bellevue, WA 98004 (Tel: 206-454-1315).

**Medical Business Package.** Apple Business Package V, for the medical profession includes the procedures normally handled by office receptionist, accounts receivable secretary, insurance clerk, and lab technician. It can also be used to analyze personal investments. Five modules are incorporated. These cover patient records, appointment schedules, private patient billing, insurance claims, internal bookeeping and audit, and statistical analysis. $450. Address: CompuSoCo, 25251 Via Roble (Box 2325), Mission Viejo, CA 92690.

**Apple Bowling.** The Bowling Data System for the Apple II provides accurate record keeping and report generation for bowling leagues. It is designed for up to 40 teams, with up to six bowlers per team. For each team, a cumulative record of total pins, games won and lost, total points, high series, etc., is maintained. This information is also maintained for each bowler, as well as high game, handicap, and other data. A season average is also produced, listing each bowler in descending order by average. Requires 32K, Applesoft in ROM, one disk, and an 80-column printer. $79.95. Address: Rainbow Computing Inc., 9719 Reseda Blvd., Northridge, CA 91324 (Tel: 213-349-0300).

**Editor/Assembler.** EDAS 3.4 is a text editor and assembler for the TRS-80 Models I and III. It provides text editing facilities with a command syntax identical to the BASIC editor, and provides text block move, global change with line range directive, string search, and line scroll. Assembler options include ability to suppress source and symbol table listing, generate object code, and output the assembled code directly to memory or diskette. The assembler features direct assembly from

disk; 14-character symbolic labels; concatenated constant declarations for octal, decimal, hex, binary and string constants; paged listings with page, title, subtitle and space psuedo-ops; sorted symbol table; and direct assembly to memory. $82. Address: Misosys, 5904 Edgehill Dr., Alexandria, VA 22303 (Tel: 703-960-2998).

**EE Programs for TRS-80.** Designed for electrical engineering calculations, the E3M Fault Current program uses per-unit calculation and permits an unlimited number of bus voltage levels, panels, and branches. Three-phase symmetrical voltage and fault currents are calculated at any point with or without line voltage drop. Files include characteristics of oil-filled and dry transformers, circuit breakers, switches and all common copper and aluminum busways, wire, and ducts. All varieties of mixed resistive and reactive loads are accepted. The EM5 Lighting Design program calculates the number, spacing, and location of luminaires for a desired level of illumination in up to 100 rooms. Thirty or more projects can exist, and all pertinent data is made available. Address: R.S. McClintock, Box 430980, Miami, FL 33143 (Tel: 305-666-1300).

**Deathmaze 5000.** Written for the TRS-80, Level II 16K machine, this program is a three-dimensional adventure based on activities within a five-story building. All you have to do is try to get out alive. Address: Med Systems Software, Box 2674, Chapel Hill, NC 27514.

**Word Processor.** Written in 8080 machine language and designed to run under CP/M, Spellbinder word processor includes automatic word wrap, print formatting, proportional spacing, screen editing, justification block text manipulation, insertion, deletion, typeovers, search and replace, and emphasis/special characters. It also provides mailing list/label, sort/merge, text/merge and legal numbering functions. The user can create special Macro Programs to fit any individual need. Address: California Pacific Computer Company, 2601 Blackburn, Davis, CA 95616. (Tel: 916-756-2921).

**OSI Software.** HEXDOS 2.3 is a disk operating system designed for use with ROM BASIC. Requiring only 2K, HEXDOS supports a real-time clock, named disk files, trace and single stepping, tone generator, multiple data files, editing, program chaining, interactive disassembler, etc. $27.50. FOCAL-65 for the 6502 allows programs 2 to 3 times more compact than similar BASIC programs. It has 9-digit floating-point arithmetic, and string-handling, all in 8K. $49.50. Address: The 6502 Program Exchange, 2920 West Moana, Reno, NV 89509. ◇


$28

ONE OF THE

Finest Pen Watches in the World at the Lowest Price!

SOLD BY OTHERS FOR $69.95

The Original ARTRON Pen/Watch

The pen/watch is not a revolutionary new product. It has been on the market now for years. Unfortunately, from our experience, almost all were novelty-looking in appearance and cheaply constructed. Comparable pen/watches sell for $60 and more.

UNTIL NOW!

We engage in world trade. Being in the import/export business, we are aware of a countries outstanding products. The Artron Pen is sold worldwide and THE EGBERT CO. is the largest distributor of them in the U.S. Since we buy thousands at a time direct from the manufacturer, we can offer the Artron Pen/Watch at $28 . . . a truly wholesale price.

A UNIQUE COMBINATION

The Artron is an accurate, easy-to-read timepiece, combined with a quality writing instrument. The 100% stainless steel construction and classic styling of the Artron Pen/Watch offers you the quality of the undisputed leaders, such as Cross and Schaeffer, with the addition of an accurate LCD watch (accurate to ± 15 sec. a month). The finest quartz digital watches have comparable accuracies usually somewhere between ± 15 to ± 5 sec. a month.

THE WATCH

The LCD display constantly shows you the hour and minutes without any awkward button pushing. When you need the month and day, you just depress the top of the pen once or twice for seconds. An additional push returns it to the time. The watch is powered by a tiny silver oxide Eveready 392 battery that lasts about two years and is easily replaced.

THE ULTIMATE PRACTICAL GIFT

Your Artron Pen/Watch comes with full instructions, a one year manufacturer's guarantee against defects and its battery in place. Included with every Pen/Watch is the beautiful presentation case shown. When you receive your Artron Pen/Watch, use it constantly for three full weeks. If, after you've thoroughly tested it, you don't agree that your

| CONTINUOUS | 1st PRESS | 2nd PRESS |
|---|---|---|
| 2:36 | 9:19 | :07 |
| TIME READOUT | MONTH DAY | SECONDS |

Artron Pen/Watch represents a major breakthrough in price, quality and value, send it back.

We'll refund your entire investment, including the delivery charge. You can't lose . . . we guarantee it.

Time is of the essence.

We can only guarantee the continuation of this introductory price for a short time.

ORDER TODAY!

©1980 Egbert Co.

**The Egbert Company,** Dept. PE1
11055 Sunset Blvd. ● Los Angeles, CA. 90049

RUSH the following Pen/Watches to me by first class insured mail:

☐ Stainless Steel Model . . . . . **$28 (2 for $52)**
☐ Gold Plated model . . . . . **$38 (2 for $70)**
A Generous 5 Micron
☐ Deluxe Stainless Steel
& Gold Plated models. . . . . **Both for $62**
plus $1.50 postage & handling per order.
Calif. add 6% sales tax.

Enclosed find check or money order for $_____
Charge to my ☐ Visa ☐ Master Charge

Card # _____ Exp. Date _____

Name: _____

Address: _____

City/State/Zip: _____

**For credit card orders only, call TOLL FREE, 24 hours, 7 days: 800-824-7880.**
Ask for operator 107.
In Calif.: 800-852-7777 ● In Alaska/Hawaii: 800-824-7919

**The Egbert Co.**
11055 Sunset Blvd.
Los Angeles, CA 90049

CIRCLE NO. 18 ON FREE INFORMATION CARD

# BUY ONE of these great professional books when you join the

**THE BYTE BOOK OF PASCAL** Edited by Blaise W. Liffick. *340 pp., illus.* In this timely book you get up-to-date *Byte* articles on the subject—from a general introduction to system hardware—from top experts in the field. Includes two versions of a Pascal compiler, one written in BASIC and the other in 8080 assembly language . . . a p-code interpreter written in both Pascal and 8080 assembly language . . . Pascal vs. COBOL . . . a chess-playing program . . . an APL interpreter . . . and more.
**789/673 Pub Pr., $25.00 Club Pr., $19.95**

**AUTOMATIC DATA PROCESSING HANDBOOK.** Edited by The Diebold Group. *976 pp., 269 illus.* Written by a staff of internationally recognized authorities on ADP, this comprehensive handbook explains systems, programming and the languages, communications processes, and the design and installation of today's computers.
**168 /075 Pub Pr., $44.95 Club Pr., $31.50**

**SOFTWARE ENGINEERING** Edited by Randall W. Jensen *and* Charles C. Tonies. *580 pp., illus.* This book examines all phases of software engineering. It provides an integrated treatment of the true foundations of effective project management and also serves as a dependable guide for designing better programs, implementing them more efficiently, and protecting them from theft or misuse.
**788/367 Pub Pr., $27.50 Club Pr., $19.95**

**THE GIANT HANDBOOK OF COMPUTER PROJECTS** By the Editors of 73 Magazine. *504 pp., 217 illus.* This book shows you how to build computer equipment from scratch—either as a hobby in itself or as part of another interest such as amateur radio or electronics. The book starts with the fundamental and then covers such projects as computer games, a bionic clock, a computer-controlled thermometer, and much more.
**582012-9 Pub Pr., $15.95 Club Pr., $13.50**

**PRINTED CIRCUITS HANDBOOK.** Edited by C. F. Coombs, Jr. *2nd Ed., 634 pp., 595 illus.* Covering the subject of printed circuits from the design's idea to final acceptance, this enormously well-received work includes double-sided plated boards through printed boards and also the major variations such as multilayer and flexible circuits.
**126 /089 Pub Pr., $32.50 Club Pr., $24.50**

**ELECTRONICS ENGINEERS' HANDBOOK.** Editor in Chief, D. G. Fink. *2,104 pp., 2026 illus.* Brings together in one instant-reference volume the essential principles, data, and design information known today on the components, circuits, equipment, and systems of all the various specialties that make up modern electronics.
**209/804 Pub. Pr., $57.50 Club Pr., $40.50**

**PRINCIPLES OF INTERACTIVE COMPUTER GRAPHICS.** By William M. Newman and Robert Sproull. *2nd Ed., 544 pp., illus.* Now in a revised, updated Second Edition, this is a volume that has long been THE standard source of information for designers!
**463/387 Pub Pr., $26.95 Club Pr $20.95**

**BIT-SLICE MICROPROCESSOR DESIGN.** By John Mick and Jim Brick. *398 pp.* All in one place—the chunk information you've been needing about the 2900 family of bit-slice microprocessor components. This remarkable "first" designs right before your eyes not just one but two complete 16-bit machines!
**417/814 Pub Pr., $18.50 Club Pr., $14.50**

**MICROPROCESSOR INTERFACING TECHNIQUES.** By Rodney Zaks *and* Austin Lesea. *3rd Ed., 456 pp., with 405 illus., diagrams, and tables.* With the availability of LSI interface chips and the easy-to-follow guidelines in this text, designing an entire system can be almost simple! The book includes input/output techniques for communicating with the external world . . . a survey of the latest interface chips . . . guidelines to interface the CPU to major peripherals . . . a detailed case study of real 32-channel multiplexer . . . tools for troubleshooting microprocessor systems . . . and much more!
**582050-1 Pub Pr., $25.00 Club Pr., $19.95**

## BE SURE TO CONSIDER THESE IMPORTANT TITLES AS WELL—

**16 BIT MICROPROCESSOR ARCHITECTURE.** By T. Dollhoff
582003-X Pub. Pr., $24.95 Club Pr., $19.95

**INFORMATION RETRIEVAL SYSTEMS: Characteristics, Testing and Evaluation, 2/e.** By F. W. Lancaster
582000-5 Pub. Pr., $22.95 Club Pr., $17.95

**MICROPROCESSORS ARCHITECTURE AND PROGRAMMING.** By W. F. Leahy
784/612 Pub. Pr., $24.50 Club Pr., $18.50

**DATA BASE COMPUTERS.** By O. H. Bray & H. A. Freeman
582042-0 Pub. Pr., $19.95 Club Pr., $16.95

**ELECTRONICS DICTIONARY.** By J. Markus
404/313 Pub. Pr., $24.50 Club Pr., $19.50

**SOFTWARE PSYCHOLOGY: Human Factors In Computer and Information Systems.** By B. Shneiderman
789/797 Pub. Pr., $24.95 Club Pr., $18.95

**ANALOG SYSTEMS FOR MICROPROCESSORS AND MINICOMPUTERS.** By P. H. Garrett
786/496 Pub. Pr., $18.95 Club Pr., $14.95

**HANDBOOK OF MICROCIRCUIT DESIGN AND APPLICATION.** By D. F. Stout & M. Kaufman
617/961 Pub. Pr., $34.50 Club Pr., $25.50

**MICROPROCESSORS/MICROCOMPUTERS SYSTEM DESIGN.** By Texas Instruments, Inc.
637/58X Pub. Pr., $24.50 Club Pr., $19.50

**DATA BASE DESIGN.** By G. Wiederhold
701/30X Pub. Pr., $25.95 Club Pr., $19.95



# and GET ONE FREE (values up to $60.00)
# COMPUTER PROFESSIONALS' BOOK CLUB

**MICROCOMPUTER INTERFACING** By Bruce Artwick, *352pp., 117 illus.* In this up-to-date, *complete* design guide you'll find the detailed descriptions and explanations necessary to enable you to select, build, and interface microcomputer systems to virtually all applications. Advanced interface devices and methods are thoroughly examined and illustrated, with emphasis on design procedures, optimization, performance, and reliability.
**789/436 Pub Pr., $21.95 Club Pr., $16.95**

**PROGRAMMING THE 6502** By Rodney Zaks, *2nd Ed., 388 pp., illus., softbound.* A "must" reference work in its original edition, this second edition has been increased by almost 100 pages, with material added to the introductory chapter and to the chapter containing advanced information on data structures. Formulas, diagrams, tables, and practical examples on almost every pate make its contents easy to grasp—and a solid refresher for computer professionals who wish to double-check basics or any specific 6502 features.
**582048-X Pub Pr., $12.95 Club Pr., $10.95**

**ELECTRONIC GAMES, Design, Programming and Troubleshooting.** By W. H. Buchsbaum and R. Mauro. *335 pp., 338 illus.* Information you need to design, program, and troubleshoot electronic games is right here in this widely popular hands-on guide.
**087/210 Pub. Pr., $21.50 Club Pr., $16.50**

**PROGRAMMING THE Z80** By Rodney Zaks. *624 pp., with diagrams, tables, and exercises.* Whether you are already familiar with programming or have never programmed at all, you'll gain a firm understanding of the Z80 with this book. It describes all concepts in simple yet precise terms—building progressively towards more complex techniques.
**582049-8 Pub Pr., $14.95 Club Pr., $12.70**

**COMPUTER DICTIONARY AND HANDBOOK.** By Charles and Robert Sippl. *624 pp., illus.* This handy reference/guide defines and explains a wide range of computer procedures, products, problems, and applications. Appendixes provide a "state-of-the art" guide to essential computer concepts.
**582079-X Pub. Pr., $29.95 Club Pr., $24.95**

**MICROPROCESSOR PROGRAMMING AND SOFTWARE DEVELOPMENT** By F.G. Duncan. *320 pp., with diagrams, tables, and index.* For the experienced professional who's a newcomer to microprocessors . . . this is the introduction to microprocessor programming you've been hoping for! One careful step at a time, the author tracks through his subject with thoroughness and clarity. The detailed discussion is based on four widely used processors—the Motorola 6800, Intel 8080 and 8085, and Zilog Z80.
**582069-2 Pub Pr., $28.00 Club Pr., $21.50**

**SOFTWARE DEBUGGING FOR MICROCOMPUTERS.** By Robert C. Bruce. *351 pp., illus.* In jargon free language, the author takes you through fundamental methods for finding errors, glitches, and faults in programs . . . goes on to more complex techniques for tracking down and exterminating program bugs . . . and then combines these techniques into a complete debugging plan for finding and correcting errors in large, segmented programs.
**582075-7 Pub Pr., $18.95 Club Pr., $14.25**

**MICROPROCESSOR APPLICATIONS MANUAL.** By Motorola Semiconductor Products, Inc. *720 pp., illus., 8½ x 11 format.* With nuts-and-bolts practicality, this manual by the Motorola people (who should know) gives you detailed applications information on microprocessors and assumes no prior knowledge on your part about MPUs.
**435/278 Pub Pr., $42.50 Club Pr., $29.50**




**ENCYCLOPEDIA OF COMPUTER SCIENCE.** Edited by Anthony Ralston and C. L. Meek. *1,500 pp., 60 illus., 100 charts, 7 x 10 format.* This first and only in-depth coverage of the entire field of computer science in a single volume is comprehensive and completely up to date.
**769/01X Pub Pr., $60.00 Club Pr., $39.95**

**PROGRAMMING LANGUAGES.** By Allen B. Tucker, Jr. *439 pp., illus.* Gives you not only the *principles* of design but the *applications* of six major programming languages. Shows you their strengths and weaknesses in solving various representative "benchmark" problems.
**654/158 Pub. Pr., $23.95 Club Pr., $16.95**

**PERSONAL COMPUTING: Hardware and Software Basics** ELECTRONIC BOOK SERIES. *224 pp., 175 illus., outsized 8½ x 11 format.* Gives you comprehensive guidance to the present state of the art in personal computers—an overall survey of the technology, and methods available to perform various tasks, facts about the work others are doing—and just how they are doing it.
**191/514 Pub. Pr., $19.50 Club Pr., $15.50**

## Choose any one of these books at the special club discount, and select any other as your gift Free of Charge when you enroll

## Why YOU should join now!

- **BEST BOOKS IN YOUR FIELD**—Books are selected from a wide range of publishers by expert editors and consultants to give you continuing access to the latest books in your field.
- **BIG SAVINGS**—Build your library and save money too! We guarantee savings of at least 15% off publishers' list prices on every book. Usually 20%, 25% or even higher!

> • **BONUS BOOKS**—You will *immediately begin to participate in our Bonus Book Plan that allows you savings between 70-80%* **off the publisher's price of many books.**

- **CONVENIENCE**—14 times a year you receive the Club Bulletin FREE, fully describing the Main Selection and alternate selections, together with a dated reply card. If you want the Main Selection, you simply do nothing—it will be shipped automatically. If you want an alternate selection—or no book at all—you simply indicate it on the regular reply card and return it by the date specified. You will have at least 10 days to decide. If, because of late mail delivery of the Bulletin you should receive a book you do not want, just return it at the Club's expense.

As a Club member, you agree only to the purchase of four books (including your first selection) over a two-year period.

**Computer Professionals' Book Club**
P.O. Box 582, Hightstown, New Jersey 08520

Please enroll me as a member and send me the two books indicated, billing me for my first selection only of the discounted member's price, plus local tax, postage and handling. If not satisfied, I may return the books within 10 days and my membership will be canceled. I agree to purchase a minimum of 3 additional books during the next 2 years as outlined under the club plan described in this ad. Membership in the club is continuous but cancellable by me any time after the four book purchase requirement has been fulfilled.

Write Code # of FREE selection here _____ Write Code # of FIRST selection here _____

Orders from outside the U.S. must be prepaid with international money orders in U.S. dollars.
Charge my ☐ VISA ☐ MASTER CHARGE* Exp. Date _____
Credit Card # _____ *MC Bank # _____
Signature _____
Name _____
Address _____
City, State, Zip _____
Corporate Affiliation _____

This order subject to acceptance by McGraw-Hill. All prices subject to change without notice. Offer good only to new members. A postage and handling charge is added to all shipments. P39500

# Educator, Entertainer, Accountant.

## Your Challenger Personal Computer.

Through the miracle of modern technology, a complete computer as powerful as the multimillion dollar room-sized computers of a few years ago can be put in a package the size of a typewriter and sells for as little as a color television set!

Through its years of microcomputer experience, Ohio Scientific has effectively channeled this tremendous computer power into a "friendly" computer with hundreds of personal uses, via a huge software library of programs for a broad range of personal, home, educational and business use.

This available software allows you to use and enjoy your computer without becoming an expert. The Challenger, however, is a powerful, general purpose computer which can be programmed in several languages by those who choose to.

Here are just a few of the popular uses of an Ohio Scientific Challenger Computer:

### Education

The personal computer is the ultimate educational aid because it can entertain while it educates. Software available ranges from enhancing your children's basic math, reading and spelling ability, through tutoring high school and college subjects, to teaching the fundamentals of computers and computer programming.

### Entertainment

Many of the Challenger's games educate while they entertain, from cartoons for preschoolers to games which sharpen mathematical and logical abilities. But, entertainment doesn't stop here. The Challenger's graphics capabilities and fast operation allow it to display action games with much more detail than the best video games, providing spectacular action in games such as Invaders, Space Wars, Tiger Tank and more! All popular sports such as golf, baseball and bowling are available as simulated computer games as well as many conventional games such as chess where the computer plays the role of a formidable opponent.

### Accounting

Your Challenger computer can keep track of your checkbook, savings account, loans, expenses, monitor your calorie intake and your biorythms.

If you are involved in a business, you can use it to do word processing; accounting, inventory control, order processing, customer lists, client records, mailing labels and planning.

### And more:

This may seem like a lot of uses, but it's only the tip of the iceberg for a general purpose computer. For example, your Challenger can be expanded to control lights and appliances, manage your energy usage and monitor for fire and break-ins. Furthermore, it can communicate with you, with other computers and the new personal computer information services over the telephone.

In fact, the uses of general purpose, personalized computers are expanding daily as more and more people discover the tremendous capabilities of these new technological wonders.

**Ohio Scientific offers you four personalized computer systems starting at just $479.**

**For a free catalog and the name of the dealer nearest you, call 1-800-321-6850 toll free.**

**OHIO SCIENTIFIC**
a MACOM Company
1333 SOUTH CHILLICOTHE ROAD
AURORA, OH 44202 • (216) 831-5600

CIRCLE NO. 46 ON FREE INFORMATION CARD

Popular Electronics
MARCH 1981

# BEEP! A LOOK AT POCKET PAGERS

How these lightweight, pocket-sized radio devices can keep you as close to home base as the nearest telephone

BY GEORGE LEON

MELODIC audio beeps from a pocket-size, battery-powered paging receiver are alerting perhaps one-million subscribers in the U.S. to call their office or home. And the numbers are growing dramatically as more and more people become aware of the convenience and modest cost of radio pagers.

New types of pagers are constantly being developed to increase convenience and reliability and to meet new demands of subscribers. Many paging companies are combining their services to provide the subscriber with wider-ranging coverage. Already, with some services, it has become possible for the subscriber to travel from one city to another without a break in coverage. At least one paging network offers New York-to-Los Angeles coverage even now; its success has prompted others to follow suit. In the very near future, therefore, we can expect to see paging-service coverage that crisscrosses the nation from coast to coast and border to border.

**What Is a Pager?** The basic radio pager is a simple one-way communication device that emits audio sounds when it detects the proper sequence of selective tone signals sent by a dispatcher. The recipient must then telephone the signal originator to get a message.

The typical pager is hardly larger than a package of cigarettes and weighs




*Fig. 1. Block diagram of a basic paging system made by Motorola.*

4 to 6.5 ounces, including battery. Therefore, it's easy to carry it in a jacket pocket or clipped to a belt.

Unlike a pocket radio, a radio pager has selective tone circuits built into it, allowing only the person or persons being paged to receive the audio alert. Though all pagers in a given network and on the same frequency band intercept a transmitted call signal, only the pager with the appropriate call code is keyed, and only his audio circuit is activated. The beeper operates until the wearer presses a reset button.

To send out the proper code, the originator of a call must dial on an ordinary telephone a seven-digit number that's unique to the particular radio pager. This accesses the paging service, where automatic equipment generates the proper call code. One can also rent equipment from the telephone company that requires only pressing a button to automatically send the tones over the air. The call between the originator and the paging company providing the service is billed as a regular telephone call.




*Fig. 2. Operational diagram of Model R-2 Receiver made by Bogen Div. of Lear-Siegler.*

## TABLE I—CODE CHANNEL TABLE

| First Digit of Code | Second Digit of Code | Third Digit of Code |
|---|---|---|
| 1 | 1 thru 0: Ch. 11 thru 20 (1st Tone) | 1 thru 0: Ch. 26 thru 35 (2nd Tone) |
| 2 | 1 thru 0: Ch. 11 thru 20 (2nd Tone) | 1 thru 0: Ch. 26 thru 35 (1st Tone) |
| 3 | 1 thru 0: Ch. 21 thru 30 (1st Tone) | 1 thru 0: Ch. 36 thru 45 (2nd Tone) |
| 4 | 1 thru 0: Ch. 21 thru 30 (2nd Tone) | 1 thru 0: Ch. 36 thru 45 (1st Tone) |
| 5 | 1 thru 0: Ch. 11 thru 20 (1st Tone) | 1 thru 0: Ch. 36 thru 45 (2nd Tone) |
| 6 | 1 thru 0: Ch. 11 thru 20 (2nd Tone) | 1 thru 0: Ch. 36 thru 45 (1st Tone) |
| 7 | 1 thru 0: Ch. 11 thru 20 (1st Tone) | 1 thru 0: Ch. 46 thru 55 (2nd Tone) |
| 8 | 1 thru 0: Ch. 11 thru 20 (2nd Tone) | 1 thru 0: Ch. 46 thru 55 (1st Tone) |
| 9 | 1 thru 0: Ch. 21 thru 30 (1st Tone) | 1 thru 0: Ch. 46 thru 55 (2nd Tone) |
| 0 | 1 thru 0: Ch. 21 thru 30 (2nd Tone) | 1 thru 0: Ch. 46 thru 55 (1st Tone) |

Most radio pagers currently in use are tone-only devices that indicate to the wearer that he's being paged by sounding a tone. A new variation of the pager, however, provides both tone and voice paging capability. As its name implies, the tone-and-voice pager beeps to alert its wearer that a voice message follows.

For situations in which a subscriber must routinely call either of two locations—a doctor might call his office or his hospital—there is a pager designed to respond to either of two call codes. Each code combination sounds a distinctly different beep alert.

Another model unobtrusively alerts its wearer by using a vibrating action rather than a beep tone. This type can be worn where a beep tone might prove indiscreet. More important, the vibrating beeper is suitable for environments where ambient noise might drown out a beep tone.

While most paging is directed to individuals, a few situations require a group of people to be alerted simultaneously. To meet the demands of, say, volunteer fire departments or emergency medical teams for simultaneous paging, manufacturers have developed the "group-call" pager. Similar to standard tone-alert pagers, group-call pagers generally have a unique call code to permit individual alerts and a second call code shared by every pager in the group. Of course, each group has its own group-call code so that only its members will be alerted.

Radio pagers exist that are even more sophisticated. Among these are two models, developed by Multitone Electric Co., that offer numeric displays in addition to audible alerts and are no larger than an ordinary tone-alert model. Appropriate coding by the paging service will activate a numerical sequence specified by the originator of the message. The displayed numbers can be assigned meanings, such as what telephone number to call, what job is to be performed next, etc.

Radiofone Corp., one of the larger paging service organizations, has also been working with pager manufacturers on two models that may eventually permit alphanumeric messages to be displayed. One would display the number of the caller; the other, now being readied for field testing, will be able to receive a message of up to 50 words that would appear line by line.

## TABLE II—CHANNEL FREQUENCY TABLE

| Channel | Frequency (Hz) |
|---|---|
| 11 | 2704 |
| 12 | 2612 |
| 13 | 2523 |
| 14 | 2437 |
| 15 | 2354 |
| 16 | 2274 |
| 17 | 2196 |
| 18 | 2121 |
| 19 | 2049 |
| 20 | 1980 |
| 21 | 1912 |
| 22 | 1847 |
| 23 | 1784 |
| 24 | 1723 |
| 25 | 1664 |
| 26 | 1608 |
| 27 | 1553 |
| 28 | 1500 |
| 29 | 1449 |
| 30 | 1400 |
| 31 | 1352 |
| 32 | 1306 |
| 33 | 1261 |
| 34 | 1219 |
| 35 | 1177 |
| 36 | 1137 |
| 37 | 1098 |
| 38 | 1061 |
| 39 | 1025 |
| 40 | 990 |
| 41 | 956 |
| 42 | 923 |
| 43 | 892 |
| 44 | 862 |
| 45 | 832 |
| 46 | 804 |
| 47 | 776 |
| 48 | 750 |
| 49 | 725 |
| 50 | 700 |
| 51 | 676 |
| 52 | 653 |
| 53 | 631 |
| 54 | 609 |
| 55 | 588 |

**Technical Details.** A radio pager is capable of receiving and decoding signals radiated from a call-service transmitter, but has no transmitting facilities of its own (Fig. 1).

Besides a radio transmitter, which is obviously necessary, the transmitting section includes an encoder, whose purpose is to generate the unique call (tone) frequencies for any desired pager in the network. The encoder contains a crystal-controlled tone oscillator. Voice output, when used, is fed to the transmitter via a preamplifier module.

The information given in Tables I and II, taken from the Reach Electronics manual, will help show how the encoder selects a specific pager within a network. Assume that the pager to be contacted is keyed to respond to the call code 324. Start by locating the number 3, the first digit of the code, in the left column of Table I. In the second column of row 3, the numbers 1, 2, 3, . . . 0 correspond to channels 21 through 30. Therefore, the second digit of the call code (2) corresponds to channel 22. In the third column of row 3, the last digit of the call code, 4, corresponds to channel 39. We can now determine from the selected channels what tone frequencies must be transmitted to activate the beeper with the call code 324.

Referring now to Table II, it is seen that channel 22, specifying the first tone frequency, corresponds to 1847 Hz. Similarly, channel 39 indicates that the second call-tone frequency is 1025 Hz. Once these two tone frequencies are determined, a timer circuit is necessary to space the tones very precisely. For example, in the GE paging system, the first tone is sent for one second, followed by 180 ms of silence before the second tone is sent. In this system, signalling tone frequencies must be within ±2% of the bandwidth, and the on-time of each tone must be precise.

To obviate problems of intelligibility with voice transmissions, voice-synthesis circuits are used in some transmitters. The final radio transmitter and antenna are fairly conventional.

Receiving circuitry is conventional except that the pager also contains a decoder (Fig. 2). The first stage is typically a superregenerative circuit that detects and amplifies all incoming r-f signals in the receiver bandpass. Detection is also accomplished by this stage. Output from the detector is a high quench frequency in the audio range, with a low-frequency tone or voice signal superimposed on it. Low-pass filtering removes the quench frequency, after which the tones are separated and analyzed by narrow, crystal-controlled

bandpass filters. Finally, if the filters "recognize" the audio-frequency code tones, an audio driver and power amplifier are energized.

Radio pagers generally are assigned to operate in only one of four frequency bands, depending on the type of service the subscriber requires. The low vhf band from 30 to 50 MHz is usually used for on-site coverage of a facility, such as a factory or construction site. For wider coverage, one might choose a pager designed to operate on the high vhf band between 132 and 174 MHz. For even greater coverage, usually obtained through the use of multiple antennas at the call service's facility, a uhf pager that operates between 406 and 420 MHz would prove to be a better choice. Finally, when signal saturation is desired on floors of buildings and in basements in metropolitan areas where there are many tall buildings, a uhf pager that operates in the 420-to-512-MHz range would be required.

Until last year, these were the only bands available for paging services. In mid-1980, however, Motorola announced the availability of a tone-and-voice pager designed to operate at 800 MHz. The new Dimension IV pager from Motorola operates in the 851-to-866-MHz band and is available to only those subscribers who qualify for their own frequencies. This pager is said to be compatible with existing 800-MHz base-station (call-service) equipment and encoders.

Highly efficient integrated circuitry has reduced power demands to where a single AA-size mercury battery will keep a pager operating for almost seven weeks. This eliminates the bulky, heavy nickel-cadmium batteries used in early pagers and the need for daily recharges as well. Higher-efficiency circuits are only a part of the battery long-life story. New circuits such as those used in the Multitone and Motorola pagers automatically switch off the major portions of the pager's circuit in the absence of calls, switching them on again when there is an incoming call.

**What Paging Costs.** Most radio-call companies offer a choice of two plans for their paging services. Under one plan, a monthly charge is levied and includes rental of the pager, handling of calls, and maintenance. Prices under this plan vary according to range of coverage and the number and types of pagers rented. The general range is from $13.50 to $18 per month per pager.

The second plan is designed for the subscriber who wishes to purchase his pagers outright. Cost is about $200 each. In this case, the cost of service including handling of calls and maintenance, ranges from $5 to $8 per month per pager. Again, the exact figure depends on the number and type of pagers being used.

Range of coverage varies from service to service. For example, Beep Communication Systems, Inc. (New York City) offers coverage from Albany and surrounding cities, down through Pennsylvania and parts of Delaware. Radiofone Corp., also in the East, covers about 20,000 square miles and was the first paging-service company to offer coast-to-coast service, connecting New York, Chicago, and Los Angeles via Western Union's Westar satellite. By linking up services in various cities with shared frequencies and exchanging access numbers, a group of paging companies can provide subscribers with a large "umbrella" under which the pager wearer can travel from city to city without loss of service. The most common coverage appears to be 30 to 75 miles.

Considering the modest cost and service, it's small wonder that radio paging has become so popular. The prestigious "beep" has even been known to get one a better table in a restaurant. ◇


EXCITING MAIL ORDER DISCOUNTS

apple® II 16K computer

Disk II with Controller $535 . . . without $429
Nearly Everything for Apple

$949
APPLE II 32K $1049
APPLE II 48K $1149
DOS 3.3 with upgrade kit $54

APPLE II ACCESSORIES

| | |
|---|---|
| Apple-Joystick | 27 |
| ABT Numeric Input Keyboard | 90 |
| ALF Music Synthesizer | 245 |
| Brightpen Lightpen from Softsign | 32 |
| CCS Prototyping Board Model 2 | 29 |
| CCS Programmable Timer Module | 125 |
| Dan Paymer Lower Case Kit (Model 3) | 59 |
| Dan Paymer Lower Case Kit (Model 5) | 75 |
| Hayes Micromodem | 235 |
| Graphics Tablet | 395 |
| Graphics Input Tablet | 645 |
| Intrel II /O Remote Control System | 239 |
| Mark Data Products Lower Case | 164 |
| MAX Sup-R-Term 80 Column Board | 229 |
| Microsoft Z-80 Soft Card | 395 |
| Novation Cat Modem | 159 |
| Numerator | 149 |
| Paymar Lower 2000/40 Word Vocabulary | 159 |
| Sequin Talker Speech Synthesizer | 239 |
| Sup-R-Mod RF TV Modulator | 25 |
| SVA 8" Disc Controller Card | 325 |
| Versa-Writer Digitizer Drawing System | 895 |

WE SHIP FAST!

SOFTWARE

| | |
|---|---|
| Adventure | 27 |
| Apple Writer | 59 |
| Assembler/Disassembler | 35 |
| Applebug Debugger | 27 |
| Apple Graph & Plot System | 25 |
| Applesoft Mailing List System | 44 |
| Applesoft Mailing List Sort & Display | 44 |
| Applewriter Word Processor | 65 |
| Bill Budges Space Game Album | 29 |
| Bill Budges Three Game Cartridge | 29 |
| The Cashier Retail Management System | 195 |
| CCA Data Management by Personal Software | 84 |
| The Controlled Volumes 1-6 Personal Software | 29 |
| Desktop Plan by Personal Software | 84 |
| Dow Jones Portfolio Evaluator | 44 |
| Forth 6 by Programma Software | 59 |
| Forthcar for use with Language System | 115 |
| Fun Pack Programs by Personal Software | 29 |
| Gangster Game-cassette | 27 |
| Gangster II Chase Game-disk | 35 |
| Hopper-disk | 27 |
| Space Invader-Cassette | 24 |
| Space Invader-disk | 30 |
| Sub-Logic FS-1 Flight Simulator Cassette | 23 |
| Sub-Logic FS-1 Flight Simulator-disk | 29 |
| System Apple 80 8080 Simulator | 17 |
| Visicalc by Personal Software | 119 |
| Business Package | 195 |

AND MUCH MORE . . . JUST CALL!

APPLE COMPUTER INTERFACE CARDS

| | |
|---|---|
| Asynchronous Serial Interface #7710A | 2140 |
| Cards Accessory Board | 29.95 |
| CCS Arithmetic Processor Card #7810B | 229 |
| CCS Parallel Interface Card #7728A | 185 |
| CCS Prototyping Board Card | 179 |
| Apple Clock/Calendar Card by Mountain Hardware | 229 |
| Communications Card & GBS Cable | 179 |
| Integer Basic Firmware Card | 149 |
| Language Card for Apple II | 195 |
| Prototyping Hobby Card | 22 |
| Romplus Card with keyboard filter | 169 |
| Romplus Card without keyboard filter | 159 |
| RAM A/D Serial-Parallel I/O Assembled & Tested | 189 |
| Serial Interface Card | 139 |
| Symtec Light Pen Card | 214 |

PRINTERS, MONITORS, DISCS

| | |
|---|---|
| Daisy Wheel Printer | 1795 |
| Anadex DP9500 | 850 |
| Anadex DP9501A | 819 |
| Centronics without cable | 679 |
| Epson TX80 W/ Graphics | 759 |
| Epson MX80 | 645 |
| Epson 100 | 1195 |
| NEC Spinwriter #5513 | 2850 |
| Paper Tiger 460G | 1394 |
| Shinshya with Interface Card | 510 |
| Leedex Video 100-12" B&W | 129 |
| Tandon TM100-1 | 279 |
| Tandon disks (pkg 10) | 30 |
| Memorex (pkg 10) | 40 |
| Verbatim (pkg 10) | 30 |

apple computer
IN STOCK, CALL FOR PRICES!

ATARI 800
PERSONAL COMPUTER SYSTEM
$747

•High Resolution COLOR Graphics •Built-in RF TV modulator
•Full Sound Generator •High speed serial I/O port
•RAM expandable to 48K

*57 key full stroke keyboard

If Atari makes it, we sell it!

| | |
|---|---|
| Atari 400 Computer | $469 |
| Atari 825 Printer | 699 |
| Atari 810 Disk Drive | 569 |
| Atari 410 Program Recorder | 69 |
| Atari 16K RAM Module | 149 |
| Atari 8K RAM Module | 99 |
| Atari Basic ROM | 45 |
| Atari Visicalc | 160 |
| Basketball | 30 |
| Video Easel | 30 |
| Super Breakout | 30 |
| Music Composer | 45 |
| Computer Chess | 30 |
| Star Raiders | 39 |
| 3D Tic-Tac-Toe | 30 |
| Joystick | 19 |
| Assembler/Editor | 45 |

"BEST PRINTER VALUE IN THE WORLD"
Check our prices on THE ULTIMATE IN QUALITY

Epson Printers
APPLE & MOST OTHER COMPUTERS

NEW! MX80, 40, 80, 132 columns
LIST $645
TX 80 col. w/Graphics
$799
Apple Controller & Card & Cable
LIST $110

CALL FOR OUR PRICE
- Most reliable small printers ever sold!
- Uses standard printed paper.
- Dumps Apple screen graphics right on the paper — with graphics option.

Order desk: 1-800-854-2833 / Information line: 714-579-0330

VISA

TO ORDER: Phone orders include using visa, Mastercard, or bank wire transfers. Visa & Mastercard orders ship within 3 weeks extra and include $25 license fee. All equipment is in factory cartons with the manufacturers warranty. Equipment is subject to price change and availability. We ship the same day on most orders. No C.O.D.s accepted. Retail store prices differ from mail order prices.

Cash add 4% sales tax. Foreign orders include 1% handling-minimum $10 plus actual freight. Add $3 for shipping. Add 3 weeks extra and include $25 license fee. All equipment is in factory cartons with the manufacturers warranty. Equipment is subject to price change and availability. We ship the same day on most orders. No C.O.D.s accepted. Retail store prices differ from mail order prices.

master charge

MAIL TO: 1251 BROADWAY EL CAJON CA., 92021

AUTHORIZED SALES & SERVICE

computer specialties
DIVISION OF CMS

CIRCLE NO. 11 ON FREE INFORMATION CARD

# BINARY, OCTAL AND HEXADECIMAL NUMBERS

*How to understand and apply the three basic numbering systems in computer programming*

BY FRED BLECHMAN

MICROCOMPUTER users often need to understand and apply number systems other than the familiar decimal system. The most popular of these is the hexadecimal (base 16) system, with octal (base 8) and binary (base 2) following close behind.

This article will help clear up some of the mysteries regarding these various systems and show how to convert decimal numbers to any of the bases and vice versa. A BASIC computer program that performs hex/decimal conversions is also given.

**The Number Systems.** Tables I through IV are designed to help you learn how the familiar decimal system relates to the binary, octal, and hexadecimal systems.

The values associated with the digits of decimal, binary, octal, and hexadecimal systems are given for the first four places in Tables I-IV. In each case, the left-hand column gives the number (or letter) "code" for that system. The other four columns contain the *decimal numbers* that represent each code location. Since decimal numbers are common to all tables, once you learn how to use these tables you can convert from one number system to another using the equivalent decimal number. The hexadecimal system requires more digits than can be expressed by the characters 0,1,2,3,4,5,6,7,8,9, so the first six letters of the alphabet are added. The full set is thus 0,1,2,3,4,5,6,7,8,9,A,B,C,D,E,F. While FFFF may be an odd-looking expression, it is a valid number in the hexadecimal system.

Using these tables takes some explanation, so let's start with Table I, the Decimal Number System. The decimal code column shows the familiar digits 0-9. Now look at the far right (Column I) which also reads vertically from 0 to 9; ten digits in all. Our base, then, is 10. These numbers are actually the numbers 0 to 9 times the zero power of the base 10. Column II shows each of the Column I digits multiplied by the base, 10, raised to the first power. Column III shows each of the Column I digits multiplied by $10^2$, or 100; column IV shows each multiplied by $10^3$, or 1000.

Suppose you wanted to know the decimal *number* for decimal *code* 6037. This is a 4-digit number, which means we'll use all four columns in the table. The first or most significant digit is 6. Look down the left-hand "Decimal Code" column to 6 and go to the right to Column IV, where you find 6000. Call this the decimal value of Column IV. The next most significant digit is 0. The Column III value for Decimal Code 0 is 0. The next significant digit of 6037 is 3. In Column II, the decimal value for Decimal Code 3 is 30. The last or least significant digit, 7, is seen to equal 7 in Column I for Decimal Code 7. Now simply add the Column I through Column IV values (6000+0+30+7) and you have 6037 (the hard way!).

You can also work backwards—that is, find the decimal *code* for a given decimal *number*. Suppose the decimal number is 2408. Start by finding the *largest* number in the table that is *smaller* than the decimal number 2408. That would be 2000 in Column IV for Decimal Code 2. Therefore, the first decimal digit is 2. Now, subtract 2000 from 2408, leaving a remainder of 408. Again, find the *largest* number in the table *less than* 408. The number is 400, in Column III, for decimal digit 4. Now, the remainder of 8 (after subtracting 400 from 408) *bypasses* Column II and we find the *exact* value, 8, in Column I at Decimal Code 8. This generates *two* decimal code numbers, a 0 for Column II and an 8 for Column I. The result: a decimal code of 2408.

**The Binary Number System.** Table II shows the Binary Number System, using the same tabular approach as shown for the decimal system. Since the binary code consists of only two digits, 0 and 1, the columns use a base of 2. That is, Column I (far right) is 2 to the zero power, times the digit. Column II is 2 to the first power, Column III is 2 to the second power, and so forth. Binary code 0 is 0 in all columns (since zero times anything is zero).

Suppose you had a 4-bit binary code 1011. Starting with Column IV and adding the values wherever a binary code of 1 appears for that column, you have 8+0+2+1 equals 11 in decimal. Going the other way—that is, starting with a decimal number and determining the binary code—use the largest-number subtraction technique described pre-

viously. Suppose you needed the binary code for decimal 14. You'd have a "1" for Column IV. Then, subtracting 8 from 14, you have 6 as a remainder. Column III has a 4, so you have a "1" for Column III, and a remainder of 2 (6−4), which is an *exact* match with Column II. That gives you a binary code of "1" for Column II, and "0" for Column I. The end result is that decimal 14 equals binary 1110.

**The Octal Number System.** Table III shows the Octal Number System using our familiar format. Since the base number is 8 this time, all the columns are powers of 8. For example, the 256 in Column III is 4 times 8 to the second power ($4 \times 8^2$), which equals 4 times 64, or 256. The table is used exactly the same way as the previous tables. Octal code 4273 is equal to decimal 2048+128+56+3, or 2235 decimal. Going the other way, 3273 decimal is equal to 6311 *octal* (3273−3072−192−8−1=0).

The advantage of octal is that a 3-bit binary number (such as 110, 101, etc.), can be represented as a single octal digit, since a 3-bit binary number can only range from 0-7. For example, binary 110 would be octal 6; binary 101 would be octal 5. Thus, a long binary number of 12 bits could be broken up into 4 groups of 3 bits each, and represented by 4 octal digits.

**The Hexadecimal Number System.** Now we arrive at "Destination Hex," where we computer users wanted to go all along. Actually, there are good reasons why hexadecimal numbers are so popular in computing. Most computers use binary 8- or 16-bit "words," 8-bit "bytes" and 4-bit "nybbles" internally. One hexadecimal character can represent a 4-bit nybble, two hex characters an 8-bit byte, and four hex characters a 16-bit word! Thus, hex code provides a reasonable "middle-ground" between the binary code the computer actually processes and the decimal code we humans like to use.

Table IV shows the tabular approach, and a simple BASIC program is also shown. Either will convert from hex to decimal or decimal to hex for the range of 0 to 65535 or 0 to FFFFh. (An h or H is often added to a hexadecimal number to indicate the type of code.)

Look at Table IV, Hex Code column. Since the base for hexadecimal code is 16, we use single-character letters to represent the 10,11,12,13,14 and 15 codes.

The table is used exactly like the previous ones. Thus, 3CB6h is equal to 12288+3072+176+6 or 15542 decimal. Going the other way, 32650 decimal equals 7F8Ah (32650−28672−3840−128−10=0).

**BASIC Hex/Decimal Conversion Program.** Although the program is self-prompting and requires no programming knowledge to operate, you may be interested in how it works. A fair understanding of TRS-80 Level II BASIC language statements and functions is assumed.

Lines 5 to 40 introduce the program and print the conversion limits and "menu" on the screen followed by a blank line. Line 50 asks which way you want to go—decimal-to-hex or hex-to-decimal. You enter a 1 or 2 and line 60 sends you to either line 100 or line 500. Assume you typed and entered a "1." Then M equals "1" and you continue at line 100. (Note that line 60 could also be: IF M=2 GO TO 500). For simplicity, error-trapping is not used, and if you enter *any* number but "2" you'll be at line 100 which clears the screen and tells you how to return to the "menu" or exit the program. Line 110 asks for your decimal number for variable N. Line 111 traps numbers over 65535, and line 112 checks if N is zero for return to menu.

Line 115 sets the value of A equal to N, and also sets counter variable X to zero. Line 120 starts a "countdown" by subtracting 4096 (which is 16 to the third power) from A. Line 130 looks at the result to see if it is less than zero; if it is, then 4096 is added, the variable Z is set to the value of X and the program branches to a subroutine, lines 1000-1060. We'll get to that later.

If, however, line 130 is bypassed because A is zero or larger, then line 140 adds 1 to the value of X and sends the program back to line 120 for another subtraction of 4096.

What's happening here is that the computer is counting down from the top of Column IV of Table IV. Each time it repeats line 120, it is adding to the hex code by 1 (X increases by 1). Finally, when line 130 finds A is less than zero, the value of X is the hex code for the most significant digit. The subroutine starting at line 1000 then defines the value of this digit.

Suppose you enter the decimal number 32650 for N in line 110. Lines 120

**TABLE I—THE DECIMAL NUMBER SYSTEM**

| Decimal Code | IV | III | II | I |
|---|---|---|---|---|
| | $10^3=1000$ | $10^2=100$ | $10^1=10$ | $10^0=1$ |
| 0 | 0 | 0 | 0 | 0 |
| 1 | 1000 | 100 | 10 | 1 |
| 2 | 2000 | 200 | 20 | 2 |
| 3 | 3000 | 300 | 30 | 3 |
| 4 | 4000 | 400 | 40 | 4 |
| 5 | 5000 | 500 | 50 | 5 |
| 6 | 6000 | 600 | 60 | 6 |
| 7 | 7000 | 700 | 70 | 7 |
| 8 | 8000 | 800 | 80 | 8 |
| 9 | 9000 | 900 | 90 | 9 |

**TABLE II—THE BINARY NUMBER SYSTEM**

| Binary Code | IV | III | II | I |
|---|---|---|---|---|
| | $2^3=8$ | $2^2=4$ | $2^1=2$ | $2^0=1$ |
| 0 | 0 | 0 | 0 | 0 |
| 1 | 8 | 4 | 2 | 1 |

and 140 will subtract 4096 seven times until, on the eighth time, the result is −118. The variable X has been advanced by line 140 seven times so it has a value of 7. Line 130 now sees that A is less than zero, so 4096 is added, making A equal to 3978. Variable Z is set equal to 7 (the present value of X) and we move to line 1000.

Line 1000 sees that the value of Z is less than 10, so it sets string-variable X$ equal to STR$(X), the numerical value of X in string form. This allows X$ to be a number or a letter. Here, X$ is equal to a string value of 7.

Lines 1005-1050 are ignored, since Z is equal to 7, and line 1060 returns the program to the latter part of line 130, where the branching took place. The next statement sets E$ to the value of X$, for later use. Then the program is directed to line 145.

Line 145 sets variable B equal to the last value of A, which is 3978 in our example. Then X is reset to zero. Now lines 150-170 subtract 256, inspect for a value less than zero, and count, in the same manner as lines 120-140. After 16 subtractions, B has a value of −118. Line 160 catches this, adds 256 to bring the value of B up to 138, sets Z equal to 15, and branches to line 1000.

Lines 1000-1040 are ignored, since Z equals 15. However, line 1050 is satisfied and X$ is made equal to the letter F. Line 160 then makes F$ equal to F.

Similary, lines 175-200 determine the third hex code, which in the example turns out to be 8, with the final value of C equal to 10. The subroutine at line 1000 sets X$ equal to a string value of 8, and line 190 makes G$ equal to 8.

Line 210 takes the remainder (C in line 190, with a value of 10 in our example) and lets variable D equal this value. It now sets Z equal to D and again goes to line 1000. Since our example has Z equal to 10, line 1000 is ignored, but line 1005 sets X$ equal to the letter A. Lines 1010-1050 are ignored, line 1060 returns the program to the end of line 210 and H$ is set to a value of A.

In memory we have E$ equal to 7, F$ equal to F, G$ equal to 8 and H$ equal to A. Line 220 skips a line on the screen and prints out 7F8A and line 225 prints a message reminding you to ignore leading zeros. Then line 230 sends the program back to line 110 for another decimal number after printing a blank screen line.

**Hex-To-Decimal Conversion.** If you had indicated, as a response to line 50, that you wanted hex-to-decimal conversion by typing and entering a "2," the program would branch to line 500. The screen is cleared, two blank lines are printed, followed by the menu/exit message and a blank line. Line 510 prints a prompt asking for the hexadecimal value, V$. If you enter zero, line 511 returns the program to the menu. Suppose you type in 45FD. Line 512 makes sure this is a 4-character string by adding leading zeros if necessary. Line 520 extracts the rightmost character of V$ and makes X$ equal to it. In our example, this would make X$ equal to D. Now the program branches to a subroutine starting at line 2000.

Line 2000 looks at X$ to see if it has a value less than A. Since numbers come before letters in the computer's pre-programmed ROM value sequence, the letter D allows the program to "fall thru" to line 2030. Since X$ *is* equal to D, this program line now makes the variable Z equal to 13. Lines 2040 to 2060 are ignored, and line 2070 returns the program to the branching point, the end of line 520. Variable D is made equal to Z, which is currently 13.

Line 2060 is a simple error-trap to keep you from entering any letters beyond F, since they would be invalid in hex code.

Line 530 looks at the third character in X$, which is an F in our 45FD example. The subroutine sets the value of Z to 15 in line 2050 and the end of line 530 makes C equal to 15 times 16 or 240.

Line 550 finds the second character in X$ to be 5. The subroutine catches this value in line 2000 as being less than A, and sets Z to the *decimal* value of 5. (VAL(X$) converts a string value to a numerical value.)

The end of line 550 makes B equal to 5 times 256, or 1280. Similarly, lines 560 and 1000 take the first character (4) of X$ and makes A equal to 4 times 4096, or 16384. Notice that A,B,C and D are all now numerical values, and can be added together. Line 600 does this and prints the result. In our example, 45FD equals 16384 plus 1280 plus 240 plus 13, for a result of 17917 decimal. Line 620 goes to line 510 for another hex number. Line 999 is just good form to identify the beginning of a subroutine, but could be omitted.

**Other Number Conversion Programs.** While the program given here is simple and can be entered from your

**TABLE III—THE OCTAL NUMBER SYSTEM**

| Octal Code | IV $8^3=512$ | III $8^2=64$ | II $8^1=8$ | I $8^0=1$ |
|---|---|---|---|---|
| 0 | 0 | 0 | 0 | 0 |
| 1 | 512 | 64 | 8 | 1 |
| 2 | 1024 | 128 | 16 | 2 |
| 3 | 1536 | 192 | 24 | 3 |
| 4 | 2048 | 256 | 32 | 4 |
| 5 | 2560 | 320 | 40 | 5 |
| 6 | 3072 | 384 | 48 | 6 |
| 7 | 3584 | 448 | 56 | 7 |

**TABLE IV—THE HEXADECIMAL NUMBER SYSTEM**

| Hexadecimal Code | IV $16^3=4096$ | III $16^2=256$ | II $16^1=16$ | I $16^0=1$ |
|---|---|---|---|---|
| 0 | 0 | 0 | 0 | 0 |
| 1 | 4096 | 256 | 16 | 1 |
| 2 | 8192 | 512 | 32 | 2 |
| 3 | 12288 | 768 | 48 | 3 |
| 4 | 16384 | 1024 | 64 | 4 |
| 5 | 20480 | 1280 | 80 | 5 |
| 6 | 24576 | 1536 | 96 | 6 |
| 7 | 28672 | 1792 | 112 | 7 |
| 8 | 32768 | 2048 | 128 | 8 |
| 9 | 36864 | 2304 | 144 | 9 |
| A | 40960 | 2560 | 160 | 10 |
| B | 45056 | 2816 | 176 | 11 |
| C | 49152 | 3072 | 192 | 12 |
| D | 53248 | 3328 | 208 | 13 |
| E | 57344 | 3584 | 224 | 14 |
| F | 61440 | 3840 | 240 | 15 |

# TRS-80™ MODEL III

**48K $1039**

# APPLE · II +

**48K $1119**

# ATARI 800

**48K $1069**

## PRINTERS

| | |
|---|---|
| MICROLINE-80 | $499.00 |
| MICROLINE-82 | $669.00 |
| MICROLINE-83 | $999.00 |
| EPSON MX-70 | $449.00 |
| EPSON MX-80 | $519.00 |
| CENTRONICS 737 | $769.00 |
| VISTA V300 | $1795.00 |

TSE:HARDSIDE

6 South St., Milford, NH 03055 (603) 673-5144

**TOLL FREE OUT-OF-STATE 1-800-258-1790**

TERMS: Prices and specifications are subject to change. HARDSIDE accepts VISA & MASTERCARD. Certified checks and Money Orders; Personal checks accepted (takes 3 weeks to clear). HARDSIDE pays all shipping charges (within 48 states) on all PREPAID orders OVER $100.00. On all orders over $100 a $2.50 handling charge must be added. COD orders accepted (orders over $250 require 25% deposit) there is a $5.00 handling charge. UPS, Blue Label, Air Freight available at extra cost.

CIRCLE NO. 27 ON FREE INFORMATION CARD




### NUMBER CONVERTING PROGRAM

```
5 REM * COPYRIGHT FRED BLECHMAN 1980 *
10 CLS
20  PRINT:PRINT:PRINT:PRINT"                NUMBER CONVERTER PROGRAM"
25 PRINT"          (MAXIMUMS: 65535 DECIMAL, FFFF HEX)"
30 PRINT:PRINT"(1) DECIMAL TO HEX CONVERSION
40 PRINT"(2) HEX TO DECIMAL CONVERSION
50 PRINT:INPUT"WHICH DO YOU WANT, 1 OR 2";M
60 ON M GOTO100,500
100 CLS:PRINT:PRINT:PRINT"ENTER 0 FOR MENU, BREAK TO EXIT....":PRINT
110 INPUT"WHAT IS THE DECIMAL NUMBER (65535 MAX,)";N
111 IF N>65535 PRINT"ABOVE 65535 LIMIT! TRY AGAIN...":GOTO110
112 IF N=0 GOTO10
115 A=N:X=0
120 A=A-4096
130 IF A<0 THEN A=A+4096:Z=X:GOSUB1000:E$=X$:GOTO145
140 X=X+1:GOTO120
145 B=A:X=0
150 B=B-256
160 IF B<0 THEN B=B+256:Z=X:GOSUB1000:F$=X$:GOTO175
170 X=X+1:GOTO150
175 C=B:X=0
180 C=C-16
190 IF C<0 THEN C=C+16:Z=X:GOSUB1000:G$=X$:GOTO210
200 X=X+1:GOTO180
210 D=C:Z=D:GOSUB1000:H$=X$
220 PRINT:PRINT"THE HEXADECIMAL VALUE IS: "E$:F$:G$:H$
225 PRINT"(IGNORE LEADING ZEROES....)"
230 PRINT:GOTO110
500 CLS:PRINT:PRINT:PRINT"ENTER 0 FOR MENU, BREAK TO EXIT...":PRINT
510 INPUT"WHAT IS THE HEXADECIMAL VALUE (FFFF MAX,)";V$
511 IF V$="0" GOTO10
512 V$=RIGHT$("0000"+V$,4)
520 X$=RIGHT$(V$,1):GOSUB2000:D=Z
530 X$=MID$(V$,3,1):GOSUB2000:C=Z*16
550 X$=MID$(V$,2,1):GOSUB2000:B=Z*256
560 X$=LEFT$(V$,1):GOSUB2000:A=Z*4096
600 PRINT:PRINT"THE DECIMAL NUMBER IS";A+B+C+D
620 PRINT:GOTO510
999 END
1000 IF Z<10 THEN X$=STR$(Z)
1005 IF Z=10 THEN X$=" A"
1010 IF Z=11 THEN X$=" B"
1020 IF Z=12 THEN X$=" C"
1030 IF Z=13 THEN X$=" D"
1040 IF Z=14 THEN X$=" E"
1050 IF Z=15 THEN X$=" F"
1060 RETURN
2000 IF X$<"A" THEN Z=VAL(X$)
2005 IF X$="A" THEN Z=10
2010 IF X$="B" THEN Z=11
2020 IF X$="C" THEN Z=12
2030 IF X$="D" THEN Z=13
2040 IF X$="E" THEN Z=14
2050 IF X$="F" THEN Z=15
2060 IF X$>"F" PRINT"ERROR!! NO LETTER GREATER THAN F! TRY AGAIN...":GOTO 510
2070 RETURN
```

keyboard in 15 to 20 minutes and stored on cassette or disk, it is limited to hex/decimal conversions and to only four hex characters. Several other cassette programs with more flexibility can be obtained from the following sources:

(1) "BASECONV/BAS" converts any number with a base between 2 and 16. No known limit to number size. Excellent, fast, easy to use. $3.95, postpaid, if payment with order. International Data Services, 340 West 55th St., New York, NY 10019. Phone: 212-757-8046.

(2) "Number/Base Converter" will add, subtract or convert numbers of any base between 2 and 16. No known limit to number size. Very flexible. $6.95, postpaid. Demi-Software, P.O. Box 570, Lynbrook, NY 11563.

(3) "Programmer's Converter" has three programs: Base Calculator converts numbers with bases 2 through 16 and performs calculations, including fractions; Hexadecimal/Decimal Training not only performs conversions but includes a teaching/testing program; Number Base Conversions converts decimal, binary, octal and hexadecimal numbers from zero to FFFF, and displays all four values simultaneously. $9.95 plus $1 shipping. Instant Software, Peterborough, NH 03458.

(4) "HEX-DEC Converter" provides hexadecimal-to-decimal or decimal-to-hexadecimal conversions "in memory" up to 65535 decimal or FFFF hex. It can be used during the writing of a BASIC program by using SHIFT-D to convert from decimal or SHIFT-H to convert from hex. The answer appears on the screen and the program returns to BASIC. Very handy. Uses less than 256 bytes of reserved upper memory. $6.95 postpaid. J. Lindsly, 8106 Quailwood Ct., West Chester, OH 45069.

For $2 postpaid, you can receive a BASIC *listing only* (no cassette) of a "number Conversion Program" that converts decimal, hex, octal and binary numbers in the range of zero to FFFF. Dean R. Zimmerman, 444 North Grove Drive, Alpine, UT 84003. ◇

BY JAMES BARBARELLO AND EDWIN IRIYE

*Inexpensive, accurate instrument measures inductance from 1 microhenry to 1 henry as well as capacitance*

BUILD THE

# Reactance Measuring Set

NOW you can measure the inductance of coils and loudspeaker windings without resorting to expensive laboratory instruments. The Reactance Measuring Set (RMS) presented here will measure inductance from 1 microhenry to 1 henry, using any multimeter as a readout device. Furthermore, capacitance from 1 picofarad to 1 microfarad can be determined.

Accurate, stable, and easy to build, the RMS project uses a measurement technique based on the relationships between currents flowing through and voltages appearing across reactive components. The resulting measurements are not influenced by any effective or internal resistances of the components under test. Moreover, the RMS can be aligned without using a precision reference standard. As a bonus, it can function as a crystal-controlled frequency standard. No batteries are needed, thanks to the presence of an internal, line-powered supply.

**Measuring Reactors.** The voltage drop across a pure inductance is directly proportional to the rate at which the magnitude of the current flowing through it changes with time. Mathematically, this is expressed by the differential equation: $v = L\, di/dt$. If a current that has a constant rate of change flows through the inductor, the voltage drop across it will be constant. Similarly, if the waveform of the current that flows through the inductor is a triangle, the resulting voltage is a square wave.

The current that flows through a pure capacitance is directly proportional to the time rate of change of the voltage across it ($i = C\, dv/dt$). If a voltage with a constant rate of change is applied across the capacitance, a current of constant magnitude flows through it. Similarly, if the waveform of the voltage that is applied across the capacitor is a triangle, a square-wave current flows through it.

Now let's look at a block diagram of the RMS ( Fig. 1). A triangle-wave voltage source is the heart of the measurement circuit. It drives both a voltage-dependent current source and a buffer/voltage-to-current converter stage. The former generates a triangle-wave current which is applied to an inductance whose value is to be determined ($L_X$). If a value of capacitance is to be measured, a triangle-wave voltage is applied across

the component under test ($C_x$). Conversion of the current through the unknown capacitance into a voltage by the latter stage means that a voltage is applied to the demodulator stage via *S3B* whether an inductance or a capacitance is being measured.

Two basic parameters of the signal generated by the triangle voltage source must be closely controlled if accurate measurements are to be obtained—its amplitude and its period. An agc stage monitors the peak-to-peak amplitude of the triangle voltage source's output and generates a control signal to suppress undesirable variations. To keep the period of the voltage source's output stable, a crystal-controlled clock and a series of frequency-divider stages are employed. The output of this portion of the RMS is a square-wave voltage whose frequency is determined by the setting of RANGE switch *S1* and which governs the frequency (and hence the period) of the triangle voltage source's output.

When the component under test is driven by the triangular test signal, a complex voltage is presented to the RMS demodulator stage. This waveform comprises a square wave, which is due to the reactive portion of the impedance of the component under test, and an added, triangle wave which is due to the resistive portion of the impedance of the component under test. (An ideal reactor contains no resistance, but practical inductors and capacitors do.) To prevent any resistive element of the component from influencing the measurement, the triangle-wave portion of the signal presented to the demodulator is averaged out.

The demodulator responds only to the square-wave portion of the signal applied to it and generates a dc output voltage. A scaling amplifier processes this voltage and presents a dc level to the output terminals of the RMS. This level, which is monitored by means of an external dc voltmeter, is scaled so that the voltage reading represents the actual value of the reactor under test.

**About the Circuit.** The schematic diagram of the RMS appears in Fig. 2. A quartz-crystal oscillator comprising *Q1, Q2, Q3* and their associated passive components generates a 2.0-MHz output signal. This signal is conditioned and its frequency divided by a factor of two by flip-flop *IC1B*, which provides a 1.0-MHz square wave to decade dividers *IC2* through *IC5*. One of the five decade-counter output frequencies (1 MHz, 100 kHz, 10 kHz, 1 kHz or 100 Hz) is selected by *S1A* to drive the active voltage divider comprising *R7, R18* and *Q14*. The divider is part of the agc stage.

Capacitor *C4* couples a portion of the driving signal to the triangle-wave generator comprising *Q5, Q6,* and *Q7* and their associated passive components. This circuit is a bipolar constant-current source which alternately charges and discharges the triangle-generating capacitor selected by *S1B* that is appropriate for the frequency selected by *S1A*. The triangle-wave voltage that appears across this capacitor is monitored by that portion of the agc circuit comprising *Q13, Q14, IC7* and their associated passive components.

The input signal to this portion of the




*Fig. 1. Block diagram of the Reactance Measuring Set. A measurement is performed by synchronous demodulation of the square-wave voltage that appears across the component being tested.*

age stage is first buffered by *Q13* and then peak-detected by *D5* and *D6*. This detected signal is then filtered and compared by *IC7* to a reference provided by voltage divider *R21R22*. The output of *IC7* is the bias applied to the gate of *Q14* that determines the channel resistance of the FET. As a result, the amplitude of the crystal-derived square wave provided to the triangle-wave voltage source is maintained such that the amplitude of the triangle-wave voltage signal remains constant.

Owing to possible differences in device and circuit parameters, an imbalance between the charge and discharge cycles could result. This would in turn cause a net buildup in charge across the triangle generating capacitor, eventually leading to saturation. A modified phase inverter comprising *Q5*, *R10*, *R20*, *R24*, *R26*, and *C36* is utilized to prevent this. The out-of-phase (180° phase-shifted), voltage that appears at the collector of *Q5* is ac-coupled and added to the in-phase, dc-coupled voltage that appears at the emitter of *Q5*. Any tendency for the dc voltage to build up (as a result of differences between the parameters of complementary transistors *Q6* and *Q7*) will automatically change the bias of both *Q6* and *Q7* to stabilize the circuit.

The output of the triangle-wave generator drives both the voltage-controlled current source and the buffer/voltage-to-current converter. The voltage-controlled current generator comprises *Q8*, *Q9*, *Q10*, and their associated passive components, and is similar to the triangle-wave generator. It converts the voltage waveform to an out-of-phase (180° phase-shifted) current which is applied to the inductor to be measured. When the component under test is so driven, a square-wave voltage whose amplitude is directly proportional to the inductance appears across it.

The buffer/current-to-voltage converter (*Q12*, et al) is a common-base amplifier with an extremely low input impedance. From the viewpoint of a capacitor whose value is to be measured, the node *R29Q12* emitter is effectively at ground. Therefore, the magnitude of the current flowing through the capacitor under test depends only on the capacitance and the voltage waveform applied to it. The output impedance of *Q12* is very high, like that of a constant-current source, and the collector current of *Q12* is therefore a replica of the transistor's base current. This arrangement allows the capacitor to "see" an effective ground and simultaneously allows *Q12* to monitor the current flowing through the capacitor under test. The square-wave collector current of *Q12* gives rise to a corresponding square-wave voltage drop across *R34*. This square-wave voltage is buffered by *Q13* and presented to the synchronous demodulator via *S3B*.

The square-wave voltage passed by *S3B* is synchronously demodulated by *IC8*. Synchronous demodulation requires the reference signal supplied to the demodulator to be in phase with the signal from the component under test. However, the square wave generated by the buffer/current-to-voltage converter is 180° out of phase with respect to the voltage generated across an inductor under test. To compensate for this, in the inductance-measuring mode, the reference signal supplied to the demodulator is inverted by NAND gate *IC9C*. The triangle-wave voltage source provides the required 90° phase shift to ensure that the signal generated by the component under test is in phase with the reference signal.

Details of the synchronous-demodulation process follow. The square-wave voltage passed by *S3B* is simultaneously provided to two of the four bilateral switches in *IC8*. During the positive portion of the square-wave input, the signal flows from the input of bilateral switch A (pin 1) to the output of that switch (pin 2). This happens because the reference signal applied to switch A's CONTROL input (pin 13) is positive. During this interval, the phase-inverted signal applied to the CONTROL input of bilateral switch B control is negative. This causes the input-to-output channel resistance of switch B to become very high. On the negative portion of the square-wave input, switch B turns on and switch A turns off. Therefore, the negative portion of the input square wave appears at the output of switch B (pin 3). The two switch outputs are summed and scaled by *IC6*.

Calibration of the RMS does not require precision inductors and capacitors. A resistor of specific value serves as the calibrating component. Transistor *Q4* and flip-flop *IC1A* generate a 10-kHz square wave shifted 90° in phase with respect to the signal that appears at the output of counter *IC3*. During calibration, the signal generated across the calibration resistor, which is connected to the terminals to which the component under test is normally attached, and the output of *IC1A* will be in phase. This allows the demodulator to produce a specific output voltage. The calibration procedure will be described later.

Power for the circuit is provided by the supply shown schematically in Fig. 3. The power supply utilizes IC voltage regulators to produce the ±12 volts dc required by the circuit. A grounded (three-wire) line cord is used for safety purposes. The ±6.8 volts supplied to *IC8* and *IC9* are derived by zener diodes *D7* and *D8*. Because *IC8* and *IC9* must generate bipolar output voltages, this lower supply potential was selected so that the 15-volt maximum differential supply-voltage rating of the CMOS devices would not be exceeded.

**Construction.** Use the full-size etching-and-drilling guide shown in Fig. 4 to make a printed-circuit board, and mount all the fixed resistors shown in the parts placement guide given in Fig. 5. Next, install the diodes, transistors, ICs and jumpers and capacitors.

When all on-board components have been mounted, wire rotary switch *S1*. In the authors' prototype, *S1* was mounted above the board using stiff, solid-conductor wire and capacitors *C10* through *C13* to give mechanical support. We connected one lead of each capacitor to the pc board. Without shortening the leads, the free end of each capacitor was soldered to the appropriate switch lug. Next, we connected pc-board points *S1B2* through *S1B5* to the corresponding terminals of *S1* using stiff, solid-conductor wire. Wire lengths equalled lengths of the capacitor leads soldered to lugs on the opposite side of *S1* so that switch was supported securely above the pc board. Finally, we connected the rotors of *S1* to appropriate pc foil pads.

You might choose another method of mounting *S1* above the pc board. In any event, once the rotary switch has been interconnected with the board, make the necessary connections between the printed-circuit board and the remaining switches, *LED1*, and binding posts *BP1* through *BP6* using suitable lengths of stranded hookup wire. Then interconnect lugs 3 and 6 of *S1A* and *S1B*. Transformer *T1*, the fuseholder for *F1*, power switch *S4* and the line cord should be interconnected and mounted in the project enclosure so as to fit in the large pc-board cutout. Once the transformer has been mounted, the secondary leads of *T1* can be connected.

The enclosure should be machined as necessary to accept all switches and binding holes should be drilled to allow easy adjustment of trimmer potentiometers *R34*, *R39* and *R47* after final assembly. When all switches and binding posts have been installed and connected to the rest of the circuit, the pc board can be mounted in the enclosure using standoffs and suitable hardware.

**Calibration.** Begin by soldering two lengths of stranded hookup wire to the lugs of a 1000-ohm, linear-taper potentiometer so that it will act as a variable resistor. The use of a multiturn potentiometer will simplify matters, but a standard potentiometer can be employed. Utilizing a 3½-digit multimeter, adjust

the potentiometer for a resistance of 856 ohms ± 1%.

Taking care not to disturb the setting of the potentiometer, disconnect its leads from the meter probes and connect them to binding posts *BP3* and *BP4*. Apply power to the project, place *S1* and *S2* in their CALIBRATE positions and *S3* in its L position. Switch the multimeter to its dc-volts operating mode and connect its probes to binding posts *BP3* and *BP4*. Adjust trimmer *R39* for a meter reading of 0 volt. Next, remove the probes from *BP3* and *BP4* and connect them to *BP5* and *BP6* and adjust trim-



mer *R47* for a reading of +10 volts. This completes the calibration of the inductance-measurement function.

Fashion a capacitance-calibration network by connecting one lead of a 10-μF nonpolarized electrolytic capacitor to one side of a 2000-ohm, linear-taper potentiometer that is wired to act as a variable resistor. If a nonpolarized electrolytic capacitor is not available, use two 10-μF, 16-volt tantalum or aluminum electrolytic capacitors connected back-to-back (negative plate to negative plate) instead. Solder a short length of stranded hookup wire to the free lead of the nonpolarized capacitor and another to the uncommitted side of the potentiometer. Connect the probes of the multimeter across the potentiometer and set the meter to read resistance. Adjust the potentiometer for a reading of 1200 ohms ±1%. Remove the ohmmeter probes.

Taking care not to disturb the setting of the potentiometer, connect the leads of the capacitance-calibration network to binding posts *BP1* and *BP2*. Set the multimeter to read dc volts and connect its probes to *BP5* and *BP6*. Set the multimeter to read dc volts and connect its probes to *BP5* and *BP6*. Apply power to the project, place switch *S3* in its C position, and place *S1* and *S2* in their CALIBRATE positions. Adjust *R34* for a meter reading of +10 volts. This completes the calibration of the capacitance-measurement function.

**Using the RMS.** The equivalent circuit of a typical inductor (Fig. 6) contains shunt capacitance and series resistance as well as inductance. Thus, the frequency at which an inductance measurement is performed can influence the reading obtained. Therefore, it should be as close to the actual frequency the inductor will "see" in use as possible. The RMS test frequencies were chosen to meet this requirement for typical applications. Relatively low-value, air-wound coils are generally used in high-frequency applications where stability is important. Ferrite-core inductors are often employed when small size is important. They are usable from dc to approximately 100 MHz, depending on the ferrite mix employed in the manufacture of the core.

In a core inductor, the magnetic characteristics of the core, which include hysteresis and saturation, should be considered, especially if the core has high permeability. Such a component's effective inductance can be affected by the amplitude of the applied signal and any dc bias current flowing through it. Under test conditions, the peak signal voltage applied across $L_X$ is approximately three-tenths of the project's dc output voltage. Under normal conditions, the RMS will apply no dc bias to the inductor under test and will not apply a large enough signal voltage to cause a typical core to saturate.

If inductance-value variation caused by the test signal is suspected, switch to the next higher inductance range. A large increase in measured inductance suggests that the core might have been

*(Continued on page 76)*




## PARTS LIST

BP1 through BP6—Binding posts
C1,C2,C3,C5,C7,C16,C17,C21,C23,C29, C30,C37—0.1-μF, 50-V disc ceramic capacitor
C4—68-pF, 50-V disc ceramic capacitor
C6,C8,C18,C19—47-μF, 16-V, radial-lead electrolytic capacitor
C9—22-pF, 50-V disc ceramic capacitor
C10—0.001-μF, 50-V, 20%, Mylar or monolithic ceramic capacitor
C11,C43—0.01-μF, 50-V, 20%, Mylar or monolithic ceramic capacitor
C12—0.1-μF, 50-V, 20%, Mylar or monolithic ceramic capacitor
C13,C35,C38 through C42—1-μF, 16-V, 20% tolerance tantalum capacitor
C14,C20,C36—22-μF, 16-V, radial-lead electrolytic capacitor
C15—6.8-μF, 16-V, radial-lead electrolytic capacitor
C22—100-μF, 16-V, radial-lead electrolytic capacitor
C24—47-pF, 50-V disc ceramic capacitor
C25,C26—100-pF, 50-V disc ceramic capacitor
C27,C28—10-μF, 16-V, radial-lead electrolytic capacitor
C31—100-μF, 50-V, radial-lead electrolytic capacitor
C32,C33,C44—1000-μF, 25-V, axial-lead electrolytic capacitor
C34—10-μF, 16-V tantalum capacitor
D1 through D4—1N4001 rectifier
D5, D6—1N914 or 1N4148 silicon switching diode
D7,D8—6.8-V, 1-W zener diode (1N5235 or equivalent)
F1—½-ampere fast-blow fuse
IC1—CD4027 J-K flip-flop
IC2 through IC5—CD4017 decade counter
IC6, IC7—μA741CV operational amplifier
IC8—CD4016 quad bilateral switch
IC9—CD4011 quad 2-input NAND gate
IC10—LM340T-12 +12-volt regulator
IC11—LM320T-12 −12-volt regulator
LED1—Red light-emitting diode
Q1,Q2,Q5,Q7,Q8,Q10,Q11,Q13,Q15—2N5129 npn silicon transistor
Q3,Q6,Q9—2N5139 pnp silicon transistor
Q4,Q12—2N918 npn silicon transistor
Q14—2N5457 n-channel JFET
The following, unless otherwise specified, are ¼-W, 10%, carbon-composition fixed resistors.
R1,R4—100 Ω
R2,R5,R10,R14,R33,R37,R48,R49,R53—2.2 kΩ
R3,R51—1.5 kΩ
R6,R21,R26,R30—4.7 kΩ
R7,R19,R23—47 kΩ
R8—220 kΩ
R9,R13,R15,R25,R36,R38,R43,R45,R50—10 kΩ
R11,R12,R27,R28,R32,R41,R42—470 Ω
R16,R17—100 kΩ
R18,R24,R31,R40—6.2 kΩ
R20—3.3 kΩ
R22—27 kΩ
R29—5.1 kΩ
R34,R39—10-kΩ, linear-taper trimmer potentiometer
R35—5.6 kΩ
R44,R46—39 kΩ
R47—200-kΩ, linear-taper trimmer potentiometer
R52—22 kΩ
S1—Two-pole, six-position rotary switch
S2—Spdt toggle switch
S3—Dpdt toggle switch
S4—Spst toggle switch
T1—25.2-V, 300-mA, center-tapped step-down transformer
XTAL—2.0-MHz quartz crystal
Misc.—Printed-circuit board, IC sockets or Molex Soldercons, fuseholder, line cord, sutable enclosure, strain relief, pc standoffs, suitable hardware, hookup wire, solder, etc.

*Note—The following are available from BNB Kits, 72 Cooper Avenue, West Long Branch, NJ 07764: Kit of parts including all components and etched and drilled printed-circuit board but not including enclosure, No. RMS-1, for $129.95 postpaid in U.S.; etched and drilled printed-circuit board only, No. RMS-PC, for $21.95 postpaid in U.S.A. New Jersey residents, add state sales tax.*

# EQUIPMENT AND TRAINING NO OTHER SCHOOL CAN MATCH.

## NTS HOME TRAINING INVITES YOU TO EXPLORE MICROCOMPUTERS, DIGITAL SYSTEMS AND MORE, WITH STATE-OF-THE-ART EQUIPMENT YOU ASSEMBLE AND KEEP.

Without question, microcomputers are the state of the art in electronics. And NTS is the only home study school that enables you to train for this booming field by working with your own production-model microcomputer.

We'll explain the principles of trouble-shooting and testing your microcomputer and, best of all, we'll show you how to program it to do what you want.

You'll use a digital multimeter, a digital logic probe and other sophisticated testing gear to learn how to localize problems and solve them.

Send for the full color catalog in the electronics area of your choice – discover *all* the advantages of home study with NTS!

NTS also offers courses in Auto Mechanics, Air Conditioning and Home Appliances. Check card for more information.

1.

2.

We believe that training on production-model equipment, rather than home-made learning devices, makes home study more exciting and relevant. That's why you'll find such gear in most of NTS's electronics programs.

For instance, to learn Color TV Servicing you'll build and keep the 25-inch (diagonal) NTS/HEATH digital color TV.

In Communications Electronics you'll be able to assemble and keep your own NTS/HEATH 2-meter FM transceiver, plus test equipment.

But no matter which program you choose, NTS's Project Method of instruction helps you quickly to acquire practical know-how.

*Simulated TV Reception*

4.




3.

1. **The NTS/Rockwell AIM 65 Microcomputer** A single board unit with on-board 20 column alphanumeric printer and 20 character display. A 6502-based unit 4K RAM, expandable. 2. **The NTS/KIM-1 Microcomputer** A single board unit with 6 digit LED display and on-board 24 key hexadecimal calculator-type keyboard. A 6502 based microcomputer with 1K RAM, expandable. 3. **The NTS/HEATH H-89 Microcomputer** features floppy disk storage, "smart" video terminal, two Z80 microprocessors, 16K RAM memory, expandable to 48K. 4. **The NTS/HEATH GR-2001 Digital Color TV (25" diagonal)** features specialized AGC-SYNC muting, filtered color and new solid-state high voltage tripler rectifier.

NATIONAL TECHNICAL SCHOOLS

TECHNICAL-TRADE TRAINING SINCE 1905
Resident and Home-Study Schools
**4000 SO. FIGUEROA ST., LOS ANGELES, CA. 90037**

**NATIONAL TECHNICAL SCHOOLS**
4000 South Figueroa Street, Dept. 205-031
Los Angeles, California 90037

Please rush FREE color catalog on course checked below

- ☐ **MicroComputers/MicroProcessors**
- ☐ **Communications Electronics**
- ☐ **Digital Electronics**
- ☐ **Industrial Technology**
- ☐ **Auto Mechanics**
- ☐ **Air Conditioning**
- ☐ **Home Appliances**
- ☐ **Color TV Servicing**

Name _____ Age _____

Address _____

Apt. _____ City _____

State _____ Zip _____

☐ Check if interested in G.I. information.
☐ Check if interested ONLY in classroom training in Los Angeles.

(Continued from page 71)

behaving nonlinearly. Occasionally, it is desirable to dc bias the inductor under test. This can be done by placing a dc milliammeter across the $L_x$ terminals prior to connecting the inductor, and adjusting DC BALANCE potentiometer *R39*. This potentiometer controls the bias of complementary transistors *Q9* and *Q10* and allows them to provide to the inductor under test a dc bias of up to 5 mA.

To make accurate measurements of inductances less than 10 $\mu$H, it is best to use a differential technique. Wind or find a coil whose inductance is approximately 30 to 50 $\mu$H (exact value not critical). Measure its inductance and record it for reference purposes. Next, connect the low-value inductor to be




*Fig. 3. Schematic diagram of the power supply which furnishes the bipolar 12 volts dc required by the circuit.*

*Fig. 4. Full-size etching and drilling guide of the project printed-circuit board.*




*Fig. 5. Component placement guide for the Reactance Measuring Set printed-circuit board. Callouts refer to components and the lugs of switches that are not mounted on the board.*

measured in series with the reference inductor and measure the inductance of the series combination. Subtract the recorded inductance of the reference inductor from this new value. The remainder is the value of the unknown. If reasonable care is taken, this technique will yield good results and offer resolution to 0.1 $\mu$H. Keep in mind, however, that, at such low levels of inductance, the proximity of a metallic object, your body, or the effects of mutual inductance can significantly influence measured values.

The equivalent circuit of a typical capacitor is shown in Fig. 7. Although practical capacitors whose values lie within the measurement range of the RMS more closely approach the ideal than inductors do, it is worth noting two of their peculiarities.

During the charge/discharge cycle, a portion of the applied charge is retained by the dielectric. This *dielectric absorption* increases with frequency and reduces a component's effective capacitance. It is generally not separately specified but lumped with other loss components.




*Fig. 6. The equivalent circuit of a typical inductor contains inductance, series resistance and shunt interwinding capacitance.*

*Fig. 7. The equivalent circuit of a capacitor consists of the capacitance and parallel leakage resistance in series with lead and foil-winding inductance and lead resistance.*

Capacitors, too, have self-resonant frequencies. This is due to stray inductances contributed by foil windings and lead inductances. The self-resonant frequency is really a figure of merit. If the frequency at which the measurement is performed is near the self-resonant frequency, misleading data will result.

The RMS will provide sufficient accuracy for most applications. If you have an inventory of bargain-basement capacitors, you might notice that the voltmeter reading will not settle or will appear to drift. Either condition indicates that the capacitor is unstable and should be used only in the most noncritical applications. To measure small values of capacitance, the use of a differen-

# Let onComputing™ be your guide to personal computing.




## Finally, there is a magazine that speaks to the beginner.

**onComputing** is the new McGraw-Hill quarterly that tells what's ahead — without talking over your head — in the 1980's with personal computers.

**onComputing** puts you on target with all the applications that go beyond your imagination.

- ☐ Personal computers in the home.
- ☐ Classrooms.
- ☐ They bring computer music.
- ☐ Electronic mail.
- ☐ Robots.
- ☐ They manage your personalized investment.
- ☐ The list goes on and on in **onComputing.**

If you're a beginner with personal computers, get the most understood magazine on computers, **onComputing**. And even if you're an experienced computer user, **onComputing** has the information you need in today's fast-growing personal computer market.

## Get onto onComputing. Call 800-258-5485.

**onComputing** Subscription Dept. P.O. Box 307, Martinsville, NJ 08836

DOMESTIC subscription rate:
☐ U.S. 1 yr. (4 issues) @ $8.50 ☐ Canada & Mexico, 1 yr. (4 issues) @ $10.00

FOREIGN (to expedite service, please remit in U.S. funds drawn on a U.S. bank)
☐ Europe (and all other countries, except above), 1 Yr. @ $12.00 — surface delivery.

☐ Bill Visa ☐ Bill Master Charge ☐ Bill me (North America only)

Card Number _____ Expiration _____

Signature _____ Name (please print) _____

Street/Apartment Number _____

City _____ State/Province/Country _____ Code _____

7331

Please allow 6-8 weeks for processing

©onComputing, Inc. 1981

CIRCLE NO. 52 ON FREE INFORMATION CARD




tial measurement technique similar to the one described for inductors is recommended. Measure and record the value of a reference capacitor of about 30 to 50 pF. Then place the unknown capacitor in parallel with the reference capacitor and measure the capacitance of the combination. Subtract the previously recorded reading from this new reading. The remainder is the value of the unknown. Due to the good linearity of the RMS within its useful range, this method will yield an accurate reading with resolution of 0.1 pF. Keep in mind that proximity effects can have great influence on measurements.

If the value of the capacitor under test is completely unknown, always start measurement at a range which is much higher than a reasonably expected value. The RMS can give a misleading capacitance reading in an extreme overrange condition.

**Another Use.** The RMS can be a handy frequency standard. The crystal oscillator and its associated divider stages will provide five decade-related frequencies from 100 Hz to 1 MHz (on the 100 mH/volt to 10 $\mu$H/volt ranges, respectively). For example, to use the RMS to provide marker frequencies spaced 100 kHz apart on a shortwave radio, place switch *S1* in its 100 $\mu$H/VOLT position and connect an 800-$\mu$H inductor to *BP3* and *BP4*. Couple the inductor to the r-f input stage of the receiver by placing it closer to that portion of the receiver enclosure directly above that stage. If the strength of the marker signals is too great, decrease either the value of the inductor or the coupling between it and the receiver.

Basic accuracy of the RMS is conservatively rated at $\pm 5\%$ of its *reading*, except on the lowest range, where the accuracy is approximately $\pm 10\%$ of the reading. Therefore, if a 3½-digit DVM is used with the RMS, on the project's lowest range, measurements will be resolved to the nearest 0.1 pF or 0.1 $\mu$H. Reliance should be placed, however, only on the two most significant digits displayed. The differential-measurement technique will permit resolution to 0.1 pF or 0.1 $\mu$H with the 10% accuracy of the lowest range. Accuracy could be improved if you have access to precision ($\pm 0.1\%$) inductors and capacitors, but, as a practical matter, such accuracy is rarely needed.

The RMS permits fast, convenient, and unambiguous measurement of inductance and capacitance over a wide range of values. Understanding its limitations and the nature of components it measures, you will find it a valuable addition to your test bench. ◇

# BUILD A HIGH-PERFORMANCE PHONO PREAMPLIFIER

BY JOHN ROBERTS

*Features low noise and distortion and allows choice of cartridge types*

ALTHOUGH the phono preamp is often taken for granted, it has a critical and difficult job to perform. The preamp must boost signals on the order of a few millivolts or less to usable levels and, at the same time, compensate for the preemphasis applied to the recorded signals. A further task is to form an appropriate interface with the phono cartridge.

To perform adequately, a preamp must obviously have low noise and low distortion. The circuit must also offer accurate equalization and good input characteristics. To many circuit designers, these requirements are contradictory, resulting in designs in which one or more aspects of phono-preamplifier performance are compromised.

To circumvent some of these compromises, the design given here (Fig. 1) combines high-slew-rate BiFET op amps with discrete devices to form an "instrumentation amplifier" input stage. For fixed-coil pickups (moving-magnet, moving-iron, and similar designs), with their relatively high impedance and signal levels, a low-noise, n-channel, JFET device offers noise performance equal to the best bipolar op amp and an input impedance many times higher. Moving-coil pickups, which have low output impedances and levels, are coupled to ultra-low-noise pnp transistors for noise performance ten times better than the best bipolar op amp with comparable input impedance.

**About the Circuit.** With the exception of input devices and first-stage gain, the fixed- and moving-coil versions are almost identical (Fig. 2). The cartridge output is applied to the circuit's differential input stage and is amplified by 30 dB (60 dB in the MC version). Any undesired, common-mode signals pass through unamplified. The following stage, a differential-to-single-ended converter, adds the oppositely phased signal components and subtracts the common-mode components. This provides excellent rejection of unwanted signals.

The next stage, containing the playback equalization, is built around a precision deemphasis network. Preemphasis and complementary deemphasis are specified by the Recording Industries Association (RIAA) as a set of time constants. The lowest pole (the frequency at which rolloff begins) in playback response is given as 3180 $\mu$s, corresponding to 50 Hz ($f = 1/2\pi T$, where $T$ is the time constant). Below 50 Hz, response is flat. Above this frequency, it falls at $-6$ dB/octave until the frequency corresponding to the next time constant, at 318 $\mu$s (500 Hz). From 500 Hz to the frequency corresponding to the smallest time constant, 75 $\mu$s (2122 Hz), response is again flat, rolling off above 2122 Hz at $-6$ dB/octave. The original standard only specified response from 30 to 15,000 Hz, but it was recently extended to cover 20 to 20,000 Hz.

No problem is caused by the extended high-frequency response (most designers had been doing this all along), but maintaining flat response to 20 Hz limits the amount of attenuation in the 5-10-Hz warp region. To counter this, the International Electro-Technical Commission (IEC) has proposed a fourth time constant of 7950 $\mu$s ($-3$ dB at 20 Hz) be added to the RIAA playback standard (see "Build a Disco Mixer," POPULAR ELECTRONICS, September 1978). The $-6$-dB/octave rolloff starting at 20 Hz that would result attenuates warp signals and, to a slight extent, some of the program material as well ($-1$ dB at 40 Hz). To date, the proposal has not been accepted by the RIAA. This preamp adheres to the RIAA standard, but offers the IEC characteristic as a switch-selectable option.

To reduce warp and infrasonic signals and still maintain flat response down to 20 Hz, a 2-pole active high-pass filter, tuned to 10 Hz has been added. Below 10 Hz, the response rolls off at $-12$ dB/octave. When the IEC time constant is switched in, the resulting response falls at $-18$ dB/octave below 10 Hz. A $\pm 1$-dB trimmer built into the filter allows gain adjustment between the channels for proper balance.

Up to this point in the chain, the signal has been amplified 34 dB (at 1 kHz). An additional 16 dB of gain is subsequently provided for more than is necessary to meet the nominal RIAA gain standard (40 dB at 1 kHz). Some benefit accrues from the fact that this gain is adjustable. High-output cartridges are provided with 6 dB more of overload margin, and low-output cartridges can be amplified up to 10 dB more.

A high-level buffer and selector switch just before the volume control allow a line-level signal to be introduced past the phono equalization/gain stages. This capability facilitates several possible interconnections with an existing system. The project can drive the power amp directly, with the existing control preamp feeding the AUX input. Alternatively, the project can drive a line-level input of the existing preamp, with the




*Fig. 1. Schematic diagram of the moving-magnet or moving-iron phono preamp.*

## PARTS LIST

(Unless marked by a *, two of each component are required for a stereo preamp.)

C1,C8,C9—100-pF, 5% polystyrene capacitor
C2,C3—10-µF, 50-V radial-lead aluminum electrolytic capacitor
C19*—Same as C2 and C3, but used in moving-coil preamp only.
C4—0.15-µF, 10% Mylar film capacitor
C5—0.33-µF, 10% Mylar film capacitor
C6,C7—8200-pF, 1% polystyrene capacitor
C10,C11,C14—0.1-µF, 5% Mylar film capacitor
C12*,C13*,C17*,C18*—0.1-µF, 50-V disc ceramic capacitor
C15*,C16*—1000-µF, 50-V radial-lead aluminum electrolytic capacitor
IC1* through IC4*—TL074CN quad BiFET operational amplifier
J1,J2,J3—Phono jack (J1 must be an insulated jack)
Q1,Q2—Matched pair of pF5103 low-noise JFETs (moving-magnet/iron version of the project)
Q1,Q2—2SB7375 very-low-noise pnp silicon BJT (moving-coil version)
The following, unless otherwise specified, are ¼-watt, 5% tolerance, carbon-film fixed resistors.
R1,R2—750 kΩ
R3,R24—50.1 kΩ, ⅛-W, 1% metal-film
R4—200 Ω
R5,R6,R7,R8,R25—3.01 kΩ, ⅛-W, 1% metal-film
R9, R10—100 kΩ
R35*—same as R9 and R10, but used in moving-coil preamp only
R11,R12,R13,R14,R26,R28,R29—20.0 kΩ, ⅛-W, 1% metal-film
R15—11.8 kΩ, ⅛-W, 1% metal-film
R16—38.3 kΩ, ⅛-W, 1% metal-film
R17—383 kΩ, ⅛-W, 1% metal-film
R18,R19—160 kΩ
R20—3.3 kΩ
R21—6.2 kΩ
R22—4.7 kΩ
R23*—10 kΩ, pc-mount, screwdriver-adjust, linear-taper potentiometer
R27,R31—51 Ω
R31*—50 kΩ, B-volume-taper, panel-mount dual potentiometer
R32*,R33*—10 Ω
R34*—33 kΩ
S1*, S2*, S3*—Pc-mount push/push dpdt switch
Misc.—Printed circuit board, standoffs, suitable metallic enclosure, hookup wire, shielded cable, suitable hardware, hum shield, solder, etc.

## KIT AND PARTS AVAILABILITY

The following are available from Phoenix Systems, 91 Elm St., Manchester, CT 06040 (Tel: 203-643-4484): complete kit of parts, including enclosure but not the optional phono-cartridge input loading network, for the moving-magnet or moving-iron phono preamplifier, No. P-10-MM, for $99.00; complete kit of parts, including enclosure but not the optional phono-cartridge input loading network, for the moving-coil phono preamplifier, No. P-10-MC, for $99.00. Also available separately are: complete kit of parts for the optional phono-cartridge input loading network, No. P-10-IL, for $10.00; etched and drilled main printed-circuit board, No. P-10-PB, for $10.00; ST-4-28 power transformer, No. P-10-T, for $6.50; pair of matched, low-noise 2XpF5103 JFETs, No. P-10-FETS, for $5.00; etched and drilled power-supply printed-circuit board, No. P-10-PSB, for $4.00; dual 50,000-ohm, B-volume-taper potentiometer, No. P-10-DP for $2.50; TL074CN quad BiFET operational amplifier, No. P-10-OA, for $2.50; very-low-noise 2SB7375 pnp bipolar junction transistor, No. P-10-BJT, for $2.00; 8200-pF, 1% tolerance polystyrene capacitor, No. P-10-PCAP, for $1.00. If total is under $10.00, add $1.00 for handling. All prices postpaid in continental U.S. Connecticut residents, add 7½% tax.




*Fig. 2. Partial schematic shows changes required to convert the circuit of Fig. 1 into a moving-coil phono preamp.*

phono preamp's AUX input providing the existing preamplifier's line-level input that would otherwise be lost.

The final stage, a polarity inverter, is partly a concession to those who insist that the absolute polarity of musical waveforms be maintained and partly to facilitate experiments to test their hypothesis. As there is no way to ensure that the polarity of a signal radiated by a speaker matches that of the original acoustic signal, there is a 50/50 chance that the switch will be in the right position. You can try both positions and see if you hear a difference. (I have never found any.) The schematic of a power supply for the preamp is shown below in Fig. 3.

For a phono cartridge to deliver the performance its designer intended, it should be loaded with the proper combination of resistance and capacitance. The preferred method is to solder resistors and capacitors of appropriate values directly across the preamp inputs, but this makes changing loading to suit different cartridges a major chore. The task is simplified by an optional, switchable input load (Fig. 4) that can be adjusted in 25-pF steps. The DIP switch specified has gold/gold contacts. (It is a good idea to exercise the switch once every year or two.)

To determine the correct load capacitance, refer to the manufacturer's literature. Subtract from this the fixed capacitances already present in your system, including those of the tonearm and hookup cables. That of typical shielded cable is 25 to 30 pF/ft. Low-capacitance (CD-4) cable has somewhat less. Next, add the input capacitance of the preamp. (The fixed-coil version has about 110 to 115 pF nominal.) If the total fixed capacitance is close to what is required, you can make up small differences by substituting cables or, if this isn't enough, by changing the value of *C1*. But don't eliminate *C1* entirely.




*Fig. 4. Schematic diagram of the optional, switchable input load.*




*Fig. 3. Schematic diagram of the supply that can be used to power either the moving-magnet/iron or moving-coil phono preamp.*

## POWER SUPPLY PARTS LIST

C1,C5—1000-µF, 35-V, radial-lead aluminum electrolytic capacitor
C2,C3,C6,C7—0.1-µF, 50-V disc ceramic capacitor
C4,C8—10-µF, 25-V radial-lead aluminum electrolytic capacitor
D1 through D4—1N4001 rectifier
F1—¼-ampere fast-blow 3AG-type fuse with pigtail leads
IC1—LM78M15 +15-V regulator
IC2—LM79M15 −15-V regulator
LED1—Light-emitting diode
R1—1000-ohm, ¼-W, 5% fixed carbon-composition resistor
S1—Pc-mount, push/push dpdt switch
T1—28-V, 250-mA, center-tapped pc-mount transformer (Signal Transformer No. ST-4-28 or equivalent)
Misc.—Printed circuit board, standoffs, line cord, strain relief, hookup wire, metal shield, solder, suitable hardware, etc.

Once you have calculated the system's total fixed capacitance, record it to save trouble in the future. Finally, subtract the fixed capacitance from the required capacitance and, if necessary, switch in enough to make up the difference. Note, however, that the loading network is intended for fixed-coil cartridges only.

**Construction.** It is preferable to use a pc board (Figs. 5, 6, and 7). Component layout (Figs. 8 to 11) is similar for the moving-coil and fixed-coil configurations, but there are changes in power-supply connections and IC, transistor, and polarized-capacitor orientation. Rather than design two different pc boards, we can take advantage of the symmetry of the TL074 op amps and rotate them 180 degrees when reversing the power supplies. Take care to follow the appropriate parts-placement diagram closely. Note that *Q1* and *Q2* are JFETs in the fixed-coil circuit and BJTs in the moving-coil preamp. Be sure to




*Fig. 5. Full-size etching and drilling guide for the project's main pc board.*




*Fig. 6. Full-size etching and drilling guide for the power supply's printed circuit board.*

use a hum shield on the end of the main board next to the power supply board as shown in the photo. The shield can be made of a piece of 1/32-inch aluminum stock 2¼" x 4" with one side folded and drilled for mounting in existing holes on the board.

JFET and BiFET op amps are not as sensitive to static discharge as MOS devices. However, recent research has shown that all components can be damaged by static so reasonable caution should be exercised. When assembling the optional input-load board, be sure to have capacitor markings facing up. You can then read them easily when changing loading. The banded end of a polystyrene capacitor denotes its outside foil plate and should be connected to ground to suppress hum.

The input-load board should be mounted inside the preamp's metallic enclosure near the phono input jacks. Use insulated jacks or, better yet, hard-




*Fig. 7. Etching and drilling guide for the optional input load.*




*Fig. 8. Component placement guide for the main printed-circuit board.*




*Fig. 9. Component placement guide reflects changes with respect to Fig. 8. that must be made for assembly of a moving-coil phono preamp.*

# FREE

**The newest in home computers, fine stereo components, color TV, HAM radio, precision test equipment, innovative electronics for the home—all in easy-to-build, money-saving kits.**

***Send today for your FREE Heathkit® Catalog***

If coupon is missing, write Heath Co., Dept. 010-753 Benton Harbor, MI 49022

**Send to: Heath Co., Dept. 010-753 Benton Harbor, MI 49022**

Send my free Heathkit Catalog now. I am not currently receiving your catalog.

Name _____

Address _____

_____

City _____ State _____

CL-724A Zip _____

CIRCLE NO. 29 ON FREE INFORMATION CARD





*Fig. 10. Component placement guide for the power supply pc board.*




*Fig. 11. Component placement guide for the optional, adjustable capacitive phono-cartridge loading network.*



*Photograph of the author's prototype reveals construction details and the presence of a metal shield between the main and power-supply pc boards.*

wire quality phono cables directly to the board. Be sure to include a ground terminal connected to both the metallic enclosure and the ground bus. The turntable ground lead will be attached to this terminal.

**Use.** Connection of a phono preamp into an audio system is straightforward and will not be reviewed here. Remember, though, to balance the right and left outputs of the cartridge by adjusting *R23* for equal levels from both channels while playing a monophonic disc. If you include the input load board, take the time to adjust it as well. Having completed these steps, you can enjoy your system secure in the knowledge that your phono preamp is close to the state of the art. ◇

BUILD AN

# AUTOMATIC LINE VOLTAGE REGULATOR

*When your line voltage nosedives, this circuit gives a 6-volt boost*

BY HERBERT ELKIN *

DO YOUR lights go dim, does your TV picture shrink and lose brightness, or are your ac appliances acting as though they're just plain tired? You may be living in an area subject to "brownouts" (low power-line voltage), and the solution to your troubles could well be some form of voltage regulation.

The automatic line voltage regulator described in this article will automatically raise power-line voltage by about six volts whenever it drops below a preset level. When the line voltage returns to normal, the compensation automatically drops out. (See Fig. 1.)

**Circuit Operation.** Filament transformer *T1* is connected with its 6.3-volt secondary in series with the primary so that the two voltages add. Relay *K1* taps an output from the primary alone or from the combined windings. The remainder of the circuit senses the output voltage and sets (or resets) *K1* to switch the extra winding in or out as needed.

As can be seen from Fig. 1 and the waveforms of Fig. 2, capacitor *C1* follows the swings of the fraction of the power-line voltage developed across the *R2* portion of voltage divider *R1-R2*. Potentiometer *R2* is adjusted so that the peak voltage across *C1* just reaches the firing level of neon lamp *I1* when the voltage across *R1-R2* reaches the level where automatic compensation is not required. The neon lamp breaks down and applies a positive pulse to the gate of *SCR1*, causing the SCR to turn on and hold relay *K1* in the position that directs the normal line voltage to the output. The SCR, then turns off when the power-line voltage passes through zero. The neon lamp fires on each positive half cycle, allowing its glow to be used as a "normal" line voltage indication. During the negative half cycles, diode *D1* clamps *C1* to circuit ground, thus keeping the neon lamp "off" and preventing the negative pulse from being applied to the SCR gate.

Because its drive switches on and off at power-line frequency, relay *K1* would normally "chatter". Capacitor *C4*, connected across the relay coil, prevents this problem as it charges when the SCR fires to provide both filtering (due to rectification of the ac voltage by *SCR1*),

*Loral Electronic Systems, Yonkers, NY.




*Fig. 1. When line voltage drops, K1 adds the 6.3-V secondary of T1 in series with the line to raise the output at SO1.*

## PARTS LIST

C1,C2,C3—0.015-μF, 400-volt ceramic capacitor
C4—4-μF, 250-volt electrolytic
D1—1N2069, 1-ampere, 200-PIV rectifier
F1—3-ampere, slow-blow fuse with holder
I1—NE-51H neon lamp assembly (Dialco 95-0463-0931-211 or similar)
K1—2pdt, 48-volt, 2500-ohm relay (Sigma 62R2-48DC-SCO or similar)
R1—51,000-ohm, ½-W, 10% resistor
R3,R4—56-ohm, ½-W, 10% resistor
R5—47-ohm, ½-W, 10% resistor
R2—100,000-ohm, multi-turn pot.
S1—2pdt switch
SCR1—4-ampere, 200-PIV silicon controlled rectifier
T1—6.3-V 3-A, filament transformer
Misc.—Ac receptable (SO1), terminal strip, suitable enclosure, spacers, mounting hardware, etc.




*Fig. 2. Waveform at (A) is line voltage; (B) is voltage across C1; (D) is SCR conduction angle.*




*Interior photo of the prototype regulator. Components can be mounted on pc or perf board.*

and relay-coil holding current when the SCR is off.

The networks consisting of *R3-C2* and *R4-C3* form arc-suppression circuits to minimize relay contact pitting, while *R5* limits SCR surge current to a safe value. Using the parts shown in Fig. 1, appliances drawing up to 350 VA can be controlled. For higher power, a larger transformer and a relay with heavier contacts can be used. Make sure that fuse *F1* is a slow-blow type to accommodate any turn-on surge currents. To bypass the compensation circuit, switch *S1* can be set to OFF.

**Construction.** With the exception of transformer *T1*, output socket *SO1*, neon lamp assembly *I1*, and on/off switch *S1*, all components can be mounted on a small pc board—or a perf board, using point-to-point wiring. The board can be mounted in any type of enclosure that can accommodate all of the components. The line cord exits through a grommetted hole.

A terminal strip with *nongrounded* lugs must be used for the transformer leads and ac power connections. If a metal enclosure is used, it is important that it be isolated from *both* sides of the power line to prevent a shock hazard.

The windings of *T1* can be phased using the setup shown in Fig. 3. Temporarily connect one secondary lead to one side of the primary as shown. Very carefully (to avoid shock), measure and note the voltage appearing across the transformer primary alone. This is the line voltage. Then measure the voltage across the combined primary/secondary and note that it is 6.3 volts higher. If the voltage indication is *less* than the noted line voltage, phasing is incorrect. Exchange the two secondary leads and repeat the above test. When the combined voltage is higher than the line voltage, you know that the transformer leads are properly phased.

**Calibration.** To adjust the low-voltage trip point, a source of variable line voltage is required. (A Variac or similar device will do.) Adjust the power-line input for 110 volts—or whatever voltage you wish the relay to trip at—and connect an ac voltmeter across the contacts of *SO1*. Vary potentiometer *R2* until neon lamp *I1* glows and note that as this happens the relay is activated, which means that the voltage is not boosted, and the ac voltmeter across *SO1* registers 110 volts.

Carefully rotate *R2* until the neon lamp just extinguishes and the relay de-energizes. The ac voltmeter across *SO1* should move up to approximately 116.3 volts. Slowly increase the input voltage level until the neon lamp lights and note that the ac voltmeter indicates about 112 volts. Set the trip point wherever you want it to occur.




*Fig. 3. Meter should read 6.3 V above line with transformer connected as shown.*

**In Conclusion.** This project represents a simple, inexpensive way to provide some compensation for low power-line voltage. Its regulation is somewhat coarse, but is sufficient for most home appliances. Note that, since relay *K1* interrupts power briefly while switching in the booster winding, the circuit may not be suitable for use with sensitive devices such as computers or digital clocks. ◇

# HOT WINTER PRICES ON PERSONAL COMPUTERS AND COMPONENTS.

## Look at this!

## Ohio Scientific Superboard II $299

- It's the first complete computer system on a board.
- Superboard II uses the ultra powerful 6502 Microprocessor
- 8K Microsoft BASIC-in-ROM
- 4K static RAM on board, expandable to 8K
- Full 53-key keyboard, with upper and lower case. Plus user expandability.
- Video interface and audio cassette interface.

The Ohio Scientific Superboard II at $299 — in today's economy — has got to be the best buy by far. It will entertain you with spectacular graphics made possible by its ultra high resolution graphics and super fast BASIC. It will help you in school or industry, as an ultra powerful scientific calculator. Advanced scientific functions and a built-in "immediate" mode allow you to solve complex problems without programming.

The Superboard II can be expanded economically, for business uses, or to remotely control your home appliances and security. Even communicate with other computers.

### Read what's been written about Superboard II:

**"We heartily recommend Superboard II for the beginner who wants to get into microcomputers with a minimum cost. A real computer with full expandability."**

—POPULAR ELECTRONICS, MARCH 1979

**"The Superboard II is an excellent choice for the personal computer enthusiast on a budget."**

—BYTE, MAY 1979

## Look at these easy hardware prices:

| | |
|---|---|
| **610 Board** For use with Superboard II and Challenger 1P. 8K static RAM. Expandable to 24K or 32K system total. Accepts up to two mini-floppy disk drives. Requires +5V @4.5 amps. | $ 298 |
| **Mini-Floppy Disk Drive** Includes Ohio Scientific's PICO DOS software and connector cable. Compatible with 610 expander board. Requires +12V @1.5 amps and +5V @ 0.7 amps. [Power supply & cabinet not included.] | 299 |
| **630 Board** Contact us for important details. | 229 |
| **AC-3P** 12" combination black and white TV/video monitor. | 159 |
| **4KP** 4K RAM chip set. | 79 |
| **PS-005** 5V 4.5 amp power supply for Superboard II. | 35 |
| **PS-003** 12V power supply for mini-floppies. | 29 |
| **CS-600** Metal case for Superboard II, 610 and 630 board and two power supplies. [While stock lasts.] | 49 |
| **CS-900B** Metal case for single floppy disk drive and power supply. [While stock lasts.] | 49 |
| **AC-12P** Wireless remote control system. Includes control console, two lamp modules and two appliance modules, for use with 630 board. | 175 |
| **AC-17P** Home security system. Includes console, fire detector, window protection devices and door unit for use with 630 board. | 249 |
| **C1P Sams** C1P Service manual | 8 |
| **C4P Sams** C4P Service manual | 16 |
| **C3 Sams** Challenger III manual | 40 |

Ohio Scientific and independent suppliers offer hundreds of programs for the Superboard II, in cassette and mini-floppy form.

**Freight Policies** All orders of $100 or more are shipped Freight prepaid. Orders of less than $100 please add $4.00 to cover shipping costs. Ohio residents add 5.5% Sales Tax.

VISA

Hours: Call Monday thru Friday. 8:00 AM to 5:00 PM E.D.T.
**TOLL FREE: 1-800-321-5805**

**Guaranteed Shipment**
Cleveland Consumer Computers & Components guarantees shipment of computer systems within 48 hours upon receipt of your order. **Our failure to ship within 48 hours entitles you to $35 of software, FREE.**

**To Order:** Or to get our free catalog **CALL 1-800-321-5805 TOLL FREE.** Charge your order to your **VISA** or **MASTER CHARGE** account. Ohio residents call: (216) 464-8047. Or write, including your check or money order, to the address listed below.

**CLEVELAND CONSUMER COMPUTERS & COMPONENTS**
**P.O. Box 46627**
**Cleveland, Ohio 44146**

## Order Form:

**CLEVELAND CONSUMER COMPUTERS & COMPONENTS** **P.O. Box 46627 Cleveland, Ohio 44146**

☐ Superboard II $299. ☐ 630 Board $299.
☐ 610 Board $298. ☐ AC-3P 12" B/W Monitor $159.
☐ Mini-Floppy Disk Drive $299. ☐ C1P Sams Manual $8.
[Attach separate sheet for other items.]

NAME _____
ADDRESS: _____
CITY: _____ STATE: _____ ZIP: _____
PHONE: _____
Payment by: VISA _____ MASTER CHARGE _____ MONEY ORDER _____
Credit Card Account #_____
Expires _____ Interbank #(Master Charge) _____
TOTAL CHARGED OR ENCLOSED $_____ [Ohio Residents add 5.5% Sales Tax]
Orders of less than $100, please add $4.00 to cover shipping costs.
All orders shipped insured UPS unless otherwise requested. FOB Cleveland, Ohio.

CIRCLE NO. 47 ON FREE INFORMATION CARD

# SOLID-STATE DEVELOPMENTS

By Forrest M. Mims

## Magnets, Bubbles and Garnets

MAGNETIC recording tapes and disks provide the cheapest form of mass data storage available. In addition, unlike most semiconductor memories, they offer nonvolatile data storage. That is, information can be retained indefinitely without the need for electrical power.

The biggest drawback of conventional magnetic recording media is that physical movement of the medium with respect to the head or write head with respect to the medium is required to write data onto and read data from the medium. Thus, drive motors are required. These consume considerable amounts of electrical power and result in relatively slow read-write access times.

The drawbacks of conventional magnetic media are obviated by the use of a new, motionless medium in which the data, not the medium, moves. The latter is a thin synthetic ferrite or garnet film containing microscopic magnetic domains which can act as information carriers and which are free to move throughout the crystal. Normally, the domains are serpentine in shape. Under the influence of an external magnetic field, however, the domains become constricted. When the strength of the field is increased to a certain threshold, the domains become cylinders having diameters of 2 to 30 micrometers.

Magnetic domains such as these can be seen through a microscope. When viewed on end, they appear like small circles, hence their popular name *magnetic bubbles*.




*Fig. 1. A bubble, once established, is moved around between soft magnetic bars by rotating magnetic field at left.*

**Advantages of Bubble Memories.** When compared to disk memories, magnetic bubbles offer the advantages of smaller size and no moving parts. The absence of moving parts eliminates the need for periodic maintenance, ensures much higher levels of reliability and provides faster access times. Bubble memories can be cheaper than disk systems in some applications, and price reductions are possible.

Semiconductor memories are faster, easier to interface and smaller than bubble memories. But they are *volatile* and lose their data if power is removed. Bubble memories retain data without the need for electrical power. They may also provide greater storage capacity at less cost than some semiconductor RAMs.

**How They Work.** Andrew H. Bobeck, a scientist at Bell Telephone Laboratories, discovered magnetic bubbles in 1967. He found that magnetic bubbles can move through their garnet matrix much like air bubbles move through water. Place a magnetized needle on the garnet, and it will attract a cluster of bubbles. Move the needle, and the cluster will follow, perhaps attracting additional bubbles along the way. The bubbles in the cluster retain their integrity and don't merge into one large bubble. Each bubble is actually a microscopic magnet and therefore tends to repel its neighbors.

Many ways have been devised to use magnetic bubbles in shift-register type memory systems. A typical memory consists of a ferrite or garnet film which has been epitaxially grown on a crystalline substrate such a gadolinium gallium garnet (GGG). A ferrite-bearing alloy is then deposited in a repetitious pattern on the upper surface of the bubble-containing film.

The metal patterns guide the bubbles through the garnet film in an organized fashion. Various patterns have been used. One consists of tiny bar- and T-shaped elements. Another consists of miniature chevrons. These elements are converted into miniature magnets by the action of an external magnetic field. When the field is rotated, a bubble between two chevrons or between a bar- and a T-shaped element is repelled to-

ward the adjacent element. If the field continues to rotate, the bubble will continue to move along the pattern of elements as shown in Fig. 1.

A bubble generator is required to enter data into a bubble memory. One type of generator consists of a metal disk deposited on the garnet film adjacent to bar and T-shaped elements. A small bump protrudes from the disk. When a rotating magnetic field is applied, a domain is generated adjacent to the disk.




*Fig. 2. Pictorial representation of a magnetic loop bubble generator.*
*(Courtesy Texas Instruments)*

As the field rotates, the domain rotates around the circumference of the disk until it arrives at the bump. The domain is then pulled toward the adjacent elements. The magnetic attraction from the elements then pulls a bubble from the domain, and the bubble proceeds to move along the elements.

This kind of bubble generator supplies a continuous stream of bubbles. To write binary data into the memory in the form of logic ones (bubble present) and logic zeros (bubble absent), a *loop generator* (Fig. 2) can be used. This is simply a very small loop formed on the garnet through which a pulse of current is passed to generate a bubble.

Bubbles are erased by a *bubble annihilator* or, as they are sometimes known, a *bubble eater*. The annihilator sets up a magnetic field which neutralizes any bubbles in its vicinity.

Bubbles can be detected optically or by a magneto-resistive element applied to the garnet. The presence of a bubble under the detector lowers the detector's resistance. The resulting increase in current through the detector is processed by a sense amplifier.

**Practical Applications.** Several years ago, Texas Instruments became the first company to manufacture integrated bubble memories on a commercial basis. In the TI memories, the rotating field is provided by two orthogonal coils mounted above the bubble-containing garnet film. The field is rotated by means of integrated-circuit coil drivers which apply alternating current levels to the two coils. A permanent magnet installed under the substrate provides the magnetic equivalent of a dc bias which preserves the bubbles even when all current is removed from the driving coils.


# ARE THE LIVES OF YOU AND YOUR LOVED ONES WORTH $29.95 AND 14 MINUTES?

Every 17 minutes someone is victimized in his home, and this year one in every 11 families will suffer at the hands of criminals. But the most insidious killer of them all—Night Fires—is on the rise, especially so during the holiday season. Fires kill most of their victims by suffocation long before they've begun to fully blaze. These tragedies kill and maim more people each year than all the people killed in the Vietnam war. These tragedies always seem to happen to someone else, but with crime increasing at almost 20 percent each year and home fires at 12 percent, it won't be long before we will all be affected. What can you do to reduce your chances of involvement in these tragedies?

There are many companies selling all manner of early warning systems and various alarm systems to the homeowner, but unfortunately they seem to be more interested in making large profits than in offering a fully rounded system at a truly affordable price. We have been in the field for many years and have dealt with many people such as yourself, and we have analyzed what the real needs of a homeowner or apartment dweller really are. We know that each system should be reliable, small and preferably provide wireless operation for ease of installation. This last feature means you could move the entire system to a new apartment or a new home, quickly and easily, without losing your investment. We know that each system should be able to detect the poisonous gasses produced by fire as well as protect the entrance ways into your home from intrusion whether you are at home or away. We also know that systems presently sold by several large national manufacturers, offering only the features mentioned above, normally retail at $250 and up, and we're not impressed. This is the age of micro-computers now, not keys and switches.

So. . .we set out to assemble the most advanced home-security package available, using today's technology, at a price no one could afford to be without. It can easily be installed by anyone capable of replacing batteries in his flashlight in just five to ten minutes. If you add the four minutes required to read this ad to the time to install our system, you have the 14 minutes mentioned in our headline. . .And the price of our *Budget System is only $29.95*. Our Budget System consists of: three window/door transensors, one UL-approved poisonous gas transensor, Computerized Control Panel with two-level alarm and our 32-page manual. PLUS at no extra cost we are including a 3-oz. mini-spray can of mace, a safe, humane way to protect yourself and your family until the police arrive, when it's your turn to be next!

We also have a Deluxe System for larger houses consisting of: six window/door transensors, two approved poisonous gas transensors, 3-oz. and 6-oz. spray cans of mace, a Deluxe Computer Console and our 32-page manual. The Deluxe Console features a large digital-readout clock and a programmable 16-level alarm sequencer, which allows you to set your normal weekly schedule into the system. Once set it will cut your exterior alarms on when you are in for the day and your internal alarms on when you are gone for the day, all automatically, until you change the settings. The specially designed circuit continually checks the status of your poison gas detectors, and the built-in battery will run the system for 72 hours should the power fail. With all these features I'm sure you'd expect a price upward of $100 or even $200, but in keeping with our plan to deliver the very best available at a really affordable price, we are pleased to be able to offer our Deluxe Unit for only $59.95 complete.

When you purchase either of our units we will also enclose a copy of Bob Reiner's new book *Safeguarding Your Family*. This book retails for $14.95, but it's yours absolutely free for trying out our system. If at anytime you are not pleased with our system, return it in its original cartons for a complete refund, but keep Bob Reiner's book as a gift for yourself.

These units need no service, repair or maintenance except for installation of a battery every year. No tools are required for installation. Each unit carries a replacement warranty for three years from date of purchase.

**International Security Corporation**
**1703 Raintree Drive,**
**Richmond, VA 23233**

☐ CHECK OR MONEY ORDER
☐ VISA ☐ MASTER CHARGE

Send me ____ Budget Units @ $29.95 each
Send me ____ Deluxe Units @ $59.95 each
Send me ____ extra Door/Window Transensors @ $10.00 each
Send me ____ extra Poison Gas Transensors @ $15.00 each
Credit Card # ____________ Exp. Date ________
Signature ____________
Name ____________
Street ____________
City ____________
State ____________ Zip ________

*Please, do not send cash* *Allow three to six weeks for delivery*

VISA
master charge

CIRCLE NO. 31 ON FREE INFORMATION CARD

# ETCO

## CABLE TV CONVERTERS AND OTHER GOOD STUFF!

**SMASHING ALL SALES RECORDS – OUR NEW 30 CHANNEL CABLE TV CONVERTER!**

Converts most 30 super band cable channels, into any channel on TV set.
No. 2944E047

39.95 $34.95 ea./5

**HOT NEW IMPORT! REMOTE CONTROL 30 CHANNEL CABLE TV CONVERTER!**

Includes remote TV on/off switch and fine tuning control!
No. 2944Z75

89.95 $79.95 ea./5 $76.95 ea./10

**ETCO MKII WIRELESS – THE ULTIMATE CABLE TV CONVERTER!**

Set TV to channel 3, and the hand-held remote control does it all!
No. 2942A008

189.00

**VIDCOR 2000 CONVERTER ELIMINATES PROBLEMS WHEN TAPING FROM CABLE TV**

Restores your VCR's cable bits for programming. Restores remote channel control. Allows viewing of one cable programming while watching another.
No. 2944A002

VIDCOR 2000 VCR CABLE CONVERTER

89.95

**UNUSUAL FACTORY SURPLUS MID-BAND – SUPER-BAND CABLE TV TUNER**

Converts cable channels to a common IF frequency. Experimenters – build cable converters, decoders, etc. With schematic. No. 2944A342

2944A389 – Detailed schematics & spec sheet – $1.50

19.95 $17.50 ea./10

**FACTORY SURPLUS UHF TUNERS**

Brand new production surplus. All solid state. Ideal for experimental work building cable TV converters, etc. No. 2945U099

4.95 $3.95 ea./10

**MINIATURE FM WIRELESS MICROPHONE**

Hidden in the palm of your hand. Reception on any standard FM radio or receiver.
No. 2944A402

29.95 $27.50 ea./5 $24.95 ea./10

**QUARTER-MILE WIRELESS MICROPHONE & RECEIVER SYSTEM**

FCC approved crystal controlled wireless mike & receiver. All battery operated. Electret wide range response. VU meter.
No. 2944A003

69.95 $49.95 ea./5

**ETCO GENERAL PURPOSE TUBE TESTER**

IN KIT FORM. Checks for leakage, shorts, emission. 7, 9-pin, octal, loctal, compactron, nuvistor, miniature tubes.
No. 2946T160
Wired: No. 2947E053 – $70.95
Pin tube adapter: 2947E364 – $18.95

49.95

**DUMPING! NORELCO ENDLESS LOOP CASSETTES!**

Impossible to find at any price!
3 minutes – No. 2944VA005
6 minutes – No. 2944VA006

4.95 $4.45 ea./10

ENDLESS

**IN STOCK – THE MURA CORDLESS TELEPHONE SYSTEM!**

Answer & originate calls with this service saving phone. Ultra lightweight! Last number recall. Page button. Ringer off memory, touch to pulse.
No. 2944A704

144.88 $129.95 ea./5

**SALE OF QUARTZ BATTERY-OPERATED CLOCK MOVEMENT!**

Accuracy of 1 min. / year, up to 4 years operation on 1 alkaline "C" cell. Imported from West Germany. No. 2945VA561

2945VA561 – Matching hands: $2.49/set, $1.95/set / 5

9.95 $8.95 ea./5

**20 AMP REGULATED 12VDC POWER SUPPLY!**

13.8 vdc no load, 12.5 vdc full load. Ideal for operating CB, marine radio, SSB linears up to 400w P.E.P. Brand new, factory sealed cartons. No. 2945A384

2945A386 – as above, 10 amps – $49.95, 39.95 ea./5

59.88 $49.95 ea./5

**FREE** OUR LATEST 98 PAGE FASCINATING CATALOG

Chock full of hard to find electronic bargains and unusual offers. Write or circle the information card number below.

**ETCO** ETCO ELECTRONICS NORTH COUNTRY SHOPPING CENTER PLATTSBURGH, N.Y. 12901

Check with order: phone Visa & Mastercard OK. Money, no C.O.D's. Add 15% for UPS & Handling (Excess refunded). N.Y. State residents add 7% sales tax. Dealer & Export inquiries invited. Our telephone order desk never closes. Call 1-518-561-8700

CIRCLE NO. 22 ON FREE INFORMATION CARD




This permits the bubbles to be stored indefinitely.

Bell Laboratories is experimenting with bubble-memory speech playback units for such computer-generated messages as, "The number you have reached has been disconnected." One unit stores 270,000 bits, enough for a few minutes of speech.

In 1977, TI became the first company to introduce commercial products containing magnetic bubble memories. The products are data terminals, each with a storage capacity of 20K bytes that can be expanded to 80K bytes. Data stored in the terminal's memory can be accessed within 15 milliseconds. Compare this with an access time of from seconds to minutes for terminals with a cassette-tape data storage.

Texas Instruments sells a 92K-bit magnetic-bubble memory kit for $191.00. The kit includes a 92,304-bit bubble memory installed in a 14-pin dual-in-line package containing both one permanent and two orthogonal-coil magnets. The bubble-containing film is imprinted with 144 circular shift registers, each of which contains 641 bit positions. These registers are called *minor loops*. They are all connected to a *major loop* which provides such control functions as bubble generation, replication and annihilation. The bubble detector is also in the major loop.

The major/minor loop arrangement greatly speeds up the memory's access time. It also improves production yield because defective minor loops can be ignored by the external access circuitry.

Defective loops occur due to the ultra-fine geometry of the metalized elements. As many as 13 of the minor loops in a TI bubble memory can be defective without affecting the memory's storage capacity. The hexadecimal addresses for the defective loops are printed on the memory's package. An external PROM can be loaded with the addresses of good loops only so that the addresses of the defective loops can be ignored.

In addition to the bubble-memory chip itself, the TI kit includes a sense-amplifier chip, two coil-driver chips and

*Scientist observing the movement of magnetic bubbles through a microscope.*
*Courtesy Bell Labs.*






*Magnetic bubble memory kit from Texas Instruments.*

a thermistor for temperature compensation. A function-driver chip to control bubble generation and annihilation is also included, as are a timing chip and a controller chip. A single pair of timing and controller chips will drive up to ten bubble-memory chips.

The TI kit does *not* include a printed circuit board, but TI sells several different assembled single-card, bubble-memory systems. These 4.5-X-6.5-inch cards contain from one to four 92K-bit bubble memories and provide 11.5K, 23K, 34.5K or 46K bytes of storage. These systems are compatible with several commercially available microprocessor and microcomputer boards, but their cost is higher than discrete memories offering greater storage capacities. The 11.5K-byte version, for example, is $650. The 46K-byte board sells for $1,215.

Prices for bubble memories and bubble memory products will probably fall in the future as this new memory technology begins to take over applications now dominated by cassette tape and floppy disks. In the meantime, the still more-expensive bubble memories can be used in applications where tape and disk drives are simply too slow. The Texas Instruments 92K-bit bubble memory, for example, has a data rate of 50 kilobits per second and an average access time of only 4 milliseconds.

Bubble memories can also be used to advantage when compact size and small weight are required. The TI memory weighs less than an ounce (.25 grams total) and occupies only 1.25 square inches of board space. And, of course, it has no moving parts and produces no annoying acoustic noise.

**Further Reading.** Many articles about bubble memories have appeared in technical magazines since 1970. For a complete listing, look up the subject in the various guides to periodical literature available at most libraries.

For detailed information about TI's bubble memories, request a copy of the booklet *TIB0203 Magnetic Bubble Memory and Associated Circuits* from a TI distributor, or write to Texas Instruments, Inc., Inquiry Answering Service, Box 225012, M/S 308 (Attn: TIBK090), Dallas, TX 75265.

**New Chips.** Remote-control enthusiasts will be interested in a new pair of encoder/decoder chips available from Signetics (811 East Arques Avenue, Box 409, Sunnyvale, CA 94086). The NE5044N encoder chip can be programmed to handle from three to seven information channels. The NE5045N is a seven-channel decoder chip which accepts either positive or negative serial inputs and provides parallel outputs.

For simpler applications, the NE5046N, a two-channel decoder chip, is available. This chip provides the same 0.3 percent linearity as its more complex counterparts.

In addition to remote control of appliances and toys, these new chips can be used in data-transmission applications. I don't know single-quantity prices for these new chips, but the 100-quantity price is $2.16 for the NE5044N, $1.99 for the NE5045N and $1.08 for the NE5046N.

The voltage comparator offers a straightforward way to detect whether a voltage is greater or less than a specified level. Silicon General (11651 Monarch St., Garden Grove, CA 92641) has taken the comparator a step beyond its usual abilities in developing the SG1542, a new chip that provides a 200-milliampere output when an overvoltage condition occurs. The output can be used to trigger an external SCR crowbar to terminate the overvoltage condition.

The SG1542 also provides outputs for a warning device and indicators of both in-tolerance and out-of-tolerance conditions. If desired, an external capacitor can be added to provide a predictable delay between the detection of the overvoltage and the triggering of the crowbar protection. The chip includes an internal 2.6-volt reference source and has a 4.5-to-40-volt operating range. Cost in 100-unit quantities is $4.00. ◇


# LEARN MICROPROCESSING on your own computer!

**You Learn How To:**

- Design & code microprocessor software
- Use logic & Bit Manipulation Techniques
- Enter & execute programs on your own computer
- Understand Microprocessor Architecture & Support Chips
- Control Programmable Input/Output Ports
- Implement Real-Time Interrupt Handling & Data Transfer
- Design your own microcomputer

8085 MICROPROCESSOR TRAINING UNIT $299.95

**You Will Receive:**

- A fully tested and assembled 8085A Microcomputer with 1K RAM, 1K EPROM and 1K PROM Memory, Programmable I/O, Keyboard Unit, CPU Card, Display and Operating System. 44 pin edge connector can be configured to any bus structure, area on CPU Card for Custom wire-wrap design or user defined interface circuitry, completely expandable
- Complete Step-by-Step Instruction Manual
- Complete User's Manual with programs included
- 352 page 8085A Cookbook takes you from basic microprocessor concepts to actual design of an 8085A Microcomputer
- 344 page 8080/8085 Software Design Book 1 with over 190 executable program examples plus detailed examination of all 244 instructions and typical assembly language program for the 8080/8085 Microprocessor

**Satisfaction Guaranteed.** If not completely satisfied you may return the product within 30 days for a full refund

***RATED BEST VALUE BY INSTRUCTORS***

PACCON
14805 NE 40th, Dept PE 3
REDMOND, WA 98052

CREDIT CARD ORDERS CALL TOLL-FREE
**1-800-426-6254** EXT 3

YES! I want to start learning Microprocessors. Please rush me:
☐ **8085AAF Microprocessor Training Unit at $299.95** plus $30.00 P & H
☐ **8085 Cookbook 21697 $12.95** ☐ **8080/8085 Software Book 21041 $9.50**

NAME
ADDRESS
CITY ST. ZIP
CARD NO. EXP. DATE
SIGNATURE

VISA MC AE DISCOVER

**CIRCLE NO. 53 ON FREE INFORMATION CARD**



ESP

**DON'T BLAME THE SOFTWARE!**

Power Line Spikes and Hash often cause memory loss or erratic operation. Often floppies, printer & processor interact!

OUR unique ISOLATORS eliminate equipment inteaction AND curb damaging Power Line Spikes, Surges and Hash.

3 filtered 3-prong sockets and integral Spike Suppression. 125 VAC, 15 Amp, 1875 W Total - 1 KW per socket.

ISO-1 ISOLATOR. 3- Filtered Sockets; 1000 Amp 8/20 usec Spike Suppressor . . . . . $56.95

ISO-4 ISOLATOR. 6 Filtered Sockets; 1000 Amp 8/20 usec Spike Suppressor . . . . . $96.95

ISO-3 SUPER-ISOLATOR. 3 DUAL filtered Sockets; 2000 Amp 8/20 usec Spike Suppressor . . . . . $85.95

ISO-7 SUPER-ISOLATOR. 5 DUAL filtered Sockets; 2000 Amp 8/20 usec Spike Suppressor . . . . . $139.95

Master-Charge, Visa, American Express
Phone:1-617-655-1532

***Electronic Specialists, Inc.***
171 South Main Street, Natick, Mass. 01760
Dept. PE (617) 655-1532

**CIRCLE NO. 20 ON FREE INFORMATION CARD**

# HOBBY SCENE

By John McVeigh, Technical Editor




## Open-Humidor Alarm

**Q.** *I hope you can help me with a problem. My roommate has an irritating habit of removing cigars from my humidor and forgetting to replace the lid. I really hate to smoke dried-out cigars. Can you publish the schematic of a small circuit that will produce an audible signal after it has been exposed to light for more than a few seconds?—Steve Resnick, Spring Valley, NY*

**A.** The circuit shown schematically in the figure should help keep your cigars fresh. I designed it around the CD4009 CMOS hex inverting buffer. When the lid is lifted off the humidor, the resistance of cadmium-sulfide photocell *LDR1* decreases dramatically and permits sufficient base current to flow into *Q1* to cause the transistor to conduct. This allows *C1* to charge and hex inverter *IC1* (*A* through *F*) to draw current from the battery. When *C1* has charged to slightly more than half of the supply voltage, the output of inverter *A* switches from logic 1 to logic 0 and the output of inverter *B* from logic 0 to logic 1. Pass transistor *Q2* begins to conduct.

In the meantime, the astable multivibrator comprising inverters *C* and *D* and their associated passive components has begun to oscillate at approximately 1000 Hz. The output of the oscillator is applied to inverters *E* and *F*, whose inputs and outputs are connected in parallel. The outputs of these inverters are switching back and forth between logic 0 and logic 1 at a rate determined by the astable multivibrator. Once pass transistor *Q2* has begun to conduct, the inverter outputs can sink current through *R9* and the dynamic speaker to ground during the logic-0 portions of the output cycle. This causes the speaker to emit an audible alert.

It takes about 12 seconds for the circuit to start beeping. That should be enough time for your friend to select the stogie of his choice, but the interval can readily be lengthened or shortened by increasing or decreasing, respectively, the time constant in the delay portion of the circuit (for example, by increasing the value of capacitor *C1*).

Nonsmoking readers can probably find other applications for this circuit, such as an open-refrigerator-door alarm. It can be built using a small piece of perforated board, which could also provide mechanical support for the 9-volt transistor battery and the miniature dynamic speaker. ◇


IS YOUR TRS-80 SMARTER THAN YOU ARE?



Novice. Hobbyist. Educator. Student. Expert. Sams Books can help you get all the performance and features out of the TRS-80 that were built into it. The more you know about the hardware, software, language, and programming involved with the TRS-80, the faster your computer will pay for itself.

THESE SAMS BOOKS WILL HELP YOU USE ALL THE TRS-80 FEATURES YOU PAID FOR

**TRS-80 INTERFACING Books 1 & 2**, By Jonathan A. Titus. Book 1 introduces the signals available within the TRS-80 and how to use them to control external devices. Book 2 explores more advanced interfacing techniques that will allow you to do real things that you didn't even know your TRS-80 could do. BOOK 1 No. 21633, $8.95; BOOK 2 No. 21739, $10.95; TWO-VOLUME SET—Books 1 & 2 No. 21765, $18.50.

**Mostly BASIC: Applications for your TRS-80**, By Howard Berenbon. No. 21788, $11.95. Contains over 15 actual programs for home, entertainment, business, financial and educational use on the TRS-80.

**Z-80 MICROCOMPUTER HANDBOOK**, By William Barden, Jr. No. 21500, $8.95. The more you know about the Z-80 microprocessor—the heart of the TRS-80—the more you can get out of your computer. Here is everything you should know about the hardware, software and microcomputers built around the Z-80.

**Z-80 MICROPROCESSOR PROGRAMMING & INTERFACING Books 1 & 2**, By Elizabeth A. Nichols, Joseph C. Nichols, and Peter R. Rony. Book 1 explores Z-80 software and machine language programming. Book 2 addresses interfacing digital circuits with the Z-80, CPU, PIP, and CTC chips. BOOK 1 No. 21609, $11.95; BOOK 2 No. 21610, $14.95; TWO-VOLUME SET—Books 1 & 2 No. 21611, $24.95.

Sams Books

Mail to: **Howard W. Sams & Co., Inc.**, 4300 West 62nd Street, P.O. Box 7092, Indianapolis, IN 46206, (317) 298-5400

| | | | Quantity |
|---|---|---|---|
| ● **TRS-80 Interfacing—Book 1** | No. 21633 | $ 8.95 | |
| ● **TRS-80 Interfacing—Book 2** | No. 21739 | $10.95 | |
| ● **TWO-VOLUME SET—TRS-80 Interfacing Books 1 & 2** | No. 21765 | $18.50 | |
| ● **Mostly BASIC: Applications for your TRS-80** | No. 21788 | $10.95 | |
| ● **Z-80 Microcomputer Handbook** | No. 21500 | $ 8.95 | |
| ● **Z-80 Microprocessor Programming & Interfacing, Book 1** | No. 21609 | $11.95 | |
| ● **Z-80 Microprocessor Programming & Interfacing Book 2** | No. 21610 | $14.95 | |
| ● **TWO-VOLUME SET—Z-80 Microprocessor Programming & Interfacing Books 1 & 2** | No. 21611 | $24.95 | |
| | | Amount of order | $ |
| | | Add local sales tax where applicable | $ |
| | | Shipping & handling costs | $ 2.00 |
| | | Total amount of order | $ |

☐ Payment Enclosed ☐ Check ☐ Money Order

☐ VISA ☐ Mastercard Interbank No. _____ (minimum credit card purchase $10)

Account No. _____ Expiration Date _____

Name (print) _____ Signature _____

Address _____

City _____ State _____ Zip _____

Prices subject to change without notice. All books available from Sams Distributors, Bookstores, and Computer Stores. Offer good in U.S.A. only. In Canada, contact Lenbrook Industries Ltd., Scarborough, M1H, 1H5, Ontario, Canada. Offer expires 6/30/81

AD072

CIRCLE NO. 57 ON FREE INFORMATION CARD

# EXPERIMENTER'S CORNER

By Forrest M. Mims

## Programmable-Gain Amplifiers

HOW would you like to control the volume of a radio or gain of an amplifier with a series of switches instead of a knob? Or, better still, how would you like to perform this and other, similar functions digitally, perhaps under microprocessor or computer control? If so, read on!




*Fig. 1. An inverting operational amplifier.*

**The Operational Amplifier.** Figure 1 shows a straightforward inverting amplifier built around a standard operational amplifier. The voltage gain of this circuit is the quotient of the value of the feedback resistor($R_F$) divided by the value of the input resistor ($R_{IN}$).

The gain of the amplifier can be altered by varying the values of $R_{IN}$ or $R_F$ or both. In practice, it's usually best to keep $R_{IN}$ fixed because changing it alters the amplifier's input impedance.

Potentiometers are customarily used when it's necessary to make either $R_{IN}$ or $R_F$ variable. Unless expensive ten-turn or detented potentiometers are used, this makes accurate changes in gain difficult. The output of the amplifier must be monitored with an oscilloscope or digital voltmeter while the adjustment is made.




*Fig. 2. Operational amplifier with gain programmable by operation of switches.*

One way to provide selectable fixed, and therefore repeatable, gain settings is to use a parallel network of resistor/switch pairs as shown in Fig. 2. By preselecting the resistor values, any desired gain setting can be achieved by simply closing the appropriate switch. If $R_F$ and $R3$ in Fig. 2 are 10,000 and 1,000 ohms respectively, then the voltage gain will be −10 when only $R3$'s switch is closed. The polarity of the gain figure is negative due to the fact that the amplifier operates in the *inverting* mode.




*Fig. 3. The input switch network of Fig. 2. can be interchanged with the feedback resistance if constant input impedance is required*

The input network and $R_F$ can be interchanged (Fig. 3) if a constant input impedance is required. In this case, if $R_{IN}$ is fixed at 10,000 ohms and $R4$ is one megohm, the voltage gain will be −1,000 when only $R4$'s switch is closed.

**Simplified Programming.** As more gain settings are required, the circuits just presented become impractical because more and more resistors and switches become necessary. One way to reduce circuit complexity while greatly increasing the number of available gain steps is to replace the custom-selected resistor network with a binary-weighted resistor network. Figure 4 shows a four-level network connected in place of $R_{IN}$




*Fig. 4. A binary-weighted resistor network can be used to simplify the overall circuit.*

in an op-amp circuit. Closing various combinations of switches will provide gains of each integer from 1 to 15. The previous circuits would require fifteen resistor/switch pairs to provide this same number of gain steps.

More resistors and switches can be added to provide progressively more gain steps. Eight resistor/switch pairs, for example, will provide 255 gain steps!

It's helpful to understand the operation of the binary-weighted resistor network in Fig. 4. Although its input network has four levels, we can understand how it works by referring to the simpler, three-level version shown in Fig. 5.

First, remember that the total resistance of two or more resistors in parallel is the reciprocal of the sum of the reciprocals of the individual resistors, or $R_{TOTAL} = 1/(1/R1 + 1/R2 + 1/R3 \ldots + 1/RN)$. Knowing this, we can make a table that shows the resistance given by each of the eight possible switch combinations. In this table, a zero represents an open switch and a one a closed switch.

| Switch | | | Resistance |
|---|---|---|---|
| C | B | A | |
| 0 | 0 | 0 | ---- |
| 0 | 0 | 1 | $R$ |
| 0 | 1 | 0 | $R/2$ |
| 0 | 1 | 1 | $1/(1/R + 2/R) = R/3$ |
| 1 | 0 | 0 | $R/4$ |
| 1 | 0 | 1 | $1/(1/R + 4/R) = R/5$ |
| 1 | 1 | 0 | $1/(2/R + 4/R) = R/6$ |
| 1 | 1 | 1 | $1/(1/R + 2/R + 4/R) = R/7$ |

As you can readily see, the seven switch combinations give seven different resistances of descending value. We can make practical use of this table by assigning a value to $R$. If, for instance, $R$ is 40,000 ohms, we obtain:

| Switch | | | Resistance |
|---|---|---|---|
| C | B | A | |
| 0 | 0 | 0 | ---- |
| 0 | 0 | 1 | $R$ = 40,000 |
| 0 | 1 | 0 | $R/2$ = 20,000 |
| 0 | 1 | 1 | $R/3$ = 13,333 |
| 1 | 0 | 0 | $R/4$ = 10,000 |
| 1 | 0 | 1 | $R/5$ = 8,000 |
| 1 | 1 | 0 | $R/6$ = 6,666 |
| 1 | 1 | 1 | $R/7$ = 5,714 |

You can verify the accuracy of this table by actually calculating the value for each step. You should arrive at the same result, whether you divide each of the integers 1 through 7 into 40,000 or use the formula for the total resistance of resistors in parallel.

Now that you know how the binary-weighted resistor network works, let's assume that it's connected as the input resistance in a straightforward inverting amplifier like the one shown in Fig. 1. If $R_F$ is made equal to $R$, then the amplifier will have switch-programmable gains ranging from $-1$ to $-7$ in equally spaced increments.




*Fig. 5. Three-level binary-weighted input network.*

It should now be obvious to you how the circuit shown in Fig. 4 provides a switch-programmable gain of from 1 to 15. Add another resistor-switch pair to the network and the available gain will range from $-1$ to $-31$. The use of eight resistor-switch pairs results in switch-programmable gains from $-1$ to $-255$.

This method of programming the gain of an op amp has a few disadvantages of which you should be aware. One is that the value of the resistor in the most significant switch position becomes progressively smaller as the number of resistor/switch pairs is increased. This places a practical limit on the maximum number of resistors that can be added since the maximum available (open-loop) gain of the op amp cannot be exceeded.

The second disadvantage also concerns the most significant switch position and is of more importance. Since the resistance of the most significant resistor is much less than that of the least significant switch position, its tolerance is much more critical. For best results, one-percent or closer tolerance resistors should be used.




*Fig. 6. Using a binary-weighted resistor network in the feedback circuit.*

Thus far, we've considered the use of the binary-weighted network as the input resistance. Of course, the network can also be used as the feedback resistance as shown in Fig. 6. The advantage of this configuration is that the amplifier's input impedance remains constant for the various gain settings. However, the disadvantage is that the uniform, stepped gains of the previous circuit are not available. If $R_{IN}$ is 1 ohm, for example, the gains range from $-5{,}714$ to $-40{,}000$. This circuit thus does not provide uniformly incremental gains, but it does give plenty of range for such an application as audio amplification.

**Adding Digital Control.** A straightforward way to provide digital control of the circuits that have been presented is to replace the conventional, manual switches with CMOS analog switches. Figure 7 shows how to use a CD4066 to replace all four mechanical switches in the circuit of Fig. 4. Keep in mind that the "on" resistances of the four analog switches in the CD4066 should be subtracted from the values of the input-network resistors to calculate the actual gains such a circuit would provide.

Barry B. Woo of Fluke Automated Systems, Inc. has written an excellent paper on various methods of adding digital control to a programmable-gain amplifier. His paper, "Digitally Programmable Gain Amplifiers with Arbitrary Range of Integer Values," appears in the *Proceedings of the IEEE* (July 1980, pp. 935-936). You can find this journal at most well-stocked technical libraries.

The circuit shown in Fig.8 is adapted from Fig.2(c) of Mr. Woo's paper. It is a noninverting amplifier which provides

positive gains of the integers 1 to *N*. Various CMOS analog multiplexers can be used in this circuit.

**Other Applications.** The emphasis in this column has been amplification, but the techniques which have been presented can be used to implement such interesting applications as a digitally controlled potentiometer with no moving parts. Other applications include analog-to-digital and digital-to-analog conversion.

You might want to explore some of these applications on your own. If so, you might also want to experiment with an interesting alternative to the binary-weighted resistor networks described here. The *R-2R* network requires more resistors, but it uses only two resistor values and is more tolerant of resistance variations.

The *R-2R* network was the subject of the July 1978 "Experimenter's Corner." It is also covered in a very useful book by Sol Libes entitled *Fundamentals and Applications of Digital Logic Circuits* (Hayden, 1975). Mr. Libes gives a concise treatment of the subject, complete with circuits, on page 136.

**Reader Letters.** Most of the letters addressed to this column request custom circuit designs or technical information. The number of requests makes it simply impossible for me to fulfill them. Of course, I will try to respond to questions having general interest by means of this column.

A few letters describe circuits built by creative experimenters. Such is the case with 17-year old Antonio Frederico de Cesaro of Porto Alegre, Brazil. Antonio's letter described a solid-state phototransistor/LED video camera and display he has assembled.

The camera portion of Antonio's project is an array of phototransistors which are scanned by a counter. A simple network of NAND gates and inverters places the sampled outputs on a single line which goes to the display cirucit. The display circuit includes an input amplifier and a second scanning system. The counter of the display scanner is driven by the




*Fig. 7. How to use a CD4066 to replace mechanical switches.*

same clock which strobes the camera's phototransistors so the two units are synchronized. Therefore, LEDs corresponding to the phototransistors in the camera glow when the photo-




# JUMBO PAK JACK'S PENNY SALE PLUS*

**Buy 1 Jumbo Pak Get 2nd for 1 Penny More!**

| Item | Price | 2nd Pak |
|---|---|---|
| 8-115VAC NEONS, NE-2 type lamps w/resistor-Amber lens, (#6793) | 2.99 | 16 for $3 |
| 8-53VAC NEONS, Asst. types, styles, & leads for panel mt. (#6794) | 2.99 | 16 for $3 |
| 60-ASST. MINI SOCKETS, Incl. screw bayonett, & snap-in types (#6789) | 2.99 | 120 for $3 |
| 5-JUMBO SWITCH BANK, 3-DPDT & one-6PDT, ganged w/reflector button (#6814) | 2.99 | 10 for $3 |
| 25-MICRO SWITCHES, Asst. SPST & SPDT rated 125V @ 5A, spade terminals (#6815) | 2.99 | 50 for $3 |
| 4-10A BAR TOGGLES, Asst. SPST & DPDT w/long chrome handles, eyelet terminals, (#6816) | 2.99 | 8 for $3 |
| 10-QUAD PHONO JACKS, 4 RCA jacks on 2 x 1½" Bakelite strip, (#6249) | 2.99 | 20 for $3 |
| 125-POLYSTYRENE CAPS, assorted types, styles & sizes, all good, (#2729) | 2.99 | 250 for $3 |
| 50-POWER TAB TRANSISTORS, plastic NPN, TO-220, asst. types, untested, (#2425) | 2.99 | 100 for $3 |
| 24-SKINNY TRIM POTS, multi & single turn, asst. values & types, (#6285) | 2.99 | 48 for $3 |
| 75-LONG LEAD DISCS, prime, marked caps, assorted material, (#2598) | 2.99 | 150 for $3 |
| 50-TTLs, 7400 series, incl. gates, flip-flops, etc. untested, (#6226) | 2.99 | 100 for $3 |
| 5-BRASS LOCKS, with key, 1½" long, for doors, windows, etc. (#6253) | 2.99 | 10 for $3 |
| 175-MOLEX SOCKETS, "on-a-strip", make your own pc sockets, (#6255) | 2.99 | 350 for $3 |
| 50-MINI POTS, pc style, single turn, assorted values, (#3345) | 2.99 | 100 for $3 |
| 15-JUMBO RED LEDS, 3V 10 mA, 100% good material, red dome lens, (#3369) | 2.99 | 30 for $3 |
| 2-SOUND TRIGGERS, sound activated amp, SCR triggered, on 3" board, (#3625) | 2.99 | 4 for $3 |
| 40-TRANSISTOR SOCKETS, assortment may include; TO-19,5,66,3,etc. (#3845) | 2.99 | 80 for $3 |
| 75-CABLE TIES, 4" non-slip white plastic, like Ty-wrap, (#5218) | 2.99 | 150 for $3 |
| 150-FEEDTHRU CAPS, assorted types & sizes, for RF, UHF, etc. (#5668A) | 2.99 | 300 for $3 |
| 175-¼ WATT RESISTORS, asstd. carbons, carbo-films, some 5%ers, (#5797A) | 2.99 | 350 for $3 |
| 100-PLESSY CAPS, ceramic blocks in assorted sizes & values, (#6221) | 2.99 | 200 for $3 |
| 25-NE-2 BULBS, neon, for 110 VAC, requires resistor, (not incl.) (#2613) | 2.99 | 50 for $3 |
| 100-METALLIC RESISTORS, mostly ½ watters, asst. val. 1-5% tol. (#6280) | 2.99 | 200 for $3 |
| 100-POWERS POWERS, 3 to 7 watt power resistors, (#6281) | 2.99 | 200 for $3 |
| 15-CRYSTALS, assorted types, some H6/U, some frequency marked, (#6256) | 2.99 | 30 for $3 |
| 150-SUBMINI IF TRANSFORMERS, asst. may include; osc. antenna, etc. (#6259) | 2.99 | 300 for $3 |
| 25-MICRO MINI REED SWITCHES, 1" long, for alarms, relay systems, etc. (#6263) | 2.99 | 50 for $3 |
| 150-PC.-CAPACITOR SPECIAL, asst. mylars, polys, micas, etc. 100% good, (#6264) | 2.99 | 300 for $3 |
| 10-PUSHBUTTON ALARM SWITCH, SPST, momentary, NC, w/hardware, (#6267) | 2.99 | 20 for $3 |
| 500-PC.-HARDWARE SURPRISE, (approx.) 1 lb. asst. screws, washers, etc. (#6271) | 2.99 | 1000 for $3 |
| 20-9V BATTERY CLIPS, snap connector, coded, insulated leads, (#6286) | 2.99 | 40 for $3 |
| 3-WATCH GUTS, 5-function, LED style, assorted sizes, untested, (#6287) | 2.99 | 6 for $3 |
| 4-HEAVY DUTY LINE CORDS, white, 2 cond. 6 ft. 16 gauge, (#6292) | 2.99 | 8 for $3 |
| 20-SINGLE PIN LEDS, green, micro style, 3V 10mA, 100%, (#6293) | 2.99 | 40 for $3 |
| 30-LED/TRANSISTOR SOCKETS, "snap-in", 3 pc leads, for TO-5,18,46,etc. (#6297) | 2.99 | 60 for $3 |
| 200-PRECISION RESISTORS, ½W, 1%, axial (#2428) | 2.99 | 400 for $3 |
| 25-SLIDE SWITCHES, various shapes, sizes, and types (#2726) | 2.99 | 50 for $3 |
| 50-TRANSISTOR ELECTROLYTICS, epoxy encapsulated, asst. values, (#2747) | 2.99 | 100 for $3 |
| 175-HALF WATTERS, 100%. color-coded resistors, asst. values, (#3046) | 2.99 | 350 for $3 |
| 20-SLIDE VOLUME CONTROLS, various values & types, for Hi-Fi, etc. (#3057) | 2.99 | 40 for $3 |
| 50-UPRIGHT ELECTROS, 100%, assorted values & voltages, marked, (#3226) | 2.99 | 100 for $3 |
| 30-PANEL SWITCHES, assorted rotary, micro, slide, etc. (#6629) | 2.99 | 60 for $3 |
| 20-PAIRS-RCA PLUGS & JACKS, popular for Hi-Fi, speakers, etc. (#6630) | 2.99 | 40 for $3 |
| 60-IN914 SWITCHING DIODES, 4 nsec. axial, glass, untested, (#6632) | 2.99 | 120 for $3 |
| 4-2N3055 NPN TRANSISTORS, 115 watts, 15 amps, TO-3, 100% material, (#6633) | 2.99 | 8 for $3 |
| 50-THERMISTORS, various types & styles, neg. coefficient, 100% (#4089) | 2.99 | 100 for $3 |
| 30-INSTRUMENT KNOBS, for half round shafts, some w/pointers, (#6498) | 2.99 | 60 for $3 |
| 5-LINE CORDS, heavy-duty, 18 gauge, 6', molded plug, 2-cond. (#6499) | 2.99 | 10 for $3 |
| 20-2N3055 HOBBY TRANSISTORS, manuf. fallout, TO-3, U-test, (#6624) | 2.99 | 40 for $3 |
| 100-DTL IC's, mostly dual JK flip flops, marked, 100% prime, (#6444) | 2.99 | 200 for $3 |
| 35-STEREO INDICATORS, tiny red 1.5V bulbs, for Hi-Fi replacement, (#6244) | 2.99 | 70 for $3 |
| 25-PLASTIC POWERS, 25 watt, npn & pnp, 50-200 bvcbo, TO-220, (#6237) | 2.99 | 50 for $3 |
| 9-DIGIT READOUTS, flat pak w/bubble mag. .120" high, 14 pin, (#5558) | 2.99 | 18 for $3 |
| 400-PREFORMED ¼ WATTERS, assorted values, precut for PC appl. (#6622) | 2.99 | 800 for $3 |
| 25-RCA PHONO PLUGS, popular audio/speaker plugs, 100% material (#3293) | 2.99 | 50 for $3 |
| 15-RCA PHONO JACKS, popular Hi-Fi jack on a Bakelite strip, (#6230) | 2.99 | 30 for $3 |
| 150-"4000" RECTIFIERS, IN4000 series, may include; 50 to 1000V, (#2417) | 2.99 | 300 for $3 |
| 50-AXIAL ELECTROS, asst. values, volts, sizes, What a buy! (#3227) | 2.99 | 100 for $3 |
| 3-SHIELDED AUDIO CABLES, 2 cond., with RCA plugs at each end, (#6412) | 2.99 | 6 for $3 |
| 200-PC-SEMICON SPECIAL, assorted semis of all types, Untested material, (#3300) | 2.99 | 400 for $3 |
| 200-PRE-FORMED ½ WATTERS, popular values, some 5 & 10%ers, (#6246) | 2.99 | 400 for $3 |
| 30-SCRs & TRIACS, assorted values, 10 Amp TO-220, untested, (#6337) | 2.99 | 60 for $3 |
| 15-MINI PLUG & CABLE SETS, 3.5mm plug, 6' insulated 2 cond. leads, (#6269) | 2.99 | 30 for $3 |
| 40-EDGE CONNECTORS, asst. 4 & 6 pin, 2-sided, pc leads, (#6364) | 2.99 | 80 for $3 |
| 6-MINI-MOTORS, Type RE56, 1.5-6 VDC, color-coded wire leads, (#6718) | 2.99 | 12 for $3 |
| 24-MINI-BULBS, asst. voltages & base styles, some colored, (#6757) | 2.99 | 48 for $3 |
| 40-STRAIN RELIEFS, asst. types, styles, & sizes. (#6756) | 2.99 | 80 for $3 |
| 6-TIME DELAYS, solid state, asst. from 450 mSec to 8 Sec. (#6758) | 2.99 | 12 for $3 |
| 3-HEAVY DUTY AUTO CHOKE, filters 12 VDC @ 5A. open frame, (#6750) | 2.99 | 6 for $3 |
| 4-CHROME PLATED ALARM SWITCH, spst, N.C. momentary, (#6742) | 2.99 | 8 for $3 |
| 200-PRE-FORMED DISCS, caps w/leads for PC use, mixed values, (#2605) | 2.99 | 400 for $3 |
| 10-RESISTOR LEDS, asst. red, green & yellow jumbos, 5V, (#6761) | 2.99 | 20 for $3 |
| 100-2 WATT RESISTORS, assorted carbons, films etc. some 5%ers, (#6238) | 2.99 | 200 for $3 |



# *PLUS FREE PREMIUMS!!

**A Six Piece Screwdriver Set with any Order Totaling $25 or more!**

**For Faster Service Order By Phone**

**1-617-245-3828**

**ORDERING INSTRUCTIONS** • Indicate Quantity in front of Jumbo Pak Desired. • Complete Coupon Section • Cut Out Along Dotted Line and Mail Ad to Poly Paks INC.

**POLY PAKS** ® P.O. BOX 942, PE3 S. LYNNFIELD, MA. 01940

Total Amount of Order $ ____
Please Add $3 for Postage & Handling
NAME ____
ADDRESS ____
CITY ____
STATE ____ ZIP ____
Enclosed is ☐ CHECK, ☐ MONEY ORDER
Charge my ☐ MASTERCARD ☐ VISA
ACCT. # ____ EXP. DATE ____
☐ Send me your FREE catalog

CIRCLE NO. 55 ON FREE INFORMATION CARD

transistors are illuminated. A brightness control is included in the circuit.

Antonio has provided a sketch of a more advanced version of the circuits he has already built. He also reports that he is working on various other LED-array projects, and he expressed interest in the LED oscilloscope projects published in this column some time ago.




*Fig. 8. A digital programmable-gain noninverting amplifier.*

Michael J. Geydoshek of Newton, NJ wants to make a ten-minute countdown timer for his sailboat. That's not a big problem. Even adding a seconds display is no problem in view of the watch and clock chips (and modules) now available. The catch is that he requires " . . . a large enough display to be seen clearly at 10 feet on a sunny day." The best solution here is to use a large-format liquid-crystal display and a standard watch or clock module. LED displays wash out in even *moderate* sunlight!

A.A. Aikin of Lansing, MI wonders if optical fibers can be used in a public-address system. Sure! However, the use of fibers will have no effect on acoustical feedback. The feedback is caused by speaker-microphone coupling and has nothing to do with whether copper wire or glass fiber couples the mike to the amplifier or the amplifier to the speaker or both.

*Many* readers have asked for technical information on subjects ranging from laser gyroscopes to ultrasonics. Some readers report they have been unable to locate certain technical journals and magazines I have cited.

Readers living in remote areas will always have a difficult time finding technical publications. But most readers live within 50 miles of a university or public library which should contain many of the most important technical periodicals. I urge you to take advantage of such libraries by visiting them as frequently as is possible. Electronics is such a fast-moving field that it's essential to read the latest technical periodicals to find out what's happening.

I live near a liberal arts college which has only a limited number of technical publications in its library. Therefore, I visit a large university about one each month. This university has more than a dozen separate libraries, including *one each* for engineering and physics. I spend about a full day and 80 or more nickels (for the copy machine) each time I visit these libraries!

If you will invest some time in investigating the technical libraries in your area, you will probably find you are within a reasonable distance of at least one and perhaps more. If so, take advantage of them. ◇


Audiomatic Electronics

HOME ENTERTAINMENT SPECIALS

Teac CX350 Cassette 184.99
Kenwood KA8D Delay 349.99
Sony PSX11X Turntable 179.00
Akai CX2600 Video 149.99

BLANK TAPES
TDK SA-C90 3.30
TDK SA-C60 2.49
TDK SA-C90 CD 2.79
TDK SA-C60 (Cr) 2.99
TDK SA-C90 (Cr) 2.19
TDK SA-C90 AD 2.49

ENTIRE SCHWANN CATALOG
ROCK, JAZZ, FOLK
(Maximum Order 4 Records)
All $8.98 List Only 6.85
All $9.98 List Only 8.35
All $6.98 List Only 5.85
Tapes/Cassettes/8-Tracks Add 40
Record Orders By Mail Only
No Telephone Orders Accepted

PHONO CARTRIDGES
Shure V15 Type IV 102.99
Shure V15 Type III ME 83.99
Shure M97 HE 53.99
Shure S-95 HE 34.99
Audio Technica AT155SLC 109.99
Audio Technica AT140LC 54.99
Audio Technica AT125LC 46.99
Stanton 681S 77.99
Stanton 681 EEE 56.99
Stanton 681 EE 44.99
Empire 2000Z/V 54.99
Empire 2000 III 18.99
Pickering XSV4000 68.99

HEADPHONES
Koss Pro 4AAA Special 45.99
Koss HV/XLC 48.99
Koss HV/X 35.99
Sennheiser HD 430 75.99
Sennheiser HD 222 73.99
Sennheiser HD 420 52.99
Audio Technica ATH 7 39.99

PIONEER SPECIAL
KP 7500 179.99
In dash auto cassette component w/Supertuner II, AM/FM stereo

PIONEER Car Stereo
KPX 9500 In dash 177.99
KP 8500 In dash 162.99
KP 8000 In dash 155.99
KP 7500 185.99
KE 3000 In dash 214.99
KE 5000 In dash 249.99
GM-80 Power Amp 49.99
GM-120 Power Amp 107.99

JENSEN Car Stereo
R-430, R-420, R-410 & R-482
Call for low Audiomatic prices

BLAUPUNKT Car Stereo
CR 20001 Indash 238.99
BEA 200 159.99

WRITE FOR FREE CATALOG

We carry a full line of PIONEER, TECHNICS, AKAI, B.I.C. and TEAC Home Stereo Equipment as well as PIONEER, JENSEN, CLARIDON, BLAUPUNKT, PANASONIC, CONCORD, MITSUBISHI, and SANYO Car Stereo Equipment.

ORDERING INSTRUCTIONS

All merchandise is Factory Fresh and complete with Manufacturer's Warranty. For immediate shipment, send Certified Check, Money Order, Cashier's Check, or Master Charge or VISA (Send Card Number and Expiration Date). Call us Toll-Free Mon-Fri 9AM-7PM, Sat 10AM-7PM (Eastern Time) for Credit Card orders. Personal Checks are accepted to hold for quick clearance. Shipping and Handling charge $4.25 (Canada, Puerto Rico, Hawaii, Alaska $8.50). Allow 5-12 days for U.P.S. delivery. For all markets other than 50 place orders please call us at 212-686-5500. No C.O.D. orders accepted. NY residents must include Sales Tax.

Audiomatic Electronics
CALL TOLL-FREE 800-223-2706
In N.Y., Hawaii, Alaska, & Canada Call (212)686-5500
1263 Broadway New York, N.Y. 10001


CIRCLE NO. 8 ON FREE INFORMATION CARD


4PDT RELAY
POTTER BRUMFIELD
• 14 pin style
• 3 amp contacts
• 24 volt coil
• Dust cover (Cl)
• Used but fully tested
$1.50 each
specify coil voltage
LARGE QUANTITIES AVAILABLE
SOCKETS FOR RELAY ON sale

SUBMINI DPDT DIP RELAY
AROMAT #HB2-DC6V
• 6 VDC coil • Fits dip socked
• Norm. op. power 580 mW
• Contacts rated 1 amp @125V
$1.50 each 10 for $13.50

7-17vdc S.S. BUZZER
STAR #CMB-12
• Fits dip socket
• CMOS compatible
• Max. current: 14mA
• Sound output
$1.25 each 10 for $10.00

TRANSFORMERS
120 volt primaries
5 VOLTS @ 200 mA $1.25
6 VOLTS @ 150 mA $1.25
12.6 VOLTS C.T. @ 150 mA $1.50
16.5 VOLTS @ 3 AMPS $6.50
24 VOLTS C.T. @ 360 mA $1.60
$1.35 each 10 for $12.50

22/44 EDGE CONNECTOR
TIN SOLDERTAIL .156" x .200"
$1.35 each 10 for $12.50

50K SLIDE POT
Knobs for Slide Pots 25c each
75c each
audio taper
• 1/2" x 2" x 1/2" long • 2-3/4 inch slide

FLASHER LED
Lumitronix FRL-4403
diffused red led with built in flashing unit. T 1¾ package
pulse rate 3hz ± 20 ms
2 for $1.70

COMPUTER GRADE CAPACITORS
ALL ARE BRAND NEW
1,700 MFD 150 VDC $2.00
2½ dia. x 4½ in.
6,400 MFD. 50 VDC $2.50
1-3/8 in. dia. x 4¾ in.
11,000 MFD. 15 VDC $1.50
1-3/8" in dia x 3-1/4" in.
22,000 MFD. 15 VDC. $2.50
2 in. dia. x 2½ in.
22,000 MFD. 50 VDC $3.50
3 in. dia. x 4½ in.
CLAMPS TO FIT CAPACITORS 50c ea.

FLAT LEVER HANDLE MINI TOGGLE
• SPDT
RATED 6 AMPS @ 125 V
1/4 - 40 BUSHING
$1.00 each
10 for $8.50
100 for $75.00

1½ RPM MOTOR
NEW SYNCHRON TIMING MOTOR
110 VAC 60 CY
$2.00 ea.
10 FOR $17.50

ELECTROLYTICS
AXIAL CAPACITORS
600 MFD. 100 VDC $1.00 ea.
3/8" long x 1/2" diameter
SALE PRICED
1000 MFD 15VDC
3/8" long x 1/16" diameter
$1.00ea 10/$8.00

ALL ELECTRONICS CORP.
905 S. Vermont Ave.
Los Angeles, CA 90006
(213) 380-8000
Store & Warehouse Hours
9 AM - 5 PM
Monday thru Friday
Saturday
10 AM - 3 PM
SEND FOR OUR FREE CATALOG
TERMS
• Quantities Limited
• Min. Order $10.00
• Add $2.00
Shipping USA
• Calif. Res. Add 6%
• Prompt Shipping


CIRCLE NO. 2 ON FREE INFORMATION CARD


apple computer
Complete Microprocessors line, peripherals & Terminals.

| | | | |
|---|---|---|---|
| APPLE II PLUS, 16K | $979.00 | Disk I/30K/controller | $575.00 |
| APPLE II PLUS, 32K | 1039.00 | SOROC IQ140 | 1395.00 |
| APPLE II PLUS, 48K | 1089.00 | TI-99/4 | 499.00 |
| TI-745 | 1440.00 | TI-810 | 1715.00 |

Texas Instruments

| | | | |
|---|---|---|---|
| Invest. Anal. | 49.95 | Speak & Spell | $54.95 |
| TI-55 | 34.50 | Spelling Bee | 30.95 |
| Accessories | call us | TI-Programmer | 52.50 |
| TI-58C | 87.50 | MBA | 52.50 |
| PC100C | 149.95 | TI-5100 | 37.50 |
| TI-59 | 207.00 | TI-5015 | 59.00 |
| Bus. Anal. II | 37.00 | TI-5025 | 61.95 |
| Lang. Tutor | 160.00 | TI-5040 | 79.00 |

HEWLETT-PACKARD

| | | | |
|---|---|---|---|
| HP-67 | $299.00 | HP-41C Prog | 199.95 |
| HP-97 | 579.00 | HP-41C Printer | 294.00 |
| HP-33C | 75.00 | HP-41C CRD RDR | 175.00 |
| HP-34C | 122.00 | HP-41C Mem. Module | 26.00 |
| HP-38C | 122.00 | HP-32E | 49.00 |

HP-85 AND ACCESSORY CALL US FOR PRICES

SCM TYPEWRITER SPECIALS

| | | | |
|---|---|---|---|
| SCM 2200 | $269.00 | INTREPID | $274.00 |
| SCM 2500 | 285.00 | CLASSIC 12 | 144.00 |

All units shipped in original cartons with accessories according to factory specs. Prices subject to change without permission (check 12 weeks to clear). In Illinois add 6% sales tax. Add $4.95 minimum shipping & handling charges per unit. We ship UPS. Subject to availability. Written warranty for specific products can be obtained free upon request. Above prices are for cash and prepaid only. Prices and specifications subject to change without notice. Send mail orders

Nabik's, Inc.
519 DAVIS, EVANSTON, ILL. 60201 TEL.: 312-869-6144


CIRCLE NO. 1 ON FREE INFORMATION CARD

# DX LISTENING

By Glenn Hauser

## Shortwave Broadcasting and the FCC

A NEW shortwave station is due on the air this fall. After considerable delay, the Federal Communications Commission finally granted a license for shortwave to *WRNO* (FM), New Orleans, LA. The station will start off using one 100-kilowatt transmitter with antennas beamed for Europe and, not incidentally, the eastern U.S. on the way, at 1600 to 0800 GMT. Unlike present U.S. private shortwave stations, this one will operate commercially with a rock music format. No doubt the U.S. broadcasting industry will be watching this closely to see whether it proves profitable. If it does, there could be a spate of similar applications.

Not, however, if Charles Ferris has his way. In announcing the grant, the FCC chairman in his lame-duck period expressed his personal reservations about privately controlled external broadcasting. He felt that only the U.S. government should have the privilege of broadcasting abroad, to ensure that foreigners would be exposed only to official policy (i.e., via the *Voice of America*). This is essentially the same argument the FCC used for many years while a freeze was imposed on shortwave broadcast applications.

Interestingly, the Billy Graham Evangelistic Association had an application in the mill for much longer than *WRNO*, and the FCC licensed it at the same time to build a shortwave outlet in Hawaii; however, there had been reports that the B.G.E.A. had already given up the project.

There are already four private shortwave stations licensed by the FCC and on the air—*WYFR, KGEI, WINB,* and *KTWR* (Guam). It's hard to see why only these organizations should be allowed to broadcast on shortwave if others want to and are qualified. Chairman Ferris cited an obscure 1948 law which prohibits the government from monopolizing shortwave broadcast frequencies as the reason why the *WRNO* application could not be denied, as he is believed to have preferred.

Although shortwave bands are undeniably overcrowded, the "shortage" of frequencies should not be taken as a serious reason for disallowing further U.S. SWBC operations. The bands are due to be expanded, and hardly any other country lets the frequency shortage stop it from broadcasting on shortwave.

Unfortunately, organizations capable of furnishing a real programming alternative from the U.S., such as National Public Radio, have shown no interest whatsoever in external broadcasting.

The FCC has also been encouraging more and more short-range local radio stations, at the expense of "clear" channels and increased interference to all. Yet, at the same time it was granting the *WRNO* and B.G.E.A. applications, the agency was cracking down on at least three small broadcasters who had been operating on shortwave. These examples were not lost on other pirate operators, as the word spread. With the FCC's get-tough attitude, some voluntarily stopped broadcasting while others resorted to random and irregular appearances on the air.

Meanwhile, the Central Intelligence Agency's name cropped up again in connection with shortwave broadcasting. In an early November 1980 column, Jack Anderson reported that Pres. Carter's national security advisor, Zbigniew Brzenski, was actively considering abolition of the Board for International Broadcasting as an obstacle to the CIA's renewed control of *Radio Free Europe* and *Radio Liberty*. And an unconfirmed report propagated by Marxist elements in Cuba, Nicaragua and Grenada said that another Caribbean island, Antigua, had granted the *Voice of America* permission to build another relay station there (though it would hardly seem necessary, with VOA's good coverage of Latin America direct from the U.S., in contrast to the BBC's and the Voice of Germany's, who, though not mentioned in the report, already operate via Antigua). However, the VOA relay is reported to be on mediumwave only. This was seen as cover for a CIA plot against the eastern Caribbean. There is, of course, no direct and official connection between the VOA and the CIA in American terms.

**Country by Country. Ecuador.** Station *HCJB* has responded to positive listener reaction by inserting more airings of a mostly nonevangelical quarter-hour show announced in English by a genuine Ecuadorian, "Música del Ecuador." It's not clear how many original programs there are per week, and which airings are repeats of which others. GMT days and times are: Sunday 0145 on 15355, 9745; 0815 on 9745; 1930 on 21480, 17790 and 15295. Monday 2345 on 15350. Tuesday 0915 on 9745. Wednesday 0515 on 11915, 9745, 6095; 0800 on 9760, 11835. Thursday 0945 on 11900, 9745, 6130. Friday 0330 on 15155,


**Enjoy Satellite TV Now**

Better than Cable TV— Over 200 TV and radio services. Why waste money? Learn the whole story and build a video system the family can enjoy. No commercials, **FREE** movies, sports and Vegas shows—world wide, crystal clear reception connects to any TV set. Big (8 x 11 in.) book loaded with details, photos, plans kits—

**TELLS EVERYTHING. Satisfaction Guaranteed.**

**GLOBAL TV ELECTRONICS**
P.O. Box 219-K, Maitland, Florida 32751
**Send $7.95 Today!** Add $2.00 for 1st class (airmail) or call our 24 hour C.O.D. Rush order line (305) 862-5068
Name _____
Full Address _____

CIRCLE NO. 25 ON FREE INFORMATION CARD

**NEW INDOOR ACTIVE ANTENNA**

**Covers 300 KHz - 30 MHz. For SWL, BCL, VLF DXers.**

***Rivals long wires***

**$79.95** (+ $4.00 shipping)

**MFJ-1020 NEW INDOOR ACTIVE ANTENNA** sits on your desk ready to listen to the world. Rivals can often exceed reception of outside long wire. Unique **Tuned** Active Antenna minimizes intermod, provides RF selectivity, reduces noise outside tuned band. Also use as preselector for external antenna. Covers 300 KHz to 30 MHz in five bands. Adjustable telescoping antenna. Controls: Tune, Band Selector, Gain, On-Off/Bypass. LED. FET, bipolar circuitry. Phono jack for external ant. 6x2x6 inches. 9-12 VDC or 9 V battery for portable use. 110 VAC with optional AC adapter, $7.95.

**Order from MFJ and try it.** If not delighted, return within 30 days for refund (less shipping).

**One year unconditional guarantee.**

**Order yours today. Call toll free 800-647-1800.**

Charge VISA, MC. Or mail check, money order.

**CALL TOLL FREE ... 800-647-1800**

**MFJ Enterprises, Inc.**
BOX 494, MISS. STATE, MS 39762

CIRCLE NO. 62 ON FREE INFORMATION CARD

## GOOD BOOKS ON MICROCOMPUTING

### MICROMATICS

What do you have when you combine microprocessors and any other technology? You have *Micromatics!* The automatic operation or control of a process, physical or mental, by an ultra-miniature electronic device: a microprocessor. The reader receives a complete overview of the basic operation of a practical microcomputer. Hardware and software is explained in easily understood terms. You won't be left up in the air with esoteric explanations. Steve Roberts, a hard working, up through the ranks engineer who learned microprocessors from hands on experience, has a rare talent – the ability to communicate what he has learned clearly and effectively to others. He has an easy going style that makes technical information read like a "who-dunnit!" mystery. It is sure to keep you intrigued and eager to read more about this exciting subject. In one complete volume he integrates the aspects of hardware, chips, peripherals.... shows how it is coupled with software, programs, machine instructions. It is truly a joy to read this kind of material. Any person who wants to deal effectively with microprocessor systems or simply wants to understand their application, will find this book of immense value.

Deluxe Hardcover Volume Only $19.95 No. 81

### GRAPHICS COOKBOOK

For the APPLE computer. This graphics cookbook illustrates a quick and easy method of drawing pictures in the low resolution display mode. The method may be extrapolated to high resolution graphics. In an hour or two you can be drawing complex color pictures on your video screen. You can maintain the individual elements in a picture as part of an ever-expanding "graphics library." As you build your library, you can use combinations of previously designed elements to form new designs. Easy and fun for everyone.

Softcover just $11.95 No. 78

### SOFTWARE COOKBOOKS

No. 99 (6502), No. 50 (6800), No. 60 (8080) are just $12.95. No. 75 (Z80) is only $15.95

### Z80 INSTRUCTION HANDBOOK

Just $5.95 No. 20

### SCELBI'S SECRET GUIDE TO COMPUTERS

Just $5.95 No. 93

### CALCULATING WITH BASIC

Just $8.95 No. 30

MANY OTHER FINE COMPUTER AS WELL AS AMATEUR RADIO TITLES AVAILABLE. ASK FOR OUR FREE CATALOG! (No. AA)

**SCELBI Publication**
20 Hurlbut St., Elmwood, CT 06110

IMPORTANT ORDERING INFO! Please include $1 shipping/handling charges for each item. Prices shown are for North American customers. MC/VISA, Postal and Bank Money Orders preferred. Allow 4 weeks for delivery.

☐ No. 20 ☐ No. 60 ☐ No. 81
☐ No. 30 ☐ No. 75 ☐ No. 93
☐ No. 50 ☐ No. 78 ☐ No. 99
☐ No. AA

Name (print) _____
Address _____
City/State _____
Zip Code _____
Card No. _____
Bank No. _____ Amt. Enc. _____
Signature _____ PE

CIRCLE NO. 58 ON FREE INFORMATION CARD


## *dx listening*

11915, 9745; 0500 on 11915, 9745, 6095. Most of these are also on 26020.

The Ecuadorian government has issued three stamps marking *HCJB*'s semi-centennial this year, and the station was offering listeners a first-day cover at $2.50—but supplies may have been exhausted by now. By the way, collecting stamps dealing with broadcasting is an interesting topical specialty. There are more such stamps than you might think.

**Argentina.** *Radio Argentina* has reorganized its external services so that English is now aired at 0100 to 0130 GMT on 11710.

**Dominican Republic.** *Radio Clarín* returned to the air in December on 11700, mostly on weekends and holidays in the afternoons and evenings Rudy Espinal was back too, with an English hour, "This is Santo Domingo," Saturday and Sunday at 2200, a highly flexible time.

**Egypt** (*to* rather than *from*). Astute DX-listeners sometimes scoop official monitoring services such as the *BBC*'s. Ernie Bahr, Kenora, Ont., discovered an Arabic-speaking clandestine on 9670 on the air daily at 1900-2000, with the ID, "Saut ul-Shaab ul-Misri," which proved to be the anti-Sadat *Voice of the Egyptian People*, previously reported to have disappeared from the air. This frequency brings to mind Malta, where, when relations are sufficiently warm, Libya has been allowed to use the Cyclops transmitter built by *Deutsche Welle*; but its actual site is not known for sure.

**Faroe Islands.** This isolated Danish possession in the North Atlantic has no shortwave broadcasting, but it's conceivable the station *Utvarp Fõroya* on 531 kHz might make it to North America, at Monday-Saturday sign-on of 0715 GMT. Only slightly more improbable as a DX target is an American forces station on U.S. channel 2, which did not appear in references, but was picked up by European TV-DXers, and finally traced to here. It's likely rather low-powered. There are also three FM stations of *Utvarp Fõroya*, on 89.85, 94.25 and 97.5 MHz, which could bounce off the aurora or reach North America via multiple-hop sporadic-E skip. The two "split" frequencies are a give-away to those who can measure them. The full schedule, per the *World Radio-TV Handbook*, is Monday-Friday 0715-0915; 1200-1300 (Wednesday to 1400), 1830-2020 (Thursday & Friday to 2110); Saturday 0715-0915, 1200-1600, 1830-2305; Sunday 1400-1915. You can prepare for the rather remote eventuality of Faroe DX by familiarizing yourself with the sound of the Faroese language. The only Faroese broadcast on shortwave is a weekly 5-minute newscast, Fridays at 1445 from *Radio Norway*, currently on 21730, 21655 and 15345 (March and April: 21730, 17795, 15175). Why this is carried out by Norway rather than the Faroes' parent country of Denmark is not clear. (This is followed at 1450 by a daily North Atlantic weather summary—in Norwe-


# SAVE!

**MONEY • TIME • FREIGHT**

- QUALITY STEREO EQUIPMENT AT LOWEST PRICES.
- YOUR REQUEST FOR QUOTATION RETURNED SAME DAY.
- FACTORY SEALED CARTONS—GUARANTEED AND INSURED.
- SAVE ON NAME BRANDS LIKE:

| | |
|---|---|
| PIONEER | SANSUI |
| KENWOOD | DYNACO |
| SHURE | SONY |
| MARANTZ | KOSS |

AND MORE THAN 50 OTHERS
BUY THE MODERN WAY
BY MAIL—FROM

**illinois audio**
BANK CARDS ACCEPTED
12 East Delaware
Chicago, Illinois 60611
312-664-0020
800-621-8042

CIRCLE NO. 30 ON FREE INFORMATION CARD



# The world of electronics gee-wizardry




# -YOURS FREE.

32-pages of test instruments—from the latest digital multimeters to the famous EICO scopes. Security systems. Automotive and hobbyist products. Kits and assembled. EICO quality. EICO value. For FREE catalog, check reader service card or send 50¢ for first class mail.

**EICO** 108 New South Road Hicksville, N.Y. 11801

CIRCLE NO. 21 ON FREE INFORMATION CARD

gian; this is also carried at 2255, 0055 and 0255 GMT on the same frequencies we list for Sunday/Monday English 65 minutes later.) The only other Faroese-language broadcast we know of is from *Trans World Radio*, Monaco, Monday at 2230-2245 GMT (which is also Faroe Islands local time), on the 1,200,000-watt 1467-kHz outlet, easily heard in North America with receivers of good selectivity (and without locals on 1460 or 1470), though at this hour there's enough darkness to eastern North America only at midwinter.

**Ghana.** Facilities at *R. Ghana* continue to deteriorate, but the station is ever-optimistic. All but one external-service frequency (6130) have been off the air for years, yet the station still sends listeners its imaginary schedule, with a P.S. to that effect. Bill Taylor in Pennsylvania received such a communication. But even before it came, he got an unsolicited pen-pal request from a Ghanaian who must have intercepted his letter at the post office. Such things have been happening for some time in Ghana and other African countries. And Ruth Hesch in New York received a domestic-service schedule from *GBC* showing that transmitters for three more frequencies were off the air—3350, 4980 and 5990 kHz.

**Israel.** Despite its small size, this country has adopted a 5-digit postal code system like U.S. zip codes. *Israel Radio* has been announcing its Jerusalem address with the code 91010, so lots of mail bound for Jerusalem is likely to take a side trip to Duarte, California. *Israel Radio* is also trying a second slow-scan television test February 15 around 2020 GMT on 9425, repeated GMT the 16th at midnight 0020 and 0220 on 11637 and other frequencies.

**Mexico.** Some small shortwave stations have made comebacks after several years of inactivity. *R. Universidad San Luis Potosí*, on 6045, and *R. Mil*, Mexico City, on 6010, were reported by Horacio Hinojosa Arce.

**Spain.** There have been reports that Spanish foreign radio will be dropping its English broadcasts this year in order to save a few pesetas.

**Publication.** *A DXer's Technical Guide* is a well-done 98-page softbound book compiled by members of the mediumwave group International Radio Club of America. It contains reviews of numerous receivers, accessories, antennas, and articles on modifications and many other topics. Much of this is applicable to shortwave as well as mediumwave. It's $5 ppd. payable to IRCA, P.O. Box 17088, Seattle, WA 98107.

**Free Information Sheet.** To help you become an "insider" in the DX-listening subculture, we've compiled a source listing of many other publications, organizations and programs about shortwave and DX listening. It's yours, only if you send a long SASE to: Glenn Hauser, University Radio WUOT, Knoxville, TN 37916. ◇


IMPROVE YOUR COST/PERFORMANCE RATIO 3 DB*
PUT YOUR MONEY WHERE IT REALLY COUNTS, IN QUALITY COMPONENTS AND A HIGH PERFORMANCE DESIGN.
BUY A PHOENIX SYSTEMS KIT.

| FOR SALE: | | PRICE INCLUDES SHIPPING |
|---|---|---|
| PARAMETRIC EQUALIZER KIT | P-94-S | $ 99.00 |
| ANALOG DELAY LINE KIT (MONO) | P-25-DL | $150.00 |
| (STEREO) | P-25-SDL | $250.00 |
| TAPE NOISE REDUCTION KIT | P-518-S | $ 65.00 |
| HP/LPF (−12db/OCT) | P-91-S | $ 15.00 |
| SAD-4096 ASR | P-4096 | $ 45.00 |

SEND FOR SPECS/CATALOG
PHOENIX SYSTEMS/91 ELM ST./MANCHESTER, CT 06040
*3DB FIGURE BASED ON APPROXIMATE DOUBLING OF DBS (DOLLAR POWER) (203) 643-4484

Hear there and everywhere.

Easy tuning, digital display, professional quality

R-1000

The R-1000 is an amazingly easy-to-operate, high-performance, communications receiver, covering 200 kHz to 30 MHz in 30 bands. This PLL synthesized receiver features a digital frequency display and analog dial, plus a quartz digital clock and timer.

R-1000 FEATURES:
- Covers 200 kHz to 30 MHz continuously.
- 30 bands, each 1 MHz wide.
- Five-digit frequency display with 1-kHz resolution and analog dial with precise gear dial mechanism.
- Built-in 12-hour quartz digital clock with timer to turn on radio for scheduled listening or control a recorder through remote terminal.
- Step attenuator to prevent overload.
- Terminal for external tape recorder.
- Tone control.
- Built-in 4-inch speaker.
- Three IF filters for optimum AM, SSB, CW. 12-kHz and 6-kHz (adaptable to 6-kHz and 2.7-kHz) for AM wide and narrow, and 2.7-kHz filter for high-quality SSB (USB and LSB) and CW reception.
- Dimmer switch to control intensity of S-meter and other panel lights and digital display.
- Effective noise blanker.
- Wire antenna terminals for 200 kHz to 2 MHz and 2 MHz to 30 MHz. Coax terminal for 2 MHz to 30 MHz.
- Voltage selector for 100, 120, 220, and 240 VAC. Also adaptable to operate on 13.8 VDC with optional DCK-1 kit.

OPTIONAL ACCESSORIES:
- SP-100 matching external speaker.
- HS-5 and HS-4 headphones.
- DCK-1 modification kit for 12-VDC operation.

KENWOOD
TRIO-KENWOOD COMMUNICATIONS INC.
1111 WEST WALNUT / COMPTON, CA 90220

CIRCLE NO. 36 ON FREE INFORMATION CARD

# Get A GNOME

## the original micro-synthesizer

Every day more people discover that PAIA's GNOME is the most versatile, cost effective special effects device on the market today.

John Simonton's time-proven design provides two envelope generators, VCA, VCO and VCF in a low cost, easy to use package. Use alone with it's built in ribbon controller or modify to use with guitar, electronic piano, polytonic keyboards, etc.

The perfect introduction to electronic music and best of all, the Gnome is only $59.95 in easy to assemble kit form. Is it any wonder why we've sold thousands?



PAIA 1020 W. Wilshire Blvd. Oklahoma City, OK 73118

) Send GNOME MICRO- SYNTHESIZER Kit ($59.95 plus $2.00 postage)
) GNOME MICRO-SYNTHESIZER (Fully Assembled) $100.00 plus $2 postage
) Send FREE CATALOG

name _____
address _____
city _____ state _____ zip _____
visa ____ mc ____ card no. _____

FREE SHIPPING WHEN ORDERED WITH THIS COUPON

Dept. 11-P (405) 843-9626
PAIA 1020 W. Wilshire Blvd. Oklahoma City, OK 73118

CIRCLE NO. 54 ON FREE INFORMATION CARD



**SEE YOUR DEALER TODAY**

*DEMAND THE ORIGINAL*

# 'Firestik®'

**The #1 Helically Wire-Wound and Most Copied Antenna in the World!**

CITIZEN BAND

2 METER • MARINE TELEPHONE
LAND MOBILE TELEPHONE

**FIBERGLASS ANTENNAS AND ACCESSORIES.**

**CORDLESS TELEPHONE ANTENNA INCREASES DISTANCE 5 TO 10 TIMES! NEW MODEL 49 V.I.P.**

**SPECIAL QUOTES!**
ON 27 TO 1000 MHZ
FIBERGLASS ANTENNAS
ANYWHERE IN THE WORLD!

Dealer & Distributor Inquiries Invited
SEND FOR FREE CATALOG

**Firestik' Antenna Company**
2614 East Adams/Phoenix, AZ 85034

Name _____
Street _____
City _____
State _____ Zip _____

**Serving the CB and Communications Market Since 1962.**

**5-YEAR REPLACEMENT WARRANTY**

CIRCLE NO. 23 ON FREE INFORMATION CARD


# PROJECT OF THE MONTH

**By Forrest M. Mims**

## Transistorized Light Flasher

A TRANSISTORIZED light-flasher circuit for model rockets played a key role in the development of the Altair 8800, the POPULAR ELECTRONICS hobby-computer breakthrough project of January 1975.

In 1969, H. Edward Roberts, Stanley Cagle, Robert Zaller, and I formed a company to manufacture and sell a commercial version of my model-rocket light flasher. I wanted our company to have a name using the initials M., I., and T. because, at the time, the Massachusetts Institute of Technology was an important center of model-rocket research activity. Stan came up with Micro Instrumentation and Telemetry Systems, or M.I.T.S.

Eventually, M.I.T.S. was simplified to MITS, and we made telemetry transmitters, light flashers, and a lightwave communicator. The company also manufactured calculators and test equipment—which led to the conception of the Altair 8800 by Ed Roberts. I left MITS in 1970 to become a full-time freelance writer and my first article was about the flasher that was to become MITS's first product.




*Fig. 1. Schematic diagram of miniature transistorized light flasher.*

Figure 1 is the schematic diagram of the circuit, commonly referred to as a regenerative amplifier, that was responsible for both MITS and my present profession. When lamp *I1* is off, *Q2* must be cut off. Since *Q1* controls the behavior of *Q2*, *Q1* must also be cut off. The voltage divider *R1R2*, however, supplies enough base drive to turn *Q1* on, which in turn causes *Q2* to conduct. When *Q2* conducts the lamp is connected directly across the power supply.

Now, *C1* begins to charge through *Q2* and *R2*. At some point, enough charge has accumulated in *C1* to turn *Q1* off. This, in turn, cuts off *Q2* and the lamp darkens. When the lamp is dark, *C1* keeps *Q1* cut off while the capacitor discharges through *R2* and the lamp. When *C1* has discharged completely, *Q1* is biased into conduction by *R1R2*. This turns on *Q2* and the lamp, and the cycle begins again.

The circuit is easily assembled on a miniature circuit board measuring only about one-half inch square. Potentiometer *R1*, which controls the flash rate, can be any standard trimmer. The lamp should be a low-voltage bulb such as the No. 122, No. 222, or a similar, miniature incandescent pilot lamp.

Peak currents of two or more amperes flow through the lamp's filament, so the filament will glow much more brightly than normal. If operated continuously at such current levels, the filament would be quickly destroyed. This does not occur, however, because the flasher circuit supplies current pulses lasting only tens of milliseconds in duration.

Actually, the circuit has broad applications. The flash is bright enough to be an effective personal warning light for cyclists and pedestrians at night. For such uses, you can build the entire circuit inside a plastic automatic lamp housing.

For model-rocket applications, install the flasher in a transparent payload capsule, preferably with the battery mounted *below* the flasher circuit. This keeps the rocket's center of gravity from moving too far forward. It also prevents the comparatively heavy battery from pressing against the flasher circuit during the acceleration phase of the flight.

I hope you enjoy experimenting with this flasher circuit. It may not impact on your career the way it did on mine, but it will certainly brighten up your life! ◇

# OPERATION ASSIST

*If you need information on outdated or rare equipment—a schematic, parts list, etc.—another reader might be able to assist. Simply send a postcard to Operation Assist, POPULAR ELECTRONICS, 1 Park Ave., New York, NY 10016. For those who can help readers, please respond directly to them. They'll appreciate it. (Only those items regarding equipment not available from normal sources are published.)*

**Hartman Marine** model 3059 transistor radiotelephone. Need schematic and service information. Dana Willis, 1057 Kingstown Rd., Peace Dale, RI 02883.

**Heathkit** model #PS-3 variable voltage regulated power supply. Schematic and operating manual needed. Mike Strawser, 315 Spring St., Saline, MI 48176.

**Triumph** model 841 oscilloscope. Need operating manual and schematic. Ronald Weagley, 2304 Stumptown Rd., Lancaster, PA 17601.

**Heathkit** model HX-10 "Marauder." Need owner's manual. Stuart Ballinger, 57 S. Clinton St., Poughkeepsie, NY 12601.

**RCA** model TMV-97-B oscillator. Schematic and information needed. Russell Sandman, 560 Forest Hills Blvd., Waverly, OH 45609.

**Lafayette** model HA-700 communications receiver. Need schematic and/or photocopy of manual. Gary Liebisch, Rte. 8, Quailridge, Spartanburg, SC 29303.

**Hallicrafters** model S 38E AM/SW receiver. Need operation and alignment manuals. John Moret, 1260 Larpenteur Ave. W., Apt. 311, St. Paul, MN 55113.

**Gertsch** model RT-7 radio transformer. Need schematic and instruction manual. Bill Schweber, Instron, 100 Royall St., Canton, MA 02021.

**Concord** model MTC-21 b/w video camera. Need schematic, manual and troubleshooting information. C. Schram, 1317 Cassland Ct., San Jose, CA 95131.

**Stromberg-Carlson** model #84 all-wave receiver. Need schematic, parts list and any available information. Judy Simeneta, 139 Ediston St., Pontiac, MI 48058.

**Wards Airline** model 62-329 receiver. Schematic and operating information needed. Susana Halpine, 10 Florence St., Worcester, MA 01610.

**Kyoritsu** model K-1400 volt/ohm milliammeter. Need service and operation manual. Faizan Haider, Box 1153, Islamabad, Pakistan.

**Precision** model E-200C, Serial #28817 signal generator. Need audio oscillator transformer. J. F. Tremitiere, 5 Austin Rd., Yardley, PA 19067.

**Electronic Assistance Corp.,** model CG-75 ultrasonic cleaner. Schematic, parts list and manual needed. R. K. Beamer, 565A Washington Ave., Nutley, NJ 07110.

**Ballantine** model 420 calibrator; **Sylvania** model 216 RF generator. Need schematics and operator's manuals. R. M. Smith, 3188 Rumsey Dr., Ann Arbor, MI 48105.

**Grundig** model TK830/U tape recorder. Need parts and schematic. Ken Scheuring, 1200 Kimberly Dr.,Valdosta, GA 31601.

**Hickok** model 217 semiconductor analyzer. Schematic and operation manual needed. Glenn Martin, 242 Cabbel Dr., Manassas Park, VA 22110.

**Allen B. DuMont Laboratories, Inc.** type 350-R cathode ray oscillograph. Need manuals. Don Bolton, 1418 Perkins Ave., Richland, WA 99352.

**Concord** model CR-50 AM/FM stereo receiver. Need schematic and operation manual. George J. Van Houten, 26 Delaware Ave., Paterson, NJ 07503.

**RCA** model WO-33A oscilloscope. Manual and/or schematic needed. Ed Herbert, 410 N. Third St., Minersville, PA 17954.




**Put Professional Knowledge and a**

**COLLEGE DEGREE**

**in your Electronics Career through**

**HOME STUDY**

***Earn Your DEGREE***

No commuting to class. Study at your own pace, while continuing your present job. Learn from easy-to-understand lessons, with help from your home-study instructors whenever you need it.

In the Grantham electronics program, you first earn your A.S.E.T. degree, and then your B.S.E.T. These degrees are *accredited* by the Accrediting Commission of the National Home Study Council.

Our *free* bulletin gives full details of the home-study program, the degrees awarded, and the requirements for each degree. Write for *Bulletin ET-81*.

**Grantham College of Engineering**
**2500 So. LaCienega Blvd.**
**Los Angeles, California 90034**



**AMAZING DEVICES**

**PHASERS**

PPF-1 *PHASER PAIN FIELD* — This device recently developed and patented in our labs is being evaluated by law enforcement agencies for riot and crowd control. It is now available but soon will come under the jurisdiction of weapons and internal machine control making it unavailable to the public. The device is hand-held and looks like a BUCK ROGERS ray gun. It is hazardous if not used with discretion.
**PPF-1** . . . . . PLANS . . . . . **$15.00**

IPG-1 *INVISIBLE PAIN FIELD GENERATOR* — This amazing, simple hand-held device is about the size of a pack of cigarettes and generates a directional field of moderate to intensive pain in the lower part of the head up to a range of 50'. Device is simple and economical to make.
**IPG-1**. PLANS **$8.00** **IPG-1K**. ALL PARTS **$39.50**
**IPG-10** ASSEMBLED&TESTED FOR ANIMAL CONTROL **$49.50**

**LASERS**

RUBY LASER RAY PISTOL — Produces highly intense red beam, capable of burning. A hazardous device. PARTS, SOURCES . . . . . **$15.00**

HIGH POWERED CARBON DIOXIDE BURNING AND CUTTING. Complete plans and all parts sources . . . . . **$15.00**

SOLID STATE IR 12 WATTS with built in power supply plans . **$8.00** . Complete kit with collimator . **$74.00**

POCKET LASER pulsed, visible red . . . . . plans . . . . . **$7.00**
Complete kit . **$69.50** . Also complete plans and parts sources for RUBY, YAG, NEODYNIUM, HeNe ARGON, DYE, NITROGEN and many more lasers.

**SECURITY**

SNP-2 *SNOOPER PHONE* — Dual home or office phone while on vacation activating sensitive mike without phone ringing. Excellent property protection and intrusion device.
**SNP2** . . . . . PLANS . . . . . **$7.00**
**SNP2K** . . . . . ALL PARTS . . . . . **$49.50**
**SNP20** . . . . . ASSEMBLED AND TESTED . . . . . **$69.50**

LONG RANGE XMTR PLANS . . . . . **$6.00**
SEE-IN-THE-DARK PLANS . . . . . **$8.00**
DIRECTIONAL SHOTGUN MIKE PLANS . . . . . **$7.00**
SUPER SENSITIVE PARABOLIC MIKE PLANS . . . . . **$7.00**
SOUND & TELEPHONE OPERATED TAPE RECORDER . . . . . **$8.00**
CATALOG ON PLANS, KITS & FINISHED UNITS . . . . . **$1.00**

Send check or money order to:
**SCIENTIFIC SYSTEMS, Dept. Q1, Box 716**
**AMHERST, N.H. 03031**

CIRCLE NO. 59 ON FREE INFORMATION CARD



**FREE McIntosh**

**STEREO CATALOG and FM DIRECTORY**

Get all the newest and latest information on the new McIntosh catalog. In addition you will receive an FM station directory that covers all of North America.

**SEND TODAY!**

McIntosh Laboratory, Inc. **PE**
East Side Station P.O. Box 96
Binghamton, N.Y. 13904

NAME _____
ADDRESS _____
CITY _____ STATE ____ ZIP _____

If you are in a hurry for your catalog please send the coupon to McIntosh. For non rush service send the **Reader Service Card** to the magazine.

CIRCLE NO. 44 ON FREE INFORMATION CARD

**Gregory** Mark XXX bass amp. Transformer, coil ratings or schematic needed. Kelly McRobb, 178 Tim Tam Terrace, West Seneca, NY 14224.

**Jackson** model CRO-2 oscilloscope. Need manual and schematic. George W. Cunningham, 10 Park View Ct., Biddeford, ME 04005.

**Dumont** model 5890-B6 deviation meter. Need schematic and operating manual. Keith Birdwell, 58 Rambler Rd., Hutchinson, KS 67501.

**Dumont** type 403 oscilloscope. Need schematic and operating manual. Joe Tokarz, 4054 Sheffield Ave., Hammond, IN 46327.

**Siltronix** 1011D radio. Need frequency counter. Dennis Marion, 5922 O'Brian, Corpus Christi, TX 78413.

**Philips** type G.M.3125 NR 1735C oscilloscope. Need data, schematic and manual. Taisto E. Yionen, SF-02200 Espoo, Finland.

**Superior Instrument Co.,** model TV-11 tube tester. Need roll chart for latest type tubes. J. W. Corrigan, 7963 Rockhill, Houston, TX 77061.

**Bogen** BT-25 P.A. amplifier. Need manual and schematics. Chip Sams, 109 Windy Circle, Brondon, FL 33511.

**Motorola** model H21-10 portable radio. Need schematic and parts list. Gary Hedge, 3526 Johnson St., High Point, NC 27260.

**RCA** model B870910 shortwave radio. Need schematic. Bob Boehnke, 3011 Antioch Road, Perry, OH 44081.

**Hitachi** model SU-88 16" B/W TV. Need picture tube 440 BPB4. Joseph Hauswirt, 16 Jones St., Worcester, MA 01604.

**Hewlett Packard** model 3311A generator. Need owner's manual, service manual, calibration instructions, parts list, and schematic. Shawn E. Baker, 1448 Cardinal Drive, W. Columbia, SC 29169.

**Gretsch** Safari ac/dc guitar amplifier and **Amplifier Corporation of America** Haynes Bass-King II instrument amplifier. Need schematics. David Calhoun, Rt. 2, Box 111, Mt. Olive, MA 39119.

**Edison** receiver model R6. Need schematic and service information. Gilbert Fontenot, 1575 Longfellow Dr., Beaumont, TX 77706.

**Hallicrafters** model S-34C shortwave receiver. Need operation manual, schematic, and service manual. J. Geissinger, Box 196, Mt. Gretna, PA 17064.

**Super Pro** 5 metal detector. Schematic needed. W. G. Eslick, 2607 E. 13th, Wichita, KS 67214.

**Commander** model 860 generator. Need schematic and operation manual. Albert Dillon, Jr., Box 27, Prichard, WV 25555.

**Pentron** model PR-66 President reel-to-reel recorder, serial #15454-J. Need schematic and service manual. Jim Arbuthnot, 212 Erie, South Haven, MI 49090.

**Masterwork** audio system model 2017, serial #F617-646. Need schematic and selector switch. P. Tan Zenith Radio Corp., 11000 Seymour Avenue, Franklin Park, IL 60131.

**RCA** radio receiver model CRV46152. Need schematic and manual. T.G. Lucas, 7830 Melbourne Rd., Indianapolis, IN 46268.

**Monarch** stereo tuner amplifier model SAT-460X. Need schematic of output amplifier and power supply. Robert N. McEntire, 323 Tram Road, Columbia SC 29210.

**Precision** model 650 tube tester. Need adapter cable P/NAD-65 and cable pin PAA. A. Horowitz, 3518 W. 228th St., Torrance, CA 90505.

**Heathkit** model AR-15 receiver. Need assembly and checkout data. Tom Chichester, Box C-42, Cinnaminson, NJ 08077.

**National** model NC46 receiver. Need schematic. Floyd Williams, 121 N. 59th St., Philadelphia, PA 19139.

**Clarion** AM/FM model 36-300, serial #TT1985 stereo. Need schematic and operation manual. John T. Barber, 501 N. Halsguero St., Carlsbad, NM 88220.

**Superior Instruments Co.,** model 670A ohm meter. Need any available information. M.W. McMahon, 3327 S. Northern, Independence, MO 64052.

**General Electric** model CRO-3A oscilloscope. Need schematic and operating manual. Gary L. Smith, 10956 S.W. 63rd St., Portland, OR 97219.

**Eico** model 425 oscilloscope. Need schematic and voltage chart. Nick Meale, 7316 Richmond, Cincinnati, OH 45236.

**Allied Radio** Ten-2 CB unit. Need schematic and manual. Paul R. Lewis, 1317 Kingston Ridge Road, Cary, NC 27511.

**Superior Instruments** model 76 CR bridge and signal tracer. Need schematic and manual. Jim Wicks, 1970 Cedar #A, Long Beach, CA 90806.

**Zenith** model F2040W2 B/W TV. Need schematic diagram. Arvind Sant, 141-35 78th Ave., Flushing, NY 11367.

**Galaxy** III transceiver. Need schematic. **Plectron** model Sentry 21 and model 77 tone generator. Need schematic and owner's manual. Philip R. Lofton, 349 Quinn Road, Collierville, TN 38017.

**Fisher** Model A-192 (Allegro) stereo. Need schematic. Norman Cizek, 1212 Kinne Street, East Syracuse, NY 13057.

**Ballantine** model 320 voltmeter and **Hewlett Packard** model 206A audio signal generator. Need service manuals and schematics. P. Young, 16W761 White Pines, Bensenville, IL 60106.

**Sears** programmable scanning radio, model 9343639. Need operation manual and schematic. Gene H. McGurrin, 21 Brookview Dr., Macedon, NY 14502.

**EMC** models 204, 205 and 209 tube tester. Need set up chart. Walter C. Fletcher, 6139 S. Kenwood Ave., #404, Chicago, IL 60637.

**Marantz** model 4270 receiver. Need owner's manual and schematic. William J. Byerly, 111 Westchester Place, Apt. D-6, Slidell, LO 70458.

**Tektronix** model 315D and 561 oscilloscopes. Need manuals and schematics. Bob Carpenter, 2435 Cherry Hill Road, Culpeper, VA 22701.

**Digital Concepts** clock chip # DCC7302N used in clock kit. Need to know where chip can be purchased. S.S. Siter, 488 Marshall St., Paxton, MA 01612.

**KLH** model 27 receiver and model 4 speaker, **Tandberg** model 64 tape recorder and **Dynaco** Mark IV amplifier. Need service manuals, operating manuals and specifications. Stephen H. Shenefield, 4501 Arlington Blvd. #220, Arlington, VA 22203.

**Sansui** model Eversonic 23 CB. Need schematic. Paul R. Lewis, 1317 Kingston Ridge Rd., Cary, NC 27511.

**Standel Company** model Artist XX amplifier. Need schematic and operational manual. H.A. Singer, Rd. 1, Box 146, Jamesburg, NJ 08831.

**Accurate Instruments Co.,** model 257 tube tester. Need parts list. Larry R. Cook, 362 East South St., Richland Center, WI 53581.

**The Voice of Music** model 20247 stereo receiver. Need manual and schematic. Jack Arnold, 3013 Fulton St., Berkeley, CA 94705.

**Masterwork** model M-812 tape recorder. Need operation manuals. Dwayne Dyals, 1214 Labelle St., #118, Jacksonville, FL 32205.

**Grundig** model TK400Uz tape recorder. Need schematic. C. Bergel, 452 N.E. 39th St., Miami, FL 32205.

**Futterman** model H-3 and H-3A power amplifiers. Need schematic diagrams and any other available information. Richard A. Matthews, 20 West 84th St., New York, NY 10024.

**Commercial Trades International** # MCB23176900 voltmeter. Need service manual and schematic. Mary V. Saunders, 304 4th Avenue, Jerome, ID 83338.


MODEL II

11% DISCOUNT
Off List
64K 1 DRIVE $3440.00
No Taxes on Out of State Shipments
Immediate Shipment On Most Items

$ DISCOUNT $
TRS-80® DEALER A301

FREE COMPUTER CATALOG UPON REQUEST

COMPUTER SPECIALISTS

26-3001 4K Color.....$360.00
26-1145 RS-232 Board.....84.00
26-1140"O" K Interface.....249.00
26-1160 Mini Disk.....419.00
26-1171 Telephone Modem.....169.00
Fost 100 CPS Centronics 730 Printer.....577.00
Text Quality Centronics 737 Printer.....737.00
CAT Modem.....149.00

26-1061 4K I.....$630.00
26-1062 16K III.....888.00
26-1063 32K III
2-Drives, RS232.....2225.00

Largest Inventory in S.E. U.S.A.

1-800-841-0860 Toll Free Order Entry
MICRO MANAGEMENT SYSTEMS, INC.
DOWNTOWN PLAZA SHOPPING CENTER
115 C SECOND AVE. S.W
CAIRO, GEORGIA 31728
GA. PHONE NO. (912) 377-7120

CIRCLE NO. 43 ON FREE INFORMATION CARD

## 7400

| Part | Price |
|---|---|
| SN7400N | .25 |
| SN7401N | .20 |
| SN7402N | .25 |
| SN7403N | .25 |
| SN7404N | .25 |
| SN7405N | .29 |
| SN7406N | .35 |
| SN7407N | .35 |
| SN7408N | .29 |
| SN7409N | .29 |
| SN7410N | .25 |
| SN7411N | .29 |
| SN7412N | .35 |
| SN7413N | .40 |
| SN7414N | .69 |
| SN7416N | .29 |
| SN7417N | .29 |
| SN7420N | .25 |
| SN7421N | .29 |
| SN7422N | .45 |
| SN7423N | .29 |
| SN7425N | .29 |
| SN7426N | .29 |
| SN7427N | .25 |
| SN7429N | .39 |
| SN7430N | .25 |
| SN7432N | .29 |
| SN7437N | .25 |
| SN7438N | .40 |
| SN7439N | .25 |
| SN7440N | .20 |
| SN7441N | .89 |
| SN7442N | .59 |
| SN7443N | 1.10 |
| SN7444N | 1.10 |
| SN7445N | .89 |
| SN7446N | .79 |
| SN7447N | .69 |
| SN7448N | .79 |
| SN7450N | .20 |
| SN7451N | .20 |
| SN7453N | .20 |
| SN7454N | .20 |
| SN7459A | .25 |
| SN7460N | .20 |
| SN7470N | .29 |
| SN7472N | .29 |
| SN7473N | .35 |
| SN7474N | .35 |
| SN7475N | .49 |
| SN7476N | .35 |
| SN7479N | 5.00 |
| SN7480N | .50 |
| SN7482N | .99 |
| SN7483N | .69 |
| SN7485N | .89 |
| SN7486N | .35 |
| SN7489N | 1.75 |
| SN7490N | .49 |
| SN7491N | .59 |
| SN7492N | .45 |
| SN7493N | .45 |
| SN7494N | .69 |
| SN7495N | .69 |
| SN7496N | .69 |
| SN7497N | 3.00 |
| SN74100N | 1.49 |
| SN74107N | .35 |
| SN74109N | .39 |
| SN74116N | 1.95 |
| SN74121N | .39 |
| SN74122N | .55 |
| SN74123N | .59 |
| SN74125N | .49 |
| SN74126N | .49 |
| SN74132N | .75 |
| SN74136N | .75 |
| SN74141N | .99 |
| SN74142N | 3.25 |
| SN74143N | 3.49 |
| SN74144N | 3.49 |
| SN74145N | .79 |
| SN74147N | 1.95 |
| SN74148N | 1.29 |
| SN74150N | 1.25 |
| SN74151N | .69 |
| SN74152N | .69 |
| SN74153N | .79 |
| SN74154N | 1.25 |
| SN74155N | .79 |
| SN74156N | .79 |
| SN74157N | .69 |
| SN74160N | .89 |
| SN74161N | .89 |
| SN74162N | .89 |
| SN74163N | .89 |
| SN74164N | .89 |
| SN74165N | .89 |
| SN74166N | 1.25 |
| SN74167N | 2.79 |
| SN74170N | 1.95 |
| SN74172N | 4.95 |
| SN74173N | 1.39 |
| SN74174N | .99 |
| SN74175N | .89 |
| SN74176N | .79 |
| SN74177N | .79 |
| SN74179N | 1.49 |
| SN74180N | .79 |
| SN74181N | 2.25 |
| SN74182N | .79 |
| SN74184N | 2.49 |
| SN74185N | 2.49 |
| SN74190N | 1.25 |
| SN74191N | 1.25 |
| SN74192N | .89 |
| SN74193N | .89 |
| SN74194N | .89 |
| SN74195N | .69 |
| SN74196N | .89 |
| SN74197N | .89 |
| SN74198N | 1.49 |
| SN74199N | 1.49 |
| SN74221N | 1.25 |
| SN74251N | .99 |
| SN74276N | 1.95 |
| SN74279N | .79 |
| SN74283N | 1.49 |
| SN74284N | 3.95 |
| SN74285N | 3.95 |
| SN74365N | .69 |
| SN74366N | .69 |
| SN74367N | .69 |
| SN74368N | .69 |
| SN74390N | 1.49 |
| SN74393N | 1.49 |

## 74LS

| Part | Price |
|---|---|
| 74LS00 | .29 |
| 74LS01 | .29 |
| 74LS02 | .29 |
| 74LS03 | .29 |
| 74LS04 | .35 |
| 74LS05 | .35 |
| 74LS08 | .29 |
| 74LS09 | .35 |
| 74LS10 | .29 |
| 74LS11 | .75 |
| 74LS12 | .35 |
| 74LS13 | .59 |
| 74LS14 | .99 |
| 74LS15 | .35 |
| 74LS20 | .29 |
| 74LS21 | .35 |
| 74LS22 | .35 |
| 74LS26 | .35 |
| 74LS27 | .35 |
| 74LS28 | .35 |
| 74LS30 | .29 |
| 74LS32 | .35 |
| 74LS33 | .59 |
| 74LS37 | .45 |
| 74LS38 | .49 |
| 74LS40 | .35 |
| 74LS42 | .89 |
| 74LS47 | .89 |
| 74LS48 | 1.15 |
| 74LS49 | 1.15 |
| 74LS51 | .29 |
| 74LS54 | .29 |
| 74LS55 | .29 |
| 74LS73 | .45 |
| 74LS74 | .45 |
| 74LS75 | .59 |
| 74LS76 | .45 |
| 74LS78 | .49 |
| 74LS83 | .89 |
| 74LS85 | 1.25 |
| 74LS86 | .45 |
| 74LS90 | .59 |
| 74LS92 | .75 |
| 74LS93 | .75 |
| 74LS95 | .99 |
| 74LS96 | 1.15 |
| 74LS107 | .45 |
| 74LS109 | .45 |
| 74LS112 | .45 |
| 74LS113 | .49 |
| 74LS114 | .49 |
| 74LS122 | .89 |
| 74LS123 | 1.25 |
| 74LS125 | .89 |
| 74LS126 | .55 |
| 74LS132 | .99 |
| 74LS133 | .89 |
| 74LS136 | .49 |
| 74LS138 | .89 |
| 74LS139 | .89 |
| 74LS151 | .89 |
| 74LS153 | .89 |
| 74LS154 | 1.75 |
| 74LS155 | 1.19 |
| 74LS156 | 1.19 |
| 74LS157 | .89 |
| 74LS158 | .99 |
| 74LS160 | 1.15 |
| 74LS161 | 1.15 |
| 74LS162 | 1.15 |
| 74LS163 | 1.15 |
| 74LS164 | 1.25 |
| 74LS165 | 1.25 |
| 74LS168 | 1.19 |
| 74LS169 | 1.19 |
| 74LS170 | 2.49 |
| 74LS173 | 1.39 |
| 74LS174 | .99 |
| 74LS175 | .99 |
| 74LS181 | 2.95 |
| 74LS190 | 1.25 |
| 74LS191 | 1.25 |
| 74LS192 | 1.15 |
| 74LS193 | 1.15 |
| 74LS194 | 1.15 |
| 74LS195 | 1.15 |
| 74LS197 | 1.19 |
| 74LS221 | 1.19 |
| 74LS240 | 1.95 |
| 74LS241 | 1.95 |
| 74LS242 | 1.95 |
| 74LS243 | 1.95 |
| 74LS244 | 1.95 |
| 74LS245 | 2.95 |
| 74LS247 | 1.19 |
| 74LS248 | 1.19 |
| 74LS249 | 1.19 |
| 74LS251 | 1.49 |
| 74LS253 | .99 |
| 74LS257 | .89 |
| 74LS258 | .99 |
| 74LS260 | .69 |
| 74LS266 | .69 |
| 74LS273 | 1.95 |
| 74LS279 | .75 |
| 74LS283 | 1.09 |
| 74LS290 | .99 |
| 74LS293 | .99 |
| 74LS298 | 1.25 |
| 74LS352 | 1.29 |
| 74LS353 | 1.29 |
| 74LS365 | .75 |
| 74LS366 | .75 |
| 74LS367 | .75 |
| 74LS368 | .75 |
| 74LS373 | 1.95 |
| 74LS374 | 1.95 |
| 74LS375 | .89 |
| 74LS386 | .69 |
| 74LS393 | 2.49 |
| 74LS399 | 2.49 |
| 74LS670 | 2.49 |
| 81LS95 | 1.95 |
| 81LS97 | 1.95 |

## 74S

| Part | Price |
|---|---|
| 74S00 | .50 |
| 74S02 | .50 |
| 74S03 | .50 |
| 74S04 | .55 |
| 74S05 | .55 |
| 74S08 | .50 |
| 74S09 | .50 |
| 74S10 | .50 |
| 74S11 | .50 |
| 74S15 | .50 |
| 74S20 | .50 |
| 74S22 | .50 |
| 74S30 | .50 |
| 74S32 | .55 |
| 74S40 | .55 |
| 74S51 | .50 |
| 74S64 | .50 |
| 74S65 | .50 |
| 74S74 | .79 |
| 74S86 | .79 |
| 74S112 | .79 |
| 74S113 | .79 |
| 74S114 | .79 |
| 74S133 | .55 |
| 74S134 | .69 |
| 74S135 | 1.19 |
| 74S136 | 1.75 |
| 74S138 | 1.35 |
| 74S139 | 1.35 |
| 74S140 | 1.15 |
| 74S151 | 1.35 |
| 74S153 | 1.35 |
| 74S157 | 1.35 |
| 74S158 | 1.35 |
| 74S174 | 1.59 |
| 74S175 | 1.59 |
| 74S188 | 4.95 |
| 74S194 | 1.95 |
| 74S195 | 1.95 |
| 74S196 | 3.95 |
| 74S240 | 2.95 |
| 74S241 | 2.95 |
| 74S242 | 3.25 |
| 74S243 | 3.25 |
| 74S244 | 3.25 |
| 74S251 | 1.45 |
| 74S253 | 1.45 |
| 74S257 | 1.35 |
| 74S258 | 1.35 |
| 74S260 | .79 |
| 74S280 | 2.95 |
| 74S287* | 4.95 |
| 74S288* | 4.95 |
| 74S373 | 3.49 |
| 74S374 | 3.49 |
| 74S387* | 5.95 |
| 74S471* | 19.95 |
| 74S472* | 19.95 |
| 74S473* | 19.95 |
| 74S474* | 21.95 |
| 74S475* | 21.95 |
| 74S570* | 7.95 |
| 74S571* | 7.95 |
| 74S572* | 19.95 |
| 74S573* | 19.95 |
| 74S940 | 3.15 |
| 74S941 | 3.15 |

* LIMITED AVAILABILITY ON THESE PROMS

## CA—LINEAR

| Part | Price |
|---|---|
| CA3013H | 2.15 |
| CA3023H | 3.25 |
| CA3039H | 1.35 |
| CA3046N | 1.30 |
| CA3059N | 3.25 |
| CA3060N | 3.25 |
| CA3080H | 1.25 |
| CA3081N | 2.00 |
| CA3082N | 2.00 |
| CA3083N | 1.60 |
| CA3086N | .85 |
| CA3089N | 3.75 |
| CA3096N | 3.95 |
| CA3130H | 1.39 |
| CA3140H | 1.25 |
| CA3160H | 1.25 |
| CA3401N | .59 |
| CA3600N | 3.50 |

## CD—CMOS

| Part | Price |
|---|---|
| CD4000 | .39 |
| CD4001 | .39 |
| CD4002 | .39 |
| CD4006 | 1.19 |
| CD4007 | .25 |
| CD4009 | .49 |
| CD4010 | .49 |
| CD4011 | .39 |
| CD4012 | .25 |
| CD4013 | .49 |
| CD4014 | 1.39 |
| CD4015 | 1.19 |
| CD4016 | .59 |
| CD4017 | 1.19 |
| CD4018 | .99 |
| CD4019 | .49 |
| CD4020 | 1.19 |
| CD4021 | 1.39 |
| CD4022 | 1.19 |
| CD4023 | .29 |
| CD4024 | .79 |
| CD4025 | .23 |
| CD4026 | 2.95 |
| CD4027 | .69 |
| CD4028 | .89 |
| CD4029 | 1.49 |
| CD4030 | .49 |
| CD4035 | .99 |
| CD4040 | 1.49 |
| CD4041 | 1.49 |
| CD4042 | .99 |
| CD4043 | .89 |
| CD4044 | .89 |
| CD4046 | 1.79 |
| CD4047 | 2.50 |
| CD4048 | 1.35 |
| CD4049 | .49 |
| CD4050 | .69 |
| CD4051 | 1.19 |
| CD4052 | 1.19 |
| CD4053 | 1.19 |
| CD4056 | 2.95 |
| CD4059 | 9.95 |
| CD4060 | 1.49 |
| CD4066 | .79 |
| CD4068 | .39 |
| CD4069 | .45 |
| CD4070 | .55 |
| CD4071 | .49 |
| CD4072 | .49 |
| CD4073 | .39 |
| CD4075 | .39 |
| CD4076 | 1.39 |
| CD4081 | .39 |
| CD4082 | .39 |
| CD4093 | .99 |
| CD4098 | 2.49 |
| CD4506 | .75 |
| CD4507 | .99 |
| CD4508 | 3.95 |
| CD4510 | 1.39 |
| CD4511 | 1.29 |
| CD4514 | 3.95 |
| CD4515 | 2.95 |
| CD4516 | 1.49 |
| CD4518 | 1.79 |
| CD4519 | .89 |
| CD4520 | 1.29 |
| CD4526 | 1.79 |
| CD4528 | 1.79 |
| CD4529 | 1.95 |
| CD4543 | 2.79 |
| CD4562 | 11.95 |
| CD4566 | 2.79 |
| CD4583 | 2.49 |
| CD4723 | 1.95 |
| CD4724 | 1.95 |
| MC14409 | 14.95 |
| MC14410 | 14.95 |
| MC14411 | 14.95 |
| MC14412 | 11.95 |
| MC14419 | 4.95 |
| MC14433 | 13.95 |

LIMITED OFFER!!

# LITRONIX DISPLAY SALE

WHILE THEY LAST!!

MULTI-DIGIT REFLECTOR ARRAYS FOR CLOCKS

| PART NUMBER | CHAR. HT. (IN.) | POLARITY | DESCRIPTION | LIGHT OUTPUT (MCD) TYP | MIN | @mA | FORWARD VOLTAGE SEGMENT (V) $I_F$ = 20mA TYP | MAX | CONTINUOUS FORWARD CURRENT PER SEGMENT (mA) MAX | PRICE |
|---|---|---|---|---|---|---|---|---|---|---|
| DL-4500 (Red) | .50 | C.C. MPX | 4 Digit 7 Segment With Colon And Auxilliary Indicators | .8 | .5 | 10 | 1.7 | 2.0 | 30 | 2.49 |
| DL-4507 (Red) | | | | -- | 1.0 | | | | | 2.49 |
| DLO-4507 (orng) | | C.C. non MPX | | .8 | .5 | | | | | 4.95 |
| DLG-4507 (grn) | | | | | | | | | | 4.95 |
| DL-4520A (red) | | | | | | | | | | 2.49 |
| DL-4120A (red) | 1.0 | C.C. non MPX | | 1.5 | .9 | | 3.4 | 4.0 | | 4.95 |

MULTI-DIGIT REFLECTOR ARRAYS

| PART NUMBER | CHAR. HT. (IN.) | POLARITY | DESCRIPTION | LIGHT OUTPUT TYP | MIN | @mA | FORWARD VOLTAGE TYP | MAX | CURRENT (mA) MAX | PRICE |
|---|---|---|---|---|---|---|---|---|---|---|
| DL-2300 (Red) | .30 | C.C. MPX | 7 Seg. 2 Digit D.P. Right | 2.5 | 1.1 | 20 | 1.7 | 2.0 | 30 | .99 |
| DLG-2535 (green) | .50 | C.A. MPX | 9 Seg. 2 Digit | | 2.5 | 20 | | 3.5 | 25 | 1.49 |
| DL-4509 (Red) | .50 | C.C. MPX | 9 Seg. 4 Digit D.P. Right | .8 | .5 | 10 | 1.7 | 2.0 | 30 | 2.49 |
| DL-6500 (Red) | .50 | C.C. MPX | 7 Seg. 6 Digit D.P. Right | .8 | .5 | 10 | 1.7 | 2.0 | 30 | 2.95 |
| DL-6530 (Red) | .50 | C.A. MPX | 7 Seg. 6 Digit D.P. Right | .8 | .5 | 10 | 1.7 | 2.0 | 30 | 2.95 |
| DL-3130 (Red) | 1.0 | C.A. MPX | 7 Seg. 3 Digit D.P. Right | 1.5 | 1.0 | 10 | 3.4 | 4.0 | 30 | 3.95 |



# DISCRETE LEDS

| Part | Size | Color | Price |
|---|---|---|---|
| XC556R | .200" | red | 5/$1 |
| XC556G | .200" | green | 4/$1 |
| XC556Y | .200" | yellow | 4/$1 |
| XC556C | .200" | clear | 4/$1 |
| XC22R | .200" | red | 5/$1 |
| XC22G | .200" | green | 4/$1 |
| XC22Y | .200" | yellow | 4/$1 |
| MV10B | .170" | red | 4/$1 |
| MV50 | .085" | red | 6/$1 |
| XC209R | .125" | red | 5/$1 |
| XC209G | .125" | green | 4/$1 |
| XC209Y | .125" | yellow | 4/$1 |
| XC526R | .185" | red | 5/$1 |
| XC526G | .185" | green | 4/$1 |
| XC526Y | .185" | yellow | 4/$1 |
| XC526C | .185" | clear | 4/$1 |
| XC111R | .190" | red | 5/$1 |
| XC111G | .190" | green | 4/$1 |
| XC111Y | .190" | yellow | 4/$1 |
| XC111C | .190" | clear | 4/$1 |

XC556 RED LED, METAL MTG. HDW. 2-6" LEADS.
RL-2 . . $.39 ea. or 3/$1.00

# DISPLAY LEDS

C.A. — Common Anode C.C. — Common Cathode

| Type | Polarity | Ht | Price |
|---|---|---|---|
| MAN 1 | C.A.—red | .270 | 2.95 |
| MAN 2 | 5x7 D.M.—red | .300 | 4.95 |
| MAN 3 | C.C.—red | .125 | .25 |
| MAN 52 | C.A.—green | .300 | 1.25 |
| MAN 54 | C.C.—green | .300 | 1.25 |
| MAN 71 | C.A.—red | .300 | .75 |
| MAN 72 | C.A.—red | .300 | .75 |
| MAN 74 | C.C.—red | .300 | 1.25 |
| MAN 82 | C.A.—yellow | .300 | .49 |
| MAN 84 | C.C.—yellow | .300 | .99 |
| MAN 3620 | C.A.—orange | .300 | .49 |
| MAN 3630 | C.A.—orange ± 1 | .300 | .99 |
| MAN 3640 | C.C.—orange | .300 | .99 |
| MAN 4610 | C.A.—orange | .400 | .99 |
| MAN 6610 | C.A.—orange—DD | .560 | .99 |
| MAN 6630 | C.A.—orange ± 1 | .560 | .99 |
| MAN 6640 | C.C.—orange—DD | .560 | .99 |
| MAN 6650 | C.C.—orange ± 1 | .560 | .99 |
| MAN 6660 | C.A.—orange | .560 | .99 |
| MAN 6710 | C.A.—red—DD | .560 | .99 |
| MAN 6750 | C.C.—red ± 1 | .560 | .99 |
| MAN 6780 | C.C.—red | .560 | .99 |
| DLO304 | C.C.—orange | .300 | 1.25 |
| DLO307 | C.A.—orange | .300 | 1.25 |
| DLG500 | C.C.—green | .500 | 1.25 |
| DLG507 | C.A.—green | .500 | 1.25 |
| DL704 | C.C.—red | .300 | 1.25 |
| DL707 | C.A.—red | .300 | 1.25 |
| DL728 | C.C.—red | .500 | 1.49 |
| DL741 | C.A.—red | .600 | 1.25 |
| DL746 | C.A.—red ± 1 | .630 | 1.49 |
| DL747 | C.A.—red | .600 | 1.49 |
| DL750 | C.C.—red | .600 | 1.49 |
| DLO847 | C.A.—orange | .800 | 1.49 |
| DLO850 | C.C.—orange | .800 | 1.49 |
| DL33B | C.C.—red | .110 | .35 |
| FND358 | C.C. ± 1 | .357 | .99 |
| FND359 | C.C. | .357 | .75 |
| FND503 | C.C. (FND500) | .500 | .99 |
| FND507 | C.A. (FND510) | .500 | .99 |
| HDSP-3401 | C.A.—red | .800 | 1.50 |
| HDSP-3403 | C.C.—red | .800 | 1.50 |
| 5082-7751 | C.A., R.H.D.—red | .430 | 1.25 |
| 5082-7760 | C.C., R.H.D.—red | .430 | 1.75 |
| 5082-7300 | 4x7 sgl. dig. RHD | .600 | 22.00 |
| 5082-7302 | 4x7 sgl. dig. LHD | .600 | 22.00 |
| 5082-7304 | Overnge. char. (±1) | .600 | 19.95 |
| 4N28 | Photo Xsistor Opto-Isol. | | .99 |
| LIT-1 | Photo Xsistor Opto-Isol. | | .69 |
| MOC3010 | Optically Isol. Triac Driver | | 1.25 |

# POTENTIOMETERS



**$2.95 each**

2 Watt @ 70°C ± 10%
7/8" Slotted Shaft
Linear Taper
Meets Mil-R-94

| Part No. | | |
|---|---|---|
| CMU 1021 | RV4NAY SD - 102A | 1K |
| CMU 5021 | RV4NAY SD - 502A | 5K |
| CMU 1031 | RV4NAY SD - 103A | 10K |
| CMU 2531 | RV4NAY SD - 253A | 25K |
| CMU 5031 | RV4NAY SD - 503A | 50K |
| CMU 1041 | RV4NAY SD - 104A | 100K |
| CMU 1052 | RV4NAY SD - 105A | 1Meg |

**$1.35 each**




3/4 Watt @ 70°C
15 turn pot. Linear taper. Printed circuit mount.

| Part No. | Part No. | Part No. |
|---|---|---|
| 830P- 50ohm | 830P- 5K | 830P-100K |
| 830P-100ohm | 830P-10K | 830P-200K |
| 830P-500ohm | 830P-20K | 830P-500K |
| 830P-1K | 830P-50K | 830P-1Meg |
| 830P-2K | | |

## LOW PROFILE (TIN) SOCKETS

| | 1-24 | 25-49 | 50-100 |
|---|---|---|---|
| 8 pin LP | .17 | .16 | .15 |
| 14 pin LP | .20 | .19 | .18 |
| 16 pin LP | .22 | .21 | .20 |
| 18 pin LP | .29 | .28 | .27 |
| 20 pin LP | .34 | .32 | .30 |
| 22 pin LP | .37 | .36 | .35 |
| 24 pin LP | .38 | .37 | .36 |
| 28 pin LP | .45 | .44 | .43 |
| 36 pin LP | .60 | .59 | .58 |
| 40 pin LP | .63 | .62 | .61 |

## SOLDERTAIL (GOLD) STANDARD

| | 1-24 | 25-49 | 50-100 |
|---|---|---|---|
| 8 pin SG | .39 | .35 | .31 |
| 14 pin SG | .49 | .45 | .41 |
| 16 pin SG | .54 | .49 | .44 |
| 18 pin SG | .59 | .53 | .48 |
| 24 pin SG | .79 | .75 | .69 |
| 28 pin SG | 1.10 | 1.00 | .90 |
| 36 pin SG | 1.65 | 1.40 | 1.26 |
| 40 pin SG | 1.75 | 1.59 | 1.45 |

## SOLDERTAIL STANDARD (TIN)

| | 1-24 | 25-49 | 50-100 |
|---|---|---|---|
| 14 pin ST | .27 | .25 | .24 |
| 16 pin ST | .30 | .27 | .25 |
| 18 pin ST | .35 | .32 | .30 |
| 24 pin ST | .49 | .45 | .42 |
| 28 pin ST | .99 | .90 | .81 |
| 36 pin ST | 1.39 | 1.26 | 1.15 |
| 40 pin ST | 1.59 | 1.45 | 1.30 |

## WIRE WRAP SOCKETS (GOLD) LEVEL #3

| | 1-24 | 25-49 | 50-100 |
|---|---|---|---|
| 8 pin WW | .59 | .54 | .49 |
| 10 pin WW | .69 | .63 | .58 |
| 14 pin WW | .79 | .73 | .67 |
| 16 pin WW | .85 | .77 | .70 |
| 18 pin WW | .99 | .90 | .81 |
| 20 pin WW | 1.19 | 1.08 | .99 |
| 22 pin WW | 1.49 | 1.35 | 1.23 |
| 24 pin WW | 1.39 | 1.26 | 1.14 |
| 28 pin WW | 1.69 | 1.53 | 1.38 |
| 36 pin WW | 2.19 | 1.99 | 1.79 |
| 40 pin WW | 2.29 | 2.09 | 1.89 |

# 1/4 WATT RESISTOR ASSORTMENTS – 5%

| | | | | | | | | |
|---|---|---|---|---|---|---|---|---|
| | | 10 Ohm | 12 Ohm | 15 Ohm | 18 Ohm | 22 Ohm | | |
| ASST. 1 | 5 ea. | 27 Ohm | 33 Ohm | 39 Ohm | 47 Ohm | 56 Ohm | 50 pcs. | $1.95 |
| | | 68 Ohm | 82 Ohm | 100 Ohm | 120 Ohm | 150 Ohm | | |
| ASST. 2 | 5 ea. | 180 Ohm | 220 Ohm | 270 Ohm | 330 Ohm | 390 Ohm | 50 pcs. | $1.95 |
| | | 470 Ohm | 560 Ohm | 680 Ohm | 820 Ohm | 1K | | |
| ASST. 3 | 5 ea. | 1.2K | 1.5K | 1.8K | 2.2K | 2.7K | 50 pcs. | $1.95 |
| | | 3.3K | 3.9K | 4.7K | 5.6K | 6.8K | | |
| ASST. 4 | 5 ea. | 8.2K | 10K | 12K | 15K | 18K | 50 pcs. | $1.95 |
| | | 22K | 27K | 33K | 39K | 47K | | |
| ASST. 5 | 5 ea. | 56K | 68K | 82K | 100K | 120K | 50 pcs. | $1.95 |
| | | 150K | 180K | 220K | 270K | 330K | | |
| ASST. 6 | 5 ea. | 390K | 470K | 560K | 680K | 820K | 50 pcs. | $1.95 |
| | | 1M | 1.2M | 1.5M | 1.8M | 2.2M | | |
| ASST. 7 | 5 ea. | 2.7M | 3.3M | 3.9M | 4.7M | 5.6M | 50 pcs. | $1.95 |
| ASST. 8R | | Includes Resistor Assts. 1-7 (350 pcs.) | | | | | | $10.95 ea. |

$10.00 Min. Order — U.S. Funds Only
Calif. Residents Add 6% Sales Tax
Postage — Add 5% plus $1 Insurance

Spec Sheets — 25¢
Send 41¢ Postage for your FREE 1981 JAMECO CATALOG

NEW 1981 CATALOG

**Jameco ELECTRONICS**

PHONE ORDERS WELCOME (415) 592-8097

*MAIL ORDER ELECTRONICS — WORLDWIDE*
1355 SHOREWAY ROAD, BELMONT, CA 94002
PRICES SUBJECT TO CHANGE

3/81

# INTERSIL

| Part No. | Function | Price |
|---|---|---|
| 7045IPI | CMOS Precision Timer | 14.95 |
| 7045EV/Kit* | Stopwatch Chip, XTL | 22.95 |
| 7106CPL | 3½ Digit A/D (LCD Drive) | 16.95 |
| 7106EV/Kit* | IC, Circuit Board, Display | 34.95 |
| 7107CPL | 3½ Digit A/D (LED Drive) | 15.95 |
| 7107EV/Kit* | IC, Circuit Board, Display | 28.95 |
| 7116CPL | 3½ Digit A/D LCD Dis. HLD. | 18.95 |
| 7117CPL | 3½ Digit A/D LED Dis. HLD. | 17.95 |
| 7201IDR | Low Battery Volt Indicator | 2.25 |
| 7205IPG | CMOS LED Stopwatch/Timer | 12.95 |
| 7205EV/Kit* | Stopwatch Chip, XTL | 19.95 |
| 7206CJPE | Tone Generator | 5.15 |
| 7206CEV/Kit* | Tone Generator Chip, XTL | 9.95 |
| 7207AIPD | Oscillator Controller | 6.50 |
| 7207AEV/Kit* | Freq. Counter Chip, XTL | 11.10 |
| 7208IPI | Seven Decade Counter | 17.95 |
| 7209IPA | Clock Generator | 3.95 |
| 7215IPG | 4 Func. CMOS Stopwatch CKT | 13.95 |
| 7215EV/Kit* | 4 Func. Stopwatch Chip, XTL | 19.95 |
| 7216AIJI | 8-Digit Univ. Counter C.A. | 32.00 |
| 7216CIJI | 8-Digit Freq. Counter C.A. | 26.95 |
| 7216DIPI | 8-Digit Freq. Counter C.C. | 21.95 |
| 7217IJI | 4-Digit LED Up/Down Counter | 12.95 |
| 7218CIJI | 8-Digit Univ. LED Drive | 10.95 |
| 7224IPL | LCD 4½ Digit Up Counter DRI | 11.25 |
| 7226AIJL | 8-Digit Univ. Counter | 31.95 |
| 7226AEV/Kit* | 5 Function Counter Chip, XTL | 74.95 |
| 7240IJE | CMOS Bin Prog. Timer/Counter | 4.95 |
| 7242IJA | CMOS Divide-by-256 RC Timer | 2.05 |
| 7250IJE | CMOS BCD Prog. Timer/Counter | 6.00 |
| 7260IJE | CMOS BCD Prog. Timer/Counter | 5.25 |
| 7555IPA | CMOS 555 Timer (8 pin) | 1.45 |
| 7556IPD | CMOS 556 Timer (14 pin) | 2.20 |
| 7611BCPA | CMOS Op Amp Comparator 5MV | 2.25 |
| 7612BCPA | CMOS Op Amp Ext. Cmvr. 5MV | 2.95 |
| 7621BCPA | CMOS Dual Op Amp Comp. 5MV | 3.95 |
| 7631CCPE | CMOS Tri Op Amp Comp. 10MV | 5.35 |
| 7641CCPD | CMOS Quad Op Amp Comp. 10MV | 7.50 |
| 7642CCPD | CMOS Quad Op Amp Comp. 10MV | 7.50 |
| 7660CPA | Voltage Converter | 2.95 |
| 8069CCQ | 50ppm Band—GAP Volt Ref. Diode | 2.50 |
| 8211CPA | Volt Ref/Indicator | 2.50 |
| 8212CPA | Volt Ref/Indicator | 2.50 |

* INTERSIL'S EVALUATION KITS

## 74C

| Part | Price |
|---|---|
| 74C00 | .39 |
| 74C02 | .39 |
| 74C04 | .39 |
| 74C08 | .39 |
| 74C10 | .39 |
| 74C14 | .75 |
| 74C20 | .39 |
| 74C30 | .39 |
| 74C42 | 1.39 |
| 74C48 | 1.95 |
| 74C73 | .79 |
| 74C74 | .79 |
| 74C85 | 1.95 |
| 74C86 | .99 |
| 74C89 | 6.95 |
| 74C90 | 1.29 |
| 74C93 | 1.29 |
| 74C95 | 1.59 |
| 74C106 | .75 |
| 74C107 | 1.89 |
| 74C151 | 2.95 |
| 74C154 | 3.95 |
| 74C157 | 2.25 |
| 74C160 | 1.69 |
| 74C161 | 1.60 |
| 74C162 | 1.49 |
| 74C163 | 1.69 |
| 74C164 | 1.59 |
| 74C173 | 1.39 |
| 74C174 | 1.39 |
| 74C175 | 1.39 |
| 74C192 | 1.69 |
| 74C193 | 1.69 |
| 74C195 | 1.59 |
| 74C221 | 1.95 |
| 74C240 | 2.25 |
| 74C244 | 2.25 |
| 74C373 | 2.49 |
| 74C374 | 2.59 |
| 74C901 | .89 |
| 74C903 | 1.15 |
| 74C911 | 10.95 |
| 74C912 | 10.95 |
| 74C915 | 1.69 |
| 74C917 | 10.95 |
| 74C922 | 5.49 |
| 74C923 | 5.75 |
| 74C925 | 7.50 |
| 74C926 | 7.50 |
| 80C95 | .79 |
| 80C97 | .79 |

## LINEAR

| Part | Price |
|---|---|
| LH0002CN | 6.85 |
| LM10CLH | 4.50 |
| LM11CLH | 4.75 |
| LH0070-OH | 6.05 |
| TL071CP | .79 |
| TL072CP | 1.39 |
| TL074CN | 2.49 |
| LH0082CD | 35.80 |
| TL082CP | 1.19 |
| TL084CN | 2.19 |
| LH0094CD | 36.80 |
| LM300H | .99 |
| LM301CN | .35 |
| LM302H | 1.95 |
| LM304H | 1.95 |
| LM305H | .99 |
| LM307CN | .45 |
| LM308CN | 1.00 |
| LM309H | 1.95 |
| LM309K | 1.25 |
| LM310CN | 1.75 |
| LM311H | .90 |
| LM312H | 2.49 |
| LM317MP | 1.15 |
| LM317T | 1.75 |
| LM317K | 3.95 |
| LM318CN | 1.95 |
| LM319N | 1.95 |
| LM320K-5 | 1.35 |
| LM320K-12 | 1.35 |
| LM320K-15 | 1.35 |
| LM320T-5 | 1.25 |
| LM320T-12 | 1.25 |
| LM320T-15 | 1.25 |
| LM323K-5 | 5.95 |
| LM324N | .99 |
| LM329DZ | .65 |
| LM331N | 3.95 |
| LM334Z | 1.30 |
| LM335Z | 1.40 |
| LM336Z | 1.75 |
| LM337T | 1.95 |
| LM337MP | 1.15 |
| LM338K | 6.95 |
| LM339N | .99 |
| LM340K-5 | 1.35 |
| LM340K-12 | 1.35 |
| LM340K-15 | 1.35 |
| LM340T-5 | 1.25 |
| LM340T-12 | 1.25 |
| LM340T-15 | 1.25 |
| LM341P-5 | .75 |
| LM341P-12 | .75 |
| LM341P-15 | .75 |
| LM342P-5 | .69 |
| LM342P-12 | .69 |
| LM342P-15 | .69 |
| LM348N | 1.25 |
| LM350K | 5.75 |
| LF351N | .60 |
| LF353N | 1.00 |
| LF355N | 1.10 |
| LF356N | 1.10 |
| LM358N | 1.00 |
| LM359N | 1.79 |
| LM370N | 4.49 |
| LM373N | 3.25 |
| LM377N | 2.95 |
| LM380N | 1.25 |
| LM381N | 1.95 |
| LM382N | 1.79 |
| LM384N | 1.95 |
| LM386N-3 | 1.29 |
| LM387N | 1.45 |
| LM389N | 1.35 |
| LM392N | .69 |
| LF398N | 4.00 |
| LM399H | 5.00 |
| TL494CN | 4.49 |
| TL496CP | 1.75 |
| NE510A | 6.00 |
| NE529A | 4.95 |
| NE531H | 3.95 |
| NE536H | 6.00 |
| NE540H | 6.00 |
| NE544N | 4.95 |
| NE550A | 1.30 |
| NE555V | .39 |
| LM556N | .99 |
| NE564N | 3.95 |
| LM565N | 1.25 |
| LM566CN | 1.95 |
| LM567V | 1.25 |
| NE570N | 4.95 |
| LM702H | .79 |
| LM703CN | .89 |
| LM709N | .29 |
| LM710N | .79 |
| LM711N | .79 |
| LM723N | .69 |
| LM733N | 1.00 |
| LM739N | 1.19 |
| LM741CN | .35 |
| MC1741SCG | 3.00 |
| LM747N | .79 |
| LM748N | .59 |
| LM1014N | 2.75 |
| LM1310N | 1.95 |
| LM1458CN | .59 |
| LM1488N | 1.25 |
| LM1489N | 1.25 |
| LM1496N | 1.95 |
| LM1556V | 1.75 |
| LM1800N | 2.95 |
| LM1877N-9 | 3.25 |
| LM1889N | 3.20 |
| LM1896N | 1.75 |
| LM2002T | 1.49 |
| LM2877P | 2.05 |
| LM2878P | 2.25 |
| LM2896P-1 | 2.25 |
| LM3189N | 2.95 |
| LM3900N | .69 |
| LM3905CN | 1.25 |
| LM3909N | 1.15 |
| LM3914N | 3.95 |
| LM3915N | 3.95 |
| LM3916N | 3.95 |
| RC4136N | 1.25 |
| RC4151NB | 3.95 |
| RC4194TK | 5.95 |
| RC4195TK | 5.49 |
| KB4428 | 4.25 |
| KB4429 | 5.95 |
| LM4500A | 3.25 |
| ICL8038B | 4.95 |
| LM13080N | 1.29 |
| LM13600N | 1.49 |
| 75138N | 1.95 |
| 75450N | .89 |
| 75451CN | .39 |

# CAPACITOR CORNER

### 50 VOLT CERAMIC DISC CAPACITORS

| Value | 1-9 | 10-99 | 100+ | Value | 1-9 | 10-99 | 100+ |
|---|---|---|---|---|---|---|---|
| 10 pf | .08 | .06 | .05 | .001µF | .08 | .06 | .05 |
| 22 pf | .08 | .06 | .05 | .0047µF | .08 | .06 | .05 |
| 47 pf | .08 | .06 | .05 | .01µF | .08 | .06 | .05 |
| 100 pf | .08 | .06 | .05 | .022µF | .09 | .07 | .06 |
| 220 pf | .08 | .06 | .05 | .047µF | .09 | .07 | .06 |
| 470 pf | .08 | .06 | .05 | .1µF | .15 | .12 | .10 |

### 100 VOLT MYLAR FILM CAPACITORS

| | | | | | | | |
|---|---|---|---|---|---|---|---|
| .001mf | .12 | .10 | .07 | .022mf | .13 | .11 | .08 |
| .0022mf | .12 | .10 | .07 | .047mf | .21 | .17 | .13 |
| .0047mf | .12 | .10 | .07 | .1mf | .27 | .23 | .17 |
| .01mf | .12 | .10 | .07 | .22mf | .33 | .27 | .22 |

### +20% DIPPED TANTALUMS (Solid) CAPACITORS

| | | | | | | | |
|---|---|---|---|---|---|---|---|
| .1/35V | .39 | .34 | .29 | 1.5/35V | .41 | .37 | .29 |
| .15/35V | .39 | .34 | .29 | 2.2/35V | .51 | .45 | .34 |
| .22/35V | .39 | .34 | .29 | 3.3/25V | .53 | .47 | .37 |
| .33/35V | .39 | .34 | .29 | 4.7/25V | .63 | .56 | .45 |
| .47/35V | .39 | .34 | .29 | 6.8/25V | .79 | .69 | .55 |
| .68/35V | .39 | .34 | .29 | 15/25V | 1.39 | 1.25 | .95 |
| 1.0/35V | .39 | .34 | .29 | 22/6V | .79 | .69 | .55 |

### MINI. ALUMINUM ELECTROLYTIC CAPACITORS

| Axial Lead | | | | Radial Lead | | | |
|---|---|---|---|---|---|---|---|
| .47/50V | .16 | .14 | .10 | .47/25V | .15 | .13 | .12 |
| 1.0/50V | .19 | .16 | .12 | .47/50V | .16 | .14 | .13 |
| 3.3/50V | .17 | .15 | .11 | 1.0/16V | .15 | .13 | .12 |
| 4.7/25V | .18 | .15 | .11 | 1.0/25V | .16 | .14 | .13 |
| 10/25V | .18 | .15 | .11 | 1.0/50V | .17 | .15 | .14 |
| 10/50V | .19 | .16 | .12 | 4.7/16V | .15 | .13 | .12 |
| 22/25V | .19 | .16 | .12 | 4.7/25V | .16 | .14 | .13 |
| 22/50V | .24 | .20 | .18 | 4.7/50V | .17 | .15 | .14 |
| 47/25V | .25 | .21 | .19 | 10/16V | .15 | .13 | .12 |
| 47/50V | .29 | .25 | .23 | 10/25V | .16 | .14 | .13 |
| 100/25V | .28 | .24 | .22 | 10/50V | .17 | .15 | .14 |
| 100/50V | .41 | .37 | .34 | 47/50V | .25 | .21 | .19 |
| 220/25V | .39 | .34 | .33 | 100/16V | .21 | .17 | .14 |
| 220/50V | .49 | .45 | .41 | 100/25V | .25 | .23 | .21 |
| 470/25V | .54 | .49 | .45 | 100/50V | .37 | .34 | .31 |
| 1000/16V | .79 | .69 | .61 | 220/16V | .25 | .21 | .19 |
| 2200/16V | .89 | .79 | .69 | 470/25V | .35 | .31 | .27 |

CIRCLE NO. 32 ON FREE INFORMATION CARD

# DIGI-KEY CORPORATION 800-346-5144

In Mn., Ak., Hi. Call 218-681-6674

VISA | master charge

Capacitors•Real-Time Clock/Calendar• E F Johnson •Terminal Strips•T.I. Connectors•Wire Wrapping Supplies•CMOS•Rectifiers•Powerace•Sams Books•Diamond Tools•Panavice AP Products•Batteries•ZNR's•Books•Zenier Diodes•Breadboarding•Wire•Buzzers•Vises •Templates•Diodes•Switches•Drafting Aids•Soldering Supplies•Edge Connectors•IC Socket •Enclosures•Resistors & Resistor Networks•Hardware•Power Supplies•Hobby Blox•Phono Plugs & Jacks•Integrated Circuits•Optoelectronics•Lamps•Multimeter•LED's•Data Books Microprocessor & Support•Luxo Lamps•Clock Bezels•PC Layout Supplies•Lithium Batteries•Tantalum Capacitors•Time-Temperature Clock•A/D & D/A•Nickle-Cadmium Batteries Electrolytic Capacitors•Potentiometers•Car Clock•Transistors•Home Clock Kits•Tools • Fuse Holder Boards•Ungar Products•Heat Sinks & Accessories•Solder Wick•AND MORE

DIGI-KEY — DIGI-KEY — DIGI-KEY — *The Big DIGI-KEY Discount makes a Big Price Difference* (SEE BELOW) — DIGI-KEY — DIGI-KEY

## INTEGRATED CIRCUITS

7400 TTL | 74LS00 LS TTL | 4000 CMOS | LINEAR I.C.'S

A/D & D/A CONVERTERS & MISCELLANEOUS

MEMORY

MICROPROCESSORS

INTERFACE I.C.'S

## DIP IC INSERTION TOOLS WITH PIN STRAIGHTENER

CMOS-SAFE DIP IC EXTRACTOR TOOL

INSERTION & EXTRACTION KIT

## 5% CARBON FILM RESISTORS

¼ WATT RESISTOR ASSORTMENTS

RS125 $9.90 · RS225 · ½ WATT RESISTORS ASSORTMENTS · RS150 $9.90 · RS250

## E.F. JOHNSON ALUMINUM SPACERS

Round Tubular · Round Threaded · Hex Threaded

## MOLEX I.C. SOCKET PINS

.95/C · 9.10/M · 42.00/5M · 300.00/50M

## TEXAS INSTRUMENTS I.C. SOCKETS

SOLDER TAIL DIP SOCKETS

- Low profile
- Face grip design for maximum rentention force
- Redundant contact points
- YOUR CHOICE — TIN OR GOLD* (*Minimum of 50 microinches gold inlay on gold sockets)
- TEXAS INSTRUMENTS QUALITY

TIN INLAY SOLDER TAIL · GOLD INLAY SOLDER TAIL

WIRE WRAP DIP SOCKETS

- Standard profile
- Universal mounting and packaging capabilities
- Closed entry, accommodate .025" through .021" rectangular or round dual-in-line leads
- Wire wrap posts held to true position of .015" providing a true position of .030" on boards for efficient automatic wire wrapping
- YOUR CHOICE — TIN OR GOLD* (*Minimum .50 microinch gold inlay on gold sockets)
- TEXAS INSTRUMENTS QUALITY

TIN PLATED WIRE WRAP · GOLD INLAY WIRE WRAP

## SILICON TRANSISTORS

## ITT RECTIFIERS

## ITT SILICON ZENER DIODES

Call or Write for your Free DIGI-KEY Catalog

## HOBBY-BLOX

THE NEW MODULAR CIRCUIT BUILDING SYSTEM

Whether you're a beginner or an advanced hobbyist, Hobby-Blox is the right system for you. The Hobby-Blox System takes you as far as your imagination will go. Begin at the beginning with a Hobby-Blox starter pack. You can expand the Hobby-Blox System with a complete line of modules.

BASIC INTEGRATED CIRCUIT STARTER PACK · BASIC DISCRETE COMPONENT STARTER PACK · TRAY · DISTRIBUTION STRIPS · TERMINAL STRIPS · BLANK PANEL PACK · BUS STRIP · L.E.D. STRIP · DISCRETE COMPONENT STRIP · BINDING POST STRIP · TRAY EXTENDER CLIPS · CONTROL PANEL PACK · SPEAKER PANEL PACK · BATTERY HOLDER PACK · VERTICAL TRAY PACK

## SUPER-STRIPS

UNIVERSAL BREADBOARDING ELEMENTS WITH SOLDERLESS PLUG-IN TIE POINTS

## POWERACE

For complete AP Products specifications get your FREE DIGI-KEY catalog today

## TEXAS INSTRUMENTS GOLD EDGEBOARD CONNECTORS

Solder Tab · Solder Eye · Wire Wrap

RELIABLE, COST-EFFICIENT CONTACT DESIGN

H4 SERIES .100"x.200" EDGEBOARD CONNECTORS · H4 SERIES .125"x.250" EDGEBOARD CONNECTORS · H4 SERIES .156"x.200" EDGEBOARD CONNECTORS

## ELECTRONIC HARDWARE KIT

CAT. NO. 1600 KIT $14.95

## "NEW" MA1032 Clock

Digital LCD Clock Module

- Operates from a single 1.5V Battery
- 0.5" LCD Display

Instructions Included In All Orders

- User selectable 12 or 24-hour mode
- 24 hour alarm with ON/OFF control
- Presettable 59-minute sleep timer with reset to zero
- 7-minute snooze timer
- Fast/Slow setting controls
- Seconds display
- 90 mA hour battery will typically last one year
- Minimum external parts required for travel clock/clock radio
- Backlighted Display

MA1032M LCD Clock Module only $24.95 · MA1032C Switch for MA1032M $2.85 · MA1032P MA1032M, MA1032C, & AA battery holder $28.20

## TIME-TEMPERATURE PROGRAMMABLE MODULE

USER PROGRAMMABLE FOR:

Instruction included with all orders

FEATURES

## THE "PROGRAMMABLE" CLOCK MODULES

USER PROGRAMMABLE FOR:

NEW! Two Giant Sizes — 0.7" and 0.84"

FEATURES:

MA1023 — 0.7" HIGH DIGITS · MA1020 — 0.84" HIGH DIGITS

## DIGITAL CLOCK BEZEL THE J.M.C. DIGITAL DISPLAY BEZEL

WITH RED FILTER Part No. 400

UNIVERSAL SIZE HANDLES MOST REQUIREMENTS

Be Sure to Order the Proper Adapter for Your Digital Clock

## DIGI-CLOCK KIT

- 12 VDC — Ideal for Car, Van or Boat!

Part No. 5001K ONLY $24.95

Do you need spacers, Banana plugs and jacks, or tip plugs and jacks? You can get these and more E. F. JOHNSON products from DIGI-KEY.

HEAT SINKS from TO-92 2W coolers to TO-3 100W sinks.

## PANASONIC ELECTROLYTIC CAPACITORS

Axial · Radial

## PANASONIC METALLIZED POLYESTER CAPACITORS

250 VDC plus minus 10% TOLERANCE

NEW! KIT 170 METALLIZED POLYESTER CAPACITORS · CAT. NO. E-KIT ONLY $54.95 · ASSORTMENT OF 15 POPULAR VALUES PANASONIC QUALITY

## PANASONIC K-SERIES CAPACITORS

## PANASONIC POLYESTER CAPACITORS

100 VDC plus minus 10% TOLERANCE

NEW! KIT 150 POLYESTER CAPACITORS · Price includes convenient divided plastic box with bin guide for easy storage and quick access. · CAT. NO. M-KIT ONLY $34.95 · ASSORTMENT OF 15 POPULAR VALUES PANASONIC QUALITY

## PLESSEY "MINI-BOX"

Metalized Poly. Cap. Kit

140 CAPACITORS · CAT. NO. 3050P-Kit ONLY $35.95 · ASSORTMENT OF 14 POPULAR "MINI-BOX" CAPACITORS

## PANASONIC ELECTROLYTIC KIT

150 CAPACITORS · Cat. No. P6200-Kit ONLY $35.95 · ASSORTMENT OF 15 POPULAR CAPACITORS

## E. F. JOHNSON PLUG & JACK KIT

150 COMPONENTS · Cat. No. J100-Kit ONLY $69.95 · ASSORTMENT OF 150 POPULAR JACKS & PLUGS

## PANASONIC DISC CAPACITORS

NEW! KIT 310 DISC CAPACITORS · CAT. NO. DI-KIT ONLY $24.95 · ASSORTMENT OF 18 POPULAR VALUES

## PANASONIC RESIN DIPPED TANTALUM CAPACITORS

NEW! KIT 180 TANTALUM CAPACITORS · CAT. NO. T-KIT ONLY $79.95 · ASSORTMENT OF 15 POPULAR VALUES PANASONIC QUALITY

## DIGI KEY Precut/Prestripped Wire

Precut-Prestripped 100 Wire Package · Bulk Wire Wrap Wire

PRECUT/PRESTRIPPED WIRE 100 Wires/Package

30 AWG Kynar Insulated in Bulk Continuous Length

| Part No. | Color | Length | Cost |
|---|---|---|---|
| 100 RD | Red | 100 feet | $ 3.10 |
| 100 BK | Black | 100 feet | 3.10 |
| 100 BU | Blue | 100 feet | 3.10 |
| 500 RD | Red | 500 feet | 13.50 |
| 500 BK | Black | 500 feet | 13.50 |
| 500 BU | Blue | 500 feet | 13.50 |
| 1000 RD | Red | 1000 feet | 23.75 |
| 1000 BK | Black | 1000 feet | 23.75 |
| 1000 BU | Blue | 1000 feet | 23.75 |

The Digi-Key volume discount and Service charges are simple to apply. Most items sold by Digi-Key may be combined for a volume discount. Items that are not discountable are identified by the suffix-ND following the part number. After writing your order, total all of the discountable items and apply the appropriate discount. To this subtotal, add the non-discountable items. Then add the Service charge. We pay all shipping and insurance to addresses in the U.S.A., Canada and Mexico when payment accompanies order.

**WHEN ORDERING BY PHONE, CALL: 1-800-346-5144 (Mn., Ak., Hi., call 218-681-6674) By mail send your order to: DIGI-KEY, Highway 32 South, Thief River Falls, MN 56701**

You may pay by check, money order, Master Charge, VISA or C.O.D. ***DIGI-KEY GUARANTEE:*** Any parts or products purchased from Digi-Key that prove to be defective will be replaced or refunded if returned within 90 days from receipt with a copy of your invoice.

| SERVICE | CHARGES | VOLUME DISCOUNT | |
|---|---|---|---|
| $ 0.00-$ 9.99 | Add $2.00 | $ 0.00-$ 99.99 | NET |
| $ 10.00-$25.00 | Add $0.75 | $ 100.00-$249.99 | Less 10% |
| $ 25.00-$49.99 | Add $0.50 | $ 250.00-$499.99 | Less 15% |
| $ 50.00-$99.99 | Add $0.25 | $ 500.00-$999.99 | Less 20% |
| $100.00 & Up | No Charge | $1000.00 & Up | Less 25% |

# DIGI-KEY CORPORATION 800-346-5144

In Min., Ak., HI, Call 218-681-6674

VISA

Capacitors•Real-Time Clock/Calendar•F.F.Johnson•Terminal Strips•T.I. Connectors•Wire Wrapping Supplies•CMOS•Rectifiers•Potentiometers•Static Books•Diamond Tools•Panavice AE Products•Electronic Chemicals•Zero Insertion Force Connectors•Wire Wrapping Tools•Soldering Irons•Soldering Supplies•Color Computers•IC Socket Products•Exclusives•Equipment & Repairs•Networks•Hardware•Power Supplies•Hobby Blues•Phono Plugs & Jacks•Integrators•Practical Aids•Soldering Supplies•Color Computers•IC Socket Microprocessor & Support•Luxo Lamps•Clock Repairs•PC Layout Supplies•Lithium Batteries•Tantalum Capacitors•Cross Reference•Data Books Electronic Capacitors•Wire Wrap Sockets•Stock•Transistors•Home Clock Kits•Tube Radio Boards•Unique Products•Tools•Disk & Accessories•Solder•Solder•S-100 BUS

DIGI-KEY DIGI-KEY DIGI-KEY

# Quest ELECTRONICS

P.O. Box 4430C
Santa Clara, CA 95054
Will calls: 2322 Walsh Ave.
(408) 988-1640 TWX 910-338-2139

**Same day shipment.** First line parts only. Factory tested. Guaranteed money back. Quality IC's and other components at factory prices.

## INTEGRATED CIRCUITS

| 74LS00 TTL | |
|---|---|
| 74LS00N | .29 |
| 74LS02N | .29 |
| 74LS04N | .35 |
| 74LS05N | .25 |
| 74LS08N | .35 |
| 74LS10N | .35 |
| 74LS13N | .55 |
| 74LS14N | 1.00 |
| 74LS20N | .35 |
| 74LS22N | .35 |
| 74LS28N | .35 |
| 74LS30N | .35 |
| 74LS33N | .60 |
| 74LS38N | .50 |
| 74LS74N | .85 |
| 74LS75N | .65 |
| 74LS90N | .60 |
| 74LS93N | .75 |
| 74LS95N | 1.00 |
| 74LS107N | .45 |
| 74LS112N | .45 |
| 74LS113N | .45 |
| 74LS132N | .89 |
| 74LS136N | .50 |
| 74LS151N | .90 |
| 74LS155N | 1.10 |
| 74LS157N | 1.10 |
| 74LS162N | 1.10 |
| 74LS163N | 1.10 |
| 74LS174N | 1.25 |
| 74LS190N | 1.25 |
| 74LS221N | 1.25 |
| 74LS258N | 1.00 |
| 74LS367N | .75 |

**Linear CMOS and 7400 complete lines in stock. Send for catalog.**

| MOS/MEMORY RAM | |
|---|---|
| 2101-1 | 2.85 |
| 2102-1 | .95 |
| 2102AL-4 | 1.45 |
| 2102AN-2L | 1.65 |
| 2104A-4 | 4.95 |
| 2107B-4 | 3.75 |
| 2111-1 | 3.75 |
| 2112-2 | 3.95 |
| 2114 | 3.75 |
| 2114L 300ns | 4.25 |
| 2114L 450ns | 4.00 |
| 4116 200ns | 5.50 |
| 8/4116 200ns | 35.00 |
| MM5262 | .40 |
| MM5280 | 3.00 |
| MM5320 | 9.95 |
| MM5330 | 5.94 |
| PD411D-3 | 4.00 |
| PD411D-4 | 5.00 |
| P5101L | 8.95 |
| 4200A | 9.95 |
| 82S25 | 2.90 |
| 91L02A | 1.50 |
| HD0165-5 | 6.95 |
| MM57100 | 4.50 |
| GIAY38500-1 | 9.95 |
| MCM66751A | 9.95 |
| 9368 | 3.50 |
| 410D | 10.00 |
| 416 | 16.00 |

| PROM | |
|---|---|
| 1702A | 4.95 |
| 2708 | 7.30 |
| 2716T1 | 18.00 |
| 2716 5 Volt | 13.50 |
| 8/2716 5 Volt | 89.00 |
| 2732 | 55.00 |
| 2758 | 19.50 |
| 8741A | 55.00 |
| 8748 | 55.00 |
| 8748-8 | 55.00 |
| 8755A | 55.00 |
| N82S23 | 2.95 |
| N82S123 | 6.50 |
| N82S126 | 3.75 |
| N82S129 | 8.50 |
| N82S131 | 8.50 |
| N82S136 | 8.75 |
| N82S137 | 8.75 |
| DM8577 | 2.90 |
| 8223 | 2.90 |

| INTERFACE | |
|---|---|
| 8095 | .65 |
| 8096 | .65 |
| 8097 | .65 |
| 8098 | .65 |
| 8T09 | 1.25 |
| 8T10 | 4.50 |
| 8T13 | 3.00 |
| 8T20 | 5.50 |
| 8T23 | 3.10 |
| 8T24 | 3.50 |
| 8T25 | 3.20 |
| 8T26 | 1.69 |
| 8T28 | 2.75 |
| 8T97 | 1.69 |
| 8T98 | 1.69 |

| MICROPROCESSOR | |
|---|---|
| 6502 | 10.95 |
| 6504 | 9.95 |
| 6522 | 9.95 |
| 6800 | 6.95 |
| 6802 | 11.95 |
| 6820 | 4.95 |
| 6850 | 5.95 |
| 8080A | 5.95 |
| 8085 | 12.95 |
| 8086 | 75.00 |
| Z80 | 9.95 |
| Z80A | 11.95 |
| 8212 | 2.90 |
| 8214 | 3.95 |
| 8216 | 2.90 |
| 8224 | 3.45 |
| 8228 | 4.95 |
| 8251 | 6.95 |
| 8253 | 15.00 |
| 8255 | 5.75 |
| 8257 | 10.95 |
| 8259 | 14.95 |
| 1802CP plas | 13.95 |
| 1802DP plas | 17.95 |
| 1861P | 9.50 |
| CDP1802CD | 28.95 |
| CDP1802D | 35.00 |
| CDP1816P | 7.95 |

| RESISTORS 1/4 watt 5% | |
|---|---|
| 10 per type | .03 |
| 25 per type | .025 |
| 100 per type | .015 |
| 1000 per type | .012 |
| 350 piece pack 5 per type | 6.75 |
| 1/2 watt 5% per type | .05 |

| IC SOCKETS Solder Tin PIN | 1 UP | Low Profile PIN | 1UP |
|---|---|---|---|
| 8 | 15 | 22 | 30 |
| 14 | 14 | 24 | 35 |
| 16 | 16 | 28 | 42 |
| 18 | 27 | 36 | 58 |
| 20 | 29 | 40 | 57 |

2 level 14 pin ww .20

| WIRE WRAP LEVEL 3 PIN | | PIN | |
|---|---|---|---|
| 14 | 37 | 24 | 86 |
| 16 | 39 | 28 | 1.00 |
| 18 | 57 | 40 | 1.23 |

| CRYSTALS | |
|---|---|
| 1 MHz | 4.50 |
| 2 MHz | 4.50 |
| 4 MHz | 4.25 |
| 5 MHz | 4.25 |
| 10 MHz | 4.25 |
| 18 MHz | 3.90 |
| 20 MHz | 3.90 |
| 32 MHz | 3.90 |
| 32768 Hz | 4.00 |
| 1.8432 MHz | 4.50 |
| 3.5795 MHz | 1.20 |
| 2.0100 MHz | 1.95 |
| 2.097152 MHz | 4.50 |
| 2.4576 MHz | 4.50 |
| 3.2768 MHz | 4.50 |
| 5.0688 MHz | 4.50 |
| 5.185 MHz | 4.50 |
| 5.7143 MHz | 4.50 |
| 6.5536 MHz | 4.50 |
| 14.31818 MHz | 4.25 |
| 18.432 MHz | 4.50 |
| 22.1184 MHz | 4.50 |

| DISPLAY LEDS | | | |
|---|---|---|---|
| MAN1 | CA | 270 | 2.90 |
| MAN3 | CC | 125 | .39 |
| MAN72 74 | CA CA | 300 | 1.00 |
| DL704 | CC | 300 | 1.25 |
| DL707 DL707R | CA | 300 | 1.00 |
| DL727 728 | CA CC | 500 | 1.90 |
| DL747 750 | CA CC | 600 | 1.95 |
| FND359 | CC | 357 | .70 |
| FND500 507 | CC CA | 500 | 1.35 |
| FND503 510 | CC CA | 500 | .90 |
| FND800 807 | CC CA | 800 | 2.20 |
| 3 digit Bubble | | | .60 |
| 10 digit display | | | 1.25 |
| 7520 Clairex photocells | | | .39 |
| TIL311 Hex | | | 9.50 |
| MAN3640 | CC | 30 | 1.10 |
| MAN4610 | CA | 40 | 1.20 |
| MAN4640 | CC | 40 | 1.20 |
| MAN4710 | CA | 40 | .95 |
| MAN4740 | CC | 40 | 1.20 |
| MAN6640 | CC | 56 | 2.95 |
| MAN6710 | CA | 60 | 1.35 |
| MAN6740 | CC | 60 | 1.35 |

| KEYBOARDS | |
|---|---|
| 56 key ASCII keyboard kit | $67.50 |
| Fully assembled | 77.50 |
| 53 key ASCII keyboard kit | 60.00 |
| Fully assembled | 70.00 |
| Enclosure Plastic | 14.95 |
| Metal Enclosure | 29.95 |

## RCA Cosmac 1802 Super Elf Computer Kit $106.95

The Quest Super Elf is the right choice for the person who has a need to learn more about computers, from an understanding of the hardware and how it goes together to beginning programming with machine language on up through basic.

### Tremendous Value

The Super Elf is a tremendous value as it combines video, digital displays, LED displays, and music, all on a single board for $106.95. Its unique ability for single step debugging, display of state and mode of the computer and display of addressing as an inexpensive option gives it an "easy to use" capability not available anywhere at the price.

### Inexpensive Expansion

The Super Elf expansion capability is virtually unlimited and you can do it inexpensively one step at a time. Expansion includes cassette interface, additional memory, color video, Basic, ASCII keyboard, printer, floppy, S-100 bus, RS232, etc.

### Strong Software Support

The Super Elf comes complete with power supply and detailed 127 page instruction manual which includes over 40 pages of software, including a series of lessons to help get you started and a music program and graphics target game. Many schools and universities are using the Super Elf as a course of study. OEM's use it for training and R&D. A monthly newsletter, Questdata is devoted exclusively to software for the Super Elf and there are many software books available at low cost. You can do a tremendous amount with the software available and there is more coming every day. Of course, you can do your own programming which is fun and very rewarding.

### Free 14 Page Brochure

Send or call for a free brochure on all details and pricing of the Super Elf and its expansion. We will get it right out to you!

### Modem Kit $60.00

State of the art, orig., answer. No tuning necessary. 103 compatible 300 baud. Inexpensive acoustic coupler plans included. Bd. only $17.00.

### Z80 Microcomputer

16 bit I/O, 2 MHz clock, 2K RAM, ROM Breadboard space. Excellent for control. Bare Board **$28.50.** Full Kit **$99.00.** Monitor **$20.00.** Power Supply Kit **$35.00. Tiny Basic $30.00**

### Video Modulator Kit $9.95

Convert TV set into a high quality monitor w/o affecting usage. Comp. kit w/full instruc.

### Multi-volt Computer Power Supply

8v 5 amp, ±18v .5 amp, 5v 1.5 amp, −5v .5 amp, 12v .5 amp, −12v option. ±5v, ±12v are regulated. Basic Kit **$29.95.** Kit with chassis and all hardware **$43.95.** Add $4.00 shipping. Kit of hardware **$14.00.** Woodgrain case **$10.00.** $1.50 shipping.

### 60 Hz Crystal Time Base Kit $4.40

Converts digital clocks from AC line frequency to crystal time base. Outstanding accuracy.

### Rockwell AIM 65 Computer

4K version **$450.00**

### Ohio Scientific Computer Products

CIP Series 2 **$459.00**
with monitor/TV combo **$599.00**
CIPMF Series 2 **$1225.00**
with monitor TV/combo **$1349.00**

**TERMS: $5.00 min. order U.S. Funds. Calif residents add 6% tax.
$10.00 min. BankAmericard and Master Charge accepted. $1.00 insurance optional.
Postage: Add 5%. C.O.D. $10.00 min. order.**

**FREE: Send for your copy of our NEW 1980 QUEST CATALOG. Include 48¢ stamp.**

CIRCLE NO. 56 ON FREE INFORMATION CARD

# EXCEPTIONAL SPECIALS

**Limited quantities on all items.** Sorry, at these low prices we cannot include spec sheets or accept COD/telephone orders. Part numbers must include the special **-S** suffix when shown or you will be charged our regular prices. Parts may be house numbered or have dual markings. **This is your chance to save!**

## 16K MEMORY EXPANSION SPECIAL: 8/$35!

Expand memory in Radio Shack computers (including the color model) as well as machines made by Apple, Exidy, Heath H89, newer PETs, etc. Low power, high speed (4 MHz) dynamic RAMs. Add $3 for 2 dip shunts plus TRS-80* conversion instructions.

TRS 80 is a trademark of the Tandy Corporation

## TTL

| | | |
|---|---|---|
| 7403-S | Quad 2 input OC | 21/$2 |
| 7410-S | Triple 3 input NAND | 21/$2 |
| 7413-S | 4 to 16 line decoder/demux | 6/$2 |
| 7430-S | 8 input NAND gate | 21/$2 |
| 7438-S | Quad 2 input NAND OC | 21/$2 |
| 7440-S | Dual 4 input NAND buffer | 21/$2 |
| 7442-S | BCD to Decimal Decoder | 7/$2 |
| 7444-S | Gray to decimal decoder | 8/$2 |
| 7450-S | And-or-invert | 21/$2 |
| 7472-S | JK M-S flip flop | 21/$2 |
| 7474-S | Dual D + Edge Trig Flip Flop | 12/$2 |
| 7496-S | 5 bit shift register | 12/$2 |
| 74151-S | 8 channel mux | 8/$2 |
| 74155-S | Dual 2/4 demux | 8/$2 |
| 74159-S | 4 to 16 line decoder/demux OC | 4/$2 |
| 74161-S | Synchro 4 bit binary counter | 8/$2 |
| 74163-S | Synchro 4 bit binary counter | 8/$2 |
| 74164-S | 8 bit shift register | 6/$2 |
| 74190-S | Up/down decade counter | 4/$2 |
| 74192-S | Up/down binary counter | 4/$2 |
| 74194-S | 4 bit bidirectional shift reg | 4/$2 |
| 74195-S | 4 bit parallel shift register | 6/$2 |

## CMOS

| | | |
|---|---|---|
| 4012-S | Dual 4 input NAND | 12/$2 |
| 4020-S | 14 stage counter | 4/$2 |
| 4023-S | Triple 3 input NAND | 12/$2 |
| 4044-S | Quad R-S latch | 4/$2 |
| 4046-S | Phase locked loop | 2/$2 |
| 4071-S | Quad 2 input OR | 12/$2 |
| 4093-S | Quad 2 in NAND Schmitt trig | 4/$2 |
| 4507-S | Quad EX-OR | 4/$2 |
| 4510-S | BCD up/down counter | 2/$2 |
| 5101L1-S | 1K RAM 4X256 450 ns | 10/$17.50 |

## TO-220 NEG VOLT REGS

| | | |
|---|---|---|
| 7906-S | -6V regulator | 2/$2 |
| 7908-S | -8V regulator | 2/$2 |
| 7912-S | -12V regulator | 2/$2 |
| 79M12-S | -12V regulator | 3/$2 |
| 79M15-S | -15V regulator | 3/$2 |
| 7918-S | -18V regulator | 2/$2 |
| 7924-S | -24V regulator | 2/$2 |

## OTHER SEMICONDUCTORS

| | |
|---|---|
| **General** purpose silicon signal diodes | 50/$2 |
| **GT5306** NPN darlington, min gain 17000, 25V 200 mA, TO92 package | 100/$8.95 |
| **NPN** transistor similar 2N3904 | 100/$7.95 |
| **PNP** transistor similar 2N3906 | 100/$8.95 |
| **4N28** opto-coupler 6 pin minidip, MCT-2/IL-1 pinout | 5/$2 |
| **SN76477** complex sound generator | 1/$2.50 |
| **MA1003** 12V DC clock module | $14.95 |
| **Opto-Isolator Grab Bag** - 50 mixed opto-isolators from a major manufacturer. Unmarked 6 and 8 lead minidips include single and dual types with diode, transistor, and darlington outputs. Test them yourself and save! Not recommended for beginners. | 50/$4 |

## SOLDERTAIL SOCKETS

8 pin **100/$5.95** 24, 28 pin **30/$4.95**
14, 16 & 18 pin **50/$4.95** 40 pin **20/$4.95**
20 pin **40/$4.95**

## TRANSISTORS AND FETS

| | | |
|---|---|---|
| 2N2221 | PNP TO-18 unmarked | 7/$1.00 |
| 2N2222 | NPN TO-18 unmarked | 5/$1.00 |
| 2N2907A | PNP plastic house # | 5/$1.00 |
| 2N3055 | NPN TO-3 house # | 1/$0.75 |
| 2N3904 | NPN TO-105 house # | 5/$1.00 |
| 2N3906 | PNP TO-105 house # | 5/$1.00 |
| 2N4124 | 30V/350 mW TO-92 | 3/$1.00 |
| 2N4304 | TO-18 plastic N-JFET gen purp | 2/$1.00 |
| 2N4400 | NPN plastic house # | 5/$1.00 |
| 2N4917 | PNP TO-106 | 5/$1.00 |
| 2N4946 | NPN TO-106 | 6/$1.00 |
| 2N5227 | PNP TO-92 30V | 6/$1.00 |
| 2N5306 | NPN TO-92 darlington | 3/$1.00 |
| 2N5449 | NPN | 6/$1.00 |
| 2N5484 | RF N-JFET | 3/$1.00 |
| D41D1 | PNP TO-220 1A max | 1/$0.50 |
| D44C4 | NPN TO-220 4A/55V | 1/$0.75 |
| D45C4 | PNP TO-220 4A/55V | 1/$0.75 |
| D45H8 | PNP TO-220 10A/60V | 3/$2.00 |
| MPS3694 | NPN gen purp | 4/$1.00 |
| FPT100 | Phototransistor | 1/$0.50 |
| FET-2 | Dual N-JFET TO-18 sim 2N4416 | 3/$1.00 |
| FET-3 | Dual N-JFET lo noise audio | 2/$1.00 |
| FET-6 | Gen purp dual gate MOSFET house # | 3/$2.00 |

TERMS: Cal res add tax. Allow at least 5% shipping; excess refunded. Orders under $15 add $2 handling. VISA® and Mastercard® orders (for 16K Memory Expansion only) call (415) 562-0636, 24 hrs. Include street address for UPS. Prices subject to change without notice.

GODBOUT
ELECTRONICS
OAKLAND AIRPORT, CA 94614

# SEND FOR OUR FREE CATALOGUE

CIRCLE NO. 26 ON FREE INFORMATION CARD

# Radio Shack is Your Parts Place™

## No Minimum Order! No Waiting! Low Prices! All Prime Devices!

### Bam! Beep! Boom! Zonk! And More with This IC



SN76488
28-Pin DIP

**NEW 6.99**

This sound-generator IC, a handful of parts, and a little imagination can create an infinite variety of sounds! Can be controlled by a microprocessor for sophisticated multiplexing of sounds. Built-in audio amplifier drives a speaker. With data.
**276-1768** ..... **6.99**

### Music-Maker Chip

S50240P
16-Pin DIP

**Save 44%** Reg. 6.99 **3.88**

Top-octave synthesizer IC produces 13 notes from $C_5$ to $C_6$#—use it in a keyboard instrument or musical doorbell! Requires single 12V supply and external clock. (A 4011, 100-pf cap and 10k pot will do the trick.) With full data.
**276-1780** ..... **Sale 3.88**

### Computer Connectors & Cables Now in Stock

Low As **2.69**

**A 20-Pin Header with Ejectors.** Polarized. For .100x.100" grid. **276-1556** ..... **2.69**
**B 20-Pin Cable Connector.** Reusable insulation-displacement type mounts at ends or along length of cable. **276-1557** ..... **3.49**
**C 40-Pin Card Edge Connector.** Reusable type. **276-1558** ..... **5.95**
**D DBM 25 Connector.** Reusable type for your RS-232 bus. **276-1559** ..... **4.99**
**E 20-Conductor Ribbon Cable.** 5 ft. **278-770** ..... **3.95**
**40-Conductor Ribbon Cable.** 5 ft. **278-771** ..... **6.95**

### Right-Angle Switch

**Save 50%** Reg. 1.99 **99¢**

DPDT-type for PC boards. 6A @ 125VAC.
**275-665** .... **Sale 99¢**

### Pack of 10 Silicon Diodes

*Stock Up Now!*

**99¢**

Type 1N914 switching diodes. 100% prime. PIV: 75, minimum.
**276-1122** .... **Pkg. of 10/99¢**

### Three DC Motors

**NEW**

**1.49** Pkg. of 3

For 1½ to 6VDC. Typical no-load RPM: 3550. Long leads for easy hookup.
**273-208** ..... **3/1.49**

### 16K Dynamic RAM

**Save 29%** Reg. 13.95 **9.95 Each**

**MM5290-055/4116.** Lots of memory in a 16-pin DIP! Requires ±5, +12VDC. Prime. Buy now and save!
**276-2505** ..... **Sale 9.95**

### Spring-Lever Terminal Strip

*Ideal for Speakers, Power Supplies*

**1.19**

Deluxe terminals with lever release. Color-coded. 2¼x1⅝".
**274-621** ..... **1.19**

### 10 Assorted Mini Reed Switches

Pkg. of 10 **1.98**

Hermetically sealed in glass. Contacts close when magnetic field is present. Gold-plated contacts rated 500 mA, 125VAC. **275-1610** ..... **1.98**

### Bar-Graph Display

**NEW 3.79**

Companion to our LM3914 and LM3915 display driver ICs. Ten LEDs in a 20-pin DIP. With data!
**276-081** ..... **3.79**

### Pack of 100 Coils, Inductors & Chokes

*Only* **1.98** Pkg. of 100

RF, IF and PC-mounts. Nice to have on hand.
**273-1570** ... **Pkg. of 100/1.98**

### Bright 12-Volt Snap-in Lamps

**NEW 1.69** Pkg. of 2

One red, one green. Long life. Heat-resistant housings. Leads.
**272-331** ..... **Pkg. of 2/1.69**

### Pack of 10 PC Electrolytics

**Save 30%** Reg. 3.95 **2.77** Pkg. of 10

Radial leads. Two each of most-used values: 4.7, 10, 22, 47 and 100 µF. Rated 35WVDC.
**272-1035** ..... **Pkg. of 10/2.77**

### Bright Red Flasher LED

**1.29**



***CMOS Timer IC and LED in One Package!***

5 Hz flash rate really gets attention. Ideal for displays, even electronic jewelry. **276-036** ..... **1.29**

### Adjustable Rhythm Generator Chip

**Save 33%** Reg. 6.59 **4.44**

Build an electronic percussion device! Six combinable patterns. 16-pin DIP with data.
**276-1785** ..... **Sale 4.44**

### Twelve Assorted Switches

**1.98** Pkg. of 12

May include slide, rocker, push-button and momentary types rated up to 3A, 125VAC.
**275-1601** ..... **1.98**

### Heavy-Duty SCRs

*TO-220 Cases*

Low As **99¢**

Ideal as motor speed controls, lamp dimmers. Rated 6 Amps.
**200V. 276-1067** ..... **99¢**
**400V. 276-1020** ..... **1.19**

### Color-Coded Test Cable Sets

Low As **3.69**

Insulated Clips At Each End

Set of ten 14"-long jumpers.
**278-1156** ..... **3.69**
Set of eight 24"-long jumpers. **278-1157** ..... **3.89**

**The Most-Popular Parts In-Stock! Start Your Next Project at The Shack®**

Prices may vary at individual stores and dealers

**Radio Shack®**

A DIVISION OF TANDY CORPORATION • FORT WORTH, TEXAS 76102
OVER 7000 LOCATIONS IN 40 COUNTRIES

CALL TOLL FREE

# 800-538-5000

CALL US FOR VOLUME QUOTES. ALL MERCHANDISE 100% GUARANTEED.
WE WILL BEAT ANY COMPETITORS PRICES. GIVE US A CALL AND WE'LL PROVE IT.

NEC UPD416C-2
4116-200NS
8/29.95 100/3.45EA

2716-SINGLE SUPPLY
10.95EA 8/9.95EA
2708 6.25EA 8/5.95EA

2114L-3 4K STATIC
LOW POWER 300 NS
8/29.95 100/3.49EA

21L02 Low Power 450NS 1.29EA
2102 450NS .99EA

## LS SERIES — LOOK AT THIS LS PRICING!

| | | | | | | | |
|---|---|---|---|---|---|---|---|
| 74LS00 | .32 | 74LS73 | .44 | 74LS156 | .95 | 74LS251 | 1.32 |
| 74LS01 | .28 | 74LS74 | .48 | 74LS157 | .79 | 74LS253 | .89 |
| 74LS02 | .38 | 74LS75 | .58 | 74LS158 | .82 | 74LS257 | .89 |
| 74LS03 | .32 | 74LS76 | .50 | 74LS160 | .94 | 74LS258 | .89 |
| 74LS04 | .35 | 74LS78 | .59 | 74LS161 | .99 | 74LS259 | 2.89 |
| 74LS05 | .28 | 74LS83 | .90 | 74LS162 | .99 | 74LS260 | .68 |
| 74LS08 | .38 | 74LS85 | 1.23 | 74LS163 | .99 | 74LS266 | .68 |
| 74LS09 | .38 | 74LS86 | .45 | 74LS164 | .99 | 74LS273 | 1.69 |
| 74LS10 | .32 | 74LS90 | .70 | 74LS165 | .99 | 74LS275 | 3.39 |
| 74LS11 | .29 | 74LS92 | .82 | 74LS166 | 2.40 | 74LS279 | .59 |
| 74LS12 | .29 | 74LS93 | .71 | 74LS168 | 1.79 | 74LS283 | 1.03 |
| 74LS13 | .38 | 74LS95 | 1.11 | 74LS169 | 1.79 | 74LS290 | 1.25 |
| 74LS14 | .99 | 74LS96 | .86 | 74LS170 | 1.89 | 74LS293 | 1.89 |
| 74LS15 | .35 | 74LS107 | .43 | 74LS173 | .82 | 74LS295 | 1.09 |
| 74LS20 | .26 | 74LS109 | .49 | 74LS174 | 1.19 | 74LS298 | 1.24 |
| 74LS21 | .30 | 74LS112 | .48 | 74LS175 | 1.09 | 74LS352 | 1.59 |
| 74LS22 | .34 | 74LS113 | .48 | 74LS181 | 2.19 | 74LS353 | 1.59 |
| 74LS26 | .40 | 74LS114 | .55 | 74LS190 | 1.15 | 74LS363 | 1.39 |
| 74LS27 | .35 | 74LS122 | .55 | 74LS191 | 1.31 | 74LS365 | .99 |
| 74LS28 | .39 | 74LS123 | .99 | 74LS192 | .88 | 74LS366 | .99 |
| 74LS30 | .35 | 74LS125 | .99 | 74LS193 | .98 | 74LS367 | .99 |
| 74LS32 | .39 | 74LS126 | .88 | 74LS194 | 1.80 | 74LS368 | .99 |
| 74LS33 | .54 | 74LS132 | .69 | 74LS195 | 1.39 | 74LS373 | 1.85 |
| 74LS37 | .78 | 74LS136 | .58 | 74LS196 | .82 | 74LS374 | 1.81 |
| 74LS38 | .39 | 74LS138 | .79 | 74LS197 | .82 | 74LS377 | 1.48 |
| 74LS40 | .25 | 74LS139 | .79 | 74LS221 | 1.28 | 74LS385 | 1.90 |
| 74LS42 | .79 | 74LS145 | 1.19 | 74LS240 | 1.89 | 74LS386 | .65 |
| 74LS47 | .78 | 74LS148 | 1.39 | 74LS241 | 1.89 | 74LS390 | 1.90 |
| 74LS48 | .78 | 74LS151 | .79 | 74LS242 | 1.89 | 74LS393 | 1.90 |
| 74LS51 | .35 | 74LS153 | .79 | 74LS243 | 1.89 | 74LS395 | 1.69 |
| 74LS54 | .35 | 74LS154 | 2.39 | 74LS244 | 1.79 | 74LS670 | 2.20 |
| 74LS55 | .32 | 74LS155 | 1.19 | 74LS245 | 2.89 | | |

## 8080 SUPPORT

| | |
|---|---|
| 8212 | 2.75 |
| 8214 | 5.25 |
| 8216 | 2.75 |
| 8224 | 2.95 |
| 8226 | 3.49 |
| 8228 | 4.95 |
| 8238 | 5.50 |
| 8251 | 6.95 |
| 8253 | 12.95 |
| 8255 | 6.50 |
| 8257 | 16.95 |
| 8259 | 14.95 |
| 8275 | 49.95 |
| 8279 | 15.95 |

## CPU's

| | |
|---|---|
| Z-80 | 9.95 |
| Z-80A | 12.95 |
| 8080A | 3.95 |
| 8085A | 12.95 |
| 2650 | 12.95 |

## MISC

| | |
|---|---|
| Ay5-1013 | 4.99 |
| 8T97 | 1.69 |
| 1488 | 1.39 |
| 1489 | 1.39 |
| 8202 | 34.95 |
| 3242 | 16.95 |

## EPROMS

| | | | |
|---|---|---|---|
| MM5203AQ | 1us | 256 × 8 | 13.95 |
| MM5204AQ | 750ns | 512 × 8 | 14.95 |
| 1702A | 1us | 256 × 8 | 4.95 |
| 2708 | 450ns | 1K × 8 | 5.95 |
| 2716 | 450ns | 2K × 8 | 10.95 |
| 2732 | 450ns | 4K × 8 | 29.95 |

## PROMS

| | | | | |
|---|---|---|---|---|
| 74S188 | (82S23) | OC | 32 × 8 | 4.75 |
| 74S287 | (82S129) | TS | 256 × 4 | 4.75 |
| 74S288 | (82S123) | TS | 32 × 8 | 4.75 |
| 74S387 | (82S126) | OC | 256 × 4 | 5.75 |
| 74S471 | | TS | 256 × 8 | 18.75 |
| 74S472 | (82S147) | TS | 512 × 8 | 18.75 |
| 74S474 | (82S141) | TS | 512 × 8 | 19.95 |
| 74S570 | (82S130) | OC | 512 × 4 | 7.80 |
| 74S571 | (82S131) | TS | 512 × 4 | 7.80 |

## DIP SWITCHES

4 Position .99 7 Position 1.09
5 Position 1.02 8 Position 1.14
6 Position 1.06

## VOLTAGE REG'S

| | | | |
|---|---|---|---|
| 7805T | .89 | 7905T | .99 |
| 7812T | .89 | 7912T | .99 |
| 7815T | .99 | 7915T | 1.19 |
| 7824T | .99 | 7924T | 1.19 |
| 7805K | 1.39 | 7905K | 1.49 |
| 7812K | 1.39 | 7912K | 1.49 |
| 78L05 | .69 | 79L05 | .79 |
| 78L12 | .69 | 79L12 | .79 |
| 78L15 | .69 | 79L15 | .79 |

## IC SOCKETS

| | |
|---|---|
| 8 PIN | 10/1.29 |
| 14 PIN | 10/1.49 |
| 16 PIN | 10/1.69 |
| 18 PIN | 10/1.99 |
| 20 PIN | 10/2.89 |
| 22 PIN | 10/2.99 |
| 24 PIN | 10/2.99 |
| 28 PIN | 10/3.99 |
| 40 PIN | 10/4.99 |

## LINEAR

| | | | |
|---|---|---|---|
| LM301V | .34 | LM567V | 1.29 |
| LM309K | 1.49 | LM723 | .49 |
| LM311V | .64 | LM741V | .29 |
| LM317T | 2.29 | LM747 | .79 |
| LM323K | 4.95 | LM1310 | 1.90 |
| LM324 | .59 | LM1414 | 1.59 |
| LM339 | .99 | LM1458 | .69 |
| LM377 | 2.29 | LM1488 | 1.39 |
| LM380 | 1.29 | LM1489 | 1.39 |
| LM555V | .39 | LM1800 | 1.99 |
| LM556 | .69 | LM1889 | 2.49 |
| LM565 | .99 | LM3900 | .59 |
| LM566V | 1.49 | 75451V | .39 |

.43"LED DISPLAY
BEAUTIFUL RED
7 SEGMENT DISPLAY
HP 5082-7760
.79 100/.65EA

JDR MICRODEVICES, INC.
1101 South Winchester Blvd.
San Jose, California 95128
408-247-4852
800-538-5000

TERMS: Include $2 for shipping. $10 minimum order. Send SASE for complete catalog. Bay Area Res. add 6½% sales tax Calif. Res. add 6% sales tax. We reserve the right to limit quantities and substitute manufacturer. Prices subject to change without notice.

master charge THE INTERBANK CARD — VISA®

CIRCLE NO. 33 ON FREE INFORMATION CARD



## Solar Power

### Solar Powered AM Radio

Place it in the sunshine and listen to your favorite station! Features good quality volume and tone from built-in speaker. Complete and ready to operate. Makes a unique gift! **$24.95**

### Solar Panels

Converts sunlight directly into electricity to power small fans, pumps, radios, recharge batteries, etc.
12V 125MA **$49.00** / 12V 500MA **$150.00**

### Special 9V 30MA Small Panel

For powering transistor radios, calculators. **$12.00**

### Silicon Solar Cell Experimentors Assortment

Each cell converts sunlight into electricity. Assortment contains one whole 2 inch cell, 5 odd shaped pieces and a small motor. **$7.95**

### Sound Effects Generator Basic Kit

Now it's possible to build your own sound effects generator without spending a fortune. We supply you with the T176477 sound chip plus an etched and drilled glass epoxy PC board with schematic and layout instructions. This board makes it simple to build a generator capable of phaser sounds, locomotive, sirens, airplanes, clocks, etc. Does not require dip switches or other expensive/unusual components. You supply a few standard resistors, capacitors, switches, pots, speaker, 2N2222 transistor and 9V battery.

**C23883** Basic Kit containing T176477, PC board and instructions
**Only $5.95**
2N2222 Transistor for above C23884 .39 each

### 120 VAC Xenon Strobe Kit

Complete variable rate strobe light kit. Contains all parts, PC board, line cord and instructions.
C23071 **$7.50**

### Wheel of Fortune

Popular game device uses LEDs, transistors, and IC to give the effect of a bright red ball spinning around numbers. Unit emits sound as ball spins and finally stops on a number. Incl. all parts, faceplate & PC board.

C23806 **$8.99**

CHANEY electronics inc.
P.O. BOX 27038
DENVER, COLORADO 80227

Phone Orders
303-781-5750

- Minimum AD Order $6.00
- Please include $1.50 for postage
- VISA MC accepted
- Phone orders are welcome

*Send for our free catalog of unique items*

CIRCLE NO. 9 ON FREE INFORMATION CARD



## Save on Calculators

**Olympic Sales is an HP franchised dealer.**

HEWLETT PACKARD — HP 41CV

| Model | Retail | Your Cost |
|---|---|---|
| New Hp-41CV 2.2K bytes, 4 mem. modules built-in, slanted keybrd | $325.00 | **$239.95** |
| System One, HP41CV & Card Reader | 495.00 | **394.95** |
| System Two, HP41CV-Card Redr & Prntr | 840.00 | **669.95** |
| Card reader for 41C/41CV | 215.00 | 169.95 |
| Printer for 41C/41CV | 385.00 | 289.95 |
| HP-41C new price | 250.00 | **189.95** |
| Quad Ram to upgrade HP41C to 2.2K bytes leaving 3 ports...Plugs into the 41C | 95.00 | 84.95 |
| Optical Wand for 41C/41CV | 125.00 | 109.95 |
| Memory Modules for 41C/41CV | 39.50 | 27.95 |
| HP-34C Scientific | 150.00 | 119.95 |
| HP-38C Bus./R.E. | 150.00 | 119.95 |
| HP-33C Scientific | 90.00 | 78.95 |
| HP-32E Adv. Scientific | 55.00 | 49.95 |
| HP-37E Bus. Calc. | 75.00 | 63.95 |
| HP-67 Progrmable Sci. | 375.00 | 299.95 |
| HP-97 Prog Printer Sci. | 750.00 | 579.95 |
| HP-85 Computer | 3250.00 | **2495.00** |
| New HP-83 Computer, similar to HP-85 without printer & cassette | 2250.00 | 1795.00 |

"C" stands for continuous memory.
One year guarantee by HP on all calcs, 90 days on computers.

### TEXAS INSTRUMENTS

| | |
|---|---|
| TI-99/4 Computer Console | $469.95 |
| TI-5230 printer (was $495.) | 189.95 |
| TI-59 | 199.95 |
| TI-58C | 89.95 |
| TI-57 | 49.95 |
| PC 100C | 159.95 |
| TI-55 | 35.95 |
| TI-50 | 35.95 |
| Speak and Spell | 58.95 |
| Speak and Read | 74.95 |
| Speak and Math | 67.95 |
| Language Tutor (Speaks) | 129.95 |
| Language Teacher | 72.95 |
| Invest Analyst | 48.95 |
| Bus Analyst II | 43.95 |
| TI Programmer | 48.95 |
| TI-5040 Printer | 74.95 |

Ask about the new line of TI plain paper printers at new low costs.
Ask about **special rebate** on some TI calculators and **free software on TI-59.**

### SPECIALS Computers at unbeatable prices



**APPLE II and APPLE III**
**Huge inventory of Apple II computers. 16K-32K-48K. Disk drives, monitors, 80 column card. Dow Jones & Quote Reporter. Pascal-Fortran—DOS 3.3, etc. You name it...we've got it at super low prices.**

**Call us!**

**Immediate delivery on Apple III computers 96K and 128K systems.**

| | |
|---|---|
| **Texas Instruments** 99/4 console computer | $469.95 |
| **Atari** 800 16K cnsle compu | 759.95 |
| **Atari** TV Game | 139.95 |
| **Mattel** Intel TV Game | 229.95 |
| **Mattel** Race Horse Anlyzr | 99.95 |
| **Sony** Walkman TPS L2 | 169.95 |
| **Centronics** printer P1 for Apple and Radio Shack computers Was $495.00. | 189.95 |
| **Craig** Translator M 100 | 99.95 |

**SCM** Typewriters • **Royal** • **Victor** • **Canon** • **Sharp** • **Casio**
320 models **Seiko** watches

Prices f.o.b. L.A. Minimum freight & handling charge—$4.95. In CA, add 6% sales tax. Goods subject to availability. We'll beat any advertised price if competitor has goods on hand.

VISA — Call Mon-Sat 7AM-6PM. Outside CA, toll free **800-421-8045** Inside CA, toll free **800-252-2153** — master charge

**OLYMPIC SALES COMPANY, INC.**
216 South Oxford Ave • P.O. Box 74545 • Los Angeles, CA 90004 • (213) 381-3911
Orders (213) 739-1130 • Customer Serv (213) 739-1100 • Telex 67-3477

CIRCLE NO. 49 ON FREE INFORMATION CARD

# THE MICROCOMPUTER MART

COMPUTER RETAIL STORES

**MICROCOMPUTER MART RATE:** 1" x 1 Column (1-5/8") $150. 1-1/2" x 1 Column (1-5/8") $225.00. 2" x 1 Column (1-5/8") $300.00. **GENERAL INFORMATION:** Frequency rates available. Payment must accompany copy except credit card—Am. Ex., Diners, MC, VISA (supply Expiration date)—or accredited ad agency insertions. Orders are not acknowledged. They will appear in next available issue after receipt. Closing date: 1st of the 2nd month preceding cover date (for example, April issue closes February 1st). Send order and remittance to MicroComputerMart, **POPULAR ELECTRONICS,** One Park Avenue, New York, NY 10016. Direct inquiries to (212) 725-3485.

## CALIFORNIA

**OHIO SCIENTIFIC MICRO-COMPUTERS**
**A.A. Office Equipment Company**
2140 American Avenue
Hayward, CA 94545
(415) 782-6110

**The Original ByteShop®**
1415 W. El Camino Real
Mountain View, CA 94040
(415) 969-5464

*OVER 4000*
Microcomputer parts, boards, peripherals, systems, and software . . . .
*IN STOCK*
Send for your free 1981 catalog
**JADE**
*Computer Products*
4901 West Rosecrans Ave.
Hawthorne, California 90250
(213) 973-7707
(800) 421-5500

## RHODE ISLAND

**WHOLESALE COMPUTER PRICES DIRECT TO THE PUBLIC!**
Apple • Atari •
HP-85 • Intertec •
Soroc • TRS-80II •
NEC Spinwriter
**CALL TOLL FREE**
**1-800-556-7586**
**ΩMEGA Sales Co.** 12 Meeting St. Cumberland, RI (401) 722-1027

**PRIME 16K DYNAMIC RAMS**
$35.00 for Memory Expansion Kit
- TRS-80 (Tandy Corp.™), Exidy, Heath, Apple, Pet.
- No special tools required
- 100% Guaranteed

**APPLICATIONS ENGINEERING**
2 Maria St., Lincoln, R.I. 02865

## CONNECTICUT

**COMPUTER INTERFACES ANALOG INPUTS AC REMOTE CONTROL**
FOR: Pet • Apple • TRS-80 • AIM 65
Write or call for free catalog.
Mention this magazine and receive a coupon for 5% discount on first order.
**CmC**
**Connecticut microComputer, Inc**
34 Del Mar Drive, Brookfield, CT 06804
203 775-4595 TWX 710 456-0052

## TEXAS

**LLOOK!!**
**TRS-80® Computer Owners**
®Trademark of Tandy Radio Shack Corporation
- Brand new Access mini-disk systems:

**AFD-100**
Single-drive — $315
Double-drive — $630
Triple-drive — $945
- 16K-Byte Memory (8 prime 4116 ICs) — $64.95

Introductory prices good for a limited time only. Prices do not include shipping, or sales tax if applicable.
Call Toll-free **1-800-527-4196**
***ACCESS UNLIMITED***
315 N. Shiloh - Ste. D1 - Garland, TX 75042
(214) 494-0206

**EAST TEXAS COMPUTERS, INC.**
Microcomputer Specialists
Full Line Atari Dealer
Suppliers of Creative
Software Products for Your Atari
**305 Clemson Drive**
**Tyler, TX 75703**

**TEXAS COMPUTER SYSTEMS**
**Radio Shack®**
Authorized Sales Center, OPTIC
**LOWEST PRICES ever**
**TRS-80**
**COMPUTERS**
Call **TOLL FREE** for the **BEST PRICES** on all Radio Shack® Computers and accessories
★ **FREE SHIPPING** on most items.
★ No out of state sales tax charged
**NEW**—Percom **DOUBLE DENSITY** for Model I. Twice the disk space. Easy to install, no mod-kit/solder. Copies single density to double density. Complete with diskette, manual, & DOS $299
**SOURCE TOTAL FREE 800-351-1473**
Fast Delivery (800) 527-2179
TEXAS COMPUTER SYSTEMS
108 E. 14th, Brady, Tx. 76825
Radio Shack® Authorized Sales Center TSS
"SOURCE" is a trademark of Tandy Inc.

## FLORIDA

**LEARN TO REPAIR COMPUTERS**
**"Training For Tomorrow Today"**
Now there is, within your reach, training to help you enter the fast growing computer field service industry. Let us help you shape your future. 8 week course. Must have electronics background to qualify. Write or call for FREE catalog.
**Systems Technology Institute,**
**775 Kirkman Rd., Suite 113-P,**
**Orlando, FL 32811. (305) 299-6535.**

## ILLINOIS

**FARNSWORTH COMPUTER**
Apple, Hewlett-Packard
I.D.S. Printers
Monthly Specials
1891 N. Farnsworth Ave.
Aurora, IL 60505. (312) 851-3888

## NEW HAMPSHIRE

**As advertised in 73 Amateur Radio, 80 Microcomputing & Kilobaud Microcomputing magazines**
**TRS-80** Model II 64K
FREE CATALOG **$3400.00** plus frt.
**ADAMS**
MAIL ORDER MICROS
Dept. PK MO-80A-5841
P.O. Box 607, Marlboro, N.H. 03455

**DON'T MISS**
Kilobaud MICROCOMPUTING™ — the encyclopedia of microcomputing
and 80 microcomputing — for the users of the TRS-80®
For subscription information write to:
Microcomputing 80 Pine Street, Peterborough, NH 03458
Atlantic Centre
*TRS-80 is a trademark of the Radio Shack Division of Tandy Corporation

## NEW JERSEY

**COMPUTER MART OF NEW JERSEY**
501 Route 27 Iselin, N.J. 08830
**(201) 283-0600**
The Microcomputer People®

## NEW YORK

**10% OFF** With This Ad! Valid Until 4/1/81
**ON**
TRS-80, APPLE, & ATARI SOFTWARE, AND ALL BOOKS
**COMPUTER CENTER**
31 E. 31st St., N.Y., N.Y. 10016
(212) 889-8130

## WISCONSIN

**OHIO SCIENTIFIC SYSTEMS**
**We'll Beat Any Price!**
Write or Call for Catalog
Toll Free
(800) 558-0870
***COMPUTERS PLUS, INC.***
2749 South 108th St.
Milwaukee, WI 53227
(414) 258-2588

## MICROCOMPUTER MART ORDER FORM

*Please Print Clearly or Type Copy in Space Below*
*(Indicate position of any illustration in ad & supply B&W photo)*

Please refer to heading on this page for rates & ad placement information:
# OF INCHES_____ # OF INSERTIONS _____
☐ PAYMENT ENCLOSED $_____
☐ CHARGE: You will be billed monthly. ☐ Amex ☐ Diners ☐ Visa ☐ MC-Interbank # _____
Account # _____ Exp.Date _____
SIGNATURE _____
PRINT NAME _____
ADDRESS _____
CITY _____ STATE _____ ZIP _____

# Electronics Classified

**CLASSIFIED RATES:** Per Word, 15 Word Minimum. **COMMERCIAL:** $3.00. **EXPAND-AD®:** $4.50. **DISPLAY:** 1" x 2¼", $370.00. 2" x 2¼", $740.00. 3" x 2¼", $1,110.00. **GENERAL INFORMATION:** Frequency rates and prepayment discounts available. Payment must accompany order except credit card—Am. Ex., Diners, MC, VISA (include exp. date)—or accredited ad agency insertions. Copy subject to publisher's approval; must be typewritten or printed. First word set in caps. Advertisers using P.O. Boxes MUST supply permanent address and telephone number. Orders not acknowledged. They will appear in next available issue after receipt. Closing date: 1st of the 2nd month preceding cover date (e.g., Mar. issue closes Jan. 1). Send order & remittance to: Classified Advertising, Popular Electronics Magazine, 1 Park Avenue, New York, NY 10016. Direct inquiries to (212) 725-3926.

## FOR SALE

FREE! Bargain Catalog—I.C.'s, LED's, readouts, fiber optics, calculators parts & kits, semiconductors, parts. Poly Paks, Box 942PEC, Lynnfield, Mass. 01940.

GOVERNMENT and industrial surplus receivers, transmitters, snooperscopes, electronic parts, Picture Catalog 25 cents. Meshna, Nahant, Mass. 01908.

ELECTRONIC PARTS, semiconductors, kits. FREE FLYER. Large catalog $1.00 deposit. BIGELOW ELECTRONICS, Bluffton, Ohio 45817.

RADIO—T.V. Tubes—49 cents each. Send for free catalog. Cornell, 4213 University, San Diego, Calif. 92105.

AMATEUR SCIENTISTS, Electronics Experimenters, Science Fair Students . . . Construction plans—Complete, including drawings, schematics, parts list with prices and sources . . . Robot Man—Psychedelic shows—Lasers—Emotion/Lie Detector—Touch Tone Dial—Quadraphonic Adapter—Transistorized Ignition—Burglar Alarm—Sound Meter . . . over 60 items. Send $1.00 (no stamps) for complete catalog. Technical Writers Group, Box 5994, University Station, Raleigh, N.C. 27650.

SOUND SYNTHESIZER KITS—Surf $16.95, Wind $16.95, Wind Chimes $22.95, Musical Accessories, many more. Catalog free. PAIA Electronics, Box J14359, Oklahoma City, OK 73114.

TELETYPE EQUIPMENT: Copy Military, Press, Weather, Amateur, Commercial Transmissions. Catalog $1.00. WEATHER MAP RECORDERS: Copy Satellite Photographs, National-Local Weather Maps. Learn How! $1.00. Atlantic Sales, 3730 Nautilus Ave., Brooklyn, NY 11224. Phone: (212) 372-0349.

BUILD AND SAVE TELEPHONES, TELEVISION, DETECTIVE, BROADCAST Electronics. We sell construction plans with an Engineering Service. Speakerphones, Answering Machines, Carphones, Phonevision, Dialers, Color TV Converters, VTR, Games, $25 TV Camera, Electron Microscope, Special Effects Generator, Time Base Corrector, Chroma Key. Engineering Courses in Telephone, Integrated Circuits, Detective Electronics. PLUS MUCH MORE. NEW Super Hobby Catalog PLUS year's subscription to Electronic News Letter, $1.00. Don Britton Enterprises, 6200 Wilshire Blvd., Los Angeles, Calif. 90048.

NAME BRAND Test Equipment. Guaranteed discounts up to 50%. Free catalog. Salen Electronics, Box 82, Skokie, Il 60077.

UNSCRAMBLERS FOR any scanner. Several models available. Free literature. Capri Electronics, 8753T Windom, St. Louis, MO 63114.

UNSCRAMBLERS, seven models available to decode police, ambulance, and fire coded transmissions. Other scanner devices. Tone encoders/decoders. Telephone accessories, etc. Free Catalog. KRYSTAL KITS, Box 445, Bentonville, AR 72712. (501) 273-5340.

POLICE/FIRE SCANNERS, crystals, antennas, CBs, Radar Detectors. HPR, Box 19224, Denver, CO 80219.

PRINTED CIRCUIT supplies, chemicals, tools, artwork, plating solutions. Major credit cards. Catalog $2.00, refundable. CIRCOLEX, Box 198, Marcy, NY 13403.

RECONDITIONED TEST EQUIPMENT $1.00 for catalog. WALTER'S TEST EQUIPMENT, 2697 Nickel, San Pablo, CA 94806, (415) 758-1050.

NEW ELECTRONIC PARTS. Continuously stocked. Stamp brings catalog. Daytapro Electronics, 3029 N. Wilshire Ln., Arlington Hts., IL 60004.

ELECTRONIC CATALOG. Over 4,500 items. Parts, & components. Everything needed by the hobbyist or technician. $2.00 (U.S. funds) Postage & handling, refundable with first $15.00 order. T & M Electronics, 472 East Main St., Patchogue, NY 11772. (516) 289-2520.

SPEAKERS SAVE 50%. Build your own speaker system. Write: McGee Radio Electronics, 1901 McGee Street, Kansas City, Missouri 64108.

PRINTED CIRCUIT BOARDS, your artwork. Quick delivery. Reasonable. Atlas Circuits, Box 974, Waynesville, NC 28786. (704) 456-3739.

HAMS, CBERS, SWLS, ELECTRONICS BUFFS! Parts, kits and plans now available for Popular Electronics projects. MORSE-A-WORD: Circuit boards $24.00; Essential parts kit $99.95; Complete four character kit $149.95; Eight character kit $169.95; Wired $249.95. RTTY READER: Boards $24.00; Complete kit $189.95; Wired $269.95. S&H $5.00 kits; $1.50 boards. Use VISA/Mastercard. (414) 241-8144. Write for catalog. MICROCRAFT, POB 513PE, Thiensville, WI 53092.

CABLE TV DESCRAMBLERS AND CONVERTERS. MICROWAVE ANTENNAS AND DOWN CONVERTERS. Plans and parts. Build or buy. For information send $2.00. C&D Company, P.O. Box 21, Jenison, MI 49428.

FIBER OPTIC SPECIALS—100 foot spool of fiber $3.00—Experimenter's kit $6.00—High Power LED with matched Detector $10.00—Data Link construction plans (detailed) $5.00. Catalog with samples $1.00. FIBERTRONICS, Box 322-A, Primos, PA 19018.

SCRAMBLED TELEVISION—Encoding/Decoding. New publication. Complete theory, circuits. $9.95. Workshop, Box 393PED, Bethpage, NY 11714.

RARE OUT-OF-PRINT ALBUMS. 25,000 in stock (FS). List $2.00 refundable. Record Warehouse, Box 4617, Dept. PE, Rochester, NY 14613.

CHEMICALS, Apparatus, Project Books, Wide Selection. Catalog send $1.00 to Pioneer Corp., 14a Hughey Street, Nashua, NH 03060.

TEST EQUIPMENT, new and used. Catalog $1.00. PTI, Box 8756; White Bear Lake, MN 55110.

QUALITY AUDIO COMPONENTS, Multi-Track Equipment, Programmable Calculators, Accessories. Competitive Pricing! Prompt Delivery! Knowledgeable staff! Service Facility! Credit Cards accepted. FREE catalog. SOUND IDEAS, Dept. SR, PO Box 340, Cary, N.C. 27511. 1-800-334-2483 (N.C. 919-467-8462).

SCRAMBLED TELEVISION. Decoder Circuit designs, parts suppliers, theory, technical advice. $10.00 Money Order only. Quest Electronics, Box 1722, Costa Mesa, Ca. 92627.

FREE CATALOG! Bargains, Parts, ICs, Kits, Musi-Kits, Specials. GODBOUT ELECTRONICS, Bldg. 725E, Oakland Airport, CA 94614.

SATELLITE TELEVISION INFORMATION—Build or buy your own Earth Station. U.S.$4.00 Satellite Television, RD 3, Oxford, NY 13830.

SUBSCRIPTION TELEVISION EDUCATION MANUAL! Two scrambling/decoding systems, theory, circuits. Decoder dealers listed. $14.95. Kits available. Satisfaction guaranteed. ABEX, P.O. Box 26601-P4, San Francisco, CA 94126.

ELECTRO-VOICE Hi Fi component loudspeakers. Building your own Speaker System? Use the best Free discount catalog. SONIX, Dept. PE, Box 58, Indian Head, MD 20640. (301) 753-6432.

PRINTED CIRCUIT BOARDS From Schematics, your artwork or ours. Free Drilling and quotes. Assembly services also available. Write: PRODUCTION DEVELOPMENT, 1320 Water Street, Brownsville, PA 15417.

VIDEO TAPES - L500 2/$21.50, L750 2/$27.50. JVC-T120 2/$28.00. Order TOLL-FREE (800) 221-0400. FREE CATALOG. Also RCA, Zenith, G.E., Sony, Panasonic, T.V. parts. Mannfred Electronics, 60-10 Kissena Blvd., Flushing, NY 11355. (212) 762-7777.

SURPLUS CATALOG 8,000 items: Electronics, Stereos, Speakers, Alarms, Tools, Games, Solar, Auto-Home, 8 Issues $2.00, BNF(X), 119 Foster St., Peabody, MA 01960.

UNSCRAMBLE CODED MESSAGES from police, fire and medical channels. Also telephone recording adaptor. Same day service. Satisfaction guaranteed. Don Nobles Electronics, Inc. Rt. 7, Box 610-A, Hot Springs, AR 71901. (501) 623-6027.

SATELLITE TELEVISION - Inexpensive system, receive anything, build antenna under $175.00. Plans and manual $19.95. MONEY BACK GUARANTEE. Satteleco, Box 265, Salem, Ohio 44460.

SHORT WAVE LISTENERS! Free new catalog #5 of short wave receivers, digital frequency displays, Colins filters, active All-Band receiving antennas, loop antennas, scanners and special DX modifications! Kenwood—Yaesu—Drake—Sony—Panasonic—Grundig. Radio West, 3417 Purer Road, Escondido, CA 92025. (714) 741-2891.




SATELLITE TELEVISION . . . HOWARD/COLEMAN boards to build your own receiver. For more information write . . . ROBERT COLEMAN, Rt. 3, Box 58-APE, Travelers Rest, S.C. 29690.

ELIMINATE FADING from your shortwave receiver. New method. Any make or model. Also CB, AM. Complete plans, $5.00. Intertech, Box 25568P, Cleveland, OH 44125.

IC SOCKETS, Gold-Plated Contacts, Gold-Plated Solder-Tails, low profile, only 2¢ per pin. 8, 14, 16, 18, 20, 22, 24, 28, 40. Min. order $25. ORION, 333 E. 46th St., NY, NY 10017.

DECODER KIT, TV UHF CHANNELS. Sine Wave Encoder System. Model 7 + 11 Mark I, complete kit $139.00, plus 5% for shipping and handling. Also parts etc. Catalog $1.00. Simple Simon Electronic Kits, 11852 S. Hawthorne Blvd., Hawthorne, California 90250. TEL: (213) 675-2335.

YOUR NAME TO ALL FREE CLASSIFIED'S under headings you mark. $1.00, FUTURE, P.O. Box 605, Dept 1, Alabaster, AL 35007.

REMODULATOR (LM I889)-audio & video inputs - output R.F. switched for T.V. channel 3 or 4 $29.00. UHF and MICROWAVE units connect to T.V. antenna for commercial free movies at home $300.00. These are not kits. VIDEO GALLERY INC., 2270 Wyandotte W., Windsor, Ontario, Canada N9B IK2 (519) 254-2001. Visa & M.C. U.S. Inquiries.

RESISTORS ¼W, ½W5%C.F. 3¢ea. NO MINIMUMS. Send for information. Bulk pricing available. JR Industries, 5834-A Swancreek, Toledo, Ohio 43614.

RECEIVE subscription or cable TV on the 2000MHz to 2500MHz frequency with our fully guaranteed, complete, detailed MDS plans. Send $9.95 to DYNACOMP ELECTRONICS, Dept. GF-1, Scottsdale, Arizona 85258.

BUILDING A ROBOT? Using stepper motors? SASE: Sparky Electronics, 64-62 Dry Harbor Rd., Middle Village, NY 11379.

NICKEL CADMIUM CELLS, wet type, used, tested. 34AH $6.00 ea. 22AH $5.00 ea. JOE CONNER, 8346 Bagley, Ashley, MI 48806.

HIGH FIDELITY COMPONENTS AND CAR TAPE PLAYERS. Buy top name brand equipment at the same price many dealers pay. 130,000 customers nationally, IN BUSINESS 29 YEARS. TOLL FREE 1-800-638-8806 or 1-301-488-9600.

**WHOLESALE DISCOUNT GUIDE**

AUDIO — VIDEO — PHOTOGRAPHIC

Save 20%—90% off retail prices! Here are discount mail order sources that sell thousands of audio and video products of every kind — TV's, Home Video Recorders, Hi-Fi Component Equipment, Cassettes, Tape Decks, LP's, Cameras, Lenses, Photo accessories and much more! Stop paying retail — Send $5.95 today! Add $1.00 for 1st class (air mail). Moneyback guarantee.

**COMMAND PRODUCTIONS • Box 26348-P • San Francisco, CA 94126**

FOR ATARI T.V. Game, Rapid firing laser cannons variation. Usable with Space Invaders program. Only $9.95. James Balis, 345 Flatbush Ave., Brooklyn, NY 11238.

PCB as low as 15¢ sq-in. FREE DRILLING. International Enterprise, 6452 Hazel Circle, Simi Valley, CA 93065.

OUTPERFORM COMPUTERS. Superhuman brain ability secrets. Lesson (stamp) Modern Humans, 22511-p Markham, Perris, CA 92370.

**Satellite TV**

**FOR THE HOME**

**Sick of Network TV?**

Our receiver lets you get over 75 channels of television directly from earth-orbiting cable TV satellites!: HBO, Showtime, super stations, sports and movies worldwide.



**We don't just sell information! We Manufacture Hardware!**

From offshore oil rigs, data links to hotels and backyard installations, we wrote the book. Constantly updated, our **94 Page** technical information book and catalog gives you all the facts. Inexpensive dishes, feeds, telemetry software, kits and more. Recommended reading by NASA, The Office of Consumer Affairs and quality companies like Rockwell/Collins. Send $7.95 today!



***CALL 24-hrs. C.O.D. Hotline (305) 339-7600***

© SPACECOAST RESEARCH CORPORATION
P.O. Box 442-A, Altamonte Spgs, FL 32701

**SATELLITE VISION SATELLITE VISION SATELLITE VISION**

We manufacture the highest spec 3-meter data & video dish in the world 41db gain! We also sell direct. Immediate delivery or you pick up. Complete details including satellite TV information, aiming service and discount schedule. Send $1.25 for postage & handling to: TIGER TENNAS, P. O. Box 561, Casselberry, Florida 32707

BUY DIRECT

COMPLETE SOLID STATE Color television recorder-reproducer electronic assembly with power supply. $24.95. Visa, Master Card. Madison Electronics, Box 217, Madison, Alabama 35758. Telephone 205-837-6658.

RF POWER TRANSISTORS/TUBES! MRF454 - $18.00. MRF455A - $14.50, 8950 - $9.75, 6LF6/6MH6 - $5.50. Catalog and cross-reference help available. WESTCOM, 1320 Grand, San Marcos, CA 92069. (714) 744-0728.

REMOTE - DISTRIBUTE your stereo anywhere, plans $10.00. New: 8" coaxial speakers with piezoelectric tweeters, $22.50. Prepaid freight with $100.00 order. INFORMATION PLEASE, 4908 Lakebluff, W. Bloomfield, Michigan 48013.

## COMPUTER EQUIPMENT

SURPLUS COMPUTER PERIPHERALS: "Selectric" I/O typewriter bargains. World's largest selection. Send 25¢ for bargain-packed flyer. CFR, Box 144, Newton, NH 03858.

CURRENT - LOOP INTERFACE ADAPTER for your terminal or computer, $99.00. For specifications write or call: DURA-COM, 7300 North Crescent Blvd., Pennsauken, NJ 08110. (609) 662-7295.

LEARN MICROCOMPUTERS on your own computer. Send $5.00 for 2 complete instruction manuals. Paccom, 14905 NE 40th, Dept. MPE021, Redmond, WA 98052.

MEMOREX FLEXIBLE DISKETTES. WE WILL NOT BE UNDERSOLD!!! Visa, Mastercharge accepted. Call free (800) 235-4137 for prices and information. All orders sent postage paid. PACIFIC EXCHANGES, 100 Foothill Blvd., San Luis Obispo, CA 93401.

SERVICE. Maintenance and repair for all microcomputers and peripherals. Fast, reasonable. Prairie Micro Clinic, Box 325, Herington, KS 67449. (913) 258-2179.

WANTED — Sell your unwanted computer through us. Big savings for buyers in pre-owned equipment. Buyers/sellers — Send SASE or 25¢ for details, Autocomp, Box 246, Glenham, NY 12527.

RF MODULATORS! Special versions for SATELLITE TELEVISION, COMPUTERS, CCTV. Also Monitors, Cameras, Kits. FREE catalog. Phone (402) 987-3771. Dealers welcomed. ATV RESEARCH, 13-P Broadway, Dakota City, NE 68731.

POCKET COMPUTER NEWSLETTER. Helpful. Informative. Free information. Sample $2. PC Newsletter, Dept. PE1, Box 232, Seymour, CT 06483.

TRS-80 COLOR COMPUTER Complete 16K. Memory Conversion Kit for the 4K. System $59.95. Instructions only $12.00. Culpeper Computer, 502-B South East St., Culpeper, VA 22701.

6800 MICROCOMPUTER KIT, ONLY $79.50. 1K bytes ram, 256 bytes rom, hex Keyboard, display, and power supply. For additional information or to order, write: SIERRA ELECTRONICS, Box 5880, Lubbock, Texas 79417.

## C.B. EQUIPMENT

GET MORE CB CHANNELS AND RANGE! Frequency Expanders, boosters, speech processors, how-to-books, plans, modifications. Catalog $1. CB CITY, Box 31500PE, Phoenix, AZ 85046.

PALOMAR - PRIDE - ATLAS: Exclusive Repair Facility. Factory trained technicians, all work guaranteed. Palomar Electronics Repair Service, 1320 Grand, San Marcos, Cal 92069. (714) 744-0720.

SKYROVER ROTARY BEAM ANTENNA! Superior performance, compact design. Entire 11 meter band. Pelican Co., Box 647-P, Hobe Sound, FL 33455.

EVERYTHING you need to know about CB. Manual only $4.95 plus 50¢ shipping and handling. Allow 6 weeks. D. Parry, 656 W. 600 No., Clearfield, UT 84015.

## CABLE TV

500 PHILIPS 32 CHANNEL CABLE TV converters and VCR programmers. $17,800 prepaid to your door. Sample $48. Birnbom, 3655 Ridgewood, Suite 103, Montreal, Canada H3V 1B4. (phone 514-739-0614). (U.S. inquiries).



**$39.95** ADD $2.50 FOR POSTAGE

**30 CHANNEL CABLE TV CONVERTER**

*ORDER No. 198AE047*

**ETCO** ROUTE 9N, PLATTSBURGH, N.Y. 12901
Tel.: (518) 561-8700.

**FREE!** UNUSUAL 96 PAGE ELECTRONIC PARTS & IDEAS CATALOG!

## AMATEUR RADIO

"OWNER REPAIR OF RADIO EQUIPMENT" Book, $8.70 (Club Discount). K6RQ, 14910 LG Blvd., Los Gatos, CA 95030.

MADISON DEEP HAM DISCOUNTS. Kenwood, Yaesu, Icom, Drake, Accessories—Stock. FREE flyer, Madison Electronics, 1508-P McKinney, Houston, TX 77010. (713) 658-0268.

RADIO AMATEUR CALLBOOKS 1981 Directories of Radio Amateurs around the world. U.S. Callbook $20.50; Foreign Callbook $19.50, shipping included. See your dealer or write for FREE catalog. Radio Amateurs Callbook, Dept. PE, 925 Sherwood Dr., Lake Bluff, IL 60044.

ATTENTION SHORT WAVE LISTENERS: The updated, 1981 edition of Short Wave Station Mailing Addresses is now available. This comprehensive collection, meticulously compiled by our staff, is a "must" for any devoted SWL. Use for correspondence, QSLs, transmission times, frequency lists, literature, etc. Only $2.00. The United States Association of Short Wave Listeners, University of Connecticut, North Campus, Box 1035, Storrs, CT 06268.

## PLANS AND KITS

PRINTED CIRCUIT Boards from sketch or artwork. Kit projects. Free details. DANOCINTHS Inc., Dept. PE, Box 261, Westland, MI 48185.

LASERS HANDBOOK with burning, cutting, Ruby Reds, CO's complete plans, books, and parts. Send $4.00 to: Famco, Dept. PE, Box 1902, Rochester, NH 03867.

PRINTED CIRCUIT BOARDS, send your sketches or artwork, kit projects. Quick Service. Free Estimates. ELECTRONIC DESIGN CONCEPTS, 2780 Skyline Circle, Memphis, TN 38127.

TOP QUALITY SPEAKERS AND KITS. Send $1.00. Speaker Warehouse, 809 North Route 441, Hollywood, FL 33021.

GIANT SCREEN TV projection system converts any television into 7-foot picture. Lens & instructions $14.95. (Dealers welcome). Bell Video, 4616 Belair Rd., Baltimore, MD 21206.

**BUILD AN ORCHESTRA THE WERSI WAY**

Preview the world's most advanced Do-It-Yourself Organs, Pianos, Synthesizers, Amps, etc. Send $6.00 for our famous "Sight & Sound" pack. WERSI Electronics, Inc., Dept. M2, P.O. Box 5318, 1720 Hempstead Rd., Lancaster, PA 17601.



KILL OBNOXIOUS LOUD TV commercials automatically. Complete plans $5.00. Bridges, 1248 N. Denver, Tulsa, OK 74106.

STEPPER MOTOR EVALUATION KIT contains Stepper Motor, Driver Board, Instructions. Ideal for hobbyists, Robot builders. $74.69, SES, Inc., 64-62 Dry Harbor Rd., Middle Village, NY 11379.

PLANS: SUBSCRIPTION TELEVISION DECODER, $10.00. Negative Ion Generator, Telephone Memory Dialer, $3.00 each. Detailed instruction and circuit board patterns included. Kits available. COLLINS ELECTRONICS, Dept. PE, Box 6424, San Bernardino, CA 92412.

BUILD low cost useful devices from salvage components. Details free. Projects, POB 1045P, Norman, OK 73070.

IN-GROUND SWIMMING POOL KIT — Blue-prints — Vinyl Liner — Side-Walls — Skimmer — Filter — Pump — All materials Necessary for Construction — Except Local Materials — 16'x32' $1,995.00-FOB. Cheswick Pool Sales Inc., Rte. 28, Cheswick, PA 15024. (412) 274-6400. Call Collect.

TV DECODER - Sinewave negative and layout for formula international tuner, $15. Jomar, 2028 Knightsbridge Dr. Cinti, Ohio 45244.

SUBSCRIPTION TV DECODER KIT. Includes parts, manual and etched board. $39.00. JOE, P.O. Box 61, Cumberland, R.I. 02864.

PROTECT your home with a simple, inexpensive security System. Complete plans only $12.95. D. Keeler, PO Box 81264, Mobile, AL 36608.

## ALARMS

**Burglar • Fire Protection**

**Protect Your Life, Home, Business, Auto, etc.**

• Our catalog shows how. Install your own alarm systems and devices and save $$$$. We offer FREE write-in engineering service.

**FREE CATALOG** Lowest Prices on Reliable, High-Quality Alarm Systems and Devices

**Burdex Security Co. Box 82802-PE Lincoln, Ne. 68501**

BURGLAR, FIRE, CAR! Finest equipment! Save! Free Catalog. Refundable! AAS, 186A Oxmoor Road, B'ham, AL 35209.

## HIGH FIDELITY

DIAMOND NEEDLES and Stereo Cartridges at Discount prices for Shure, Pickering, Stanton, Empire, Grado, Audio Technica, Osawa, Satin and ADC. Send for free catalog. LYLE CARTRIDGES, Dept. P, Box 69, Kensington Station, Brooklyn, New York 11218. Toll Free 800-221-0906 9AM - 8PM except Sunday.

193 MARANTZ SQA-2 and 156 Marantz CD400B quad adapters. Original sealed factory cartons. $5950 the lot. Ridgewood, BOX 777, Champlain, NY 12919.

## WANTED

GOLD, Silver, Platinum, Mercury, Tantalum wanted. Highest prices paid by refinery. Ores assayed. Free circular. Mercury Terminal, Norwood, MA 02062.

## TUBES

RADIO & T.V. Tubes — 49 cents each. Send for free Catalog. Cornell, 4213 University, San Diego, Calif. 92105.

TUBES: "Oldies", Latest. Supplies, components, schematics. Catalog Free (stamp appreciated). Steinmetz, 7519-PE Maplewood, Hammond, Ind. 46324.

TUBES-RECEIVING, Industrial and Semiconductors Factory Boxed. Free price sheet including TV, Radio and audio parts list. Transleteronic, Inc., 1365 39th St., Brooklyn, New York 11218. Telephone: (212) 633-2800. Toll free: 800-221-5802.

HUGE INVENTORY! Thousands of types. Wholesale prices. FREE CATALOG! ETCO Electronics, DEPT. 290, Plattsburgh, NY 12901.

## GOVERNMENT SURPLUS

MANUALS for Govt Surplus radios, test sets, scopes. List $1.00 (cash). Books, 7218 Roanne Drive, Washington, D.C. 20021.

JEEPS—$19.30!!—CARS—$13.50!!—650,000 ITEMS!!—GOVERNMENT SURPLUS!! — MOST COMPREHENSIVE DIRECTORY AVAILABLE tells how, where to buy!! — YOUR AREA — $2. — MONEYBACK GUARANTEE!! — "Government Information Services", Department GE-71, Box 99249, San Francisco, California 94109.

"GOVERNMENT SURPLUS DIRECTORY." Buy 500,000 items (including Jeeps) . . . low as 2¢ on dollar! Most complete information available — $2.00. Surplus Disposal, Box 19107-HC, Washington, DC 20036.

## PERSONALS

MAKE FRIENDS WORLDWIDE through international correspondence, illustrated brochure free. Hermes-Verlag, Box 110660Z, D-1000 Berlin 11, W. Germany.

PENFRIENDS — ENGLAND — USA, through correspondence. Send age, interests. Free reply. Harmony, Box 89PE, Brooklyn, New York, 11235.

CORRESPONDENCE FOR FRIENDSHIP IN PHILIPPINES, MALAYSIA. Free information. AACC-(PE), Box 1542, Canoga Park, Calif. 91304.

## INSTRUCTION

UNIVERSITY DEGREES BY MAIL! Bachelors, Masters, Ph.D's. Free revealing details. Counseling, Box 317-PE03, Tustin, California 92680.

LEARN WHILE ASLEEP! HYPNOTIZE! Astonishing details, strange catalog free! Autosuggestion, Box 24-ZD, Olympia, Washington 98507.

RADIO BROADCASTING: Become DJ, engineer. Start your own station — investment experience unnecessary! Receive free equipment, records. Free details. Broadcasting, Box 130-A3, Paradise, CA 95969.

**PASS FCC EXAMS**

The Original FCC Tests-Answers exam manual that prepares you at home for FCC First and Second class Radiotelephone licenses. Newly revised multiple-choice exams cover all areas tested on the actual FCC exam. Plus "Self-Study Ability Test." Proven! $9.95 postpaid. Moneyback Guarantee.

FCC TESTS-ANSWERS FOR FCC FIRST AND SECOND CLASS COMMERCIAL LICENSE

COMMAND PRODUCTIONS
Radio Engineering Division
P.O. Box 26348 P
San Francisco, CA 94126

LEARN ELECTRONIC ORGAN SERVICING at home. Completely revised course covers latest models including digital, LSI's, synthesizers, etc. TEXAS BRYANT SCHOOL, PO Box 20153, Sacramento, CA 95820.

MEDICAL ELECTRONICS TECHNOLOGY, home study. Troubleshoot medical instruments. MDC, P.O. Box 124, Pinedale, CA 93650.

LEARN TELEVISION-Complete theory in really simple language. Many illustrations and complete transmitter & receiver circuits. $6.50 post paid in USA. Aptron Laboratories, P.O. Box 323, Bloomington, IN 47402.

COLLEGE DEGREES BY SPECIAL EVALUATION of EXISTING Credentials & Job Experience. Fast, Inexpensive, (614) 863-1791. Guidance, Box 13151-A3, Columbus, Ohio 43213 Be Specific.

YOU CAN NOW EARN A Bachelor, Master, or Doctoral Degree without leaving home. Courses are under faculty guidance. Kensington University, (P.O. Box 2036-M), 512 E. Wilson, Glendale, CA 91209.

DIGITAL computer training. Free course description. Guaranteed. Innovative Home Study, Box 1046 E, Indian Rocks Beach, FL 33535.

TECHNICIAN? ENGINEER? AMBITIOUS? Want to become TOP-NOTCH? A TROUBLE SHOOTING & PROBLEM SOLVING ACE? A costly industrial seminar is now available in manual form for only $15 written by an expert for experts. It contains the most effective insights to TOP PERFORMANCE. Order now "The MASTERMIND" from the author at full-refund, ONE YEAR-TRIAL, guarantee. Alex Botai, 4020-10 Brandongate L4T 3W8 Ont., CND. U.S. Inquiries.

## FOR INVENTORS

PATENT AND DEVELOP Your invention. Registered Patent Agent and Licensed Professional Engineer, Send for FREE PATENT INFORMATION every inventor should have. Richard L. Miller, P.E., 3612 Woolworth Building, New York, NY 10007. (212) 267-5252.

**INVENTIONS WANTED**

FREE CONSULTATION ● NO IDEA TOO SMALL

Disclosure registration. Potential cash or royalties from manufacturers seeking new ideas. For free information on how to register your ideas. Call or write.

**AMERICAN INVENTORS CORP.**

15 Interstate Dr. Dept PE
West Springfield, MA 01089 (413) 737-5376
The Total Based Service Company

INVENTORS Patent your invention. Free initial consultation. We are registered by the U.S. Government. VICTOR J. EVANS & CO., 4637 Eastern Ave. N.E., Washington, DC 20018. Since 1898.

MANUFACTURER SEEKING Patented, Unpatented Inventions. Generous royalties. Advantek International, 1100 17th NW, Washington, DC 20036.

IDEAS, INVENTIONS, new products wanted! Write for Kit-Pe, IMI, 701 Smithfield, Pittsburgh, PA 15222.

## BUSINESS OPPORTUNITIES

FREE CATALOGS. Repair air conditioning, refrigeration. Tools, supplies, full instructions. Doolin, 2016 Canton, Dallas, Texas 75201.

MECHANICALLY INCLINED individuals desiring ownership of Small Electronics Manufacturing Business — without investment. Write: BUSINESSES, 92-K3 Brighton 11th, Brooklyn, New York 11235.

**MECHANICALLY INCLINED INDIVIDUALS**

Assemble electronic devices in your home. Knowledge, or experience not necessary. Get started in spare time. Above average profits. $300 - $600/Wk possible. Sales handled by others. No investment — Write for free details.

**ELECTRONIC DEVELOPMENT LAB**
**Box 1560PE, Pinellas Park, FL 33565**

ERASE DEBTS with little-known law — create wealth!! Details FREE — Blueprints, No. EE3, LaGrangeville, NY 12540.

BORROW $25,000 "OVERNIGHT." Any purpose. Keep indefinitely! Free Report! Success Research, Box 29263-GC, Indianapolis, IN 46229.

FREE BOOK "2042 Unique Proven Enterprises." Fabulous "unknowns," second inflation income. Haylings-M, Carlsbad, CA 92008.

YOU CAN EARN $1,000-$3,000 WEEKLY rebuilding CRTs with Lakeside equipment. Lakeside, 4071 Elston, Chicago, Ill 60618. (312) 583-6565.

SPARE TIME FORTUNE in Vinyl Repair. Huge demand creates exceptional profits. We supply everything. Details free. VIP, 2012 Montrose, Chicago, IL 60618.

NEW TAX LOOPHOLES DISCOVERED. Everyone Eligible. Free sample newsletter. Write ULC, Box 179-BA, Clarkston, GA 30021.

BIG MONEY IN BUSINESS PRINTING! 25% COMMISSION PLUS BIGGEST CASH BONUS! Build your own profitable year around business. Show tremendous line of salesbooks, register forms, unit sets, letterheads, envelopes, invoices, statements, business cards and dozens of other printed products. Lowest prices in industry. Something for every business and professional person. Free sales kit includes ad specialties, calendars, signs and ad matches. No experience needed. Out catalogs are easy to understand. We're over 50 but still young and aggressive, so we can show you the road to a very profitable full or part time career. Free sales kit. National Press, Dept. 128, North Chicago, IL 60064.

MAILORDER OPPORTUNITY! Start profitable home business without experience or capital. Write for free book, case histories, plus complete details. No obligation. Mail Order Associates, Dept 795, Montvale, NJ 07645.

MAKE DURABLE BUILDING Plastic easily. Waterproof, Fireproof, Economical. Bays Laboratory, 2086-2075 Drive, Cedaredge, CO 81413.

PROJECTION TV . . . Make $200.00 + per evening assembling Projectors . . . Easy . . . Results equal to $2,500 projectors . . . Your total cost less than $15.00 . . . PLANS, LENS & Dealer's information $14.00 . . . Illustrated information FREE . . . Macrocomcgx, Washington Crossing, PA 18977.

CASH WITH YOUR CAMERA! Earn $5000-$15,000 yearly selling to 4,000 clients. Sell photos 15 or more times. Guaranteed details - 25¢. Pictureprofits, Box 479-PE, Port Jefferson Station, NY 11776.

BORROW $30,000 without interest! All eligible. Repay anytime. Free details. Infohouse-PE3, Box 1004, New York, NY 10003.

## EMPLOYMENT OPPORTUNITIES

ELECTRONICS/AVIONICS EMPLOYMENT OPPORTUNITIES. Report on jobs now open. Details FREE. Aviation Employment Information Service, Box 240E, Northport, New York 11768.

## REPAIRS & SERVICES

TV TUNERS REBUILT, VHF or UHF only $11.90. Send for free mailing kit. JW Electronics, Box 51A, Bloomington, IN 47402.

ALL T.V. TUNERS repaired $11.95. Also repair Modules. Fast, quality work. MIKE'S T.V. TUNER SERVICE, Box 187, Bean Station, TN 37708. (615) 581-6393.

## REAL ESTATE

BIG . . . FREE CATALOG! Over 2,800 top values coast to coast! UNITED FARM AGENCY, 612-EP West 47th, Kansas City, MO 64112.

## RUBBER STAMPS

RUBBER STAMPS, BUSINESS CARDS. Many new products. Catalog. Jackson's, E-100, Brownsville Rd., Mt. Vernon, Ill. 62864.

## MUSICAL EQUIPMENT

MUSICAL INSTRUMENTS HOT LINE! Incredible prices: Amps. PA gear. All instruments. Huge selection. Sam Ash, established 1924. 800-645-3518. NYS: (212) 347-7757.

## BOOKS AND MAGAZINES

ELECTRONICS BOOKS AVAILABLE. World publishers. Lowest prices. Ask catalogue. Business promotion, Lajpatrai Market, Delhi, India.

ELECTRONIC MUSIC and home recording in Polyphony magazine. Advanced applications, interviews, projects, computer music. Sample $1.50. Subscription (6 issues). $8.00 US $10.00 foreign. POLYPHONY, Box P20305, Okla. City, OK 73156.

THE SUPERMARKET OF ELECTRONICS — thousands of items for sale or trade each month. Free classified ad with subscription. Only $5.00 to Nuts & Volts, POB 1111-P, Placentia, CA 92670.

PUBLISHERS' OVERSTOCKS, BARGAIN BOOKS. 2,000 titles, all subjects! Free catalog: Hamilton, 98-84 Clapboard, Danbury, CT 06810.

## MOTION PICTURE/VIDEO

ORDER "TOP 10" S-8 Sound Sellers: "The Electric Horseman," "Animal House," "Smokey and the Bandit" (B. Reynolds), "The Jerk" (S. Martin) — 1x400' clr snd. budget price $49.95 ea*. 2-reelers (2x400') $105./set delivered (a $124. val.). Order now! M. Brando, The Godfather; J. Travolta, Sat. Night Fever; Marathon Man (D. Hoffman); Barbarella (J. Fonda); Chinatown (J. Nicholson). Build a library of these star studded Paramount Pix — only $49.95 ea PPD (reg $65.). We welcome Visa & Master Card — just write card #, exp. date and sign. Maj. League Base. video cassettes — choice of any World Series since 1943. Indicate year choice & VHS or Beta. $64.95 ea + $2.50 ea ship. S-8 Sd official 400' films include '75 Series (Reds/Red Sox); '74 Series (Oakland/LA); also '75 All-Star Game — only $51.95 PPD. Fights your bag? Order Leonard/Duran I or II champ. action; 200' S-8 col sil, $27.50 ea; 400' sd, $67.50 ea; or Ali-Holmes (just out!) 200' S-8 col $25.95; 200' col sd $35.95 — only source of Ali Frazer I 200' std 8 col $24.95 PPD & Ali/Frazer II Std 8 B&W 2 reel spec., $17.95*, or 1 reel Std 8 col $19.95 ea*. *Add $2. per reel sound; $1. for silent. Hollywood Gold Video/Film cat (100 pg) $1.75; new Univ S-8/16mm cat. $1.50; Columbia VTR cat. $1.; Sportlite Films, Sports Tapes, Ring Classics, Paramount fliers, Mag Video lists, 50¢ ea. Univ 8 enter. cat. $1. SPORTLITE FILMS, Elect-2, Box 24-500, Speedway, IN 46226.

## ENGINES & MOTORS

ENGINES TO 19 h.p. for mowers, tillers, hobby. Repair manuals, parts. Tremendous savings. Fast, dependable, Illustrated price catalog $1.00. Ashland Small Engines, Ashland, MO 65010.

## DO-IT-YOURSELF

PROJECTION TV . . . Convert your TV to project 7 Foot picture. Results equal to $2,500 projector. Total cost less than $20.00. PLANS & LENS $16.00. Illustrated info. FREE: Macrocomcg, Washington Crossing, PA 18977.

## RECORDS & TAPES

RECORDS — TAPES! Discounts to 73% All labels; no purchase obligations; newsletter; discount dividend certificates. 100% guarantees. Free details. Discount Music Club, 650 Main St., Dept. 5-0381, New Rochelle, NY 10801.

## HYPNOTISM

FREE Hypnotism, Self-Hypnosis. Sleep Learning Catalog! Drawer H400, Ruidoso, New Mexico 88345.

## MISCELLANEOUS

MPG INCREASED! Bypass Pollution Devices easily. REVERSIBLY!! Free details — Posco GEE3, LaGrangeville, NY 12540.

FREE! World's Leading Novelty Catalog. 1800 Jokes, Tricks, Science, Sports, Hobbies. Johnson-Smith, C-24, Mt. Clemens, Mich. 48043.

AUTOMOBILE RE-TUNING FOR MAXIMIZED ECONOMY. Details FREE! Techneering, Box 12191DD, Norfolk, VA 23502.

CP/M SOFTWARE 40% discount special send to RP & B Inc., P.O. Box 178, Ketchi, KS 67067.

Don't miss your copy!

**1981 STEREO DIRECTORY & BUYING GUIDE**

Here are the facts you need to make sense out of today's bewildering stereo marketplace. It's over 250 pages of product listings, facts and data, compiled by the best team of experts in the business. *Thousands* of products are fully described, complete with photographs, manufacturers' descriptions, *even latest retail prices!*

Order from 1981 Stereo Directory, Dept. 01453, P.O. Box 278, Pratt Station, Brooklyn, NY 11205. Enclose $3.95* ($2.95 plus $1.00 postage and handling). Outside USA $5.00. *Residents of CA, CO, DC, FL, IL, MA, MO, MI, NY State, UT and VT add applicable sales tax.

# Popular Electronics

## ADVERTISERS INDEX


| RS no. | ADVERTISER | PAGE no. |
|---|---|---|
| | Albia Electronics | 45 |
| 2 | All Electronics Corp. | 96 |
| 4 | Antenna Specialists | 41 |
| 5 | AP Products | 12 |
| 6 | Apple Computer | Cover 2 |
| 7 | Arkon Electronics | 50 |
| 8 | Audiomatic | 96 |
| 63 | Beckman Instruments | 1 |
| | Bullet Electronics | 115 |
| 9 | Chaney Electronics | 110 |
| | Classified Advertising | 112, 113, 114, 115 |
| 47 | Cleveland Consumer Computers | 87 |
| | Cleveland Institute of Electronics, Inc. | 16, 17, 18, 19 |
| 1 | Communications Electronics | 42 |
| 10 | Components Express | 20 |
| | Computer Professionals Book Club | 54, 55, 56, 57 |
| 11 | Computer Specialties | 62 |
| 12 | Computique | 50 |
| 66 | Cooper Group | 33 |
| 14 | DBX | 6 |
| 15 | Digi-Key Corp. | 104, 105 |
| 16, 17 | Discwasher | 3, 25 |
| 64 | Dynascan | Cover 3 |
| 18 | Egbert Co. | 53 |
| 19 | Electra Corp. | 22 |
| 20 | Electronic Specialists | 91 |
| 21 | EICO | 98 |
| 22 | ETCO | 90 |
| 23 | Firestik | 100 |
| 24 | Fluke | 5 |
| 25 | Global | 97 |
| 26 | Godbout Electronics, Bill | 106 |
| | Grantham College of Engineering | 101 |
| 27 | Hardside | 66 |
| 28, 29 | Heath Co. | 30, 84 |
| 30 | Illinois Audio | 98 |
| 31 | Int'l Security Corp. | 89 |
| 32 | Jameco Electronics | 103 |
| 33 | JDR Microdevices | 110 |
| 34 | J&R Music World | 52 |
| 36 | Kenwood | 99 |
| 37 | Koss Corp. | Cover 4 |
| 38, 39 | Magnavox | 9, 11 |
| 40 | Maxell Corp. of America | 21 |
| 44 | McIntosh Laboratory, Inc. | 101 |
| 62 | M.F.J. Enterprises | 97 |
| | MICROCOMPUTER MART | 111 |
| 42 | Micro Ace | 47 |
| 43 | Micro Management Systems | 102 |
| | Nabih's | 96 |
| 45 | National Guard | 27, 28, 29 |
| | National Technical Schools | 72, 73, 74, 75 |
| | Netronics, R & D Ltd. | 49 |
| | NRI Schools | 36, 37, 38, 39 |
| 46 | Ohio Scientific | 58 |
| 48 | OK Machine & Tool Corp. | 35 |
| 49 | Olympic Sales | 110 |
| | Omega Sales Corp. | 26 |
| 51 | Omnisonix Ltd. | 15 |
| 52 | On Computing | 78 |
| 53 | Paccom | 91 |
| 54 | PAIA Electronics, Inc. | 100 |
| | Phoenix Systems | 99 |
| 55 | Poly Paks | 95 |
| 56 | Quest Electronics | 106 |
| | Radio Shack | 109 |
| 57 | Howard W. Sams & Co. | 92 |
| 58 | Scelbi Publications | 98 |
| 59 | Scientific Systems | 101 |
| 50 | Shure Bros. | 7 |
| 60 | Simutek | 43 |
| | Sinclair Electronics | 13 |
| 61 | Sperry, A.W. | 51 |
| 35 | 3-M | 2 |


**BULLET**
ELECTRONICS, Inc.
P.O.BOX 401244P,GARLAND,TX.75040

### Super Music Maker Kit — REVISION 2 — $24.95

Now you can play hundreds of songs using the Bullet **Super Music Maker.** The unit **features a single factory programmed microprocessor IC** that comes with 20 pre-programmed short tunes. By adding the additional PROMS (2708's) the system can be expanded to play up to **1000 notes per PROM.** Just think . . . a compact electronic instrument that will play dozens, hundreds or even thousands of selections of music. The kit comes with **all electronic components (less the PROM),** and a drilled, plated and screened PC Board which measures 4" x 4¾". The **7 watt amplifier** section is on the same PC board and drives an 8 ohm speaker (not included), from a whisper to ear splitting volume. Since the unit works on **12 VDC** or **12 VAC*,** vehicle or portable operation is possible. **What do you get for $24.95? Everything but a speaker, transformer, case, switches,** and **PROM.** Additional 2708 albums containing popular tunes are available for **$15.00** each or you can program your own PROMS using information provided with the kit instructions. Lists of available PROM albums are available on request. *(Note: Unit plays electronic music one note at a time, it is not possible to play chords or a melody with harmony simultaneously.)*

OPTIONAL ACCESSORIES

**DIP Switches** One 8 pos., One 5 pos. **2.00/Set**
(Can be **directly soldered** to PC Bd. to access tunes)

**Rotary Switches** Two 5 position **2.50/Set**
(For **remote wiring** to PC Bd. to access tunes)

**Attractive Black Plastic Case** **6.50**

**Wallplug Transformer** **3.00**
(For operation on 117VAC house voltage)

### Sound Effects Kit $18.50

The **SE-01 Sound Effects Kit** is a complete kit; all you need to build a programmable sound effects machine except a battery and speaker. Our kit is designed to really ring out the **TI 76477** Sound Chip. Only the SE-01 provides you with additional circuitry that includes a **PULSE GENERATOR, MUX OSCILLATOR and COMPARITOR** to make more complex sounds a snap. We help you in building the kit with a clear, easy-to-follow construction manual and we show you how to easily program the unit. Other dealers will sell you the chip or a "kit" of parts but you are on your own to do the most difficult part...make neat sounds! Within a short time after you build the SE-01 you can easily create **Gunshots, Explosions, Space Sounds, Steam Trains** and much more. We think the Bullet SE-01 is the best deal on the market but don't ask us, — ask the **15,000** happy SE-01 owners!

**Complete Kit** With Quality Plated PC Board **$18.50**
(Less battery & speaker)

### 7 Watt Audio Amp Kit $5.95

SMALL, SINGLE, HYBRID IC AND COMPONENTS FIT ON A 2" x 3" PC BOARD (INCLUDED). RUNS ON 12 VDC. GREAT FOR ANY PROJECT THAT NEEDS AN INEXPENSIVE AMP. LESS THAN 3% THD @ 5 WATTS. COMPATIBLE WITH SE-01 SOUND KIT.

**AY3-8910 PROGRAMMABLE SOUND GENERATOR**

The AY3-8910 is a 40 pin LSI chip with three oscillators, three amplitude controls, programmable noise generator, three mixers, an envelope generator, and three D/A converters that are controlled by 8 BIT WORDS. No external pots or caps required. This chip hooked to an 8 bit microprocessor chip or Buss (8080, Z80, 6800 etc.) can be software controlled to produce almost any sound. It will play three note chords, make bangs, whistles, sirens, gunshots, explosions, bleets, whines, or grunts. In addition, it has provisions to control its own memory chips with two IO ports. The chip requires +5V @ 75ma and a standard TTL clock oscillator. A truly incredible circuit.

*12.95* W/Basic Spec Sheet (4 pages)
60 page manual with S-100 interface instructions and several programming examples, **$3.00 extra**

**BANKRUPT Game Manufacturer Dumps Computer Backgammon Game** — **$39.95** Includes Case **Does not include player pieces**

The Engineers designed this one too good, making it too costly to be competitive. Result . . . Chapter XI. We bought all the parts and can offer the unit as a kit for over **60% off retail!**




You get:
**Double sided glass PC Board**
**Powerful 8035 Micro Processor Chip**
**Two 2716 style mask ROMS**
**RAM Chips, LED readouts,**
**Keyboard, Instructions**
**AC Plug transformer**

8035 and program ROMS only with schematics. **$12.00**

### COMPONENTS

*INDICATES ITEM IS "HOUSE NUMBERED"

| | |
|---|---|
| 301 OP AMP 8 LEAD CAN | 3/1.00 |
| 723 VOLT REG. 10 LEAD CAN | .39 |
| 723 14 PIN DIP | .50 |
| 741 OP AMP MINI DIP | 4/1.10 |
| 30,000 @ 15V COMPUTER GRADE | 2.10 |
| 2N4402 PNP COMPLIMENT | 8/1.00 |
| 2N6028 P.U.T. W/SPECS | .50 |
| LM380 2W AUDIO IC W/SPECS | 1.09 |
| LM377 DUAL LM380 W/SPECS | 2.50 |
| LM3900 QUAD NORTON AMP | .69 |
| LM324 QUAD OP AMP | .55 |
| 7812 1A 12V REG | .95 |
| IL-1 OPTO ISOLATOR MINI DIP | .60 |
| *MEM 631 DUAL GATE MOSFET, DIODE PROTECTED, SIMILAR TO 40673 | .50 |
| MV1624 VARICAP DIODE 10 PFD | .39 |
| IN5148 VARICAP DIODE 47 PFD NOM. 3:1 RATIO | .49 |
| *MC1351P FM IF. DISC IC | .50 |
| TL490 BAR GRAPH DRIVER | 2.50 |
| 7805 5V 1A REGULATOR | .99 |
| *78M05 ½A 5V REG. TO -5 | .60 |
| LM3911 TEMP. TRANSDUCER IC W/SPECS | 1.10 |
| LM3302 QUAD COMPARATOR IC | .50 |
| 555 TIMER IC | .49 |
| *MC3401 QUAD NORTON AMP | .39 |
| MC3340 ELECTRONIC ALTERNATOR W/SPECS | .75 |
| LED'S | |
| JUMBO GREEN | 4/.89 |
| JUMBO RED | 5/.89 |
| MEDIUM RED (⅛") | .15 |
| MEDIUM GRN OR YELLOW | .16 |

**Call or write for FREE catalog.**

*POLICIES*

*NO C.O.D.'s SEND CHECK, MONEY ORDER, CREDIT CARD # ADD 5% FOR SHIPPING. TX. RES. ADD 5% TAX, FOREIGN ORDERS (EXCEPT CANADA) ADD 10% (20% AIRMAIL) U.S. FUNDS ONLY PHONE ORDERS ON MASTER CHARGE & VISA ONLY (214) 278-3553*

# ELECTRONICS WORLD® *Personal Electronics News*

**U.S. LAUNCHES FACSIMILE SERVICE TO CANADA.** The U.S. Postal Service's high-speed international telecommunication service, called "INTELPOST," operates from Washington, DC and the World Trade Center in New York City to metropolitan Toronto. Facsimile messages can be sent in less than two minutes for $5 per page. For this fee, messages are delivered to addressees the following day by regular mail service, but same-day service is available in some instances. Special delivery is also available at extra cost. Postal Service Headquarters in Washington and New York are open Monday through Friday from 8 a.m. to 5 p.m. Plans are also afoot to expand the service in the near future to western Europe.

**THE ELECTRO VOICE PATRICIAN CULT** lives on!—seven years after the company discontinued production of these 5-foot tall, 350-pound speaker systems with 30-inch woofers. Recently, E-V went into limited production of the Patrician 800s to make 100 pairs for Japanese customers who had paid more than $12,000 per pair in advance (1973 list price was $1750 per pair). Does E-V plan to go back into full production of the Patrician 800? In answer, Bob Morrill, Vice President of Marketing for E-V, just smiles.



**"TELECONFERENCING" WITH MAGIC BLACKBOARD.** The Gemini 100 Electronic Blackboard from Western Electric is pressure-sensitive and converts marks from an ordinary piece of chalk into digital data signals. The latter are transmitted over telephone lines and displayed on TV screens. Unlike closed-circuit TV connections, the board requires no special transmission lines and can be hooked up anywhere there is a telephone. Tape recorders can also be used to store diagrams and information for future transmission.

**A 3-D HOME-TV RECEIVER THAT COSTS $200** more than standard color is the goal of an international committee which met in Geneva, Switzerland last October. The system would provide true 3-D viewing without viewer discomfort; group viewing from any location in a room; compatibility with present 2-D receivers; color and resolution comparable to present pictures; minimal modification of governmental and industry standards; and moderate conversion cost to the broadcaster. A system using quality polarized glasses for viewing is said to meet these requirements.

**FCC BEGINS PHASE II OF FEE REFUND PROGRAM.** Some $31 million will be refunded under Phase II. Individuals who paid the FCC more than $4 but $20 or less between August 1, 1970 and February 28, 1975 may be eligible for a partial refund. (This does not include the $4 for CB licenses granted after February 28, 1975.) To request a refund under Phase II, licensees must obtain a Fee Refund Program request form and instructions (Phase II) from any FCC Field Office, P.O. Box 19209, Washington, DC 20036. For specific details about the fee-refund program, you can call toll-free 800-424-2901.

**AM/FM SYNTHESIZER IC FOR RADIO TUNING** on a single chip was designed by Texas Instruments to improve accuracy of tuning of automotive and home radios. It contains the digital portion of a phase-locked loop synthesized AM/FM radio plus an interface to a microcomputer. The AC5945N uses integrated injection logic and operates at 5 mA at 5 V. It will also provide a reference frequency for use by a clock radio. Intermediate frequencies available are 10.7 MHz, 460, 455, or 260 kHz.

**COMPUTER AIDS FOR HANDICAPPED** will be sought in a national competition sponsored by the Applied Physics Laboratory of Johns Hopkins University, the National Science Foundation, and Radio Shack. They will be looking for ideas, devices, methods, and computer programs to help handicapped people overcome difficulties in learning, working, and adapting to their surroundings. Aids may be applicable to the blind, deaf, or mentally retarded, those with learning disabilities, the orthopedically handicapped, etc. One hundred awards will be made, including a $10,000 grand prize. Address: Aid the Handicapped, Johns Hopkins Univ., Box 670, Laurel, MD 20810.




# Now–anyone can afford to stay in touch–with the newest Cobraphone...

## It goes wherever you go—indoors or out—and makes sure you receive calls you might otherwise miss...

With this new economical Cobraphone cordless extension phone, you can stay in touch for less than $100.00! And you can use it anywhere in and around your home or even at your neighbors.

Uses for the new Cobraphone are limited only by your imagination: on the patio or at poolside; in the yard, garage, or basement; in the sickroom, by recuperating patients or invalids; in a warehouse or on a construction site. Also use it while watching TV—take calls without leaping up from your favorite chair. Or leave it at your next door neighbor's home, so they can answer your phone while you're away—a great aid to home security!

You'll marvel at the outstanding quality of voice communications on your Cobraphone. That's because Cobra's famous power and quality make sure conversation is "loud and clear" with your Cobraphone—as with Cobra CB radios. And it features the same full FM duplex system found on all Cobraphones: talk and listen as you would with a conventional phone—no annoying push-to-talk buttons.

The CP-15S installs in seconds: just plug into the nearest AC outlet and phone jack. That's all there is to it!

So visit your favorite retail, department or electronics specialty store today. Ask to see the full Cobraphone line. Then take home your choice and enjoy all your activities—and still be in touch with everyone—anywhere in the world.

Write for free color brochure.

Cobraphone®

**Conversation Loud and Clear**

Cobra Communications Product Group
**DYNASCAN CORPORATION**
6460 W. Cortland St. Chicago, Illinois 60635

CIRCLE NO. 64 ON FREE INFORMATION CARD

# The Sound of Koss is no longer something you have to keep to yourself.

You no longer have to limit your listening to stereophones to enjoy the incredible Sound of Koss. Because now you can get the optimum loudspeaker system, and the Sound of Koss, in any Koss CM series system you choose.

## KOSS CM 1010

Here's the ultimate 2-bandpass system. The Koss CM 1010 has a unique passive radiator to enhance the lower two octaves of bass. As well as a special 8-inch woofer to increase the midrange frequency response up to 3500Hz.

And with the CM 1010's 1-inch dome tweeter, you get the highest energy output, and lowest distortion, of any tweeter on the market.

## KOSS CM 1020

No three bandpass loudspeaker system currently available offers the benefits of the Koss CM 1020. Its dual ports improve cabinet tuning and structural stability. And its 10-inch woofer provides a 3db gain in efficiency, as well as flat response over the lower bandpass. In addition, the CM 1020 uses a 4½-inch midrange driver to capture all the energy and presence of this critical bandpass. And the CM 1020's unique 1-inch dome tweeter produces the highest energy output and lowest distortion of any tweeter currently available. Indeed, the Koss CM 1020 is the 3-bandpass loudspeaker system you really have to hear to believe.

## KOSS CM 1030

The Koss CM 1030 represents the ultimate in 4-bandpass loudspeaker systems. It includes a 10-inch woofer, mass aligned dual port system, a parallel midrange system with two 4½-inch drivers, and both a tweeter and a 1-inch treble tweeter that feature a unique acoustic transformer. Each has been carefully and specifically designed to produce the optimum spectral characteristics of their respective bandpass.

Uniting the CM 1030 into a total system that represents the ultimate in loudspeaker technology, is a unique, quasi second-order crossover network. In all, the CM 1030 is so amazing, no other 4-bandpass system even comes close in bass, midrange or high bandpass performance.

## KOSS CM 530

Setting entirely new standards for bookshelf speakers is the Koss CM 530. Whether you place them horizontally or vertically, they deliver perfect mirror imaging, an incredible degree of dispersion, and the breathtaking Sound of Koss.

## KOSS PRO 4/TRIPLE A

Write us, c/o Virginia Lamm for a free copy of our full-color loudspeaker catalog. And when you visit your audio dealer to hear the incredible Sound of Koss loudspeakers, take an extra moment for a private listening experience with the world famous Koss Pro/4 Triple A. Once you've heard the Sound of Koss for yourself, you'll know why hearing is believing.

©1979 Koss Corp.

**KOSS® stereophones/loudspeakers**

**hearing is believing®**

**KOSS CORPORATION,** 4129 N. Port Washington Ave., Milwaukee, Wisconsin 53212 International Headquarters: Milwaukee · facilities: Canada · France · Germany · Ireland

**CIRCLE NO. 37 ON FREE INFORMATION CARD**